

# **CERIO Corporation**

## **CS-3424G-24P**

**PoE CS-3000 Series - 24 Port Gigabit Managed PoE+  
L2/L3 Lite Switch with 4 Combo Gigabit Ports  
( 400Watt Power )**

**Command Line Interface  
Managed Switch Software**

**Rev. 1.1**



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

## **Table of Contents**

---

Command Line Interface.....	1
Managed Switch Software.....	1
1. AAA.....	16
aaa authentication .....	16
login authentication .....	14
ip http login authentication .....	15
enable authentication.....	16
show aaa authentication.....	17
show line lists .....	17
tacacs default-config .....	18
tacacs host .....	19
show tacacs default-config .....	20
show tacacs.....	20
show default-config.....	21
radius host .....	23
show radius default-config .....	24
show radius.....	24
2. ACL.....	24
mac acl .....	24
permit (MAC).....	24
deny (MAC) .....	26
ip acl.....	29
permit (IP) .....	29
deny (IP).....	33
ipv6 acl .....	36
permit (IPv6).....	36
deny (IPv6) .....	40
bind acl.....	37
show acl .....	37
show acl utilization .....	38
3. Administration .....	38
configure .....	38
clear arp .....	39
clear service .....	39
enable.....	40
end .....	41
exit.....	41

# Command Line Interface

## User Guide

---

history .....	43
hostname.....	43
interface.....	45
ip address .....	45
ip default-gateway.....	46
ip dhcp .....	47
ip dns .....	47
ip dns lookup.....	48
ipv6 autoconfig.....	48
ipv6 address.....	49
ipv6 default-gateway .....	49
ipv6 dhcp .....	49
ip service.....	50
ip session-timeout .....	52
ip ssh.....	52
line.....	53
reboot.....	53
enable password .....	53
exec-timeout .....	54
password-thresh .....	56
ping .....	58
traceroute.....	60
show arp .....	60
show cpu utilization .....	61
show history .....	61
show info .....	59
show ip .....	59
show ip dhcp .....	60
show ip dns .....	60
show ip http.....	61
show ipv6 .....	61
show ipv6 dhcp.....	62
show line.....	62
show memory statistics.....	63
show privilege.....	64
show username.....	64
show users.....	65
show version.....	65
silent-time .....	66
ssl .....	67



# Command Line Interface User Guide

---

system name .....	67
system contact.....	69
system location.....	70
terminal length .....	70
username.....	70
4. Authentication Manager .....	71
authentication.....	71
authentication (Interface).....	72
authentication mac radius.....	72
authentication mac local.....	74
authentication guest-vlan .....	75
authentication guest-vlan (Interface).....	76
authentication host-mode .....	76
authentication max-hosts.....	77
authentication method.....	78
authentication order .....	79
authentication port-control.....	79
authentication radius-attributes vlan.....	79
authentication reauth .....	80
authentication timer inactive.....	81
authentication timer quiet.....	81
authentication timer reauth .....	82
authentication web local.....	83
authentication web max-login-attempts .....	84
clear authentication sessions.....	85
dot1x.....	85
dot1x guest-vlan .....	86
dot1x max-req .....	87
dot1x port-control .....	87
dot1x reauth .....	88
dot1x timeout reauth-period.....	89
dot1x timeout quiet-period .....	90
dot1x timeout server-timeout.....	90
dot1x timeout supp-timeout .....	91
dot1x timeout tx-period .....	92
show authentication.....	93
show authentication sessions.....	95
5. Diagnostic.....	97
show cable-diag .....	97



# Command Line Interface

## User Guide

show fiber-transceiver.....	98
6. DHCP Snooping.....	100
ip dhcp snooping .....	100
ip dhcp snooping vlan .....	100
ip dhcp snooping trust .....	98
ip dhcp snooping verify.....	99
ip dhcp snooping rate-limit .....	99
clear ip dhcp snooping statistics .....	100
show ip dhcp snooping .....	101
show ip dhcp snooping interface .....	101
show ip dhcp snooping binding .....	102
ip dhcp snooping option.....	102
ip dhcp snooping option action.....	103
ip dhcp snooping option circuit-id .....	104
ip dhcp snooping option remote-id .....	104
show ip dhcp snooping option .....	105
ip dhcp snooping database.....	105
ip dhcp snooping database write-delay .....	106
ip dhcp snooping database timeout.....	107
clear ip dhcp snooping database statistics .....	108
renew ip dhcp snooping database.....	109
show ip dhcp snooping database.....	110
7. DoS .....	111
dos.....	111
dos (interface) .....	113
show dos.....	113
8. Dynamic ARP Inspection .....	114
ip arp inspection.....	114
ip arp inspection vlan.....	115
ip arp inspection trust.....	115
ip arp inspection validate.....	116
ip arp inspection rate-limit.....	117
clear ip arp inspection statistics .....	117
show ip arp inspection .....	118
show ip arp inspeciton interface.....	118
9. GVRP .....	119
gvrp (Global).....	119
gvrp (Interface) .....	120
gvrp registration-mode.....	120



# Command Line Interface

## User Guide

gvrp vlan-create-forbid .....	121
clear gvrp statistics .....	121
show gvrp statistics .....	122
show gvrp .....	123
show gvrp configuration .....	125
10. IGMP Snooping .....	126
ip igmp snooping .....	126
ip igmp snooping report-suppression .....	126
ip igmp snooping version .....	127
ip igmp snooping unknown-multicast action .....	127
ip igmp snooping querier .....	128
ip igmp snooping vlan .....	128
ip igmp snooping vlan fastleave .....	129
ip igmp snooping vlan last-member-query-count .....	130
ip igmp snooping vlan last-member-query-interval .....	130
ip igmp snooping vlan query-interval .....	130
ip igmp snooping vlan response-time .....	130
ip igmp snooping vlan robustness-variable .....	131
ip igmp snooping vlan router .....	131
ip igmp snooping vlan forbidden-port .....	132
ip igmp snooping vlan static-port .....	133
ip igmp snooping vlan forbidden-router-port .....	133
ip igmp snooping vlan static-router-port .....	134
ip igmp snooping vlan static-group .....	134
ip igmp snooping vlan group .....	135
profile range .....	136
ip igmp profile .....	136
ip igmp filter .....	137
ip igmp max-groups .....	137
ip igmp max-groups action .....	138
clear ip igmp snooping groups .....	139
clear ip igmp snooping statistics .....	139
show ip igmp snooping groups counters .....	140
show ip igmp snooping groups .....	141
show ip igmp snooping router .....	141
show ip igmp snooping querier .....	142
show ip igmp snooping .....	143
show ip igmp snooping vlan .....	144
show ip igmp snooping forward-all .....	144
show ip igmp profile .....	145



# Command Line Interface User Guide

---

show ip igmp filter .....	145
show ip igmp max-group .....	146
show ip igmp max-group action.....	147
11. IP SourceGuard .....	147
ip source verify.....	147
ip source binding .....	148
show ip source interface .....	149
show ip source binding .....	150
12. Link Aggregation.....	150
lag.....	150
lag load-balance.....	151
lacp port-priority.....	152
lacp system-priority.....	152
lacp timeout.....	153
show lacp.....	153
show lag.....	155
13. LLDP .....	156
clear lldp statistics.....	156
lldp .....	156
lldp rx.....	157
lldp tx-interval.....	158
lldp reinit-delay .....	160
lldp holdtime-multiplier.....	160
lldp lldpdu .....	161
lldp med .....	161
lldp med fast-start-repeat-count .....	163
lldp med location .....	163
lldp med network-policy .....	164
lldp med network-policy (Interface) .....	167
lldp med network-policy voice auto .....	168
lldp med tlv-select .....	168
lldp tlv-select .....	169
lldp tlv-select pvid.....	170
lldp tlv-select vlan-name .....	171
lldp tx.....	170
lldp tx-delay.....	171
show lldp .....	172
show lldp local-device .....	173
show lldp med.....	174



# Command Line Interface User Guide

---

show lldp neighbor.....	177
show lldp statistics.....	178
show lldp tlv-overloading.....	181
14. Logging .....	183
clear logging.....	183
logging.....	183
logging host .....	183
logging severity.....	184
show logging.....	184
15. MAC AddressTable .....	187
clear mac address-table .....	187
mac address-table aging-time .....	187
mac address-table static .....	188
show mac address-table .....	189
show mac address-table counters.....	190
show mac address-table aging-time .....	190
16. MAC VLAN .....	191
vlan mac-vlan group (Global) .....	191
vlan mac-vlan group (Interface).....	191
show vlan mac-vlan groups .....	191
show vlan mac-vlan interfaces .....	192
17. Management ACL .....	192
management access-list.....	192
management access-class .....	193
deny .....	193
permit .....	194
no sequence .....	195
show management access-class.....	195
show management access-list .....	196
18. Mirror .....	196
mirror session destination interface .....	196
mirror session source interface .....	197
show mirror .....	198
19. MLD Snooping.....	199
ipv6 mld snooping .....	199
ipv6 mld snooping report-suppression .....	199
ipv6 mld snooping version .....	201
ipv6 mld snooping unknown-multicast action.....	201



# Command Line Interface

## User Guide

ipv6 mld snooping vlan .....	202
ipv6 mld snooping vlan parameters .....	202
ipv6 mld snooping vlan fastleave .....	204
ipv6 mld snooping vlan last-member-query-count .....	205
ipv6 mld snooping vlan last-member-query-interval .....	205
ipv6 mld snooping vlan query-interval .....	206
ipv6 mld snooping vlan response-time .....	206
ipv6 mld snooping vlan robustness-variable .....	207
ipv6 mld snooping vlan router .....	207
ipv6 mld snooping vlan static-port .....	207
ipv6 mld snooping vlan forbidden-router-port .....	208
ipv6 mld snooping vlan forbidden-router-port .....	208
ipv6 mld snooping vlan static router port .....	209
ipv6 mld snooping vlan static-group .....	209
ipv6 mld snooping vlan group .....	210
profile range .....	211
ipv6 mld profile .....	211
ipv6 mld filter .....	212
ipv6 mld max-groups .....	212
ip igmp max-groups action .....	213
clear ipv6 mld snooping groups .....	214
clear ipv6 mld snooping statistics .....	214
show ipv6 mld snooping groups counters .....	215
show ipv6 mld snooping groups .....	215
show ipv6 mld snooping router .....	216
show ipv6 mld snooping .....	217
show ipv6 mld snooping vlan .....	218
show ipv6 mld snooping forward-all .....	218
show ipv6 mld profile .....	219
show ipv6 mld filter .....	219
show ipv6 mld max-group .....	220
show ipv6 mld port max-group action .....	221
20. MVR .....	221
mvr .....	221
mvr vlan .....	222
mvr group .....	223
mvr mode .....	223
mvr query-time .....	225
mvr port type .....	226
mvr port immediate .....	226



# Command Line Interface User Guide

mvr static group .....	228
clear mvr members .....	228
show mvr members .....	229
show mvr interface .....	229
show mvr .....	230
21. Port .....	230
back-pressure.....	230
clear interface.....	231
description .....	231
duplex.....	232
eee .....	232
flowcontrol.....	233
jumbo-frame .....	234
media-type.....	234
protected .....	235
show interface.....	236
speed .....	238
shutdown.....	238
22. Port Error Disable.....	238
errdisable recovery cause .....	238
errdisable recovery interval.....	239
show errdisable recovery .....	240
23. Port Security.....	241
port-security (Global).....	241
port-security (Interface) .....	241
port-security address-limit.....	242
show port-security.....	243
show port-security interface.....	243
24. Protocol VLAN .....	244
vlan protocol-vlan group (Global).....	244
vlan protocol-vlan group (Interface) .....	245
show vlan protocol-vlan.....	246
show vlan protocol-vlan interfaces.....	246
25. QoS .....	247
qos.....	247
qos cos .....	248
qos map .....	248
qos queue.....	251



# Command Line Interface

## User Guide

---

qos remark .....	252
qos trust .....	253
qos trust (Interface) .....	253
show qos .....	254
show qos interface .....	255
show qos map .....	255
show qos queueing .....	256
 26. Rate Limit .....	257
rate limit egress .....	257
rate limit egress queue .....	257
rate limit ingress .....	258
 27. RMON .....	259
rmon event .....	259
rmon alarm .....	260
rmon history .....	261
clear rmon interfaces statistics .....	262
show rmon interfaces statistics .....	263
show rmon event .....	264
show rmon event log .....	265
show rmon alarm .....	265
show rmon history .....	266
show rmon history statistic .....	267
show snmp community .....	268
show snmp engineid .....	269
show snmp group .....	269
show snmp host .....	270
show snmp trap .....	271
show snmp view .....	271
show snmp user .....	272
snmp .....	272
snmp community .....	273
snmp engineid .....	273
snmp engineid rmote .....	274
snmp group .....	274
snmp host .....	275
snmp trap .....	277
snmp user .....	277
snmp view .....	278
 29. Spanning Tree .....	279



# Command Line Interface User Guide

---

instance (MST) .....	279
name (MST).....	279
revision (MST) .....	280
show spanning-tree .....	280
show spanning-tree interface.....	281
show spanning-tree mst .....	282
show spanning-tree mst configuration .....	283
show spanning-tree mst interface .....	285
spanning-tree.....	286
spanning-tree bpdu .....	286
spanning-tree bpdu-filter.....	286
spanning-tree bpdu-guard .....	287
spanning-tree cost.....	287
spanning-tree forward-time .....	288
spanning-tree hello-time.....	288
spanning-tree edge.....	289
spanning-tree link-type .....	290
spanning-tree max-hops .....	290
spanning-tree maximum-age.....	291
spanning-tree mcheck.....	291
spanning-tree mode .....	292
spanning-tree mst configuration .....	292
spanning-tree mst cost .....	293
spanning-tree mst port-priority .....	294
spanning-tree mst priority .....	294
spanning-tree pathcost method.....	295
spanning-tree port-priority.....	297
spanning-tree priority .....	297
spanning-tree tx-hold-count.....	298
30. Storm Control.....	298
show storm-control.....	298
storm-control.....	298
storm-control action .....	299
storm-control ifg .....	300
storm-control level .....	301
storm-control unit .....	302
31. System File.....	302
boot system .....	302
copy .....	303



# Command Line Interface User Guide

delete .....	304
restore-defaults .....	305
save .....	306
show bootvar .....	306
show config .....	307
show flash .....	308
32. Surveillance VLAN .....	309
surveillance-vlan (Global) .....	309
surveillance-vlan (Interface) .....	309
surveillance-vlan vlan .....	310
surveillance-vlan oui-table .....	311
surveillance-vlan cos (Global) .....	312
surveillance-vlan cos (Interface) .....	313
surveillance-vlan mode .....	313
surveillance-vlan aging-time .....	315
show surveillance-vlan .....	315
33. Time .....	316
clock set .....	316
clock timezone .....	317
clock source .....	318
clock summer-time .....	318
show clock .....	321
ntp .....	321
show ntp .....	321
34. UDLD .....	323
errdisable recovery cause udld .....	323
udld .....	323
udld aggressive .....	323
udld message time .....	324
udld reset .....	325
show udld .....	325
35. VLAN .....	326
vlan .....	326
Name (vlan) .....	327
switchport mode .....	327
switchport hybrid pvid .....	328
switchport hybrid ingress-filtering .....	329
switchport hybrid acceptable-frame-type .....	330
switchport hybrid allowed vlan .....	331



# Command Line Interface User Guide

switchport access vlan .....	332
switchport tunnel vlan .....	333
switchport trunk native vlan .....	335
switchport trunk allowed vlan .....	337
switchport default-vlan tagged .....	339
switchport forbidden default-vlan .....	341
switchport forbidden vlan .....	341
switchport vlan tpid .....	338
management-vlan .....	339
show vlan .....	340
show vlan interface membership .....	340
show interface switchport .....	341
show management-vlan .....	341
36.     Voice VLAN .....	342
voice-vlan (Global) .....	342
voice-vlan (Interface) .....	343
voice-vlan vlan .....	344
voice-vlan oui-table .....	344
voice-vlan cos (Global) .....	345
voice-vlan cos (Interface) .....	346
voice-vlan mode .....	347
voice-vlan aging-time .....	348
show voice-vlan .....	349
37.     Static Routing .....	350
IPv4 Interface .....	350
IPv4 Routes .....	352
IPv4 ARP .....	352
IPv6 Interface .....	353
IPv6 Address .....	354
IPv6 Routes .....	355
IPv6 Neighbors .....	355
38.     POE .....	356
POE Port Setting .....	356
POE Port Schedule Setting .....	357
39.     ERPS .....	358
Erps ( global ) .....	358
Erps instance ( Global ) .....	358
Control-vlan .....	359
wtr-timer .....	359



## Command Line Interface User Guide

---

guard-timer .....	360
work-mode .....	360
ring<ID> .....	361
ring-level .....	361
port.....	362
mel.....	362
Ring enable .....	363
protected-instance .....	363
Show erps instance .....	364
 40.     DNS.....	364
ip domain .....	364
ip domain name.....	365
ip name-server.....	365
ip host.....	366
show hosts .....	366

---



## 1. AAA

### aaa authentication

#### Syntax

```
aaa authentication (login | enable) (default | LISTNAME) METHODLIST
[METHODLIST] [METHODLIST] [METHODLIST]
no aaa authentication (login | enable) LISTNAME
```

#### Parameter

<b>login</b>	Add/Edit login authentication list
<b>enable</b>	Add/Edit enable authentication list
<b>default</b>	Edit default authentication list
<i>LISTNAME</i>	Specify the list name for authentication type
<i>METHODLIST</i>	Specify the authenticate method, including none, local, enable, tacacs+, radius.

#### Default

Default authentication list name for type login is “default” and default method is “local”.

Default authentication list name for type enable is “default” and default method is “enable”

#### Mode

Global Configuration

#### Usage

Login authentication is used when user try to login into the switch. Such as CLI login dialog and WEBUI login web page.

Enable authentication is used only on CLI for user trying to switch from User EXEC mode to Privileged EXEC mode.

Both of them support following authenticate methods.

**Local:** Use local user account database to authenticate. (This method is not supported for enable authentication)

**Enable:** Use local enable password database to authenticate.

**Tacacs+:** Use remote Tacacs+ server to authenticate.

**Radius:** Use remote Radius server to authenticate.

**None:** Do nothing and just make user to be authenticated.

Each list allows you to combine these methods with different orders. For example, we want to authenticate login user with remote Tacacs+ server, but server may be crashed. Therefore, we need a backup plan, such as another Radius server. So we can configure the list with Tacacs+ server as first authentication method and Radius server as second one.

Use no form to delete the existing list. However, “default” list is not allowed to remove.



**Example**

This example shows how to add a login authentication list to authenticate with order tacacs+, radius, local.

```
Switch(config)# aaa authentication login test1  
tacacs+ radius local
```

This example shows how to show existing login authentication lists

```
Switch# show aaa authentication login lists  
Login List Name | Authentication Method List  
-----+-----  
      default | local  
      test1   | tacacs+   radius   local
```

This example shows how to add an enable authentication list to authenticate with order tacacs+, radius, enable.

```
Switch(config)# aaa authentication enable test1  
tacacs+ radius enable
```

This example shows how to show existing enable authentication lists

```
Switch# show aaa authentication login lists  
Enable List Name | Authentication Method List  
-----+-----  
      default | enable  
      test2   | tacacs+   radius   enable
```

---

## login authentication

**Syntax**

```
login authentication LISTNAME  
no login authentication
```

**Parameter**

<i>LISTNAME</i>	Specify the login authentication list name to use.
-----------------	--

**Default**

Default login authentication list for each line is “default”.

**Mode**

Line Configuration

**Usage**

Different access methods are allowed to bind different login authentication lists. Use “**login authentication**” command to bind the list to specific line (console, telnet, ssh).

Use no form to bind the “default” list back.

**Example**

This example shows how to create a new login authentication list and bind to telnet line.

```
Switch(config)# aaa authentication login test1
```



```
tacacs+ radius local
Switch(config)# line telnet
Switch(config-line)# login authentication test1
```

This example shows how to show line binding lists.

```
Switch# show line lists
Line Type | AAA Type | List Name
-----+-----+-----+
  console |           login | default
          |           enable | default
  telnet  |           login | test1
          |           enable | default
    ssh   |           login | default
          |           enable |
  default http |      login | default
 https |      login | default
```

---

## ip http login authentication

---

### Syntax

```
ip (http | https) login authentication LISTNAME
no ip (http | https) login authentication
```

<b>http</b>	Bind login authentication list to user access WEBUI with http protocol
<b>https</b>	Bind login authentication list to user access WEBUI with https protocol
<i>LISTNAME</i>	Specify the login authentication list name to use.

---

### Default

Default login authentication list for each line is “default”.

---

### Mode

Global Configuration

---

### Usage

Different access methods are allowed to bind different login authentication lists. Use “**ip (http | https) login authentication**” command to bind the list to WEBUI access from http or https.

Use no form to bind the “default” list back.

---

### Example

This example shows how to create two new login authentication lists and bind to http and https.

```
Switch(config)# aaa authentication login test1
tacacs+ radius local
Switch(config)# aaa authentication login test2
```

---



**radius local**

```
Switch(config) # ip http login authentication test1
Switch(config) # ip https login authentication test2
```

This example shows how to show line binding lists.

```
Switch# show line lists
```

Line Type	AAA Type	List Name
console	login   enable	default   default
telnet	login   enable	default   default
ssh	login   enable	default   default
default http	login	test1
https	login	test2

## enable authentication

### Syntax

```
enable authentication LISTNAME
no enable authentication
```

### Parameter

*LISTNAME* Specify the enable authentication list name to use.

### Default

Default enable authentication list for each line is “default”.

### Mode

Line Configuration

### Usage

Different access methods are allowed to bind different enable authentication lists. Use “**enable authentication**” command to bind the list to specific line (console, telnet, ssh).

Use no form to bind the “default” list back.

### Example

This example shows how to create a new enable authentication list and bind to telnet line.

```
Switch(config) # aaa authentication enable test1
tacacs+ radius enable
Switch(config) # line telnet
Switch(config-line) # enable authentication test1
```

This example shows how to show line binding lists.

```
Switch# show line lists
```

Line Type	AAA Type	List Name
telnet	enable	test1



```
-----+-----+
      console |          login   | default
                  |          enable   | default
      telnet  |          login   | default
                  |          enable   | test1
      ssh    |          login   | default
                  |          enable   |
      default http |        login   | default
      https |          login   | default
```

---

## show aaa authentication

---

### Syntax

**show aaa authentication (login | enable) lists**

---

### Parameter

<b>login</b>	Show login authentication list
<b>enable</b>	Show enable authentication list

---

### Default

No default value for this command

---

### Mode

Privileged EXEC

---

### Usage

Use “**show aaa authentication**” command to show login authentication or enable authentication method lists.

---

### Example

This example shows how to show existing login authentication lists

```
Switch# show aaa authentication login lists
Login List Name | Authentication Method List
-----+
      default | local
      test1  | tacacs+ radius local
```

This example shows how to show existing enable authentication lists

```
Switch# show aaa authentication login lists
Enable List Name | Authentication Method List
-----+
      default | enable
      test2  | tacacs+ radius enable
```

---

## show line lists



---

**Syntax**

**show line lists**

---

**Parameter**

---

**Default**

No default value for this command

---

**Mode**

Privileged EXEC

---

**Usage**

Use “**show line lists**” command to show all lines’ binding list of all authentication, authorization, and accounting function.

---

**Example**

This example shows how to show line binding lists.

Switch# **show line lists**

Line Type	AAA Type	List Name
console	login	default
	enable	default
	exec	default
	commands	default
	accounting-exec	default
telnet	login	default
	enable	default
	exec	default
	commands	default
	accounting-exec	default
ssh	login	default
	enable	default
	exec	default
	commands	default
	accounting-exec	default
http	login	default
https	login	default

---

## tacacs default-config

---

**Syntax**

**tacacs default-config [key TACACSKEY] [timeout <1-30>]**

---

**Parameter**

**key TACACSKEY**      Specify default tacacs+ server key string

**timeout <1-30>**      Specify default tacacs+ server timeout value



<b>Default</b>	Default tacacs+ key is “”. Default tacacs+ timeout is 5 seconds.
<b>Mode</b>	Global Configuration
<b>Usage</b>	Use “ <b>tacacs default-config</b> ” command to modify default values of tacacs+ server. These default values will be used when user try to create a new tacacs+ server and not assigned these values.
<b>Example</b>	This example shows how modify default tacacs+ configuration <pre>Switch(config)# tacacs default-config timeout 20 Switch(config)# tacacs default-config key tackey</pre>
	This example shows how to show default tacacs+ configurations. <pre>Switch# show tacacs default-config Timeout   Key -----+-----     10   tackey</pre>
	This example shows how to create a new tacacs+ server with above default config and show results. <pre>Switch(config)# tacacs host 192.168.1.111 Switch# show tacacs   Prio   Timeout        IP Address        Port     Key -----+-----+-----+-----+-----+   1         10           192.168.1.111        49    tackey</pre>

## **tacacs host**

<b>Syntax</b>	<b>tacacs host</b> <i>HOSTNAME</i> [ <b>port</b> <0-65535>] [ <b>key</b> <i>TACPLUSKEY</i> ] [ <b>priority</b> <0-65535>] [ <b>timeout</b> <1-30>] <b>no tacacs</b> [ <b>host</b> <i>HOSTNAME</i> ]
<b>Parameter</b>	<b>host</b> <i>HOSTNAME</i> Specify tacacs+ server host name, both IP address and domain name are available.
	<b>port</b> <0-65535>      Specify tacacs+ server udp port
	<b>key</b> <i>TACPLUSKEY</i> Specify tacacs+ server key string
	<b>priority</b> <0-65535>      Specify tacacs+ server priority
	<b>timeout</b> <1-30>      Specify tacacs+ server timeout value

<b>Default</b>	Default tacacs+ key is “”. Default tacacs+ timeout is 5 seconds.
----------------	---



---

**Mode** Global Configuration

---

**Usage** Use “**tacacs host**” command to add or edit tacacs+ server for authentication, authorization or accounting.

Use no form to delete one or all tacacs+ servers from database.

---

**Example** This example shows how to create a new tacacs+ server  
Switch(config)# **tacacs host 192.168.1.111 port 12345 key tacacs+ priority 100 timeout 10**

This example shows how to show existing tacacs+ server.

```
Switch# show tacacs
Prio | Timeout | IP Address | Port |
Key
---+-----+-----+-----+
--+
 100 |      10 |    192.168.1.111 | 12345 |
tacacs+
```

## show tacacs default-config

---

**Syntax** **show tacacs default-config**

---

**Parameter**

---

**Default** No default value for this command

---

**Mode** Privileged EXEC

---

**Usage** Use “**show tacacs default-config**” command to show tacacs+ default configurations.

---

**Example** This example shows how to show default tacacs+ configurations.

```
Switch# show tacacs default-config
Timeout | Key
---+-----
 10 | taclekey
```

## show tacacs

---

**Syntax** **show tacacs**

**Parameter**

**Default** No default value for this command

**Mode** Privileged EXEC

**Usage** Use “**show tacacs**” command to show existing tacacs+ servers.

**Example**

This example shows how to show existing tacacs+ server.

```
Switch# show tacacs
Prio | Timeout | IP Address | Port |
Key
-----+-----+-----+-----+
--+
100 | 10 | 192.168.1.111 | 12345 |
tacacs+
```

## show default-config

**Syntax**

```
radius default-config [key RADIUSKEY] [retransmit <1-10>] [timeout <1-30>]
```

**Parameter**

**key RADIUSKEY** Specify default radius server key string

**retransmit <1-10>** Specify default radius server retransmit value

**timeout <1-30>** Specify default radius server timeout value

**Default**

Default radius key is “”.

Default radius retransmit is 3 times. Default radius timeout is 3 seconds.

**Mode**

Global Configuration

**Usage**

Use “**radius default-config**” command to modify default values of radius server. These default values will be used when user try to create a new radius server and not assigned these values.



## Command Line Interface User Guide

### Example

This example shows how modify default radius configuration

```
Switch(config) # radius default-config timeout 20
Switch(config) # radius default-config key radiuskey
Switch(config) # radius default-config retransmit 5
```

---



This example shows how to show default radius configurations. Switch# **show radius**

default-config	Retries	Timeout	Key
5	20	radiuskey	

This example shows how to create a new radius server with above default config and show results.

```
Switch(config)# radius host 192.168.1.111
Switch# show radius
  Prio | IP Address | Auth-Port |
  Retries | Timeout | Usage-Type | Key
  -----+-----+-----+-----+-----+
  1   | 192.168.1.111 |      1812    |      5    |
  20  |      All     | radiuskey
```

---

## radius host

---

### Syntax

```
radius host HOSTNAME [auth-port <0-65535>] [key RADIUSKEY]
[priority <0-65535>] [retransmit <1-10>] [timeout <1-30>] [type
(login|802.1x|all)]
no radius [host HOSTNAME]
```

---

### Parameter

<b>host <i>HOSTNAME</i></b>	Specify radius server host name, both IP address and domain name are available.
<b>auth-port &lt;0-65535&gt;</b>	Specify radius server udp port
<b>key <i>RADIUSKEY</i></b>	Specify radius server key string
<b>priority &lt;0-65535&gt;</b>	Specify radius server priority
<b>retransmit &lt;1-10&gt;</b>	Specify radius server retransmit times
<b>timeout &lt;1-30&gt;</b>	Specify radius server timeout value
<b>type</b>	Usage type of this server
<b>login</b>	Use for login
<b>802.1X</b>	Use for 802.1X authentication
<b>all</b>	Use for both login and 802.1X authentication

---

### Default

Default radius key is “”.  
Default radius timeout is 3 seconds.

---

### Mode

Global Configuration

---

### Usage

Use “**radius host**” command to add or edit an existing radius server.

Use no form to delete one or all radius servers from database.



**Example**

This example shows how to create a new radius server  
**Switch (config) # radius host 192.168.1.111 auth-port 12345 key radiuskey priority 100 retransmit 5 timeout 10 type all**

This example shows how to show existing radius server.

**Switch# show radius**

Prio	IP Address	Auth-Port	Retries
Timeout	Usage-Type	Key	
100	192.168.1.111	12345	5
All	radiuskey		10

## **show radius default-config**

**Syntax**

**show radius default-config**

**Parameter**

**Default**

No default value for this command

**Mode**

Privileged EXEC

**Usage**

Use “**show radius default-config**” command to show radius default configurations.

**Example**

This example shows how to show default radius configurations.

**Switch# show radius default-config**

Retries	Key
5	20
	radiuskey

## **show radius**

**Syntax**

**show radius**

**Parameter**

**Default**

No default value for this command



<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Use “ <b>show radius</b> ” command to show existing radius servers.

Example	This example shows how to show existing radius server.					
	Switch# <b>show radius</b>					
	Prio	IP Address	Auth-Port	Retries		
	Timeout	Usage-Type	Key			
	-----+-----+-----+-----+-----+-----+-----	+-----+-----+				
	100	192.168.1.111	12345	5		10
	All	radiuskey				

## 2. ACL

## mac acl

Syntax	<b>mac acl</b> <b>NAME no mac</b> <b>aclNAME</b>
Parameter	<b>NAME</b> Specify the name of MAC ACL
Default	No default is defined
Mode	Global Configuration
Usage	Use the <b>mac acl</b> command to create a MAC access list and to enter configuration mode. The name of ACL must be unique that can not have same name with other ACL or QoS policy. Once an ACL is created, an implicit “deny any” ACE created at the end of the ACL. That is, if there are no matches, the packets are denied. Use the no form of this command to delete.
Example	The example shows how to create a mac acl. You can verify settings using following <b>show acl</b> command
	Switch334455(config)# <b>mac acl test</b> Switch334455(mac-al)# <b>show acl</b> MAC access list test

## permit (MAC)



# Command Line Interface

## User Guide

---

### Syntax

```
[sequence <1-2147483647>] permit (A:B:C:D:E:F/A:B:C:D:E:F|any)  
(A:B:C:D:E:F/A:B:C:D:E:F|any) [vlan <1-4094>] [cos <0-7> <0-7>]  
[ethertype <0x0600-0xFFFF>]
```

---



### no sequence <1-2147483647>

<b>Parameter</b>	<b>&lt;1-2147483647&gt;</b>	(Optional) Specify sequence index of ACE, the sequence index represent the priority of an ACE in ACL.
	<b>(A:B:C:D:E:F/A:B:C:D:E:F any)</b>	Specify the source MAC address and mask of packet or any MAC address.
	<b>(A:B:C:D:E:F/A:B:C:D:E:F any)</b>	Specify the destination MAC address and mask of packet or any MAC address
	<b>[vlan &lt;1-4094&gt;]</b>	(Optional) Specify the vlan ID of packet.
	<b>[cos &lt;0-7&gt; &lt;0-7&gt;]</b>	(Optional) Specify the Class of Service value and mask of packet.
	<b>[ethertype &lt;0x0600-0xFFFF&gt;]</b>	(Optional) Specify Ethernet protocol number of packet

**Default** No default is defined.

**Mode** MAC ACL Configuration

**Usage** Use the permit command to add permit conditions for a mac ACE that bypass those packets hit the ACE. The “sequence” also represents hit priority when ACL bind to an interface. An ACE not specifies “sequence” index would assign a sequence index which is the largest existed index plus 20. If packet content can match more than one ACE, the lowest sequence ACE is hit. An ACE can not be added if has the same conditions as existed ACE.

**Example** The example shows how to add an ACE that permit packets with source MAC address 22:33:44:55:66:77 ` VLAN 3 and Ethernet type 1999. You can verify settings by the following **show acl** command

```
Switch334455(config)# mac acl test
Switch334455(mac-al)# sequence 999 permit
22:33:44:55:66:77/FF:FF:FF:FF:FF:FF any vlan 3 ethtype 0x2800
Switch334455(mac-al)# show acl
MAC access list test
    sequence 999 permit 22:33:44:55:66:77/FF:FF:FF:FF:FF:FF any vlan 3
    ethtype 0x2800
```

## deny (MAC)

<b>Syntax</b>	<b>[sequence &lt;1-2147483647&gt;] deny</b> <b>(A:B:C:D:E:F/A:B:C:D:E:F any)</b> <b>(A:B:C:D:E:F/A:B:C:D:E:F any) [vlan &lt;1-4094&gt;] [cos &lt;0-7&gt; &lt;0-7&gt;]</b> <b>[ethertype &lt;0x0600-0xFFFF&gt;]</b>
---------------	---



# Command Line Interface

## User Guide

[shutdown] no sequence  
<1-2147483647>

---

Parameter

<1-2147483647>

(Optional) Specify sequence

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+[\(886\) 2-8911-6160](tel:+886289116160)



[service@cerio.com.tw](mailto:service@cerio.com.tw)

	index of ACE, the sequence index represent the priority of an ACE in ACL.
(A:B:C:D:E:F/A:B:C:D:E:F any)	Specify the source MAC address and mask of packet or any MAC address.
(A:B:C:D:E:F/A:B:C:D:E:F any)	Specify the destination MAC address and mask of packet or any MAC address.
[vlan <1-4094>]	(Optional) Specify the vlan ID of packet.
[cos <0-7> <0-7>]	(Optional) Specify the Class of Service value and mask of packet.
[ethertype <0x0600-0xFFFF>]	(Optional) Specify Ethernet protocol number of packet
[shutdown]	(Optional) Shutdown interface while ACE hit

**Default** No default is defined.

**Mode** MAC ACL Configuration

**Usage** Use the deny command to add deny conditions for a mac ACE that drop those packets hit the ACE. The “sequence” also represents hit priority when ACL bind to an interface. An ACE not specifies “sequence” index would assign a sequence index which is the largest existed index plus 20. If packet content can match more than one ACE, the lowest sequence ACE is hit. An ACE cannot be added if has the same conditions as existed ACE. Use “shutdown” to shutdown interface while ACE hit.

**Example** The example shows how to add an ACE that denies packets with destination MAC address aa:bb:cc:xx:xx:xx and VLAN 9. You can verify settings by the following **show acl** command

```

Switch334455(config)# mac acl test
Switch334455(mac-al)# sequence 30 permit any any
Switch334455(mac-al)# deny any aa:bb:cc:00:00:FF:FF:FF:00:00:00
vlan 9 shutdown
Switch334455(mac-al)# show acl
MAC access list test
    sequence 30 permit any any
        sequence 50 deny any AA:BB:CC:00:00:00/FF:FF:FF:00:00:00 vlan 9
    shutdown

```

---



## ip acl

---

### Syntax

**ip acl**  
**NAME no ip**  
**acl NAME**

---

---

### Parameter

**NAME**      Specify the name of IPv4 ACL

---

---

### Default

No default is defined

---

---

### Mode

Global Configuration

---

---

### Usage

Use the **ip acl** command to create an IPv4 access list and to enter ip-acl configuration mode. The name of ACL must be unique that can not have same name with other ACL or QoS policy. Once an ACL is created, an implicit “deny any” ACE created at the end of the ACL. That is, if there are no matches, the packets are denied. Use the no form of this command to delete.

---

---

### Example

The example shows how to create an IP ACL. You can verify settings by the following **show acl** command

```
Switch334455(config)#ip acl iptest  
Switch334455(ip-al)# show acl  
IP access list iptest
```

---

## permit (IP)



# Command Line Interface

## User Guide

---

### Syntax

```
[sequence <1-2147483647>] permit (<0-  
255>|ipinip|egp|igp|hmp|rdp|ipv6|  
ipv6:rout|ipv6:frag|rsvp|ipv6:icmp|ospf|pim|l2tp|ip)  
(A.B.C.D/A.B.C.D|any) (A.B.C.D/A.B.C.D|any)  
[(dscp|precedence) VALUE]]
```

```
[sequence <1-2147483647>] permit icmp  
(A.B.C.D/A.B.C.D|any) (A.B.C.D/A.B.C.D|any) (<0-  
255>|echo-reply|destination-unreachable|source-quench|echo-  
request|  
router-advertisement|router-solicitation|time-  
exceeded|timestamp| timestamp-reply|traceroute|any) (<0-  
255>|any) [(dscp|precedence) VALUE]
```

```
[sequence <1-2147483647>] permit tcp  
(A.B.C.D/A.B.C.D|any) (<0-65535>|echo|  
discard|daytime|ftp-  
data|ftp|telnet|smtp|time|hostname|whois|tacacs-  
ds|domain|www|  
pop2|pop3|syslog|talk|klogin|kshell|sunrpc|drip|PORT_RANG  
E|any) (A.B.C.D/A.B.C.D|any) (<0-
```

---



```
65535>|echo|discard|daytime|ftp-
data|ftp|telnet|smtp|time|hostname|whois|
tacacs-
ds|domain|www|pop2|pop3|syslog|talk|klogin|kshell|sunrpc|dri
p|PORT_RANGE|any)
[match-all TCP_FLAG] [(dscp|precedence) VALUE]
```

```
[sequence <1-2147483647>] permit udp
(A.B.C.D/A.B.C.D|any) (<0-65535>|echo|discard|
time|nameserver|tacacs-
ds|domain|bootps|bootpc|tftp|sunrpc|ntp|netbios-ns|snmp|
snmptrap|who|syslog|talk|rip|PORT_RANGE|any)
(A.B.C.D/A.B.C.D|any) (<0-65535>|echo|
discard|time|nameserver|tacacs-
ds|domain|bootps|bootpc|tftp|sunrpc|ntp|netbios-ns|
snmp|snmptrap|who|syslog|PORT_RANGE|any)
[(dscp|precedence) VALUE]
```

**no sequence <1-2147483647>**

<b>Parameter</b>	<b>&lt;1-2147483647&gt;</b>	(Optional) Specify sequence index of ACE, the sequence index represent the priority of an ACE in ACL.
	<b>(A.B.C.D/A.B.C.D any)</b>	Specify the source IPv4 address and mask of packet or any IPv4 address.
	<b>(A.B.C.D/A.B.C.D any)</b>	Specify the destination IPv4 address and mask of packet or any IPv4 address.
	<b>[dscp VALUE]</b>	(Optional) Specify the DSCP of packet.
	<b>[precedence VLAUE]</b>	(Optional) Specify the IP precedence of packet.
	<b>icmp-type</b>	Specify ICMP message type for filtering ICMP packet. Enter a type name of list or a number of ICMP message type.
	<b>icmp-code</b>	Specify ICMP message code for filtering ICMP packet.
	<b>l4-source-port</b>	Specify TCP/UDP source port of for filtering TCP/UDP packet. Enter a port name of list or a number of TCP/UDP port.
	<b>l4-destination-port</b>	Specify TCP/UDP destination port of for filtering TCP/UDP packet. Enter a port name of list or a number of TCP/UDP port.
	<b>match-all</b>	Specify tcp flag for TCP packet. If a flag should be set it is prefixed by "+\". If a flag should be unset it is prefixed by "-\". Available options



are +urg, +ack, +psh, +rst, +syn, +fin, -urg, -ack, -psh, -rst, -syn and -fin. To define more than 1 flag - enter additional flags one after another without a space (example +syn-ack).

---

<b>Default</b>	No default is defined.
----------------	------------------------

<b>Mode</b>	IP ACL Configuration
-------------	----------------------

<b>Usage</b>	Use the permit command to add permit conditions for an IP ACE that bypasses those packets hit the ACE. The “ <b>sequence</b> ” also represents hit priority when ACL bind to an interface. An ACE not specifies “ <b>sequence</b> ” index would assign a sequence index which is the largest existed index plus 20. If packet content can match more than one ACE, the lowest sequence ACE is hit. An ACE can not be added if has the same conditions as existed ACE.
--------------	--

<b>Example</b>	The example shows how to add a set of ACEs. You can verify settings by the following <b>show acl</b> command.
----------------	---

This command shows how to permit a source IP address subnet.  
Switch334455(ip-al)# **permit ip 192.168.1.0/255.255.255.0**

This command shows how to permit ICMP echo-request packet with any IP address.

Switch334455(ip-al)# **permit icmp any any echo-request any**

This command shows how to permit any IP address HTTP packets with DSCP 5.

Switch334455(ip-al)# **permit tcp any any www dscp 5**

This command shows how to permit any source IP address SNMP packet connect to destination IP address 192.168.1.1.

Switch334455(ip-al)# **permit udp any any 192.168.1.1/255.255.255.255 snmp**

Switch334455(ip-al)# **show acl**  
IP access list iptest  
sequence 1 permit ip 192.168.1.0/255.255.255.0 any  
sequence 21 permit icmp any any echo-request any  
sequence 41 permit tcp any any www dscp 5  
sequence 61 permit udp any any 192.168.1.1/255.255.255.255 snmp

---



**deny (IP)**

---



Syntax

```
[sequence <1-2147483647>] deny (<0-  
255>|ipinip|egp|igp|hmp|rdp|ipv6|  
ipv6:route|ipv6:frag|rsvp|ipv6:icmp|ospf|pim|l2tp|ip)  
(A.B.C.D/A.B.C.D|any) (A.B.C.D/A.B.C.D|any)  
[(dscp|precedence) VALUE]] [shutdown]

[sequence <1-2147483647>] deny icmp  
(A.B.C.D/A.B.C.D|any) (A.B.C.D/A.B.C.D|any) (<0-  
255>|echo-reply|destination-unreachable|  
source-quench|echo-request|router-advertisement|router-  
solicitation|  
time-exceeded|timestamp| timestamp-reply|traceroute|any)  
(<0-255>|any) [(dscp|precedence) VALUE] [shutdown]

[sequence <1-2147483647>] deny tcp (A.B.C.D/A.B.C.D|any)  
(<0-65535>|echo|  
discard|daytime|ftp-  
data|ftp|telnet|smtp|time|hostname|whois|tacacs-ds|  
domain|www|pop2|pop3|syslog|talk|klogin|kshell|sunrpc|drip|  
PORT_RANGE|any)  
(A.B.C.D/A.B.C.D|any) (<0-65535>|echo|discard|daytime|ftp-  
data|ftp|telnet|  
smtp|time|hostname|whois|tacacs-  
ds|domain|www|pop2|pop3|syslog|talk|  
klogin|kshell|sunrpc|drip|PORT_RANGE|any)  
[match-all TCP_FLAG] [(dscp|precedence) VALUE]  
[shutdown]

[sequence <1-2147483647>] deny udp (A.B.C.D/A.B.C.D|any)  
(<0-65535>|echo|discard|time|nameserver|tacacs-  
ds|domain|bootps|  
bootpc|tftp|sunrpc|ntp|netbios-ns|snmp|snmptrap|who|syslog|  
talk|rip|PORT_RANGE|any) (A.B.C.D/A.B.C.D|any) (<0-  
65535>|echo|  
discard|time|nameserver|tacacs-ds|domain|bootps|bootpc|tftp|  
sunrpc|ntp|netbios-  
ns|snmp|snmptrap|who|syslog|PORT_RANGE|any)  
[(dscp|precedence) VALUE] [shutdown]
```

**no sequence <1-2147483647>**

Parameter	<table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 30%; padding: 5px;"><b>&lt;1-2147483647&gt;</b></td><td style="width: 70%; padding: 5px;">(Optional) Specify sequence index of ACE, the sequence index represent the priority of an ACE in ACL.</td></tr> <tr> <td style="padding: 5px;"><b>(A.B.C.D/A.B.C.D any)</b></td><td style="padding: 5px;">Specify the source IPv4 address and mask of packet or any IPv4 address.</td></tr> <tr> <td style="padding: 5px;"><b>(A.B.C.D/A.B.C.D any)</b></td><td style="padding: 5px;">Specify the destination IPv4 address and mask of packet or any IPv4 address.</td></tr> <tr> <td style="padding: 5px;"><b>[dscp VALUE]</b></td><td style="padding: 5px;">(Optional) Specify the DSCP of</td></tr> </table>	<b>&lt;1-2147483647&gt;</b>	(Optional) Specify sequence index of ACE, the sequence index represent the priority of an ACE in ACL.	<b>(A.B.C.D/A.B.C.D any)</b>	Specify the source IPv4 address and mask of packet or any IPv4 address.	<b>(A.B.C.D/A.B.C.D any)</b>	Specify the destination IPv4 address and mask of packet or any IPv4 address.	<b>[dscp VALUE]</b>	(Optional) Specify the DSCP of
<b>&lt;1-2147483647&gt;</b>	(Optional) Specify sequence index of ACE, the sequence index represent the priority of an ACE in ACL.								
<b>(A.B.C.D/A.B.C.D any)</b>	Specify the source IPv4 address and mask of packet or any IPv4 address.								
<b>(A.B.C.D/A.B.C.D any)</b>	Specify the destination IPv4 address and mask of packet or any IPv4 address.								
<b>[dscp VALUE]</b>	(Optional) Specify the DSCP of								



	packet.
<b>[precedence VLAUE]</b>	(Optional) Specify the IP precedence of packet.
<b>icmp-type</b>	Specify ICMP message type for filtering ICMP packet. Enter a type name of list or a number of ICMP message type.
<b>icmp-code</b>	Specify ICMP message code for filtering ICMP packet.
<b>l4-source-port</b>	Specify TCP/UDP source port of for filtering TCP/UDP packet. Enter a port name of list or a number of TCP/UDP port.
<b>l4-destination-port</b>	Specify TCP/UDP destination port of for filtering TCP/UDP packet. Enter a port name of list or a number of TCP/UDP port.
<b>match-all</b>	Specify tcp flag for TCP packet. If a flag should be set it is prefixed by "+\". If a flag should be unset it is prefixed by "-\". Available options are +urg, +ack, +psh, +rst, +syn, +fin, -urg, -ack, -psh, -rst, -syn and -fin. To define more than 1 flag - enter additional flags one after another without a space (example +syn-ack).
<b>[shutdown]</b>	(Optional) Shutdown interface while ACE hit

---

**Default** No default is defined.

---

**Mode** IP ACL Configuration

---

**Usage** Use the deny command to add deny conditions for an IP ACE that drop those packets hit the ACE. The “**sequence**” also represents hit priority when ACL bind to an interface. An ACE not specifies “**sequence**” index would assign a sequence index which is the largest existed index plus 20. If packet content can match more than one ACE, the lowest sequence ACE is hit. An ACE can not be added if has the same conditions as existed ACE. Use “**shutdown**” to shutdown interface while ACE hit.

---

**Example** The example shows how to add an ACE that denies packets with source IP address 192.168.1.80. You can verify settings by the following **show acl** command

---

```
Switch334455(config)# ip acl iptest
Switch334455(ip-al)# deny ip 192.168.1.80/255.255.255.255 any
```



---

```
Switch334455(ip-al)# show acl
```

```
IP access list iptest
sequence 1 deny ip 192.168.1.80/255.255.255.255 any
```

---

## ipv6 acl

---

### Syntax

```
ipv6 acl NAME
no ipv6 acl NAME
```

---

### Parameter

NAME	Specify the name of IPv6 ACL
------	------------------------------

---

### Default

No default is defined

---

### Mode

Global Configuration

---

### Usage

Use the **ipv6 acl** command to create an IPv6 access list and to enter ipv6-acl configuration mode. The name of ACL must be unique that can not have same name with other ACL or QoS policy. Once an ACL is created, an implicit “deny any” ACE created at the end of the ACL. That is, if there are no matches, the packets are denied. Use the no form of this command to delete.

---

### Example

The example shows how to create an IPv6 ACL. You can verify settings by the following **show acl** command

```
Switch334455(config)#ipv6 acl ipv6test
Switch334455(ipv6-al)# show acl
IPv6 access list iptest
```

---

## permit (IPv6)

---

### Syntax

```
[sequence <1-2147483647>] permit (<0-255>|ipv6
(X:X::X:X/<0-128>|any) (X:X::X:X/<0-128>|any)
[(dscp|precedence) VALUE]

[sequence <1-2147483647>] permit icmp (X:X::X:X/<0-
128>|any) (X:X::X:X/<0-128>|any) (<0-255>|destination-
unreachable|packet-too-big|
time-exceeded|parameter-problem|echo-request|echo-reply|
mld-query|mld-report|mldv2-report|mld-done| router-
solicitation|router-advertisement|nd-ns|nd-na|any) (<0-
255>|any)[(dscp|precedence) VALUE]
```

---



## Command Line Interface User Guide

---

[sequence <1-2147483647>] permit tcp (X:X::X:X/<0-128>|any) (<0-65535>|echo|discard|daytime|ftp-



```

data|ftp|telnet|smtp|
time|hostname|whois|tacacs-
ds|domain|www|pop2|pop3|sys
log|
talk|klogin|kshell|sunrpc|drip|PORT_RANGE|any)
(X:X::X:X/<0-128>|any)
(<0-65535>|echo|discard|daytime|ftp- data|ftp|
telnet|smtp|time|hostname|whois|tacacs-ds|domain|www|pop2|
pop3|syslog|talk|klogin|kshell|sunrpc|drip|PORT_RANGE|an
y)           [match-all TCP_FLAG]
[(dscp|precedence) VALUE]

[sequence <1-2147483647>] permit udp
(X:X::X:X/<0- 128>|any)
(<0-65535>|echo|discard|time|nameserver|tacacs-ds|dom
ain| bootps|bootpc|tftp|sunrpc|ntp|netbios-
ns|snmp|snmptrap|who|syslog|
talk|rip|PORT_RANGE|any) (X:X::X:X/<0-128>|any)
(<0-
65535>|echo|discard|time|nameserver|tacacs-ds|domain
| bootps|bootpc|tftp|sunrpc|ntp|netbios-ns|
snmp|snmptrap|who|syslog|PORT_RANGE|any)
[(dscp|precedence) VALUE]
```

**no sequence <1-2147483647>**

<b>Parameter</b>	
<1-2147483647>	(Optional) Specify sequence index of ACE, the sequence index represent the priority of an ACE in ACL.
(X:X::X:X/<0-128> any)	Specify the source IPv6 address and prefix of packet or any IPv6 address.
(X:X::X:X/<0-128> any)	Specify the destination IPv6 address and prefix of packet or any IPv6 address.
[dscp VALUE]	(Optional) Specify the DSCP of packet.
[precedence VLAUE]	(Optional) Specify the IP precedence of packet.
<b>icmp-type</b>	Specify ICMP message type for filtering ICMP packet. Enter a type name of list or a number of ICMP message type.
<b>icmp-code</b>	Specify ICMP message code for filtering ICMP packet.
<b>l4-source-port</b>	Specify TCP/UDP source port of for filtering TCP/UDP packet. Enter a port name of list or a number of TCP/UDP port.



## Command Line Interface User Guide

---

<b>l4-destination-port</b>	Specify TCP/UDP destination port of for filtering TCP/UDP packet. Enter a port name or list or a number of TCP/UDP port.
----------------------------	--

---



**match-all**      Specify tcp flag for TCP packet. If a flag should be set it is prefixed by "+\". If a flag should be unset it is prefixed by "-\". Available options are +urg, +ack, +psh, +rst, +syn, +fin, -urg, -ack, -psh, -rst, -syn and -fin. To define more than 1 flag - enter additional flags one after another without a space (example +syn-ack).

---

**Default**      No default is defined.

---

**Mode**      IPv6 ACL Configuration

---

**Usage**      Use the permit command to add permit conditions for an IPv6 ACE that bypasses those packets hit the ACE. The “**sequence**” also represents hit priority when ACL bind to an interface. An ACE not specifies “**sequence**” index would assign a sequence index which is the largest existed index plus  
20. If packet content can match more than one ACE, the lowest sequence ACE is hit. An ACE can not be added if has the same conditions as existed ACE.

**Example**      The example shows how to add a set of ACEs. You can verify settings by the following **show acl** command.

This command shows how to permit a source IP address subnet.  
Switch334455(ipv6-al)# **permit permit ipv6 fe80:1122:3344:5566::1/64 any**

Switch334455(ipv6-al)# **show acl**  
IPv6 access list ipv6test  
sequence 1 permit ipv6 fe80:1122:3344:5566::1/64 any

---

## deny (IPv6)



# **Command Line Interface**

## **User Guide**

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

Syntax

```
[sequence <1-2147483647>] deny (<0-255>|ipv6) (X:X::X:X/<0-128>|any) (X:X::X:X/<0-128>|any) [(dscp|precedence) VALUE] [shutdown]
```

```
[sequence <1-2147483647>] deny icmp (X:X::X:X/<0-128>|any) (X:X::X:X/<0-128>|any) (<0-255>|destination-unreachable|packet-too-big|time-exceeded|parameter-problem|echo-request|echo-reply|mld-query|mld-report|mldv2-report|mld-done|router-solicitation|router-advertisement|nd-ns|nd-na|any) (<0-255>|any)[(dscp|precedence) VALUE] [shutdown]
```

```
[sequence <1-2147483647>] deny tcp (X:X::X:X/<0-128>|any) (<0-65535>|echo|discard|daytime|ftp-data|ftp|telnet|smtp|time|hostname|whois|tacacs-ds|domain|www|pop2|pop3|syslog|talk|klogin|kshell|sunrpc|drip|PORT_RANGE|any) (X:X::X:X/<0-128>|any) (<0-65535>|echo|discard|daytime|ftp-data|ftp|telnet|smtp|time|hostname|whois|tacacs-ds|domain|www|pop2|pop3|syslog|talk|klogin|kshell|sunrpc|drip|PORT_RANGE|any) [match-all TCP_FLAG] [(dscp|precedence) VALUE] [shutdown]
```

```
[sequence <1-2147483647>] deny udp (X:X::X:X/<0-128>|any) (<0-65535>|echo|discard|time|nameserver|tacacs-ds|domain|bootps|bootpc|tftp|sunrpc|ntp|netbios-ns|snmp|snmptrap|who|syslog|talk|rip|PORT_RANGE|any) (X:X::X:X/<0-128>|any) (<0-65535>|echo|discard|time|nameserver|tacacs-ds|domain|bootps|bootpc|tftp|sunrpc|ntp|netbios-ns|snmp|snmptrap|who|syslog|PORT_RANGE|any) [(dscp|precedence) VALUE] [shutdown]
```

**no sequence <1-2147483647>**

---

Parameter

<1-2147483647>	(Optional) Specify sequence index of ACE, the sequence index represent the priority of an ACE in ACL.
----------------	---

(A.B.C.D/A.B.C.D any)	Specify the source IPv4 address and mask of packet or any IPv4 address.
-----------------------	---

(A.B.C.D/A.B.C.D any)	Specify the destination IPv4 address and mask of packet or any IPv4
-----------------------	---



# Command Line Interface

## User Guide

	address.
[dscp VALUE]	(Optional) Specify the DSCP of packet.
[precedence VLAUE]	(Optional) Specify the IP precedence of packet.
<b>icmp-type</b>	Specify ICMP message type for filtering ICMP packet. Enter a type name of list or a number of ICMP message type.
<b>icmp-code</b>	Specify ICMP message code for filtering ICMP packet.
<b>l4-source-port</b>	Specify TCP/UDP source port of for filtering TCP/UDP packet. Enter a port name of list or a number of TCP/UDP port.
<b>l4-destination-port</b>	Specify TCP/UDP destination port of for filtering TCP/UDP packet. Enter a port name of list or a number of TCP/UDP port.
<b>match-all</b>	Specify tcp flag for TCP packet. If a flag should be set it is prefixed by "+\". If a flag should be unset it is prefixed by "-\". Available options are +urg, +ack, +psh, +rst, +syn, +fin, -urg, -ack, -psh, -rst, -syn and -fin. To define more than 1 flag - enter additional flags one after another without a space (example +syn-ack).
<b>[shutdown]</b>	(Optional) Shutdown interface while ACE hit

**Default** No default is defined.

**Mode** IP ACL Configuration

**Usage** Use the deny command to add deny conditions for an IPv6 ACE that drop those packets hit the ACE. The “sequence” also represents hit priority when ACL bind to an interface. An ACE not specifies “sequence” index would assign a sequence index which is the largest existed index plus 20. If packet content can match more than one ACE, the lowest sequence ACE is hit. An ACE can not be added if has the same conditions as existed ACE. Use “shutdown” to shutdown interface while ACE hit.

**Example** The example shows how to add an ACE that denies packets with destination IP address fe80::abcd. You can verify settings by the following **show acl** command



---

```
Switch334455(config)# ipv6 acl ipv6test
Switch334455(ip-al)# deny ipv6 any
fe80::abcd/128 Switch334455(ip-al)# show acl
```

```
IPv6 access list ipv6test
sequence 1 deny ipv6 any fe80::abcd/128
```

---

## bind acl

---

### Syntax

```
(mac|ip|ipv6) acl NAME
[no] (mac|ip|ipv6) acl NAME
```

---

### Parameter

(mac ip ipv6)	Specify a type of ACL to binding to interface
NAME	Specify the name of ACL

---

### Default

No default is defined

---

### Mode

Interface Configuration

---

### Usage

Use the **(mac|ip|ipv6) acl NAME** command to bind an ACL to interfaces. An interface can bind only one ACL or QoS policy. Use the **no** form of this command to return to unbind an ACL from interface.

---

### Example

```
switch(config)# interface fa1
switch(config-if)# mac acl test
switch(config-if)# do show running-config interfaces fa1
interface fa1
  mac acl test
```

---

## show acl

---

### Syntax

```
show acl
show (mac|ip|ipv6) acl
show (mac|ip|ipv6) acl NAME
```

---

### Parameter

(mac ip ipv6)	Specify a type of ACL to show
NAME	Specify the name of ACL

---

---

### Default

No default is defined



<b>Mode</b>	Global Configuration Context Configuration
<b>Usage</b>	Use the <b>show acl</b> command to show created ACLs. You can specify mac ` ip or ipv6 to show specific type ACL or specify unique name string to show ACL with the name.
<b>Example</b>	The example shows how to show all IP ACL. Switch334455(config)#  <b>show ip acl</b>  IP access list iptest sequence 1 deny ip 192.168.1.80/255.255.255.255 any

## **show acl utilization**

<b>Syntax</b>	<b>show acl utilization</b>
<b>Parameter</b>	None
<b>Default</b>	No default is defined
<b>Mode</b>	Global Configuration
<b>Usage</b>	Use the <b>show acl utilization</b> command to show the usage of PIE of ASIC. When an ACL bind to interface, it needs ASIC resource to help to filter packet. An ASIC has limited resource. This command help user to know the PIE usage of AISC.
<b>Example</b>	The example shows how to show utilization  Switch(config-if)# do show acl utilization Type: sys usage: 128 Type: mac ACL usage: 128 Type: IPv4 ACL usage: 128 Type: IPv6 ACL usage: 128

## **3. Administration**

### **configure**

<b>Syntax</b>	<b>configure</b>
---------------	------------------



**Parameter**

**Default** No default value for this command.

**Mode** Privileged EXEC

**Usage** Use “**configure**” command to enter global configuration mode. In global configuration mode, the prompt will show as “**Switch(config)#**”.

**Example** This example shows how to enter global configuration mode.

```
Switch# configure
Switch(config) #
```

**clear arp**

**Syntax** **clear arp [A.B.C.D]**

**Parameter** *A.B.C.D* Specify specific arp entry to clear.

**Default** No default value for this command.

**Mode** User EXEC  
Privileged EXEC

**Usage** Use “**clear arp**” command to clear all or specific one arp entry.

**Example** This example shows how to clear all arp entries.

```
Switch(config) # clear arp
```

**clear service**

**Syntax** **clear (telnet | ssh)**

**Parameter** **telnet** Clear all telnet sessions.  
**ssh** Clear all ssh sessions.



**Default** No default value for this command.

**Mode** Privileged EXEC

**Usage** Use “**clear service**” command to kill all existing sessions for the select service.

**Example** This example shows how to enable telnet service and show current telnet service status.

Switch# **clear telnet**

---

## **enable**

**Syntax** **enable** [<1-15>]  
**disable** [<1-14>]

**Parameter** <1-15> Specify privileged level to enable  
<1-14> Specify privileged level to disable

---

**Default** Default privilege level is 15 if no privilege level is specified on enable command.

Default privilege level is 1 if no privilege level is specified on disable command.

**Mode** User EXEC

**Usage** In User EXEC mode, user only allows to do a few actions. Most of commands are only available in privileged EXEC mode. Use “**enable**” command to enter the privileged mode to do more actions on switch.

In privileged EXEC mode, use “**exit**” command is able to go back to user EXEC mode with original user privilege level. If you need to go back to user EXEC mode with different privilege level, use “**disable**” command to specify the privilege level you need.

In privileged EXEC mode, the prompt will show “**Switch#**”

**Example** This example shows how to enter privileged EXEC mode and show current privilege level.

Switch> **enable**  
Switch# **show privilege**  
Current CLI Username:

---



Current CLI Privilege: 15

This example show how to enter user EXEC mode with privilege 3.

```
Switch# disable 3
Switch> show
privilege Current
CLI Username:
Current CLI Privilege: 3
```

---

## end

---

### Syntax

**end**

---

### Parameter

---

### Default

No default value for this command.

---

### Mode

Privileged EXEC  
Global  
Configuration  
Interface  
Configuration Line  
Configuration  
.....

---

### Usage

Use “**end**” command to return to privileged EXEC mode directly. Every mode except User EXEC mode has the “**end**” command.

---

### Example

This example shows how to enter Interface Configuration mode and use end command to go back to privileged EXEC mode

```
Switch# configure
Switch(config)# interface f1
Switch(config-if)# end
Switch#
```

---

## exit

---

### Syntax

**exit**

---

### Parameter

---

### Default

No default value for this command.



# Command Line Interface

## User Guide

---

<b>Mode</b>	User EXEC Privileged EXEC Global Configuration
-------------	--

---



Interface  
Configuration Line  
Configuration  
.....

### Usage

In User EXEC mode, “exit” command will close current CLI session. In other modes, “exit” command will go to the parent mode. And every mode has the “exit” command.

### Example

This example shows how to enter privileged EXEC mode and use exit command to go back to user EXEC mode.

```
Switch> enable  
Switch# exit  
Switch>
```

## history

### Syntax

```
history <1-256>  
no history
```

### Parameter

<1-256>	Specify maximum CLI history entry number.
---------	---

### Default

Default maximum history entry number is 128.

### Mode

Line Configuration

### Usage

Use “**history**” command to specify the maximum commands history number for CLI running on console, telnet or ssh service. Every command input by user will record in history buffer. If all history commands exceed configured history number, older ones will be deleted from buffer.

Use “**no history**” to disable the history feature. And use “**show history**” to show all history commands.



## Command Line Interface User Guide

### Example

This example shows how to change console history number to 100, telnet history number to 150 and ssh history number to 200.

```
Switch(config)# line console
Switch(config-line)# history 100
Switch(config-line)# exit
Switch(config)# line telnet
Switch(config-line)# history 150
Switch(config-line)# exit
Switch(config)# line ssh
Switch(config-line)# history 200
Switch(config-line)# exit
```

This example shows how show line information.

```
Switch# show line
Console =====
Session Timeout : 10 (minutes)
```



```
History Count      :  
100 Password Retry  
                  :  
      3  
      Silent Time    : 0 (seconds)  
Telnet  
=====  
      Telnet Server   : disabled  
      Session Timeout : 10 (minutes)  
      History Count   : 150  
      Password Retry   : 3  
      Silent Time     : 0 (seconds)  
SSH =====  
      SSH Server     : disabled  
      Session Timeout : 10 (minutes)  
      History Count   : 200  
      Password Retry   : 3  
      Silent Time     : 0 (seconds)
```

This example shows how show history commands.

```
Switch# show history  
Maximum History Count: 100  
-----  
1. enable  
2. configure  
3. line console  
4. exit  
5. show history  
6. line  
7. exit  
8. show history  
9. configure  
10. line  
11. line console  
12. exit  
13. line console  
14. history 100  
15. exit  
16. show history  
17. exit  
18. show history
```

## hostname

---

### Syntax

**hostname WORD**

---

### Parameter

*WORD*      Specify the hostname of the switch.

---

### Default

Default name string is “Switch”.

---

### Mode

Global Configuration



# Command Line Interface

## User Guide

---

### Usage

Use “**hostname**” command to modify hostname of the switch. The system name is also used to be CLI prompt.



---

**Example**

This example shows how to modify contact information

```
Switch(config)# hostname myname  
myname(config) #
```

---

**interface**

---

**Syntax**

```
interface IF_PORTS  
interface range IF_PORTS
```

---

**Parameter**

*IF\_PORTS*      Specify the port to select. This parameter allows partial port name and ignore case. For Example:  
fa1  
FastEthernet3  
Gigabit4  
.....

If port range is specified, the list format is also available. For Example:

```
fa1,3,5  
fa2,gi1-3  
.....
```

---

---

**Default**

No default value for this command.

---

**Mode**

Global Configuration

---

**Usage**

Some configurations are port based. In order to configure these configurations, we need to enter Interface Configuration mode to configure them. Use “**interface**” command to enter the Interface Configuration mode and select the port to be configured.

In Interface Configuration mode, the prompt will show as “**Switch(config-if)#[**”

---

**Example**

This example shows how to enter Interface Configuration mode

```
Switch# configure  
Switch(config)# interface fa1  
Switch(config-if) #
```

---

**ip address**

---

**Syntax**

**ip address *A.B.C.D* [mask *A.B.C.D*]**



<b>Parameter</b>	<b>address A.B.C.D</b> Specify IPv4 address for switch <b>mask A.B.C.D</b> Specify net mask address for switch
<b>Default</b>	Default IP address is 192.168.1.1 and default net mask is 255.255.255.0.
<b>Mode</b>	Global Configuration
<b>Usage</b>	Use “ <b>ip address</b> ” command to modify administration ipv4 address. This address is very important. When we try to use telnet, ssh, http, https, snmp... to connect to the switch, we need to use this ip address to access it.
<b>Example</b>	This example shows how to modify the ipv4 address of the switch. <pre>Switch(config)# ip address 192.168.1.200 mask 255.255.255.0</pre> This example shows how to show current ipv4 address of the switch. <pre>Switch# show ip IP Address: 192.168.1.200 Subnet Netmask: 255.255.255.0 Default Gateway: 192.168.1.254</pre>

## ip default-gateway

<b>Syntax</b>	<b>ip default-gateway A.B.C.D</b> <b>no ip default-gateway</b>
<b>Parameter</b>	<b>A.B.C.D</b> Specify default gateway IPv4 address for switch
<b>Default</b>	Default IP address of default gateway is 192.168.1.254.
<b>Mode</b>	Global Configuration
<b>Usage</b>	Use “ <b>ip default-gateway</b> ” command to modify default gateway address. And use “ <b>no ip default-gateway</b> ” to restore default gateway address to factory default.
<b>Example</b>	This example shows how to modify the ipv4 address of the switch. <pre>Switch(config)# ip default-gateway 192.168.1.100</pre> This example shows how to show current ipv4 default gateway of the switch. <pre>Switch# show ip IP Address: 192.168.1.1 Subnet Netmask: 255.255.255.0 Default Gateway: 192.168.1.100</pre>



## ip dhcp

---

### Syntax

```
ip dhcp  
no ip dhcp
```

---

### Parameter

---

### Default

Default DHCP client is disabled.

---

### Mode

Global Configuration

---

### Usage

Use “**ip dhcp**” command to enabled dhcp client to get IP address from remote DHCP server.

Use “**no ip dhcp**” command to disabled dhcp client and use static ip address.

---

### Example

This example shows how to enable dhcp client.

```
Switch(config)# ip dhcp
```

This example shows how to show current dhcp client state of the switch.

```
Switch# show ip dhcp  
DHCP Status : enabled
```

## ip dns

---

### Syntax

```
ip dns A.B.C.D [A.B.C.D]  
no ip dns [A.B.C.D]
```

---

### Parameter

*A.B.C.D*      Specify the DNS server ip address.

---

### Default

Default IP address of DNS server is 168.95.1.1 and 168.95.192.1.

---

### Mode

Global Configuration

---

### Usage

Use “**ip dns**” command to modify DNS server address. And use “**no ip dns**” to delete existing DNS server.

---

### Example

This example shows how to modify the DNS server of the switch.

```
Switch(config)# ip dns 111.111.111.111 222.222.222.222
```



This example shows current DNS server of the switch.

```
Switch# show ip dns
DNS lookup is enabled
DNS Server 1 : 111.111.111.111
DNS Server 2 : 222.222.222.222
```

---

## ip dns lookup

---

### Syntax

```
ip dns lookup
no ip dns lookup
```

---

### Parameter

---

### Default

Default DNS lookup is enabled

---

### Mode

Global Configuration

---

### Usage

Use “**ip dns lookup**” command to enable the Domain Name to IP address service. And use “**no ip dns**” to disable the DNS service.

---

### Example

This example enables the DNS service on the system.

```
Switch(config)# ip dns lookup
```

This example shows the DNS service status.

```
Switch# show ip dns
DNS Server 1 : 111.111.111.111
DNS Server 2 : 222.222.222.222
```

---

## ipv6 autoconfig

---

### Syntax

```
ipv6 autoconfig
no ipv6 autoconfig
```

---

### Parameter

---

### Default

Default IPv6 auto config is enabled.

---

### Mode

Global Configuration



---

**Usage**

Use “**ipv6 autoconfig**” command to enable IPv6 auto configuration feature. Use “**no ipv6 autoconfig**” command to disable IPv6 auto configuration feature.

---

**Example**

This example shows how to disable IPv6 auto config.

```
Switch(config)# no ipv6 autoconfig
```

This example shows how to show current IPv6 auto config state.

```
Switch# show ipv6
IPv6 DHCP Configuration      : Disabled
IPv6 DHCP DUID                :
IPv6 Auto Configuration       : Disabled
IPv6 Link Local Address       : fe80::dcad:beff:feef:102/64
IPv6 static Address           : fe80::20e:2eff:fef1:4b3c/128
IPv6 static Gateway Address   : ::
IPv6 in use Address          : fe80::dcad:beff:feef:102/64
IPv6 in use Gateway Address   : ::
```

---

## ipv6 address

---

**Syntax**

**ipv6 address X:X::X:X prefix <0-128>**

---

**Parameter**

**address X:X::X:X**      Specify IPv6 address for switch

**prefix <0-128>**      Specify IPv6 prefix length for switch

---

---

**Default**

No default ipv6 address on the switch.

---

**Mode**

Global Configuration

---

**Usage**

Use “**ipv6 address**” command to specify static IPv6 address.

---

**Example**

This example shows how to add static ipv6 address of the switch.

```
Switch(config)# ipv6 address fe80::20e:2eff:fef1:4b3c prefix
128
```

This example shows how to show current ipv6 address of the switch.

```
Switch# show ipv6
IPv6 DHCP Configuration      : Disabled
IPv6 DHCP DUID                :
IPv6 Auto Configuration       : Enabled
IPv6 Link Local Address       : fe80::dcad:beff:feef:102/64
IPv6 static Address           : fe80::20e:2eff:fef1:4b3c/128
IPv6 static Gateway Address   : ::
IPv6 in use Address          : fe80::dcad:beff:feef:102/64
IPv6 in use Gateway Address   : ::
```

---



## ipv6 default-gateway

Syntax	<b>ipv6 default-gateway</b> <i>X:X::X:X</i>
Parameter	<i>X:X::X:X</i> Specify default gateway IPv6 address for switch
Default	No default ipv6 default gateway address on the switch.
Mode	Global Configuration
Usage	Use “ <b>ipv6 default-gateway</b> ” command to modify default gateway IPv6 address.
Example	<p>This example shows how to modify the ipv6 default gateway address of the switch.</p> <pre>Switch(config)# ipv6 default-gateway fe80::dcad:beff:feef:103  Switch# show ipv6 IPv6 DHCP Configuration      : Disabled IPv6 DHCP DUID               : IPv6 Auto Configuration     : Enabled IPv6 Link Local Address     : fe80::dcad:beff:feef:102/64 IPv6 static Address          : fe80::20e:2eff:fef1:4b3c/128 IPv6 static Gateway Address : ::  IPv6 in use Address         : fe80::dcad:beff:feef:102/64 IPv6 in use Gateway Address : ::</pre>

## ipv6 dhcp

Syntax	<b>ipv6 dhcp</b> <b>no ipv6 dhcp</b>
Parameter	
Default	Default DHCPv6 client is disabled.
Mode	Global Configuration
Usage	Use “ <b>ipv6 dhcp</b> ” command to enabled dhcpcv6 client to get IP address from remote DHCPv6 server. Use “ <b>no ipv6 dhcp</b> ” command to disabled dhcpcv6 client and use static ipv6



address or ipv6 auto config address.

---

**Example**

This example shows how to enable dhcp client.

```
Switch (config) # ipv6 dhcp
```

This example shows how to show current dhcpcv6 client state of the switch.

```
Switch# show ipv6 dhcp  
DHCPv6 Status : enabled
```

---

## ip service

---

**Syntax**

```
ip (telnet | ssh | http | https)  
no ip (telnet | ssh | http | https)
```

---

**Parameter**

<b>telnet</b>	Enable/Disable telnet service
<b>ssh</b>	Enable/Disable ssh service
<b>http</b>	Enable/Disable http service
<b>https</b>	Enable/Disable https service

---

---

**Default**

Default telnet service is disabled.  
Default ssh service is  
disabled. Default http service  
is enabled. Default https  
service is disabled.

---

**Mode**

Global Configuration

---

**Usage**

Use “ip service” command to enable all kinds of ip services. Such as telnet,  
ssh, http and https.  
Use no form to disable service.

---



# Command Line Interface

## User Guide

### Example

This example shows how to enable telnet service and show current telnet service status.

```
Switch(config)# ip telnet
Telnethd daemon enabled.
Switch(config)# exit
Switch# show line telnet
Telnet =====
    Telnet Server      : enabled
    Session Timeout   : 10 (minutes)
    History Count     : 128
    Password Retry    : 3
    Silent Time       : 0 (seconds)
```

This example shows how to enable https service and show current https service status.

```
Switch(config)# ip https
```



---

```
Switch(config)# exit
Switch# show ip https
    HTTPS daemon : enabled
Session Timeout : 10 (minutes)
```

---

## ip session-timeout

### Syntax

**ip (http | https) session-timeout <0-86400>**

### Parameter

<b>http</b>	Specify session timeout for http service.
<b>https</b>	Specify session timeout for https service.
<0-86400>	Specify session timeout minutes. 0 means never timeout.

### Default

Default session timeout for http and https is 10 minutes.

### Mode

Global Configuration

### Usage

Use “**ip session-timeout**” command to specify the session timeout value for http or https service. When user login into WEBUI and do not do any action after session timeout will be logged out.

### Example

This example shows how to change http session timeout to 15min and https session timeout to 20min

```
Switch(config)# ip http session-timeout 15
Switch(config)# ip https session-timeout 20
```

This example shows how to enable https service and show current https service status.

```
Switch# show ip http
    HTTPS daemon : enabled
Session Timeout : 15 (minutes)
Switch# show ip https
    HTTPS daemon : disabled
Session Timeout : 20 (minutes)
```

## ip ssh

### Syntax

**ip ssh (v1|v2|all)**  
**no ip ssh (v1|v2|all)**

### Parameter

<b>v1</b>	Generate/Delete version 1 key files
<b>v2</b>	Generate/Delete version 2 key files
<b>all</b>	Generate/Delete version 1 and 2 key files



<b>Default</b>	Version 2 key files will be generated by default
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use “ip ssh” command to generate the key files for ssh connection. Use no form to delete key files. SSH connection may not connect if no any v1 or v2 ssh key files exist.</p>
<b>Example</b>	<p>This example shows how to delete and re-generate ssh version 2 key files.</p> <pre>Switch(config)# no ip ssh v2 Switch(config)# do show flash   File Name          File Size      Modified -----   startup-config      1913        2000-01-01 08:29:10   rsa1                976         2000-01-05 23:28:38   ssl_cert             875         2000-01-05 23:03:20   image0 (active)    4856825     2014-04-02 15:17:34  Switch(config)# ip ssh v2  Generating a SSHv2 default RSA Key. This may take a few minutes, depending on the key size.  Generating a SSHv2 default DSA Key. This may take a few minutes, depending on the key size.  Switch(config)# do show flash   File Name          File Size      Modified -----   startup-config      1913        2000-01-01 08:29:10   rsa1                976         2000-01-05 23:28:38   rsa2                1675        2000-01-05 23:34:43   dsa2                668         2000-01-05 23:34:58   ssl_cert             875         2000-01-05 23:03:20   image0 (active)    4856825     2014-04-02 15:17:34</pre>

## line

<b>Syntax</b>	<code>line ( console   telnet   ssh )</code>						
<b>Parameter</b>	<table><tr><td><b>console</b></td><td>Select console line to configure.</td></tr><tr><td><b>telnet</b></td><td>Select telnet line to configure.</td></tr><tr><td><b>ssh</b></td><td>Select ssh line to configure.</td></tr></table>	<b>console</b>	Select console line to configure.	<b>telnet</b>	Select telnet line to configure.	<b>ssh</b>	Select ssh line to configure.
<b>console</b>	Select console line to configure.						
<b>telnet</b>	Select telnet line to configure.						
<b>ssh</b>	Select ssh line to configure.						
<b>Default</b>	No default value for this command.						



<b>Mode</b>	Global Configuration
-------------	----------------------

<b>Usage</b>	Some configurations are line based. In order to configure these configurations, we need to enter Line Configuration mode to configure them. Use “ <b>line</b> ” command to enter the Line Configuration mode and select the line to be configured.
--------------	--

In Line Configuration mode, the prompt will show as “**Switch(config-line)#[/]**”

<b>Example</b>	This example shows how to enter Interface Configuration mode Switch# <b>configure</b> Switch(config)# <b>line console</b> Switch(config-line)#[/]
----------------	--

## reboot

<b>Syntax</b>	<b>reboot</b>
---------------	---------------

<b>Parameter</b>	
------------------	--

<b>Default</b>	No default value for this command.
----------------	------------------------------------

<b>Mode</b>	Privileged EXEC
-------------	-----------------

<b>Usage</b>	Use “ <b>reboot</b> ” command to make system hot restart.
--------------	---

<b>Example</b>	This example shows how to restart the system Switch# <b>reboot</b>
----------------	---

## enable password

<b>Syntax</b>	<b>enable [privilege &lt;1-15&gt;] (password <i>UNENCRYPY-PASSWORD</i>   secret <i>UNENCRYPY-PASSWORD</i>   secret encrypted <i>ENCRYPT-PASSWORD</i>) no enable [privilege &lt;0-15&gt;]</b>
---------------	--

<b>Parameter</b>	<b>privilege &lt;0-15&gt;</b> Specify the privilege level to configure. If no privilege level is specified, default is 15.
------------------	--

<b>password <i>UNENCRYPY-</i></b>	Specify password string and make it not encrypted.
-----------------------------------	--



*PASSWORD*

<b>secret</b> <i>UNENCRYPY- PASSWORD</i>	Specify password string and make it encrypted.
<b>secret encrypted</b> <i>ENCRYPT- PASSWORD</i>	Enter an encrypted password. Use this keyword to enter a password that is already encrypted (for instance, a password that you copied from another the configuration file of another device).

---

**Default**

Default enable password for all privilege levels are “”.

---

**Mode**

Global Configuration

---

**Usage**

Use “**enable password**” command to edit password for each privilege level for enable authentication. And use “**no enable**” command to restore enable password to default empty value.

The only way to show this configuration is using “**show running-config**” command.

---

**Example**

This example shows how to edit enable password for privilege level 15  
Switch(config)# **enable secret enb1passwd**

---

**exec-timeout**

---

**Syntax**

**exec-timeout <0-65535>**

---

**Parameter**

*<0-65535>* Specify session timeout minutes. 0 means never timeout

---

---

**Default**

Default session timeout for all lines are 10 minutes.

---

**Mode**

Line Configuration

---

**Usage**

Use “**exec-timeout**” command to specify the session timeout value for CLI running on console, telnet or ssh service. When user login into CLI and do not do any action after session timeout will be logged out from the CLI session.



## Command Line Interface User Guide

### Example

This example shows how to change console session timeout to 15min ,telnet session timeout to 20min and ssh session timeout to 25min.

Switch(config)# line console

---



---

```
Switch(config-line)# exec-timeout
15 Switch(config-line)# exit
Switch(config)# line telnet
Switch(config-line)# exec-timeout
20 Switch(config-line)# exit
Switch(config)# line ssh
Switch(config-line)# exec-timeout
25 Switch(config-line)# exit
```

This example shows how show line information.

```
Switch# show line
Console =====
Session Timeout : 15 (minutes)
History Count   : 128
Password Retry  : 3
Silent Time     : 0 (seconds)
Telnet
=====
Telnet Server   : disabled
Session Timeout : 20 (minutes)
History Count   : 128
Password Retry  : 3
Silent Time     : 0 (seconds)
SSH
=====
SSH Server      : disabled
Session Timeout : 25 (minutes)
History Count   : 128
Password Retry  : 3
Silent Time     : 0 (seconds)
```

---

## password-thresh

---

### Syntax

**password-thresh <0-120>**

---

### Parameter

<0-120>	Specify password fail retry number. 0 means no limit.
---------	---

---

### Default

Default password fail retry number is 3.

---

### Mode

Line Configuration

---

### Usage

Use “**password-thresh**” command to specify the password fail retry number for CLI running on console, telnet or ssh service. When user input password to login and authenticate failed, the fail retry number will increase one. After fail retry number exceed configured one, the CLI will block login for the period of silent time which configured by the command “**silent-time**”.



## Command Line Interface User Guide

### Example

This example shows how to change console fail retry number to 4, telnet fail retry number to 5 and ssh fail retry number to 6.

```
Switch(config)# line console
Switch(config-line)# password-thresh 4
Switch(config-line)# exit
Switch(config)# line telnet
```



```
Switch(config-line)#
password-thresh 5
Switch(config-line)#
exit
Switch(config)#
line ssh
Switch(config-line)#
password-thresh 6
Switch(config-line)#
exit
```

This example shows how show line information.

```
Switch# show line
Console =====
Session Timeout : 10
(minutes) History Count :
128
Password Retry : 4
Silent Time     : 0 (seconds)
Telnet =====
Telnet Server   : disabled
Session Timeout : 10
(minutes) History Count :
128
Password Retry : 5
Silent Time     : 0 (seconds)
SSH =====
SSH Server     : disabled
Session Timeout : 10
(minutes) History Count :
128
Password Retry : 6
Silent Time     : 0 (seconds)
```

## ping

### Syntax

**ping** *HOSTNAME* [**count** <1-99999999>]

### Parameter

<i>HOSTNAME</i>	Specify IPv4/IPv6 address or domain name to ping.
<b>count</b> <1-99999999>	Specify how many times to ping.

### Default

No default value for this command.

### Mode

User EXEC  
Privileged EXEC

### Usage

Use “ping” command to do network ping diagnostic.



# Command Line Interface

## User Guide

---

### Example

This example shows how to ping remote host 192.168.1.111.

```
Switch# ping 192.168.1.111
PING 192.168.1.111 (192.168.1.111): 56 data bytes
64 bytes from 192.168.1.111: icmp_seq=0 ttl=128 time=10.0 ms
64 bytes from 192.168.1.111: icmp_seq=1 ttl=128 time=0.0 ms
64 bytes from 192.168.1.111: icmp_seq=2 ttl=128 time=0.0 ms
64 bytes from 192.168.1.111: icmp_seq=3 ttl=128 time=0.0 ms

--- 192.168.1.111 ping statistics ---
4 packets transmitted, 4 packets received, 0% packet loss
round-trip min/avg/max = 0.0/2.5/10.0 ms
```

---



## traceroute

---

### Syntax

**traceroute *A.B.C.D* [*max\_hop <2-255>*]**

---

### Parameter

*A.B.C.D*      Specify IPv4 to trace.  
**max\_hop <2-255>**      Specify maximum hop to trace.

---

### Default

No default value for this command.

---

### Mode

User EXEC  
Privileged EXEC

---

### Usage

Use “**traceroute**” command to do network trace route diagnostic.

---

### Example

This example shows how to trace route host 192.168.1.111.

```
Switch# traceroute 192.168.1.111
traceroute to 192.168.1.111 (192.168.1.111), 30 hops max, 40
byte packets
 1  192.168.1.111 (192.168.1.111)  0 ms  10 ms  0 ms
```

---

## show arp

---

### Syntax

**show arp**

---

### Parameter

---

### Default

No default value for this command.

---

### Mode

User EXEC  
Privileged EXEC

---

### Usage

Use “**show arp**” command to show all arp entries.

---

### Example

This example shows how to show arp entries.

```
Switch# show arp
Address      HWtype  HWaddress          Flags Mask       Iface
192.168.1.111 ether   00:0E:2E:F1:4B:3C  C          00:0E:2E:*
```

---



## **show cpu utilization**

---

### **Syntax**

**show cpu utilization**

---

### **Parameter**

---

### **Default**

No default value for this command.

---

### **Mode**

Privileged EXEC

---

### **Usage**

Use “**show cpu utilization**” command to show current CPU utilization.

---

### **Example**

This example shows how to show current CPU utilization.

```
Switch# show cpu utilization
CPU utilization
-----
Current: 30%
```

## **show history**

---

### **Syntax**

**show history**

---

### **Parameter**

---

### **Default**

No default value for this command.

---

### **Mode**

User EXEC  
Privileged EXEC  
Global  
Configuration

---

### **Usage**

Use “**show history**” to show commands we input before.



## Command Line Interface User Guide

---

### Example

This example shows how show history commands.

```
Switch# show history
Maximum History Count: 100
-----
1. enable
2. configure
3. line console
```

---



---

```
4. exit
5. show history
6. line
7. exit
8. show history
9. configure
10. line
11. line console
12. exit
13. line console
14. history 100
15. exit
16. show history
17. exit
18. show history
```

---

## show info

---

### Syntax

**show info**

---

### Parameter

---

### Default

No default value for this command.

---

### Mode

User EXEC  
Privileged EXEC

---

### Usage

Use “**show info**” command to show system summary information.

---

### Example

This example shows how to show system version.

```
Switch# show info
System Name      : Switch
System Location  : Default Location
System Contact   : Default Contact
MAC Address     : DE:AD:BE:EF:01:02
IP Address       : 192.168.1.1
Subnet Mask     : 255.255.255.0
Loader Version   : 1.3.0.26225
Loader Date      : Thu May 17 15:19:42 CST 2012
Firmware Version : 2.5.0-beta.32811
Firmware Date    : Mon Sep 24 19:33:42 CST 2012
System Object ID : 1.3.6.1.4.1.27282.3.2.10
System Up Time   : 0 days, 1 hours, 49 mins, 29 secs
```

---

## show ip

---

### Syntax

**show ip**



**Parameter**

**Default** No default value for this command.

**Mode** User EXEC  
Privileged EXEC

**Usage** Use “**show ip**” command to show system IPv4 address, net mask and default gateway.

**Example** This example shows how to show current ipv4 address of the switch.

```
Switch# show ip
IP Address: 192.168.1.200
Subnet Netmask: 255.255.255.0
Default Gateway: 192.168.1.254
```

## **show ip dhcp**

**Syntax** **show ip dhcp**

**Parameter**

**Default** No default value for this command.

**Mode** User EXEC  
Privileged EXEC

**Usage** Use “**show ip dhcp**” command to show IPv4 dhcp client enable state.

**Example** This example shows how to show current dhcp client state of the switch.

```
Switch# show ip dhcp
DHCP Status : enabled
```

## **show ip dns**

**Syntax** **show ip dns**

**Parameter**



**Default** No default value for this command.

**Mode** User EXEC  
Privileged EXEC

**Usage** Use “**show ip dns**” command to show system IPv4 DNS addresses.

**Example** This example shows how to show current ipv4 address of the switch.

```
Switch# show ip dns
DNS lookup is enabled
DNS Server 1 : 168.95.1.1
DNS Server 2 : 168.95.192.1
```

## show ip http

**Syntax** **show ip (http|https)**

**Parameter**

**Default** No default value for this command.

**Mode** Privileged EXEC

**Usage** Use “**show ip http**” command to show HTTP/HTTPS information.

**Example** This example shows how to show current ipv4 address of the switch.

```
Switch# show ip http
HTTP daemon : enabled
Session Timeout : 10 (minutes)

Switch# show ip https
HTTPS daemon : enabled
Session Timeout : 10 (minutes)
```

## show ipv6

**Syntax** **show ipv6**

**Parameter**

**Default** No default value for this command.

**Mode** User EXEC  
Privileged EXEC

**Usage** Use “**show ipv6**” command to show system IPv6 address, net mask, default gateway and auto config state.

**Example** This example shows how to show current ipv6 address of the switch.

```
Switch# show ipv6
IPv6 DHCP Configuration      : Disabled
IPv6 DHCP DUID               :
IPv6 Auto Configuration     : Enabled
IPv6 Link Local Address     : fe80::dcad:beff:feef:102/64
IPv6 static Address          : fe80::20e:2eff:fef1:4b3c/128
IPv6 static Gateway Address : :::
IPv6 in use Address         : fe80::dcad:beff:feef:102/64
IPv6 in use Gateway Address : :::
```

## show ipv6 dhcp

**Syntax** **show ipv6 dhcp**

**Parameter**

**Default** No default value for this command.

**Mode** User EXEC  
Privileged EXEC

**Usage** Use “**show ipv6 dhcp**” command to show system IPv6 dhcp client enable state.

**Example** This example shows how to show current dhcpcv6 client state of the switch.

```
Switch# show ipv6 dhcp
DHCPv6 Status : enabled
```

## show line

**Syntax** **show line [(console | telnet | ssh)]**

**Parameter** **console** Select console line to show.

<b>telnet</b>	Select telnet line to show.
<b>ssh</b>	Select ssh line to show.

---

**Default** No default value for this command.

---

**Mode** Privileged EXEC

---

**Usage** Use “**show line**” command to show all line configurations including session timeout, history count, password retry number and silent time. For telnet and ssh, it also shows the service enable/disable state.

---

**Example** This example shows how show all lines’ information.

```
Switch# show line
Console =====
Session Timeout : 15 (minutes)
History Count   : 128
Password Retry  : 3
Silent Time     : 0 (seconds)
Telnet =====
Telnet Server   : disabled
Session Timeout : 20 (minutes)
History Count   : 128
Password Retry  : 3
Silent Time     : 0 (seconds)
SSH =====
SSH Server      : disabled
Session Timeout : 25 (minutes)
History Count   : 128
Password Retry  : 3
Silent Time     : 0 (seconds)
```

---

## show memory statistics

---

**Syntax** **show memory statistics**

---

**Parameter**

---

**Default** No default value for this command.

---

**Mode** Privileged EXEC

---

**Usage** Use “**show memory statistics**” command to show current memory utilization.



**Example**

This example show how to show current system memory statistics.

```
Switch# show memory statistics
      total (KB)     used (KB)     free (KB)    shared (KB)   buffer (KB)   cache (KB)
-----+-----+-----+-----+-----+-----+
Mem:       62408        56424       5984          0         1320       19328
-/+ buffers/cache:           35776      26632
Swap:        0            0            0
```

---

## show privilege

**Syntax**

**show privilege**

**Parameter**

**Default**

No default value for this command.

**Mode**

User EXEC  
Privileged EXEC

**Usage**

Use “**show privilege**” command to show the privilege level of the current user.

**Example**

This example shows how to show arp entries.

```
Switch# show privilege
Current CLI Username: admin
Current CLI Privilege: 15
```

---

## show username

**Syntax**

**show username**

**Parameter**

**Default**

No default value for this command

**Mode**

Privileged EXEC



**Usage**

Use “**show username**” command show all user accounts in local database.

**Example**

This example shows how to show existing user accounts.

```
Switch# show username
Priv | Type      | User Name          |           Password
-----+-----+-----+
 01  | secret    |                   | dnXencJRWf1V6
 15  | secret    |           admin | FzjrGO6vfbERY
 15  | secret    |           test  | 7p57T9yMkViSUS
```

---

## show users

**Syntax**

**show users**

**Parameter**

**Default**

No default value for this command

**Mode**

Privileged EXEC

**Usage**

Use “**show users**” command show information of all active users.

**Example**

This example shows how to show existing user accounts.

```
Switch# show users
Username        Protocol        Location
-----+-----+-----+
  admin       console       0.0.0.0
  admin       telnet        192.168.1.111
  admin       ssh           192.168.1.111
```

---

## show version

**Syntax**

**show version**

**Parameter**

**Default**

No default value for this command.



<b>Mode</b>	User EXEC Privileged EXEC
<b>Usage</b>	Use “ <b>show version</b> ” command to show loader and firmware version and build date.
<b>Example</b>	This example shows how to show system version. Switch# <b>show version</b> Loader Version : 1.3.0.26225 Loader Date : Thu May 17 15:19:42 CST 2012 Firmware Version : 2.5.0-beta.32811 Firmware Date : Mon Sep 24 19:33:42 CST 2012

## **silent-time**

<b>Syntax</b>	<b>silent-time &lt;0-65535&gt;</b>
<b>Parameter</b>	<b>&lt;0-65535&gt;</b> Specify silent time with unit seconds. 0 means do not silent.
<b>Default</b>	Default silent time is 0.
<b>Mode</b>	Line Configuration
<b>Usage</b>	Use “ <b>silent time</b> ” command to specify the silent time for CLI running on console, telnet or ssh service. When user input password to login and authenticate failed, the fail retry number will increase one. After fail retry number exceed configured one, the CLI will block login for the period of silent time which configured by the command “ <b>silent-time</b> ”.
<b>Example</b>	This example shows how to change console silent time to 10, telnet silent time to 15 and ssh silent time to 20. Switch(config)# <b>line console</b> Switch(config-line)# <b>silent-time 10</b> Switch(config-line)# <b>exit</b> Switch(config)# <b>line telnet</b> Switch(config-line)# <b>silent-time 15</b> Switch(config-line)# <b>exit</b> Switch(config)# <b>line ssh</b> Switch(config-line)# <b>silent-time 20</b> Switch(config-line)# <b>exit</b>
	This example shows how show line information. Switch# <b>show line</b> Console ====== Session Timeout : 10 (minutes)



```
History Count      :  
128 Password Retry  
      :  
      3  
      Silent Time      : 10 (seconds)  
Telnet  
=====  
      Telnet Server      : disabled  
      Session Timeout : 10  
      (minutes) History Count :  
      128  
      Password Retry   : 3  
      Silent Time      : 15 (seconds)  
SSH  
=====  
      SSH Server      : disabled  
      Session Timeout : 10  
      (minutes) History Count :  
      128  
      Password Retry   : 3  
      Silent Time      : 20 (seconds)
```

## ssl

---

### Syntax

**ssl**

---

### Parameter

---

### Default

No default value for this command.

---

### Mode

Global Configuration

---

### Usage

Use “ssl” command to generate security certificate files such as RSA, DSA.

---

### Example

This example shows how to generate certificate files.

```
Switch(config)# ssl
```

This example shows how to show the certificate file lists.

```
Switch# show flash  
-----  
File Name          File Size       Modified  
-----  
startup-config     1191           2000-01-01 00:00:23  
backup-config      1607           2000-01-01 08:36:23  
rsa1               974            2000-01-01 00:00:18  
rsa2               1675           2000-01-01 00:00:18  
dsa2               668            2000-01-01 00:00:18  
ssl_cert           993            2000-01-01 00:00:18  
image0 (active)    4372401        2012-09-24 01:57:29  
image1 (backup)    0
```

---

## system name



# **Command Line Interface**

## **User Guide**

---

### **Syntax**

**system name *NAME***



<b>Parameter</b>	<i>NAME</i>	Specify system name string.
<b>Default</b>		Default name string is “Switch”.
<b>Mode</b>		Global Configuration
<b>Usage</b>		Use “ <b>system name</b> ” command to modify system name information of the switch. The system name is also used to be CLI prompt.
<b>Example</b>		<p>This example shows how to modify contact information</p> <pre>Switch(config)# system name myname myname(config)#</pre> <p>This example shows how to show system name information</p> <pre>Switch# show info System Name      : myname System Location  : Default Location System Contact   : Default Contact MAC Address     : DE:AD:BE:EF:01:02 IP Address       : 192.168.1.1 Subnet Mask     : 255.255.255.0 Loader Version   : 1.3.0.26225 Loader Date      : Thu May 17 15:19:42 CST 2012 Firmware Version : 2.5.0-beta.32811 Firmware Date    : Mon Sep 24 19:33:42 CST 2012 System Object ID : 1.3.6.1.4.1.27282.3.2.10 System Up Time   : 0 days, 0 hours, 2 mins, 37 secs</pre>

## system contact

<b>Syntax</b>	<b>system contact</b> <i>CONTACT</i>	
<b>Parameter</b>	<i>CONTACT</i>	Specify contact string.
<b>Default</b>		Default contact string is “Default Contact”.
<b>Mode</b>		Global Configuration
<b>Usage</b>		Use “ <b>system contact</b> ” command to modify contact information of the switch.



---

**Example**

This example shows how to modify contact information

```
Switch(config)# system contact callme
```

This example shows how to show system contact information

```
Switch# show info
```

```
System Name      : Switch
System Location  : Default Location
System Contact   : callme
MAC Address     : DE:AD:BE:EF:01:02
IP Address      : 192.168.1.1
Subnet Mask     : 255.255.255.0
Loader Version   : 1.3.0.26225
Loader Date      : Thu May 17 15:19:42 CST 2012
Firmware Version: 2.5.0-beta.32811
Firmware Date    : Mon Sep 24 19:33:42 CST 2012
System Object ID: 1.3.6.1.4.1.27282.3.2.10
System Up Time   : 0 days, 0 hours, 2 mins, 37 secs
```

---

## system location

---

**Syntax**

**system location** *LOCATION*

---

**Parameter**

*CONTACT*      Specify location string.

---

**Default**

Default location string is “Default Location”.

---

**Mode**

Global Configuration

---

**Usage**

Use “**system location**” command to modify location information of the switch.

---

**Example**

This example shows how to modify contact information

```
Switch(config)# system location home
```

This example shows how to show system location information

```
Switch# show info
```

```
System Name      : SwitchEF0102
System Location  : home
System Contact   : Default Contact
MAC Address     : DE:AD:BE:EF:01:02
IP Address      : 192.168.1.1
Subnet Mask     : 255.255.255.0
Loader Version   : 1.3.0.26225
Loader Date      : Thu May 17 15:19:42 CST 2012
Firmware Version: 2.5.0-beta.32811
Firmware Date    : Mon Sep 24 19:33:42 CST 2012
System Object ID: 1.3.6.1.4.1.27282.3.2.10
System Up Time   : 0 days, 0 hours, 2 mins, 37 secs
```

---



## terminal length

### Syntax

**terminal length <0-24>**

### Parameter

**<0-24>** Specify terminal length value. 0 means no limit.

### Default

Default terminal length is 24.

### Mode

User EXEC  
Privileged EXEC

### Usage

Use “**terminal length**” command to specify the maximum line number the terminal is able to print.

### Example

This example shows how to change terminal length.

```
Switch# terminal length 3
Switch# show running-config
SYSTEM CONFIG FILE ::= BEGIN
! System Description: RTK RTL8380-24FE-4GEC Switch
! System Version: v3.0.4.46766
--More--
```

## username

### Syntax

**username WORD<0-32> [privilege (admin|user)<0-15>] (nopassword | password UNENCRYPY-PASSWORD | secret UNENCRYPY-PASSWORD | secret encrypted ENCRYPT-PASSWORD)**

**no username WORD<0-32>**

### Parameter

**username WORD<0-32>** Specify user name to add/delete/edit.

**WORD<0-32>**

**privilege admin** Specify privilege level to be admin (privilege 15)

**privilege user** Specify privilege level to be user (privilege 1)

**privilege <0-15>** Specify custom privilege level

**password UNENCRYPY-PASSWORD** Specify password string and make it not encrypted.

**UNENCRYPY-PASSWORD**

**secret UNENCRYPY-PASSWORD** Specify password string and make it encrypted.

**UNENCRYPY-PASSWORD**

**secret encrypted ENCRYPT-PASSWORD** Enter an encrypted password. Use this keyword to enter a password that is already encrypted (for instance, a password that you copied from another the



---

configuration file of another device).

---

**Default**

Default username “admin” has password “admin” with privilege 15.

**Mode**

Global Configuration

**Usage**

Use “**username**” command to add a new user account or edit an existing user account. And use “**no username**” to delete an existing user account. The user account is a local database for login authentication.

**Example**

This example shows how to add a new user account.

```
Switch(config) # username test secret passwd
```

This example shows how to show existing user accounts.

```
Switch# show username
Priv | Type | User Name | Password
-----+-----+-----+-----+
 01 | secret |           | dnXencJRWf1V6
 15 | secret |           | FzjrGO6vfbERY
 15 | secret | admin | 7p57T9yMkVisUS
```

## 4. Authentication Manager

### authentication

**Syntax**

**authentication (dot1x|mac|web)**  
**no authentication (dot1x|mac|web)**

**Parameter**

**Default**

Default is disabled for all type

**Mode**

Global Configuration

**Usage**

Use “**authentication**” command to enable the global setting of 802.1x/MAC/WEB authentication network access control.  
Use the **no** form of this command to disable 802.1x/MAC/WEB authentication.

**Example**

The following example shows how to enable 802.1x/MAC/WEB authentication.

```
Switch(config) # authentication dot1x
```



```
Switch(config) # authentication mac
Switch(config) # authentication web
Switch# show authentication
Autentication dot1x state      :
enabled Autentication mac state:
enabled Autentication web state:
enabled
Guest VLAN                      : enabled (3)
Mac-auth Radius User ID Format:
XXXXXXXXXXXXXX
.....
```

---

## authentication (Interface)

---

### Syntax

**authentication (dot1x|mac|web)**  
**no authentication (dot1x|mac|web)**

---

### Parameter

---

### Default

Default is disabled for all type

---

### Mode

Interface Configuration

---

### Usage

Use “**authentication**” interface command to enable the port setting of 802.1x/MAC/WEB authentication network access control.  
Use the **no** form of this command to disable 802.1x/MAC/WEB authentication.

---

### Example

The following example shows how to enable 802.1x/MAC/WEB authentication.

```
Switch(config) # interface fa1
Switch(config-if) # authentication dot1x
Switch(config-if) # authentication mac
Switch(config-if) # authentication web
Switch# show authentication interface fa1
Interface FastEthernet1
    Admin Control      : disable
    Host Mode          : multi-auth
    Type dot1x State   : enabled
    Type mac State     : enabled
    Type web State     : enabled
.....
```

---

## authentication mac radius



# Command Line Interface

## User Guide

---

### Syntax

**authentication mac radius [mac-case (lower|upper)] [mac-delimiter]**



[www.cerio.com.tw](http://www.cerio.com.tw)



+[\(886\) 2-8911-6160](tel:+886289116160)



[service@cerio.com.tw](mailto:service@cerio.com.tw)

**(colon|dot|hyphen|none) [gap (2|4|6)]**

<b>Parameter</b>	<b>mac-case (lower upper)</b>	Select radius user id to be upper case or lower case.
	<b>mac-delimiter (colon dot hyphen none)</b>	Select radius user id delimiter colon: XX:XX:XX:XX:XX dot: XX.XX.XX.XX.XX hyphen: XX-XX-XX-XX-XX none: XXXXXXXXXXXX
	<b>gap (2 4 6)</b>	Select delimiter gap 2: XX-XX-XX-XX-XX 4: XXXX-XXXX-XXXX 6: XXXXXX-XXXXXX

**Default** Default radius id format is upper case with none delimiter.

**Mode** Global Configuration

**Usage** Use “**authentication mac radius**” command to configure the radius user id format used by MAC authentication Radius method.

**Example** The following example shows how to configure MAC authentication radius id format to be upper case with colon delimiter every 2 chars

```
Switch(config)# authentication mac radius mac-case upper
Switch(config)# authentication mac radius mac-delimiter colon
Switch# show authentication Autentication
dot1x state : enabled
Autentication mac state : disabled
Autentication web state : disabled
Guest VLAN : disabled
Mac-auth Radius User ID Format: XX:XX:XX:XX:XX:XX
.....
```

## authentication mac local

**Syntax**

```
authentication mac local mac-addr control auth [vlan <1-4094>] [reauth-period <300-4294967294>] [inactive-timeout <60-65535>]
authentication mac local mac-addr control unauth
no authentication mac local mac-addr
```

<b>Parameter</b>	<b><i>mac-addr</i></b>	MAC Authentication local MAC address
	<b>control auth</b>	Host with this MAC address will be authorized



<b>control unauth</b>	Host with this MAC address will be force-unauthorized
<b>vlan &lt;1-4094&gt;</b>	MAC Authentication host assigned VLAN
<b>reauth-period &lt;300-4294967294&gt;</b>	MAC Authentication host reauthentication period
<b>inactive-timeout &lt;60-65535&gt;</b>	MAC authentication host inactive timeout

---

**Default** Default is no local MAC Authentication entry.

---

**Mode** Global Configuration

---

**Usage** Use “**authentication mac local**” command to add local MAC authentication hosts in database. This local host database is used when MAC authentication method is configured as “local”. The MAC authentication module will find host in this local database and authenticated it. Use the **no** form of this command to delete local host from database.

---

**Example** The following example shows how to add a new local mac authentication host.

```
Switch(config)# authentication mac local 00:11:22:33:00:01
control auth vlan 3 reauth-period 500 inactive-timeout 300
Switch# show authentication
```

.....

Mac-auth Local Entry :		Reauth	Inactive	
MAC Address	Control	VLAN	Period	Timeout
00:11:22:33:00:01	Authorized	3	500	300

.....

---

## authentication guest-vlan

---

**Syntax** **authentication guest-vlan <1-4094>**  
**no authentication guest-vlan**

---

**Parameter** <1-4094> Guest VLAN ID

---

**Default** Default guest VLAN is disabled

---

**Mode** Global Configuration



**Usage**

Use “**authentication guest-vlan**” command to enable the global setting of guest VLAN and specify guest VLAN ID.  
Use the **no** form of this command to disable guest VLAN.

**Example**

The following example shows how to create guest VLAN.

```
Switch(config)# vlan 3
Switch(config-vlan)# exit
Switch(config)# authentication guest-vlan 3
Switch# show authentication
Autentication dot1x state      : enabled
Autentication mac state       : disabled
Autentication web state       : disabled
Guest VLAN                   : enabled (3)
Mac-auth Radius User ID Format: XXXXXXXXXXXXXXXX
```

.....

## **authentication guest-vlan (Interface)**

**Syntax**

**authentication guest-vlan**  
**no authentication guest-vlan**

**Parameter**

**Default**

Default guest VLAN is disabled

**Mode**

Interface Configuration

**Usage**

Use “**authentication guest-vlan**” command to enable the port setting of guest VLAN.  
Use the **no** form of this command to disable guest VLAN.

**Example**

The following example shows how to enable guest VLAN.

```
Switch(config)# interface fa1
Switch(config-if)# authentication guest-vlan
```

## **authentication host-mode**

**Syntax**

**authentication host-mode (multi-auth|multi-host|single-host)**  
**no authentication host-mode**

**Parameter**

**multi-auth**

Multiple Authentication Mode. In this



mode, every client need to pass authenticate procedure individually.

---

**multi-host**      Multiple Host Mode. In this mode, only one client need to be authenticated and other clients will get the same access accessibility.

---

**single-host**      Single Host Mode. In this mode, only one host is allowed to be authenticated. It is the same as multi-auth mode with max hosts number configure to be 1.

---

**Default**      Default is multi-auth mode.

---

**Mode**      Interface Configuration

---

**Usage**      Use “**authentication host-mode**” command to configure the port authentication host mode.  
Use the **no** form of this command to restore default value.

---

**Example**      The following example shows how to modify port host mode to multi-host.

```
Switch(config)# interface fa1
Switch(config-if)# authentication host-mode multi-host
Switch# show authentication interface fa1
Interface FastEthernet1
    Admin Control      : auto
    Host Mode         : multi-host
    Type dot1x State   : disabled
    Type mac State     : disabled
    Type web State      : disabled
....
```

---

## authentication max-hosts

---

**Syntax**      **authentication max-hosts <1-256>**

**no authentication max-hosts**

---

**Parameter**      <1-256>      Available max host number in multi-auth mode.

---

**Default**      Default max host number is 256

---

**Mode**      Interface Configuration



---

**Usage**

Use “**authentication max-hosts**” command to configure the port max hosts number for multi-auth mode. The host exceed the max host number is not allowed to create authentication session and do authenticating. Use **no** form of this command to restore default value.

---

**Example**

The following example shows how to change port max hosts number.

```
Switch(config)# interface fa1
Switch(config-if)# authentication max-hosts 100
Switch# show mac-auth interface fa1
Interface FastEthernet1
    Admin Control      : disable
    Host Mode          : multi-auth
    Type dot1x State   : disabled
    Type mac State     : disabled
    Type web State     : disabled
    Type Order          : dot1x
    MAC/WEB Method Order: radius
    Guest VLAN          : disabled
    Reauthentication     : disabled
    Max Hosts           : 100
....
```

---

## authentication method

---

**Syntax**

**authentication method (local [radius] | radius [local])**  
**no authentication order**

---

**Parameter**

<b>local</b>	Use local account to authenticate
<b>radius</b>	Use remote RADIUS server to authenticate

---

**Default**

Default is RADIUS method in first place and no other method.

---

**Mode**

Interface Configuration

---

**Usage**

Use “**authentication method**” command to configure the port authentication method order.  
Use the **no** form of this command to restore default value.

---

**Example**

The following example shows how to modify port authentication order to local and then RADIUS.

```
Switch(config)# interface fa1
Switch(config-if)# authentication method local radius
Switch# show authentication interface fa1
Interface FastEthernet1
    Admin Control      : auto
    Host Mode          : multi-host
    Type dot1x State   : disabled
    Type mac State     : disabled
    Type web State     : disabled
```

---



```
Type Order          : dot1x mac
web MAC/WEB Method Order : local
radius
.....
```

---

## authentication order

<b>Syntax</b>	<b>authentication order (dot1x [mac] [web]   mac [dot1x] [web]   web)</b> <b>no authentication order</b>
---------------	---

<b>Parameter</b>	<b>dot1x</b> Authenticating user by IEEE 802.1X <b>mac</b> Authenticating user by mac based authentication <b>web</b> Authenticating user by web based authentication
------------------	---

<b>Default</b>	Default is dot1x type in first place and no other types.
----------------	--

<b>Mode</b>	Interface Configuration
-------------	-------------------------

<b>Usage</b>	Use “ <b>authentication order</b> ” command to configure the port authentication type order. Use the <b>no</b> form of this command to restore default value.
--------------	--

<b>Example</b>	The following example shows how to modify port authentication order to dot1x, mac and web.  Switch(config)# <b>interface fa1</b> Switch(config-if)# <b>authentication order dot1x mac web</b> Switch# <b>show authentication interface fa1</b> Interface FastEthernet1 Admin Control         : auto Host Mode             : multi-host Type dot1x State     : disabled Type mac State      : disabled Type web State      : disabled Type Order           : dot1x mac web .....
----------------	---

## authentication port-control

<b>Syntax</b>	<b>authentication port-control (auto force-auth force-unauth)</b> <b>no authentication port-control</b>
---------------	--

<b>Parameter</b>	<b>auto</b> Need passing authentication procedure to get network accessibility <b>force-auth</b> Port is force authorized and all clients have network accessibility.
------------------	--



## Command Line Interface User Guide

---

**force-unauth**

Port is force unauthorized and all clients

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+[\(886\) 2-8911-6160](tel:+886289116160)



[service@cerio.com.tw](mailto:service@cerio.com.tw)

---

have no network accessibility.

---

---

<b>Default</b>	Default is disabled.
----------------	----------------------

---

<b>Mode</b>	Interface Configuration
-------------	-------------------------

---

<b>Usage</b>	Use “ <b>authentication port-control</b> ” command to enable the port authentication control mode. Use the <b>no</b> form of this command to disable authentication port control.
--------------	--

---

<b>Example</b>	The following example shows how to configure port control to auto mode. Switch(config)# <b>interface fa1</b> Switch(config-if)# <b>authentication port-control auto</b> Switch# <b>show authentication interface fa1</b> Interface FastEthernet1 Admin Control : auto Host Mode : multi-auth Type dot1x State : disabled Type mac State : disabled Type web State : disabled .....
----------------	--

## authentication radius-attributes vlan

---

<b>Syntax</b>	<b>authentication radius-attributes vlan (reject   static)</b> <b>no authentication radius-attributes vlan</b>
---------------	---

---

<b>Parameter</b>	<b>reject</b> If get VLAN authorized information, just use it. However, if there is no VLAN authorized information, reject the host and make it unauthorized. <b>static</b> If get VLAN authorized information, just use it. If there is no VLAN authorized information, keep original VLAN of host.
------------------	---

---

<b>Default</b>	Default radius attributes VLAN assign mode is static.
----------------	---

---

<b>Mode</b>	Interface Configuration
-------------	-------------------------

---

<b>Usage</b>	Use “ <b>authentication radius-attributes vlan</b> ” command to configure the port RADIUS VLAN assign mode. Use the <b>no</b> form of this command to disable the port RADIUS VLAN assign.
--------------	---



**Example**

The following example shows how to configure port VLAN assign to reject mode.

```
Switch(config)# interface fa1
Switch(config-if)# authentication radius-attributes vlan
reject
Switch# show authentication interface fa1
Interface FastEthernet1
    Admin Control      : disable
    Host Mode          : multi-auth
    Type dot1x State   : disabled
    Type mac State     : disabled
    Type web State     : disabled
    Type Order          : dot1x
    MAC/WEB Method Order: radius
    Guest VLAN          : disabled
    Reauthentication     : disabled
    Max Hosts           : 256
    VLAN Assign Mode    : reject
....
```

---

## **authentication reauth**

**Syntax**

**authentication reauth**  
**no authentication reauth**

**Parameter**

**Default**

Default is disabled.

**Mode**

Interface Configuration

**Usage**

Use “**authentication reauth**” command to enable the port reauthentication.  
Use the **no** form of this command to disable reauthentication.

**Example**

The following example shows how to enable port reauthentication.

```
Switch(config)# interface fa1
Switch(config-if)# authentication reauth
Switch# show authentication interface fa1
Interface FastEthernet1
    Admin Control      : disable
    Host Mode          : multi-auth
    Type dot1x State   : disabled
    Type mac State     : disabled
    Type web State     : disabled
    Type Order          : dot1x
    MAC/WEB Method Order: radius
    Guest VLAN          : disabled
    Reauthentication     : enabled
....
```

---



## authentication timer inactive

<b>Syntax</b>	<b>authentication timer inactive &lt;60-65535&gt;</b> <b>no authentication timer inactive</b>
<b>Parameter</b>	<60-65535> Interval in seconds after which if there is no activity from the client then it will be unauthorized
<b>Default</b>	Default inactive timeout is 60 seconds.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	<p>Use “<b>authentication timer inactive</b>” command to configure the port inactive timeout value.</p> <p>Sometimes, we may assign a long aging time for a host, but in fact, it is not active. This inactive timeout will detect the host is active or not. If the host is inactive exceed this timeout, it should be removed.</p> <p>Use <b>no</b> form of this command to restore default value.</p>
<b>Example</b>	<p>The following example shows how to configure port inactive period.</p> <pre>Switch(config)# interface fa1 Switch(config-if)# authentication timer inactive 300 Switch# show authentication interface fa1 Interface FastEthernet1 ..... Common Timers   Reauthenticate Period: 300   Inactive Timeout : 300 Quiet   Period : 60 802.1x Parameters   EAP Max Request      : 2   EAP TX Period       : 30   Supplicant Timeout   : 30   Server Timeout       : 30 Web-auth Parameters   Login Attempt : 3</pre>

## authentication timer quiet

<b>Syntax</b>	<b>authentication timer quiet &lt;0-65535&gt;</b> <b>no authentication timer quiet</b>
<b>Parameter</b>	<0-65535> Interval in seconds to wait following a failed authentication exchange



<b>Default</b>	Default quiet period is 60 seconds.
----------------	-------------------------------------

<b>Mode</b>	Interface Configuration
-------------	-------------------------

<b>Usage</b>	<p>Use “<b>authentication timer quiet</b>” command to configure the port quiet period value. After authenticating fail many times and the port is guest VLAN disabled, the port/host will enter lock state until quiet period expired. In lock state, the port/host is not allowed to do authenticating. Use <b>no</b> form of this command to restore default value.</p>
--------------	---

<b>Example</b>	The following example shows how to configure port quiet period.
----------------	---

```
Switch(config)# interface fa1
Switch(config-if)# authentication timer quiet 300
Switch# show authentication interface fa1 Interface
FastEthernet1
-----
Common Timers
  Reauthenticate Period: 300
  Inactive Timeout : 300 Quiet
  Period : 300
802.1x Parameters
  EAP Max Request      : 2
  EAP TX Period       : 30
  Supplicant Timeout   : 30
  Server Timeout       : 30
Web-auth Parameters
  Login Attempt : 3
```

---

## authentication timer reauth

<b>Syntax</b>	<b>authentication timer reauth &lt;300-4294967294&gt;</b> <b>no authentication timer reauth</b>
---------------	--

<b>Parameter</b>	<b>&lt;300-4294967294&gt;</b>	Time in seconds after which an automatic re-authentication should be initiated
------------------	-------------------------------	--

<b>Default</b>	Default reauthentication period is 3600 seconds.
----------------	--

<b>Mode</b>	Interface Configuration
-------------	-------------------------

<b>Usage</b>	Use “ <b>authentication timer reauth</b> ” command to configure the port reauthentication period value with unit second if the reauthentication time is not assigned by local database or remote authentication server. On the other
--------------	--



hand, if the reauthentication time is assigned by local database or remote server, this configured reauthentication time will be ignored. Use **no** form of this command to restore default value.

### Example

The following example shows how to configure port reauthentication period.

```
Switch(config)# interface fa1
Switch(config-if)# authentication timer reauth 300
Switch# show authentication interface fa1
Interface FastEthernet1
.....
Common Timers
  Reauthenticate Period: 300
  Inactive Timeout      : 60
  Quiet Period          : 60
802.1x Parameters
  EAP Max Request       : 2
  EAP TX Period         : 30
  Supplicant Timeout    : 30
  Server Timeout        : 30
Web-auth Parameters
  Login Attempt : 3
```

## authentication web local

### Syntax

```
authentication web local username USERNAME password (encrypted CRYPT-PASSWORD | PASSWORD) [vlan <1-4094>] [reauth-period <300-4294967294>] [inactive-timeout <60-65535>]
no authentication web local username USERNAME
```

### Parameter

<i>USERNAME</i>	Local account user name
<b>encrypted</b> <i>CRIPT-PASSWORD</i>	Encrypted password.
<i>PASSWORD</i>	Un-encrypted password.
<b>vlan</b> <i>&lt;1-4094&gt;</i>	Assigned VLAN of this local account
<b>reauth-period</b> <i>&lt;300-4294967294&gt;</i>	Reauthentication period of this local account
<b>inactive-timeout</b> <i>&lt;60-65535&gt;</i>	Inactive timeout of this local account

### Default

Default is no local authentication entry.

### Mode

Global Configuration

### Usage

Use “**authentication web local**” command to add local account in database. This local account database is used when web authentication method is configured as “local”. The web authentication module will find account in this local database and authenticated it.



Use the **no** form of this command to delete local account from database.

---

**Example**

The following example shows how to add/delete a new local account.

```
Switch(config)# authentication web local username acct1
password acct1 vlan 3 reauth-period 301 inactive-timeout 61
Switch# show authentication
.....
Web-auth Local Entry      :
User Name          VLAN   Reauth    Inactive
.....              Period   Timeout
acct1                3       301      61
.....
```

---

## authentication web max-login-attempts

---

**Syntax**

**authentication web max-login-attempts (infinite|<3-10>)**  
**no authentication web max-login-attempts**

---

**Parameter**

<b>infinite</b>	Do not care user login fail number
<3-10>	Allow user login fail number

---

---

**Default**

Default max login attempt number is 3.

---

**Mode**

Interface Configuration

---

**Usage**

Use “**authentication web max-login-attempts**” command to configure the port WEB authentication max login attempt number. After login fail number exceed, the host will enter Lock state and is not able to authenticate until quiet period exceed.

Use **no** form of this command to restore default value.

---

**Example**

The following example shows how to configure port max login attempt number.

```
Switch(config)# interface fa1
Switch(config-if)# authentication web max-login-attempts 5
Switch# show authentication interface fa1
Interface FastEthernet1
.....
Common Timers
  Reauthenticate Period: 300
  Inactive Timeout : 300 Quiet
  Period : 300
802.1x Parameters
  EAP Max Request      : 1
  EAP TX Period        : 10
  Supplicant Timeout   : 120
  Server Timeout       : 150
Web-auth Parameters
```

---



---

Login Attempt : 5

---

## clear authentication sessions

---

### Syntax

**clear authentication sessions**  
**clear authentication sessions interfaces *IF\_PORTS***  
**clear authentication sessions mac *mac-addr***  
**clear authentication sessions session-id *WORD***  
**clear authentication sessions type (dot1x|mac|web)**

---

### Parameter

<b>interfaces</b>	Clear sessions on specific interface
<i>IF_PORTS</i>	
<b>mac</b> <i>mac-addr</i>	Clear session with specific MAC address
<b>session-id</b> <i>WORD</i>	Clear session with specific session ID
<b>type</b> (dot1x mac web)	Clear session with specific authentication type

---

### Default

Default is no local authentication entry.

---

### Mode

Privileged EXEC

---

### Usage

Use “**clear authentication sessions**” command to delete existing authentication sessions. If no parameter is specified, all sessions will be deleted.  
After authentication session is deleted, host need to do authentication procedure again.

---

### Example

The following example shows how to clear all authentication sessions.

```
Switch# clear authentication sessions
Switch# show authentication sessions
No Auth Manager sessions currently exist
```

---

## dot1x

---

### Syntax

**dot1x**  
**no dot1x**

---

### Parameter

---

### Default

Default 802.1x is disabled



---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

<b>Usage</b>	Use “ <b>dot1x</b> ” command to enable the global setting of 802.1x. The “ <b>authentication dot1x</b> ” command has the same effect as this one. This command is a backward compatible command. Use the <b>no</b> form of this command to disable 802.1x authentication.
--------------	--

---

<b>Example</b>	The following example shows how to enable 802.1x authentication. Switch(config)# <b>dot1x</b> Switch# <b>show authentication</b> Autentication dot1x state : enabled Autentication mac state : disabled Autentication web state : disabled Guest VLAN : enabled (3) Mac-auth Radius User ID Format: XXXXXXXXXXXXXXXX .....
----------------	--

## **dot1x guest-vlan**

---

<b>Syntax</b>	<b>dot1x guest-vlan &lt;1-4094&gt;</b> <b>no dot1x guest-vlan</b>
---------------	--

---

<b>Parameter</b>	<b>&lt;1-4094&gt;</b> Guest VLAN ID
------------------	-------------------------------------

---

<b>Default</b>	Default guest VLAN is disabled
----------------	--------------------------------

---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

<b>Usage</b>	Use “ <b>dot1x guest-vlan</b> ” command to enable the global setting of guest VLAN and specify guest VLAN ID. Use the <b>no</b> form of this command to disable guest VLAN.
--------------	--

---

<b>Example</b>	The following example shows how to create guest VLAN. Switch(config)# <b>vlan 3</b> Switch(config-vlan)# <b>exit</b> Switch(config)# <b>dot1x guest-vlan 3</b> Switch# <b>show authentication</b> Autentication dot1x state : enabled Autentication mac state : disabled Autentication web state : disabled Guest VLAN : enabled (3) Mac-auth Radius User ID Format: XXXXXXXXXXXXXXXX
----------------	--



## **dot1x max-req**

<b>Syntax</b>	<b>dot1x max-req &lt;1-10&gt;</b> <b>no dot1x max-req</b>
<b>Parameter</b>	<b>&lt;1-10&gt;</b> The maximum number of EAP requests that can be sent. If a response is not received after the defined period (supplicant timeout), the authentication process is restarted.
<b>Default</b>	Default EAP max request number is 2.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	Use “ <b>dot1x max-req</b> ” command to configure the port 802.1x max EAP request value. The max request is the maximum number of EAP requests that can be sent. If a response is not received after the defined period (supplicant timeout), the authentication process is restarted. Use <b>no</b> form of this command to restore default value.
<b>Example</b>	The following example shows how to configure port 802.1x EAP TX period. Switch(config)# <b>interface fa1</b> Switch(config-if)# <b>dot1x max-req 1</b> Switch# <b>show authentication interface fa1</b> Interface FastEthernet1 ..... Common Timers Reauthenticate Period: 300 Inactive Timeout : 300 Quiet Period : 300 802.1x Parameters EAP Max Request      : 1 EAP TX Period        : 10 Supplicant Timeout    : 120 Server Timeout       : 150 Web-auth Parameters Login Attempt     : 3

## **dot1x port-control**

<b>Syntax</b>	<b>dot1x port-control (auto force-auth force-unauth)</b> <b>no dot1x port-control</b>
---------------	--



<b>Parameter</b>	<b>auto</b> Need passing authentication procedure to get network accessibility <b>force-auth</b> Port is force authorized and all clients have network accessibility. <b>force-unauth</b> Port is force unauthorized and all clients have no network accessibility.
<b>Default</b>	Default is disabled.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	Use “ <b>dot1x port-control</b> ” command to enable the port authentication control mode. The “ <b>authentication port-control</b> ” command has the same effect. Use the <b>no</b> form of this command to disable authentication port control.
<b>Example</b>	The following example shows how to configure port control to auto mode. <pre>Switch(config)# interface fa1 Switch(config-if)# dot1x port-control auto Switch# show authentication interface fa1 Interface FastEthernet1   Admin Control      : auto   Host Mode          : multi-auth   Type dot1x State   : enabled   Type mac State     : disabled   Type web State     : disabled .....</pre>

---

## dot1x reauth

<b>Syntax</b>	<b>dot1x reauth</b> <b>no dot1x reauth</b>
<b>Parameter</b>	
<b>Default</b>	Default is disabled.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	Use “ <b>dot1x reauth</b> ” command to enable the port reauthentication. The “ <b>authentication reauth</b> ” command has the same effect, it is a backward compatible command Use the <b>no</b> form of this command to disable reauthentication.



---

**Example**

The following example shows how to enable port reauthentication.

```
Switch(config)# interface fa1
Switch(config-if)# dot1x reauth
Switch# show authentication interface fa1
Interface FastEthernet1
    Admin Control          : disable
    Host Mode              : multi-auth
    Type dot1x State       : disabled
    Type mac State         : disabled
    Type web State         : disabled
    Type Order              : dot1x
    MAC/WEB Method Order   : radius
    Guest VLAN             : disabled
    Reauthentication        : enabled
.....
```

---

## **dot1x timeout reauth-period**

---

**Syntax**

**dot1x timeout reauth-period <300-4294967294>**

**no dot1x timeout reauth-period**

---

**Parameter**

<b>&lt;300-4294967294&gt;</b>	Time in seconds after which an automatic re-authentication should be initiated
-------------------------------	--

---

---

**Default**

Default reauthentication period is 3600 seconds.

---

**Mode**

Interface Configuration

---

**Usage**

Use “**dot1x timeout reauth**” command to configure the port reauthentication period value with unit second if the reauthentication time is not assigned by local database or remote authentication server. On the other hand, if the reauthentication time is assigned by local database or remote server, this configured reauthentication time will be ignored. The “**authentication timer reauth**” command has the same effect and it is a backward compatible command.

Use **no** form of this command to restore default value.

---

**Example**

The following example shows how to configure port 802.1x reauthentication period.

```
Switch(config)# interface fa1
Switch(config-if)# dot1x timeout reauth-period 300
Switch# show authentication interface fa1
Interface FastEthernet1
.....
```

<b>Common Timers</b>
Reauthenticate Period: 300
Inactive Timeout      : 60
Quiet Period          : 60

---



---

```
802.1x Parameters
  EAP Max Request      : 2
  EAP TX Period       : 30
  Supplicant Timeout : 30
  Server Timeout     : 30
Web-auth Parameters
  Login Attempt : 3
```

---

## dot1x timeout quiet-period

### Syntax

```
dot1x timeout quiet-period <0-65535>
no dot1x timeout quiet-period
```

### Parameter

<0-65535>	Interval in seconds to wait following a failed authentication exchange
-----------	--

### Default

Default quiet period is 60 seconds.

### Mode

Interface Configuration

### Usage

Use “**dot1x timeout quiet-period**” command to configure the port quiet period value. The “**authentication timer quiet**” command has the same effect and it is backward compatible command.  
After authenticating fail many times and the port is guest VLAN disabled, the port/host will enter lock state until quiet period expired. In lock state, the port/host is not allowed to do authenticating.  
Use **no** form of this command to restore default value.

### Example

The following example shows how to configure port 802.1x quiet period.

```
Switch(config)# interface fa1
Switch(config-if)# dot1x timeout quiet-period 300
Switch# show authentication interface fa1 Interface
FastEthernet1
.....
  Common Timers
    Reauthenticate Period: 300
    Inactive Timeout : 300 Quiet
    Period : 300
  802.1x Parameters
    EAP Max Request      : 2
    EAP TX Period       : 30
    Supplicant Timeout : 30
    Server Timeout     : 30
Web-auth Parameters
  Login Attempt : 3
```

---

## dot1x timeout server-timeout

### Syntax

```
dot1x timeout server-timeout <1-65535>
```



### **no dot1x timeout server-timeout**

<b>Parameter</b>	<code>&lt;1-65535&gt;</code>	Number of seconds that lapses before the device resends a request to the authentication server.
------------------	------------------------------	---

<b>Default</b>	Default server timeout is 30 seconds.
----------------	---------------------------------------

<b>Mode</b>	Interface Configuration
-------------	-------------------------

<b>Usage</b>	Use “ <b>dot1x timeout server-timeout</b> ” command to configure the port 802.1x server timeout value. The server timeout is the number of seconds that lapses before the device resends a request to the authentication server. Use <b>no</b> form of this command to restore default value.
--------------	---

<b>Example</b>	The following example shows how to configure port 802.1x server timeout.
----------------	--

```
Switch(config)# interface fa1
Switch(config-if)# dot1x timeout supp-timeout 150
Switch# show authentication interface fa1 Interface
FastEthernet1
-----
Common Timers
  Reauthenticate Period: 300
  Inactive Timeout : 300 Quiet
  Period : 300
802.1x Parameters
  EAP Max Request      : 2
  EAP TX Period        : 30
  Supplicant Timeout   : 120
  Server Timeout       : 150
  Web-auth Parameters
    Login Attempt       : 3
```

### **dot1x timeout supp-timeout**

<b>Syntax</b>	<code>dot1x timeout supp-timeout &lt;1-65535&gt;</code>
	<code>no dot1x timeout supp-timeout</code>

<b>Parameter</b>	<code>&lt;1-65535&gt;</code>	Number of seconds that lapses before EAP requests are resent to the supplicant
------------------	------------------------------	--

<b>Default</b>	Default supplicant timeout is 30 seconds.
----------------	---

<b>Mode</b>	Interface Configuration
-------------	-------------------------



---

**Usage**

Use “**dot1x timeout supp-timeout**” command to configure the port supplicant timeout value. The supplicant timeout is the number of seconds that lapses before EAP requests are resent to the supplicant. Use **no** form of this command to restore default value.

---

**Example**

The following example shows how to configure port 802.1x supplicant timeout.

```
Switch(config)# interface fa1
Switch(config-if)# dot1x timeout supp-timeout 120
Switch# show authentication interface fa1 Interface
FastEthernet1
.....
Common Timers
    Reauthenticate Period: 300
    Inactive Timeout : 300 Quiet
    Period : 300
802.1x Parameters
    EAP Max Request      : 2
    EAP TX Period        : 30
    Supplicant Timeout   : 120
    Server Timeout       : 30
    Web-auth Parameters
        Login Attempt     : 3
```

---

**dot1x timeout tx-period**

---

**Syntax**

**dot1x timeout tx-period <1-65535>**  
**no dot1x timeout tx-period**

---

**Parameter**

**<1-65535>** Number of seconds that the device waits for a response to an Extensible Authentication Protocol (EAP) request/identity frame from the supplicant (client) before resending the request.

---

---

**Default**

Default EAP TX period is 30 seconds.

---

**Mode**

Interface Configuration

---

**Usage**

Use “**dot1x timeout tx-period**” command to configure the port 802.1x EAP TX period value. The TX period is the number of seconds that the device waits for a response to an Extensible Authentication Protocol (EAP) request/identity frame from the supplicant (client) before resending the request.

Use **no** form of this command to restore default value.

---

**Example**

The following example shows how to configure port 802.1x EAP TX period.

```
Switch(config)# interface fa1
Switch(config-if)# dot1x timeout tx-period 10
```

---



```
Switch# show authentication interface fal
Interface FastEthernet1
.....
Common Timers
Reauthenticate Period:
300 Inactive Timeout :
300 Quiet Period : 300
802.1x Parameters
EAP Max Request      : 2
EAP TX Period        :
10 Supplicant Timeout:
120 Server Timeout   :
150
Web-auth Parameters
Login Attempt         : 3
```

---

## **show authentication**

---

### Syntax

**show authentication**  
**show authentication interfaces *IF\_PORTS***

---

### Parameter

**interfaces *IF\_PORTS***      Specify port list to show port configurations.

---

### Default

No default value for this command.

---

### Mode

Privileged EXEC

---

### Usage

Use “**show authentication**” command to show all authentication manager configurations.

Use “**show authentication interface**” command to show authentication manager configuration of specific port.

---



# Command Line Interface

## User Guide

### Example

This example shows how to show the mac authentication configurations of port fa1.

```
Switch# show authentication Autentication
dot1x state           : enabled
Autentication mac state : disabled
Autentication web state : disabled
Guest VLAN             : disabled
Mac-auth Radius User ID Format: XXXXXXXXXXXXXXXX

Mac-auth Local Entry      :
MAC Address          Control     VLAN   Reauth    Inactive
-----  -----  -----  -----
00:11:22:33:44:55  Authorized    3    30000    123

Web-auth Local Entry      :
User Name            VLAN   Reauth    Inactive
-----  -----  -----
acct1                  5    12345    333
```



---

```
Interface
Configurations
Interface
FastEthernet1
  Admin Control      : disable
  Host Mode          : multi-auth
  Type dot1x State   : disabled
  Type mac State     : disabled
  Type web State     : disabled
  Type Order         :
  dot1x MAC/WEB Method Order :
    radius Guest VLAN   :
    disabled
    Reauthentication    : disabled
    Max Hosts          : 256
    VLAN Assign Mode   :
    static Common Timers
      Reauthenticate Period:
        3600 Inactive Timeout:
          60
      Quiet Period       :
    60 802.1x Parameters
      EAP Max Request   : 2
      EAP TX Period     : 30
      Supplicant Timeout :
        30 Server Timeout : 30
    Web-auth Parameters
      Login Attempt     : 3
.....
Switch# show authentication interface fa7
Interface Configurations
Interface
  FastEthernet7 Admin
  Control           :
  auto
  Host Mode         :
  multi-auth Type dot1x State
    : enabled
  Type mac State    : disabled
  Type web State    : disabled
  Type Order        : dot1x
  MAC/WEB Method Order :
    radius Guest VLAN   :
    disabled Reauthentication
    :
    disabled Max Hosts 256
    VLAN Assign Mode   :
    static Common Timers
    Reauthenticate Period:
      3600 Inactive Timeout
        60
    Quiet Period       : 60
  802.1x Parameters
    EAP Max Request   : 2
    EAP TX Period     : 30
    Supplicant Timeout : 30
    Server Timeout     :
    65535 Web-auth
    Parameters
    Login Attempt     : 3
```

---

## show authentication sessions



## Command Line Interface User Guide

---

### Syntax

**show authentication sessions [detail]**  
**show authentication sessions interface *IF\_PORTS***  
**show authentication sessions session-id *WORD***  
**show authentication session type (dot1x|mac|web)**

---

### Parameter

<b>detail</b>	Show session detail information.
<b>interface</b>	Show session detail information of specific

---



<i>IF_PORTS</i>	port
<b>session-id</b> WORD	Show session detail information of specific session id
<b>type</b> <b>(dot1x mac web)</b>	Show session detail information of specific authentication type

---

<b>Default</b>	No default value for this command.
----------------	------------------------------------

---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	Use “ <b>show authentication sessions</b> ” command to show authentication detail session information.
--------------	--

---

<b>Example</b>	This example shows how to show current authentication session brief and detail information.
----------------	---

```

Switch# show authentication sessions
Interface  MAC Address      Type     Status      Session ID
-----  -----
fa7        00:01:6C:CB:29:4A dot1x    Authorized   000000010000A028

Switch# show authentication sessions detail
Interface                : FastEthernet7
MAC Address              : 00:01:6C:CB:29:4A
Session ID               : 000000010000A028
Current Type             : dot1x
Status                   : Authorized
Authorized Information
  VLAN                  : 5 (from RADIUS)
  Reauthenticate Period: 301 (from RADIUS)
  Inactive Timeout     : 600 (from RADIUS)
Operational Information
  VLAN                 : 5
  Session Time         : 1143
  Inactive Time        : 168
  Quiet Time           : N/A

```

---

## 5. Diagnostic

### show cable-diag

---

<b>Syntax</b>	<b>show cable-diag interfaces <i>IF_NMLPORTS</i></b>
---------------	--

---

<b>Parameter</b>	<b>interfaces <i>IF_NMLPORTS</i></b>	Display the cable diagnostic information of the copper media for an interface ID or a list of interfaces IDs.
------------------	--------------------------------------	---

---

<b>Default</b>	N/A
----------------	-----



---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	To show the estimated copper cable length attached to a specific interface, use the command <b>show cable-diag</b> in the Privileged EXEC mode. For the proper information of the cable length, the interface must be active and linked up.
--------------	---

---

<b>Example</b>	The following example shows the result of cable diagnostic for the interface fa1 and fa2.
----------------	---

```
Switch# show cable-diag interfaces fa1-2
  Port | Speed | Local pair | Pair length | Pair status
-----+-----+-----+-----+
    fa1 | auto |     Pair A |      0.88 | Open
          |       |     Pair B |      0.82 | Open Pair
          |       | C |      0.80 | Open Pair D |
          |       |       | 0.78 | Open
    fa2 | auto |     Pair A |      0.81 | Open
          |       |     Pair B |      0.81 | Open Pair
          |       | C |      0.77 | Open
          |       | Pair D |      0.81 | Open
```

---

## show fiber-transceiver

---

<b>Syntax</b>	<b>show fiber-transceiver interfaces <i>IF_NMLPORTS</i></b>
---------------	---

---

<b>Parameter</b>	<b>interfaces <i>IF_NMLPORTS</i></b>	Display the diagnostic information of the fiber transceiver for an interface ID or a list of interface IDs.
------------------	--------------------------------------	---

---

<b>Default</b>	N/A
----------------	-----

---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	To show the diagnostic information of the fiber transceiver use the command <b>show fiber-transceiver</b> in the Privileged EXEC mode.
--------------	--



## Command Line Interface User Guide

- Example** The following example shows the diagnostic information for the interface gi1 and gi2, wherer the int fiber media ports with the transceiver inserted.

```
Switch# show fiber-transceiver interfaces gi1-2
  Port | Temperature | Voltage | Current | Output power | Input power |
        | [C]         | [Volt]   | [mA]    | [mWatt]     | [mWatt]     |
=====
  gi1  | N/S        | N/S      | N/S     | N/S       | N/S        | Insert     |
  gi2  | N/S        | N/S      | N/S     | N/S       | N/S        | Insert     |
```



Temp - Internally measured transceiver  
temperature Voltage - Internally measured supply voltage  
Current - Measured TX bias current  
Output Power - Measured TX output power in milliWatts  
Input Power - Measured RX received power in milliWatts  
OE-Present - SFP Presetn or Not Present  
LOS - Loss of signal  
N/A - Not Available, N/S - Not Supported, W - Warning, E - Error

---

## 6. DHCP Snooping

### ip dhcp snooping

<b>Syntax</b>	<code>ip dhcp snooping</code> <code>no ip dhcp snooping</code>
<b>Parameter</b>	None
<b>Default</b>	DHCP snooping is disabled
<b>Mode</b>	Global Configuration
<b>Usage</b>	Use the <code>ip dhcp snooping</code> command to enable DHCP Snooping function. Use the <code>no</code> form of this command to disable.
<b>Example</b>	The example shows how to enable DHCP Snooping on VLAN 1. You can verify settings by the following <code>show ip dhcp snooping</code> command.  <code>switch(config)# ip dhcp snooping</code> <code>switch(config)# ip dhcp snooping vlan 1</code> <code>switch(config)# show ip dhcp snooping</code> <code>DHCP Snooping : enabled</code> <code>Enable on following Vlans 1</code> <code>  circuit-id default format : vlan-port</code> <code>  remote-id : 00:11:22:33:44:55 (Switch Mac in Byte Order)</code>

### ip dhcp snooping vlan

<b>Syntax</b>	<code>ip dhcp snooping vlan VLAN-LIST</code>	
<b>Parameter</b>	<b>VLAN-LIST</b>	Specify VLAN ID or a range of VLANs to enable or disable dynamic Arp inspection



**Default** Default is disabled on all VLANs

**Mode** Global Configuration

**Usage** Use the **ip dhcp snooping vlan** command to enable VLANs on DHCP Snooping function. Use the **no** form of this command to disable VLANs on DHCP Snooping function.

**Example** The example shows how to enable VLAN 1-100 on DHCP Snooping, and then disable VLAN 30-40 on DHCP Snooping. You can verify settings by the following **show ip dhcp snooping** command.

```
switch(config)# vlan 1-100
switch(config)# exit
switch(config)# ip dhcp snooping
switch(config)# ip dhcp snooping vlan 1-100
switch(config)# show ip dhcp snooping
DHCP Snooping      : enabled
Enable on following Vlans   : 1-100
    circuit-id default format : vlan-port
    remote-id: 00:11:22:33:44:55 (Switch Mac in Byte Order)
```

```
switch(config)# no ip dhcp snooping vlan 30-40
switch(config)# show ip dhcp snooping
DHCP Snooping      : enabled
Enable on following Vlans   : 1-29,41-100
    circuit-id default format : vlan-port
    remote-id : 00:11:22:33:44:55 (Switch Mac in Byte Order)
```

## ip dhcp snooping trust

**Syntax** **ip dhcp snooping**  
**trust no ip dhcp**  
**snooping trust**

**Parameter** None

**Default** DHCP snooping trust is disabled

**Mode** Interface Configuration



**Usage**

Use the **ip dhcp snooping trust** command to set trusted interface. The switch does not check DHCP packets that are received on the trusted interface; it simply forwards it. Use the **no** form of this command to set untrusted interface.

**Example**

The example shows how to set interface gi1 to trust. You can verify settings by the following **show ip dhcp snooping interface** command.

```
switch(config)# interface gi1
switch(config-if)# ip dhcp snooping trust
switch(config-if)# do show ip dhcp snooping interface gi1
Interfaces | Trust State | Rate (pps) | hwaddr Check | Insert Option82 |
-----+-----+-----+-----+
gi1 | Trusted | None | disabled | disabled |
```

## ip dhcp snooping verify

**Syntax**

```
ip dhcp snooping verify mac-address
[no] ip dhcp snooping verify
mac-address
```

**Parameter**

None

**Default**

DHCP snooping verify mac-address is disabled

**Mode**

Interface Configuration

**Usage**

Use the **ip dhcp snooping verify** command to verify MAC address function on interface.

The “**mac-address**” drop DHCP packets that chaddr and ethernet-source-mac is not match.

**Example**

The example shows how to set interface gi1 to validate “**mac-address**”. You can verify settings by the following **show ip dhcp snooping interface** command.

```
switch(config)# interface gi1
switch(config-if)# ip dhcp snooping verify mac-address
switch(config-if)# do show ip dhcp snooping interface gi1
Interfaces | Trust State | Rate (pps) | hwaddr Check | Insert Option82 |
-----+-----+-----+-----+
gi1 | Untrusted | None | disabled | disabled |
```

## ip dhcp snooping rate-limit



**Syntax**

```
ip dhcp snooping rate-limit  
<1-300> [no] ip dhcp snooping  
rate-limit
```

**Parameter**

<1-300> Set 1 to 300 PPS of DHCP packet rate limitation

**Default**

Default is un-limited of DHCP packet

**Mode**

Interface Configuration

**Usage**

Use the **ip dhcp snooping rate-limit** command to set rate limitation on interface. The switch drop DHCP packets after receives more than configured rate of packets per second. Use the **no** form of this command to return to default settings.

**Example**

The example shows how to set rate limit to 30 pps on interface gi1. You can verify settings by the following **show ip dhcp snooping interface** command.

```
switch(config)# interface gi1  
switch(config-if)# ip dhcp snooping rate-limit 30  
switch(config-if)# do show ip dhcp snooping interfaces gi1  
Interfaces|Trust State|Rate (pps)|hwaddr Check|Insert Option82|  
-----+-----+-----+-----+-----+  
gi1 | Untrusted | 30 | disabled | disabled |
```

## clear ip dhcp snooping statistics

**Syntax**

```
clear ip dhcp snooping interfaces IF_PORTS statistics
```

**Parameter**

IF\_PORTS specifies ports to clear statistics

**Default**

No default is defined

**Mode**

Privileged EXEC

**Usage**

Use the **clear ip dhcp snooping interfaces statistics** command to clear statistics that are recorded on interface.

**Example**

The example shows how to clear statistics on interface gi1. You can verify settings by the following **show ip dhcp snooping interface statistics** command.



```
switch# clear ip dhcp snooping interfaces gi1 statistics
switch# show ip dhcp snooping interfaces gi1 statistics
Interfaces | Forwarded | Chaddr Check Dropped | Untrust Port
Dropped | Untrust Port With Option82 Dropped | Invalid Drop
-----+-----+-----+-----+-----+
gi1 | 0 | 0 | 0 | 0 | 0
```

## show ip dhcp snooping

**Syntax** **show ip dhcp snooping**

**Parameter** **None**

**Default** No default is defined

**Mode** Privileged EXEC

**Usage** Use the **show ip dhcp snooping** command to show settings of DHCP Snooping.

**Example** The example shows how to show settings of DHCP Snooping

```
switch(config)# show ip dhcp snooping
DHCP Snooping : enabled
Enable on following Vlans : 1
    circuit-id default format: vlan-port
    remote-id: : 00:11:22:33:44:55 (Switch Mac in Byte Order)
```

## show ip dhcp snooping interface

**Syntax** **show ip dhcp snooping interfaces IF\_PORTS**  
**show ip dhcp snooping interfaces IF\_PORTS statistics**

**Parameter** **IF\_PORTS** specifies ports to show statistics

**Default** No default is defined

**Mode** Privileged EXEC



**Usage**

Use the **show ip dhcp snooping interfaces** command to show settings or statistics of interface.

**Example**

The example shows how to show settings of interface gi1.

```
switch# show ip dhcp snooping interface gi1
Interfaces | Trust State | Rate (pps) | hwaddr Check | Insert Option82 |
-----+-----+-----+-----+
gi1 | Untrusted | None | enabled | disabled |
```

The example shows how to show statistics of interface gi1.

```
switch# show ip dhcp snooping interfaces gi1 statistics
Interfaces | Forwarded | Chaddr Check Dropped | Untrust Port Dropped |
Untrust Port With Option82 Dropped | Invalid Drop
-----+-----+-----+-----+
gi1 | 0 | 0 | 0 | 0 | 0
```

---

## show ip dhcp snooping binding

**Syntax**

**show ip dhcp snooping binding**

**Parameter**

**None**

**Default**

No default is defined

**Mode**

Privileged EXEC

**Usage**

Use the **show ip dhcp snooping binding** command to show binding entries that learned by DHCP Snooping.

**Example**

The example shows how to show binding entries that learned by DHCP Snooping.

```
switch# show ip dhcp snooping binding
Bind Table: Maximum Binding Entry Number 192
Port | VID | MAC Address | IP | Type | Lease Time
-----+-----+-----+-----+
fa1 | 1 | 48:5B:39:C7:12:62 | 192.168.1.100(255.255.255.255)|DHCP Snooping | 86400
```

---

## ip dhcp snooping option

**Syntax**

**ip dhcp snooping option**  
**no ip dhcp snooping option**



<b>Parameter</b>	None
<b>Default</b>	DHCP snooping option82 is disabled
<b>Mode</b>	Interface Configuration
<b>Usage</b>	Use the <b>ip dhcp snooping option</b> command to enable that insert option82 content into packet. Use the <b>no</b> form of this command to disable.
<b>Example</b>	The example shows how to enable option82 insertion. You can verify settings by the following <b>show ip dhcp snooping interface</b> command.  <pre>switch(config)# interface gi1 switch(config-if)# ip dhcp snooping option switch(config-if)# do show ip dhcp snooping interfaces gi1 Interfaces   Trust State   Rate (pps)   hwaddr Check   Insert Option82   -----+-----+-----+-----+ gi1     Untrusted   None      disabled     enabled    </pre>

## ip dhcp snooping option action

<b>Syntax</b>	<b>ip dhcp snooping option action (drop keep replace)</b> <b>no ip dhcp snooping option action</b>
<b>Parameter</b>	<b>Drop</b> Drop packets with option82 that are received from un trusted port <b>Keep</b> Keep original option82 content in packet <b>Replace</b> Replace option82 content by switch setting
<b>Default</b>	DHCP snooping option82 is drop
<b>Mode</b>	Interface Configuration
<b>Usage</b>	Use the <b>ip dhcp snooping option action</b> command to set the action when receive packets that with option82 content. Use the <b>no</b> form of this command to default setting.
<b>Example</b>	The example shows how to set action to replace option82 content. You can verify settings by the following <b>show running-config</b> command.



```
switch(config)# interface gi1
switch(config-if)# ip dhcp snooping option action replace
```

---

## ip dhcp snooping option circuit-id

### Syntax

```
ip dhcp snooping [vlan <1-4094>] option circuit-id STRING
no ip dhcp snooping [vlan <1-4094>] option circuit-id
```

---

### Parameter

Vlan <1-4094>	VLAN ID to set user defined circuit-id string
STRING	Circuit-id string, 1 to 63 ASCII characters, no spaces.

---

### Default

Default circuit-id is port id + vlan id in byte format.

### Mode

Interface Configuration

### Usage

Use the **ip dhcp snooping option circuit-id** command to set user-defined circuit-id string. Circuit-id is per port per VLAN setting. If a VLAN is not found user-defined circuit-id then use per port circuit-id string. Use the **no** form of this command to default setting.

### Example

The example shows how to set a user-defined circuit-id string on interface gi1 and VLAN 1. You can verify settings by the following **show running-config** command

```
switch(config)# interface gi1
switch(config-if)# ip dhcp snooping vlan 1 option circuit-id test
```

---

## ip dhcp snooping option remote-id

### Syntax

```
ip dhcp snooping option remote-id STRING
no ip dhcp snooping option remote-id
```

---

### Parameter

STRING	Remote-id string, 1 to 63 ASCII characters, no spaces.
--------	--

---

### Default

Default remote-id is the switch MAC address in byte order

### Mode

Global Configuration



---

**Usage**

Use the **ip dhcp snooping option remote-id** command to set user-defined remote-id string.

Remote-id is a global and unique string. Use the **no** form of this command to default setting.

---

**Example**

The example shows how to set a user-defined remote-id string on switch. You can verify settings by the following **show ip dhcp snooping option remote-id**

```
switch(config)# ip dhcp snooping option remote-id test_remote  
switch(config)# do show ip dhcp snooping option remote-id  
Remote ID: test_remote
```

---

## show ip dhcp snooping option

---

**Syntax**

**show ip dhcp snooping option remote-id**

---

**Parameter**

**None**

---

---

**Default**

No default is defined

---

**Mode**

Privileged EXEC

---

**Usage**

Use the **show ip dhcp snooping option remote-id** command to show remote-id string.

---

**Example**

The example shows how to show remote-id string

```
switch(config)# do show ip dhcp snooping option remote-id  
Remote ID: test_remote
```

---

## ip dhcp snooping database

---

**Syntax**

**ip dhcp snooping database flash**  
**ip dhcp snooping database tftp (A.B.C.D|HOSTNAME) NAME**  
**no ip dhcp snooping database**

---

**Parameter**

(A.B.C.D|HOSTNAME) Specify the IP address or hostname of remote TFTP server  
NAME Input name of backup file

---



<b>Default</b>	DHCP snooping database is disabled
<b>Mode</b>	Global Configuration
<b>Usage</b>	Use the <b>ip dhcp snooping database</b> command to enable DHCP Snooping database agent. The “ <b>flash</b> ” means that write backup file to switch local drive. The “ <b>tftp</b> ” means that write backup file to remote TFTP server. Use the <b>no</b> form of this command to disable.
<b>Example</b>	<pre>switch(config)# ip dhcp snooping database tftp 192.168.1.50 backup_file switch(config)# do show ip dhcp snooping database Type : tftp: 192.168.1.50 FileName : backup_file Write delay Timer : 300 seconds Abort Timer : 300 seconds  Agent Running : Running Delay Timer Expiry : 300 seconds Abort Timer Expiry : 299  Last Succeeded Time : None Last Failed Time : None Last Failed Reason : No failure recorded.  Total Attempts      : 1 Successful Transfers : 0   Failed Transfers : 0 Successful Reads    : 0   Failed Reads   : 0 Successful Writes   : 0   Failed Writes  : 0</pre>

## **ip dhcp snooping database write-delay**

<b>Syntax</b>	<b>ip dhcp snooping database write-delay</b> <b>&lt;15-86400&gt; no ip dhcp snooping database</b> <b>write-delay</b>
<b>Parameter</b>	<b>&lt;15-86400&gt;</b> Specifies the seconds of timeout. Specify the duration for which the transfer should be delayed after the <u>binding database changes</u>



<b>Default</b>	DHCP snooping database write-delay is 300 seconds
<b>Mode</b>	Global Configuration
<b>Usage</b>	Use the <b>ip dhcp snooping database write-delay</b> command to modify the write-delay timer. Use the <b>no</b> form of this command to default setting.
<b>Example</b>	<p>The example shows how to set write-delay timer to 60 seconds. You can verify settings by the following <b>show ip dhcp snooping database</b> command.</p> <pre>switch(config)# ip dhcp snooping database write-delay 60 switch(config)# do show ip dhcp snooping database Type : tftp: 192.168.1.50 FileName : backup_file Write delay Timer : 60 seconds Abort Timer : 300 seconds  Agent Running : Running Delay Timer Expiry : 300 seconds Abort Timer Expiry : 299  Last Succeeded Time : None Last Failed Time : None Last Failed Reason : No failure recorded.  Total Attempts      : 1 Successful Transfers : 0   Failed Transfers : 0 Successful Reads    : 0   Failed Reads   : 0 Successful Writes   : 0   Failed Writes  : 0</pre>

## ip dhcp snooping database timeout

<b>Syntax</b>	<b>ip dhcp snooping database timeout &lt;0-86400&gt;</b> <b>no ip dhcp snooping database timeout</b>
<b>Parameter</b>	<b>&lt;15-86400&gt;</b> Specifies the seconds of timeout ° Specify (in seconds) how long to wait for the database transfer process to finish before stopping the process. Use 0 to define an infinite duration, which means to continue trying the transfer indefinitely



**Default** DHCP snooping database timeout is 300 seconds

**Mode** Global Configuration

**Usage** Use the **ip dhcp snooping database timeout** command to modify the timeout timer. Use the **no** form of this command to default setting.

**Example** The example shows how to set timeout timer to 60 seconds. You can verify settings by the following **show ip dhcp snooping database** command.

```
switch(config)# ip dhcp snooping database timeout 60
switch(config)# do show ip dhcp snooping database
```

Type : tftp: 192.168.1.50

FileName : backup\_file

Write delay Timer : 300 seconds

Abort Timer : 60 seconds

Agent Running : Running

Delay Timer Expiry : 300 seconds

Abort Timer Expiry : 299

Last Succeeded Time : None

Last Failed Time : None

Last Failed Reason : No failure recorded.

Total Attempts : 1

Successful Transfers : 0 Failed Transfers : 0

Successful Reads : 0 Failed Reads : 0

Successful Writes : 0 Failed Writes : 0

---

## clear ip dhcp snooping database statistics

**Syntax** **clear ip dhcp snooping database statistics**

**Parameter** None

**Default** No default is defined

**Mode** Privileged EXEC



**Usage**

Use the **clear ip dhcp snooping database statistics** command to clear statistics of DHCP Snooping database.

**Example**

The example shows how to clear statistics of DHCP Snooping agent. You can verify settings by the following **show ip dhcp snooping database** command.

```
switch# clear ip dhcp snooping database statistics  
switch# show ip dhcp snooping database
```

Type : tftp: 192.168.1.50

FileName : backup\_file

Write delay Timer : 300 seconds

Abort Timer : 60 seconds

Agent Running : Running

Delay Timer Expiry : 300 seconds

Abort Timer Expiry : 299

Last Succeeded Time : None

Last Failed Time : None

Last Failed Reason : No failure recorded.

Total Attempts : 0

Successful Transfers : 0 Failed Transfers : 0

Successful Reads : 0 Failed Reads : 0

Successful Writes : 0 Failed Writes : 0

---

## renew ip dhcp snooping database

**Syntax**

```
renew ip dhcp snooping database
```

**Parameter**

None

**Default**

No default is defined

**Mode**

Privileged EXEC

**Usage**

Use the **renew ip dhcp snooping database** command to renew DHCP Snooping database from backup file.



**Example**

The example shows how to renew DHCP Snooping database. You can verify settings by the following **show ip dhcp snooping database** and **show ip dhcp snooping binding** command.

```
switch# show ip dhcp snooping database
```

Type : tftp: 192.168.1.50

FileName : backup\_file

Write delay Timer : 300 seconds

Abort Timer : 60 seconds

Agent Running : Running

Delay Timer Expiry : 300 seconds

Abort Timer Expiry : 299

Last Succeeded Time : None

Last Failed Time : None

Last Failed Reason : No failure recorded.

Total Attempts : 1

Successful Transfers : 1 Failed Transfers :

0 Successful Reads : 1

Failed Reads : 0 Successful Writes :

0 Failed Writes : 0

```
switch# show ip dhcp snooping binding
```

Bind Table: Maximun Binding Entry Number 192

Port	VID	MAC Address	IP	Type	Lease Time
fa1	1	48:5B:39:C7:12:62	192.168.1.100(255.255.255.255)	DHCP Snooping	86400

---

## show ip dhcp snooping database

---

**Syntax**

**show ip dhcp snooping database**

---

**Parameter**

None

---

**Default**

No default is defined

---

**Mode**

Privileged EXEC

---

**Usage**

Use the **show ip dhcp snooping database** command to show settings of DHCP Snooping agent.



## **Example**

The example shows how to show settings of DHCP Snooping agent.

```
switch(config)# show ip dhcp snooping database
Type : tftp: 192.168.1.50
FileName : backup_file
Write delay Timer : 300 seconds
Abort Timer : 60 seconds

Agent Running : Running
Delay Timer Expiry : 300 seconds
Abort Timer Expiry : 299

Last Succeeded Time : None
Last Failed Time : None
Last Failed Reason : No failure recorded.

Total Attempts      : 1
Successful Transfers : 1   Failed Transfers :
                        0 Successful Reads    : 1
Failed Reads        : 0   Successful Writes   :
                        0   Failed Writes       : 0
```

---

## **7. DoS**

### **dos**

#### Syntax

```
dos (daeqsa-deny|icmp-frag-pkts-deny|icmpv4-ping-max-
check|icmpv6-ping-max-check|ipv6-min-frag-size-check|land-
deny|nullscan-deny|pod-denry|smurf-denry|syn-sport1024-
denry|synfin-denry|synrst-denry|tcp-frag-off-min-check|tcpblat-
denry|tcphdr-min-check|udpblat-denry|xmas-denry)
dos icmp-ping-max-length MAX_LEN
dos ipv6-min-frag-size-length MIN_LEN
dos smurf-netmask MASK
dos tcp(hdr)-min-length HDR_MIN_LEN
no dos (tcp-frag-off-min-check|synrst-denry|synfin-denry|xma-
denry|nullscan-deny|syn-sport1024-denry|tcp(hdr)-min-check|smurf-
denry|icmpv6-ping-max-check|icmpv4-ping-max-check|icmp-frag-
pkts-denry|ipv6-min-frag-size-check|pod-denry|tcpblat-
denry|udpblat-denry|land-denry|daeqsa-denry)
```

<b>Parameter</b>	<b>daeqsa-deny</b>	Drops the packets if the destination MAC address is equal to the source MAC address.
	<b>icmp-frag-pkts-deny</b>	Drops the fragmented ICMP packets.
	<b>icmpv4-ping-max-check</b>	Checks the maximum size of ICMP ping packets, and drops the packets larger than the maximum packet size defined by the command <b>dos icmp-ping-max-length <i>MAX_LEN</i></b> .



<b>icmpv6-ping-max-check</b>	Checks the maximum size of ICMPv6 ping packets, and drops the packets larger than the maximum packet size defined by the command <b>dos icmp-ping-max-length MAX_LEN</b> .
<b>ipv6-min-frag-size-check</b>	Checks the minimum size of IPv6 fragments, and drops the packets smaller than the minimum size defined by the command <b>dos ipv6-min-frag-size-length MIN_LEN</b> .
<b>land-deny</b>	Drops the packets if the source IP address is equal to the destination IP address.
<b>nullscan-deny</b>	Drops the packets with NULL scan.
<b>pod-deny</b>	Avoids ping of death attack.
<b>smurf-deny</b>	Avoids smurf attack.
<b>syn-sportl1024-deny</b>	Drops SYN packets with sport less than 1024.
<b>synfin-deny</b>	Drops the packets with SYN and FIN bits set.
<b>synrst-deny</b>	Drops the packets with SYN and RST bits set.
<b>tcp-frag-off-min-check</b>	Drops the TCP fragment packets with offset equals to one.
<b>tcpblat-deny</b>	Drops the packages if the TCP source port is equal to the TCP destination port.
<b>tcphdr-min-check</b>	Checks the minimum TCP header and drops the TCP packets with the header smaller than the minimum size defined by the command <b>dos tcphdr-min-length HDR_MIN_LEN</b> .
<b>udpblat-deny</b>	Drops the packets if the UDP source port equals to the UDP destination port.
<b>xmas-deny</b>	Drops the packets if the sequence number is zero, and the FIN, URG and PSH bits are set.
<b>icmp-ping-max-length MAX_LEN</b>	Specify the maximum size of the ICMPv4/ICMPv6 ping packets. The valid range is from 0 to 65535 bytes, and the default value is 512 bytes.
<b>ipv6-min-frag-size-length MIN_LEN</b>	Specify the minimum size of IPv6 fragments. The valid range is from 0 to 65535 bytes, and default value is 1240 bytes.
<b>smurf-netmask MASK</b>	Specify the netmask of smurf attack. The length range is from 0 to 323 bytes, and default length is 0 bytes.
<b>tcphdr-min-length HDR_MIN_LEN</b>	Specify the minimum TCP header length. The length range is from 0 to 31 bytes, and default length is 20 bytes.

## Default

All of DoS protections are enabled by default. The default parameter are:

- The maximum size of ICMP ping packages is 512 bytes
- The minimum size of IPv6 fragments is 1240 bytes.
- The Smurf netmask length is 0 bytes.
- The minimum TCP header length is 20 bytes.



<b>Mode</b>	Global Configuration
<b>Usage</b>	To enable the specific Deniel of Service (DoS) protection, use the command <b>dos</b> in the Global Configuration mode. Otherwise, use the <b>no</b> form of the command to disable the specific DoS protection.
<b>Example</b>	The following example sets the minimum fragment size to 1024 bytes, and enables the minimum size of IPv6 fragments validation.
<pre>Switch(config)# dos ipv6-min-frag-size-length 1024 Switch(config)# dos ipv6-min-frag-size-check</pre>	
<b>dos (interface)</b>	
<b>Syntax</b>	<b>dos</b> <b>no dos</b>
<b>Parameter</b>	N/A
<b>Default</b>	DoS protection is disabled on each interface.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	To enable the DoS on the specific interface, use the command <b>dos</b> in the Interface Configuration mode. Otherwise, use the <b>no</b> form of the command to disable the DoS on the interface.
<b>Example</b>	The following example enables the DoS on the interface fa1.
<pre>Switch(config)# interface fa1 Switch(config-if)# dos</pre>	
<b>show dos</b>	
<b>Syntax</b>	<b>show dos</b> <b>show dos interface <i>IF_PORTS</i></b>
<b>Parameter</b>	<b>interface <i>IF_PORTS</i></b> An interface ID or the list of interface IDs.
<b>Default</b>	N/A



<b>Mode</b>	Privileged EXEC
<b>Usage</b>	To show the DoS protection configuration, use the command <b>show dos</b> in the Privileged EXEC mode. For the status of DoS protection on each interface, use the command <b>show dos interface</b> in the Privileged EXEC mode.
<b>Example</b>	The following example shows the global DoS protection configuration.
<hr/>	
	<pre>Switch# show dos   Type                                  State (Length) -----+-----+-----+-----+-----+-----+   DMAc equal to SMAC        enabled   Land (DIP = SIP)          enabled UDP   Blat (DPORT = SPORT)     enabled TCP   Blat (DPORT = SPORT)     enabled POD   (Ping of Death)           enabled   IPv6 Min Fragment Size   enabled (1024 Bytes)   ICMP Fragment Packets   enabled   IPv4 Ping Max Packet Size   enabled (512 Bytes)   IPv6 Ping Max Packet Size   enabled (512 Bytes)   Smurf Attack             enabled (Netmask Length: 0)   TCP Min Header Length   enabled (20 Bytes)   TCP Syn (SPORT &lt; 1024)   enabled   Null Scan Attack         enabled   X-Mas Scan Attack       enabled   TCP SYN-FIN Attack      enabled   TCP SYN-RST Attack      enabled   TCP Fragment (Offset = 1)   enabled</pre>
	<pre>Switch# show dos</pre>
<hr/>	
	The following example shows the status of DoS protection on the interface fa1.
	<pre>Switch# show dos interfaces fa1   Port        DoS Protection -----+-----+-----+-----+   fa1        disabled</pre>

## 8. Dynamic ARP Inspection

### ip arp inspection

<b>Syntax</b>	<b>ip arp inspection no ip arp inspection</b>
<b>Parameter</b>	None
<b>Default</b>	Dynamic Arp inspection is disabled



<b>Mode</b>	Global Configuration
-------------	----------------------

<b>Usage</b>	Use the <b>ip arp inspection</b> command to enable Dynamic Arp Inspection function. Use the <b>no</b> form of this command to disable.
--------------	--

<b>Example</b>	The example shows how to enable Dynamic Arp Inspection on VLAN 1. You can verify settings by the following <b>show ip arp inspection</b> command.
----------------	---

```
switch(config)# ip arp inspection
switch(config)# ip arp inspection vlan 1
switch(config)# show ip arp inspection
Dynamic ARP Inspection    : enabled
Enable on Vlans           : 1
```

## ip arp inspection vlan

<b>Syntax</b>	<b>ip arp inspection vlan VLAN-LIST no ip arp inspection vlan VLAN-LIST</b>
---------------	---

<b>Parameter</b>	VLAN-LIST                          Specify VLAN ID or a range of VLANs to enable or disable dynamic Arp inspection
------------------	--

<b>Default</b>	Default is disabled on all VLANs
----------------	----------------------------------

<b>Mode</b>	Global Configuration
-------------	----------------------

<b>Usage</b>	Use the <b>ip arp inspection vlan</b> command to enable VLANs on Dynamic Arp Inspection function. Use the <b>no</b> form of this command to disable VLANs on Dynamic Arp Inspection function.
--------------	---

<b>Example</b>	The example shows how to enable VLAN 1-100 on Dynamic Arp Inspection, and then disable VLAN 30-40 on Dynamic Arp Inspection. You can verify settings by the following <b>show ip arp inspection</b> command.
----------------	--

```
switch(config)# vlan 1-100
switch(config)# exit
switch(config)# ip arp inspection
switch(config)# ip arp inspection vlan 1-100
switch(config)# show ip arp inspection
Dynamic ARP Inspection    : enabled
Enable on Vlans           : 1-100

switch(config)# no ip arp inspection vlan 30-40
switch(config)# show ip arp inspection
Dynamic ARP Inspection    : enabled
Enable on Vlans           : 1-29,41-100
```

## ip arp inspection trust



---

**Syntax**

**ip arp inspection trust**



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

**no ip arp inspection trust**

---

**Parameter**

None

---

**Default**

Dynamic Arp inspection trust is disabled

---

**Mode**

Interface Configuration

---

**Usage**

Use the **ip arp inspection trust** command to set trusted interface. The switch does not check ARP packets that are received on the trusted interface; it simply forwards it. Use the **no** form of this command to set untrusted interface.

---

**Example**

The example shows how to set interface gi1 to trust. You can verify settings by the following **show ip arp inspection interface** command.

```
switch(config)# interface gi1
switch(config)# ip arp inspection trust
switch(config)# do show ip arp inspection interface gi1
Interfaces | Trust State | Rate (pps) | SMAC Check | DMAC Check | IP Check/Allow Zero
|-----+-----+-----+-----+-----+
gi1   | Trusted | None    | disabled | disabled | disabled/disabled
```

---

## ip arp inspection validate

---

**Syntax**

```
ip arp inspection validate
src-mac ip arp inspection
validate dst-mac
ip arp inspection validate ip
[allow-zeros] no ip arp inspection
validate src-mac
no ip arp inspection validate dst-mac
no ip arp inspection validate ip [allow-zeros]
```

---

**Parameter**

None

---

**Default**

Default is disabled of all validation

---

**Mode**

Interface Configuration

---

**Usage**

Use the **ip arp inspection validate** command to enable validate function on interface. The **'src-mac'** drop ARP requests and reply packets that arp-sender-mac and ethernet-source-mac is not match. The **'dst-mac'** drops ARP reply packets that arp-target-mac and ethernet-dst-mac is not match. The **'ip'** drop ARP request and reply packets that sender-ip is invalid such as broadcast、multicast、all zero IP address and drop ARP reply packets that target-ip is invalid. The **'allow-zeros'** means won't drop all zero IP address. Use the **no** form of this command to disable validation.



## Example

The example shows how to set interface gi1 to validate '**'src-mac'**、'**'dst-mac'** and '**'ip allow zeros'**'. You can verify settings by the following **show ip arp inspection interface** command.

```
switch(config)# interface gi1
switch(config-if)# ip arp inspection validate src-mac
switch(config-if)# ip arp inspection validate dst-mac
switch(config-if)# ip arp inspection validate ip allow-zeros
switch(config)# do show ip arp inspection interface gi1
Interfaces | Trust State | Rate (pps) | SMAC Check | DMAC Check | IP Check/Allow Zero
|
-----+-----+-----+-----+
gi1   | Untrusted | None    | enabled  | enabled  | enabled/ enabled
```

## ip arp inspection rate-limit

### Syntax

```
ip arp inspection rate-limit
<1-50> [no] ip arp inspection
rate-limit
```

### Parameter

<1-50>	Set 1 to 50 PPS of DHCP packet rate limitation
--------	--

### Default

Default is un-limited of ARP packet

### Mode

Interface Configuration

### Usage

Use the **ip arp inspection rate-limit** command to set rate limitation on interface. The switch drop ARP packets after receives more than configured rate of packets per second. Use the **no** form of this command to return to default settings.

## Example

The example shows how to set rate limit to 30 pps on interface gi1. You can verify settings by the following **show ip arp inspection interface** command.

```
switch(config)# interface gi1
switch(config)# ip arp inspection rate-limit 30
switch(config)# do show ip arp inspection interface gi1
Interfaces | Trust State | Rate (pps) | SMAC Check | DMAC Check | IP Check/Allow Zero
|
-----+-----+-----+-----+
gi1   | Untrusted | 30     | disabled | disabled | disabled/disabled
```

## clear ip arp inspection statistics

### Syntax

```
clear ip arp inspection interfaces IF_PORTS statistics
```

### Parameter

IF_PORTS	specifies ports to clear statistics
----------	-------------------------------------

### Default

No default is defined



---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	Use the <b>clear ip arp inspection interfaces statistics</b> command to clear statistics that are recorded on interface.
--------------	--

---

<b>Example</b>	The example shows how to clear statistics on interface gi1. You can verify settings by the following <b>show ip arp inspection interface statistics</b> command.
----------------	--

```
switch# clear ip arp inspection interfaces gi1 statistics
switch# show ip arp inspection interfaces gi1 statistics
Port| Forward |Source MAC Failures|Dest MAC Failures|
SIP Validation Failures|DIP Validation Failures|IP-MAC Mismatch Failures
-----+-----+-----+-----+-----+
gi1| 0 | 0 | 0 | 0 | 0 | 0
```

## show ip arp inspection

---

<b>Syntax</b>	<b>show ip dhcp snooping</b>
---------------	------------------------------

---

<b>Parameter</b>	<b>None</b>
------------------	-------------

---

<b>Default</b>	No default is defined
----------------	-----------------------

---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	Use the <b>show ip arp inspection</b> command to show settings of Dynamic Arp Inspection
--------------	--

---

<b>Example</b>	The example shows how to show settings of Dynamic Arp Inspection
----------------	--

```
switch(config)# show ip arp inspection
Dynamic ARP Inspection : enabled
Enable on Vlans 1
```

## show ip arp inspeciton interface

---

<b>Syntax</b>	<b>show ip arp inspection interfaces IF_PORTS</b> <b>show ip arp inspection interfaces IF_PORTS statistics</b>
---------------	---

---

<b>Parameter</b>	<b>IF_PORTS</b> specifies ports to show statistics
------------------	--



**Default** No default is defined

**Mode** Privileged EXEC

**Usage** Use the **show ip arp inspection interfaces** command to show settings or statistics of interface.

**Example** The example shows how to show settings of interface gi1.

```
switch# show ip arp inspection interface gi1
Interfaces | Trust State | Rate (pps) | SMAC Check | DMAC Check | IP Check/Allow Zero
|-----+-----+-----+-----+-----+
gi1   | Trusted    | None     | disabled  | disabled  | disabled/disabled
```

The example shows how to show statistics of interface gi1.

```
switch# show ip arp inspection interfaces gi1 statistics
Port| Forward |Source MAC Failures|Dest MAC Failures|
SIP Validation Failures|DIP Validation Failures|IP-MAC Mismatch Failures
-----+-----+-----+-----+-----+
gi1| 0 | 0 | 0 | 0 | 0 | 0
```

## 9. GVRP

### gvrp (Global)

**Syntax** **gvrp**  
**no gvrp**

**Parameter** None

**Default** GVRP is disabled

**Mode** Global Configuration

**Usage** Disable gvrp will clear all learned dynamic vlan entry and do not learn dynamic vlan anymore.  
Use ‘show gvrp’ to show configuration.

**Example** The following example specifies that set global gvrp test.  
Switch(config)# **gvrp**  
Switch# **show gvrp**



GVRP Status	
GVRP	: Enabled
Join time	: 200 ms
Leave time	: 600 ms
LeaveAll time	: 10000 ms

## gvrp (Interface)

<b>Syntax</b>	<b>gvrp</b> <b>no gvrp</b>
<b>Parameter</b>	none
<b>Default</b>	GVRP is disabled on interface
<b>Mode</b>	Interface mode
<b>Usage</b>	‘no gvrp’ will remove dynamic port from vlan. ‘gvrp’ must work at port mode is trunk.
<b>Example</b>	<p>The following example specifies that set port gvrp test. The port gvrp enable must set port mode is trunk firstly.</p> <pre>Switch(config)#interface gi1 Switch(config-if)# switchport mode trunk Switch(config)#gvrp Switch# show gvrp configuration interfaces gi1 Port   GVRP-Status   Registration   Dynamic VLAN Creation -----+-----+-----+ gi1    Enabled     Normal      Disabled</pre>

## gvrp registration-mode

<b>Syntax</b>	<b>gvrp registration-mode (normal   fixed   forbidden)</b>
<b>Parameter</b>	(normal   fixed   forbidden) <p>normal: register dynamic vlan, and transmit all vlan attribute.</p> <p>fixed: do not register dynamic vlan, and only transmit static vlan attribute.</p> <p>forbidden: do not register dynamic vlan, and only transmit default vlan attribute.</p>



---

<b>Default</b>	Default is Normal
<b>Mode</b>	Interface mode
<b>Usage</b>	When set registration-mode is fixed or forbidden, will remove the port from vlan which is dynamic port. And do not learning vlan.
<b>Example</b>	<p>The following example specifies that set gvrp registration mode test.</p> <pre>Switch(config)# interface gi1 Switch(config-if)# gvrp registration-mode fixed Switch# show gvrp configuration interfaces gi1   Port   GVRP-Status   Registration   Dynamic VLAN Creation   +-----+-----+ gi1   Enabled    Fixed      Disabled</pre>

## **gvrp vlan-create-forbid**

---

<b>Syntax</b>	<b>gvrp vlan-creation-forbid</b> <b>no gvrp vlan-creation-forbid</b>
<b>Parameter</b>	none
<b>Default</b>	Default is disabled.
<b>Mode</b>	Interface mode
<b>Usage</b>	‘gvrp vlan-creation-forbid’ will not remove dynamic port from vlan immediate.
<b>Example</b>	<p>The following example specifies that set port gvrp vlan-creation-forbid test.</p> <pre>Switch(config)#interface gi1 Switch(config-if)# gvrp vlan-creation-forbid Switch(config-if)#exit Switch# show gvrp configuration interfaces gi1   Port   GVRP-Status   Registration   Dynamic VLAN Creation   +-----+-----+ gi1   Enabled    Normal     Enabled</pre>

## **clear gvrp statistics**



Syntax

**clear gvrp (error-statistics | statistics) [interfaces IF\_PORTS]**

Parameter

(error-statistics   statistics)	Error-statistics: error gvrp packet statistics Statistics: gvrp event message
[interfaces <u>IF_PORTS]</u>	Specifies posts to clear statistics

Default

none

Mode

Privileged EXEC

Usage

This command will clear the ports error statistics or statistics info.

Example

The following example specifies that clear gvrp error statistics and statistics test.

```
Switch# clear gvrp statistics  
Switch# clear gvrp error-statistics
```

## show gvrp statistics

Syntax

**show gvrp (statistics | error-statistics) [interfaces IF\_PORTS]**

Parameter

none	Display all ports
(statistics  error- statistics)	statistics – GVRP statistics error-statistics GVRP error
[interfaces <u>IF_PORTS]<td>Specifies posts</td></u>	Specifies posts

Default

Display all ports statistics info

Mode

Privileged EXEC

Usage

This command will display the ports error statistics or statistics info.



---

**Example**

The following example specifies that display gvrp error statistics and statistics test.

Switch# **show gvrp statistics**

```
Port id      : fa1
Total RX    : 0
JoinEmpty RX : 0
JoinIn RX   : 0
Empty RX    : 0
LeaveIn RX  : 0
LeaveEmpty RX :
              0
LeaveAll RX  : 0
Total TX    : 0
JoinEmpty TX : 0
JoinIn TX   : 0
Empty TX    : 0
LeaveIn TX  : 0
LeaveEmpty TX :
              0
LeaveAll TX  : 0
```

```
Port id      : fa2
Total RX    : 0
JoinEmpty RX : 0
JoinIn RX   : 0
Empty RX    : 0
LeaveIn RX  : 0
LeaveEmpty RX :
              0
LeaveAll RX  : 0
Total TX    : 0
...
```

Switch# **show gvrp error-statistics**

INVPROT : Invalid protocol Id

INVATYP : Invalid Attribute Type INVALEN : Invalid Attribute Length

INVAVAL : Invalid Attribute Value INVEVENT: Invalid Event

Port	INVPROT	INVATYP	INVALEN	INVAVAL	INVEVENT
gi1	0	0	0	0	0
gi2	0	0	0	0	0
gi3	0	0	0	0	0
gi4	0	0	0	0	0
gi5	0	0	0	0	0
gi6	0	0	0	0	0

---

**show gvrp**

---

**Syntax**

**show gvrp**

---



# **Command Line Interface**

## **User Guide**

---

<b>Parameter</b>	none
------------------	------

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

---

**Default** None

---

**Mode** Privileged EXEC

---

**Usage** This command will display the gvrp global info.

---

**Example** The following example specifies that display gvrp test.

```
Switch# show gvrp
      GVRP Status
```

---

GVRP	: Disabled
Join time	: 200 ms
Leave time	: 600 ms
LeaveAll time	: 10000 ms

---

## show gvrp configuration

---

**Syntax** **show gvrp configuration [interface IF\_PORTS]**

---

none	Display all ports configuration
[interfaces IF_PORTS]	Display Specifies posts configuration

---

---

**Default** Display all ports configuration info

---

**Mode** Privileged EXEC

---

**Usage** This command will display the ports configuration info.

---

**Example** The following example specifies that display gvrp port configuration test.

```
Switch# show gvrp configuration
      Port | GVRP-Status | Registration | Dynamic VLAN Creation
```

---

gi1	Disabled	Normal	Enabled
gi 2	Disabled	Normal	Enabled

---



---

gi 3	Disabled	Normal	Enabled
gi 4	Disabled	Normal	Enabled
gi 5	Disabled	Normal	Enabled
gi 6	Disabled	Normal	Enabled
gi 7	Disabled	Normal	Enabled
--More--			

---

## 10. IGMP Snooping

### ip igmp snooping

---

Syntax	<b>ip igmp snooping</b> <b>no ip igmp snooping</b>
Parameter	None
Default	Default is enabled
Mode	Global Configuration
Usage	Use the <b>ip igmp snooping</b> command to enable IGMP snooping function. Use the <b>no</b> form of this command to disable. You can verify settings by the <b>show ip igmp snooping</b> command.
Example	The following example specifies that set ip igmp snooping test. Switch(config)# <b>no ip igmp snooping</b>

---

### ip igmp snooping report-suppression

---

Syntax	<b>ip igmp snooping report-suppression</b> <b>no ip igmp snooping report-suppression</b>
Parameter	None
Default	Default is enabled
Mode	Global Configuration

---



---

<b>Usage</b>	Use the <b>ip igmp snooping report-suppression</b> command to enable IGMP snooping report-suppression function. Use the <b>no</b> form of this command to disable. Disable report-supression will forward all received reports to the vlan router ports. You can verify settings by the <b>show ip igmp snooping</b> command.
--------------	---

---

<b>Example</b>	The following example specifies that disable ip igmp snooping report-suppression test.
----------------	--

## ip igmp snooping version

---

<b>Syntax</b>	<b>ip igmp snooping version (2 3)</b>	
<b>Parameter</b>	(2 3)	IGMP version 2 or IGMP version 3 basic mode
<b>Default</b>	Default is version 2	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Use the <b>ip igmp snooping version</b> command to change IGMP support version. Only basic mode is supported in v3. When change version from v3 to v2, all querier version will update to version 2. You can verify settings by the <b>show ip igmp snooping</b> command.	
<b>Example</b>	The following example specifies that set ip igmp snooping version 3. Switch(config)# <b>ip igmp snooping version 3</b>	

## ip igmp snooping unknown-multicast action

---

<b>Syntax</b>	<b>ip igmp snooping unknown-multicast action (drop   flood   router-port) no ip igmp snooping unknown-multicast action</b>	
<b>Parameter</b>	(drop   flood   router-port)	Drop、flood in vlan or forward to router port of unknown multicast packet
<b>Default</b>	Default is flood.	
<b>Mode</b>	Global Configuration	



---

**Usage**

When igmp and mld snooping disabled, it can't set action router-port.  
When disable igmp snooping & mld snooping, it set unknown multicast action flood. When action is router-port to flood or drop, it will delete the unknown multicast group entry.

Use the **ip igmp snooping unknown-multicast action** command to change action.

Use the **no** form of this command to restore to default.

You can verify settings by the **show ip igmp snooping** command.

---

**Example**

The following example specifies that set ip igmp unknown multicast action router-port test.

Switch(config)# **ip igmp snooping**

Switch(config)# **ip igmp snooping unknown-multicast action router-port**

---

## ip igmp snooping querier

---

**Syntax**

**ip igmp snooping vlan <VLAN-LIST> querier [version (2|3)]**  
**no ip igmp snooping [vlan <VLAN-LIST>] querier**

---

**Parameter**

VLAN-LIST	specifies VLAN ID list to set
(2 3)	Query version 2 or 3

---

**Default**

No ip igmp snooping querier by default

---

**Mode**

Global Configuration

---

**Usage**

When enable ip igmp vlan querier, there will process router select, the select successful will send general and specific query.

Use the **ip igmp snooping querier** command to add querier.

Use the **no** form of this command to delete querier.

You can verify settings by the **show ip igmp snooping querier** command.

---

**Example**

The following example specifies that set ip igmp snooping querier test.

Switch(config)# **ip igmp snooping vlan 2 querier version 3**

---

## ip igmp snooping vlan

---

**Syntax**

**ip igmp snooping vlan VLAN-LIST**



---

**no ip igmp snooping vlan VLAN-LIST**

---

<b>Parameter</b>	VLAN-LIST	specifies VLAN ID list to set
<b>Default</b>	Default is disabled for all VLANs	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Disable will clear all ip igmp snooping dynamic group and dynamic router port and make all static ip igmp group invalid of this vlan. Will not learn dynamic group and router port by igmp message any more. Use the <b>ip igmp snooping vlan</b> command to enable IGMP on VLAN. Use the <b>no</b> form of this command to disable You can verify settings by the <b>show ip igmp snooping vlan</b> command.	
<b>Example</b>	The following example specifies that set ip igmp snooping vlan test.	
	<pre>Switch(config)# ip igmp snooping Switch(config)# ip igmp snooping vlan 2</pre>	
<hr/>		
<h2>ip igmp snooping vlan fastleave</h2>		
<b>Syntax</b>	<b>ip igmp snooping vlan &lt;VLAN-LIST&gt; fastleave</b> <b>no ip igmp snooping vlan &lt;VLAN-LIST&gt; fastleave</b>	
<b>Parameter</b>	VLAN-LIST	specifies VLAN ID list to set
<b>Default</b>	Default is disabled	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Use the <b>ip igmp snooping vlan fastleave</b> command to enable fastleave function. Group will remove port immediately when receive leave packet. Use the <b>no</b> form of this command to disable. You can verify settings by the <b>show ip igmp snooping vlan</b> command	
<b>Example</b>	The following example specifies that set ip igmp snooping vlan <b>fastleave</b> test. <pre>Switch(config)# ip igmp snooping vlan 1 fastleave</pre>	

---

## ip igmp snooping vlan last-member-query-count

**Syntax**      **ip igmp snooping vlan <VLAN-LIST> last-member-query-count <1-7>**  
**no ip igmp snooping vlan <VLAN-LIST> last-member-query-count**

**Parameter**      **VLAN-LIST**      specifies VLAN ID list to set  
**last-member-query-**      specifies last member query count to set.  
**count <1-7>**

**Default**      Default is 2

**Mode**      Global Configuration

**Usage**      Use the **ip igmp snooping vlan last-member-query-count** command to change how many query packets will send.  
Use the **no** form of this command to restore to default.  
You can verify settings by the **show ip igmp snooping vlan** command

**Example**      The following example specifies that set **ip igmp snooping vlan last-member-query-count** test.  
Switch(config)# **ip igmp snooping vlan 1 last-member-query-count 5**

## ip igmp snooping vlan last-member-query-interval

**Syntax**      **ip igmp snooping vlan <VLAN-LIST> last-member-query-interval <1-60>**  
**no ip igmp snooping vlan <VLAN-LIST> last-member-query-interval**

**Parameter**      **VLAN-LIST**      specifies VLAN ID list to set  
**last-member-query-**      specifies last member query interval to set  
**interval <1-60>**

**Default**      Default is 1

**Mode**      Global Configuration

**Usage**      Use the **ip igmp snooping vlan last-member-query-interval** command to set interval between each query packet.  
Use the **no** form of this command to restore to default



You can verify settings by the **show ip igmp snooping vlan** command

---

**Example**

The following example specifies that set **ip igmp snooping vlan last-member-query-interval** test.

Switch(config)# **ip igmp snooping vlan 1 last-member-query-interval 3**

---

## ip igmp snooping vlan query-interval

---

**Syntax**

**ip igmp snooping vlan <VLAN-LIST> query-interval <30-18000>**  
**no ip igmp snooping vlan <VLAN-LIST> query-interval**

---

**Parameter**

VLAN-LIST      specifies VLAN ID list to set  
query-interval <30-  
18000>      specifies query interval to set

---

**Default**

Default is 125

**Mode**

Global Configuration

---

**Usage**

Use the **ip igmp snooping vlan query-interval** command to set interval between each query.

Use the **no** form of this command to restore to default

You can verify settings by the **show ip igmp snooping vlan** command

---

**Example**

The following example specifies that set **ip igmp snooping vlan query-interval** test.

Switch(config)# **ip igmp snooping vlan 1 query-interval 100**

---

## ip igmp snooping vlan response-time

---

**Syntax**

**ip igmp snooping vlan <VLAN-LIST> response-time <5-20>**  
**no ip igmp snooping vlan <VLAN-LIST> response-time**

---

**Parameter**

VLAN-LIST      specifies VLAN ID list to set  
response-time <5-  
20>      specifies a response time to set

---



---

<b>Default</b>	Default is 10
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>ip igmp snooping vlan response-time</b> command to set response time</p> <p>Use the <b>no</b> form of this command to restore to default.</p> <p>You can verify settings by the <b>show ip igmp snooping vlan</b> command</p>
<b>Example</b>	<p>The following example specifies that set <b>ip igmp snooping vlan response-time</b> test.</p> <pre>Switch(config)# ip igmp snooping vlan 1 response-time 12</pre>

---

## ip igmp snooping vlan robustness-variable

---

<b>Syntax</b>	<b>ip igmp snooping vlan &lt;VLAN-LIST&gt; robustness-variable &lt;1-7&gt;</b> <b>no ip igmp snooping vlan &lt;VLAN-LIST&gt; robustness-variable</b>						
<b>Parameter</b>	<table><tr><td><b>VLAN-LIST</b></td><td>specifies VLAN ID list to set</td></tr><tr><td><b>robustness-variable</b></td><td>specifies a robustness value to set</td></tr><tr><td><b>&lt;1-7&gt;</b></td><td></td></tr></table>	<b>VLAN-LIST</b>	specifies VLAN ID list to set	<b>robustness-variable</b>	specifies a robustness value to set	<b>&lt;1-7&gt;</b>	
<b>VLAN-LIST</b>	specifies VLAN ID list to set						
<b>robustness-variable</b>	specifies a robustness value to set						
<b>&lt;1-7&gt;</b>							
<b>Default</b>	Default is 2						
<b>Mode</b>	Global Configuration						
<b>Usage</b>	<p>Use the <b>ip igmp snooping vlan robustness-variable</b> command to times to retry.</p> <p>Use the <b>no</b> form of this command to restore to default</p> <p>You can verify settings by the <b>show ip igmp snooping vlan</b> command</p>						
<b>Example</b>	<p>The following example specifies that set ip igmp snooping vlan parameters test.</p> <pre>Switch(config)# ip igmp snooping vlan 1 robustness-variable</pre>						

---

## ip igmp snooping vlan router

---

<b>Syntax</b>	<b>ip igmp snooping vlan VLAN-LIST router learn pim-dvmrp</b> <b>no ip igmp snooping vlan VLAN-LIST router learn pim-dvmrp</b>
---------------	---



---

<b>Parameter</b>	VLAN-LIST	specifies VLAN ID list to set
<b>Default</b>	Default is enabled	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Use the <b>ip igmp snooping vlan router</b> command to enable learning router port by routing protocol packets such as PIM/PIMv2, DVMRP, MOSPF. Use the <b>no</b> form of this command to disable. You can verify settings by the <b>show ip igmp snooping vlan</b> command	
<b>Example</b>	The following example specifies that set <b>ip igmp snooping vlan router</b> test. Switch(config)# <b>ip igmp snooping vlan 99 router</b>	

---

## ip igmp snooping vlan forbidden-port

---

<b>Syntax</b>	<b>ip igmp snooping vlan &lt;VLAN-LIST&gt; forbidden-port IF_PORTS</b> <b>no ip igmp snooping vlan &lt;VLAN-LIST&gt; forbidden-port IF_PORTS</b>
<b>Parameter</b>	VLAN-LIST      specifies VLAN ID list to set IF_PORTS      specifies a port list to set or remove
<b>Default</b>	No forbidden ports by default
<b>Mode</b>	Global Configuration
<b>Usage</b>	‘ip igmp snooping vlan 1 static-port gi1-2’ will add static port gi1-2 for vlan 1.the all known vlan 1 ipv4 group will add the static ports. ‘ip igmp snooping vlan 1 forbidden-port gi3-4’ will add forbidden port gi3-4 for vlan 1.the all known vlan 1 ipv4 group will remove the forbidden ports. The configure can use ‘show ip igmp snooping forward-all’.
	Use the <b>ip igmp snooping vlan forbidden-port</b> command to add static non-forwarding port, all known vlan 1 ipv4 group will remove the forbidden ports. Use the <b>no</b> form of this command to delete forbidden port. You can verify settings by the <b>show ip igmp snooping forward-all</b> command.

---



**Example**

The following example specifies that set ip igmp snooping static/forbidden port test.

Switch(config)# **ip igmp snooping vlan 1 forbidden -port gi3-4**

---

## **ip igmp snooping vlan static-port**

**Syntax**

**ip igmp snooping vlan <VLAN-LIST> static-port IF\_PORTS**  
**no ip igmp snooping vlan <VLAN-LIST> static-port IF\_PORTS**

**Parameter**

<b>VLAN-LIST</b>	specifies VLAN ID list to set
<b>IF_PORTS</b>	specifies a port list to set or remove

---

**Default**

No static port by default

**Mode**

Global Configuration

**Usage**

Use the **ip igmp snooping vlan static-port** command to add static forwarding port, all known vlan 1 ipv4 group will add the static ports.  
Use the **no** form of this command to delete static port.  
You can verify settings by the **show ip igmp snooping forward-all** command.

**Example**

The following example specifies that set ip igmp snooping static port test.

Switch(config)# **ip igmp snooping vlan 1 static -port gi1-2**

---

## **ip igmp snooping vlan forbidden-router-port**

**Syntax**

**ip igmp snooping vlan <VLAN-LIST> forbidden-router-port IF\_PORTS**  
**no ip igmp snooping vlan <VLAN-LIST> forbidden-router-port IF\_PORTS**

**Parameter**

<b>VLAN-LIST</b>	specifies VLAN ID list to set
<b>IF_PORTS</b>	specifies a port list to set or remove

---

**Default**

No forbidden router ports by default

**Mode**

Global Configuration



---

**Usage**

Use the **ip igmp snooping vlan forbidden-router-port** command to add static forbidden router port. This will also remove port from static router port. The forbidden router port will not forward received query packet.  
Use the **no** form of this command to delete forbidden router port.  
You can verify settings by the **show ip igmp snooping router** command.

---

**Example**

The following example specifies that set ip igmp snooping forbidden test.  
Switch(config)# **ip igmp snooping vlan 1 forbidden-router-port gi2**

---

## **ip igmp snooping vlan static-router-port**

---

**Syntax**

**ip igmp snooping vlan <VLAN-LIST> static-router-port IF\_PORTS**  
**no ip igmp snooping vlan <VLAN-LIST> static-router-port IF\_PORTS**

---

**Parameter**

<b>VLAN-LIST</b>	specifies VLAN ID list to set
<b>IF_PORTS</b>	specifies a port list to set or remove

---

---

**Default**

No static router ports by default

---

**Mode**

Global Configuration

---

**Usage**

Use the **ip igmp snooping vlan static-router-port** command to add static router port. All query packets will forward to this port.  
Use the **no** form of this command to delete static router port.  
You can verify settings by the **show ip igmp snooping router** command.

---

**Example**

The following example specifies that set ip igmp snooping static test.  
Switch(config)# **ip igmp snooping vlan 1 static-router-port gi1-2**

---

## **ip igmp snooping vlan static-group**

---

**Syntax**

**ip igmp snooping vlan <VLAN-LIST> static-group [<ip-addr>] interfaces IF\_PORTS**  
**no ip igmp snooping vlan <VLAN-LIST> static-group <ip-addr> interfaces IF\_PORTS**

---

**Parameter**

<b>VLAN-LIST</b>	specifies VLAN ID list to set
------------------	-------------------------------

---



ip-addr	specifies multicast group ipv4 address
IF_PORTS	specifies port list to set or remove

---

**Default** No static group by default

---

**Mode** Global Configuration

---

**Usage** Use the **ip igmp snooping vlan static-group** command to add a static group. The static group will not learn other dynamic ports. If the dynamic group exists, then the static group will overlap the dynamic group. The static group set to valid unless igmp snooping global and vlan enable.

Use the **no** form of this command to delete a port in static group. If remove the last member of static group, the static group will be delete.

You can verify settings by the **show ip igmp snooping group** command.

---

**Example** The following example specifies that set ip igmp snooping static group test.  
Switch(config)# **ip igmp snooping vlan 1 static-group 224.1.1.1 interfaces gi1-2**

---

## **ip igmp snooping vlan group**

---

**Syntax** **no ip igmp snooping vlan <VLAN-LIST> group <ip-addr>**

---

Parameter	VLAN-LIST	specifies VLAN ID list to set
	ip-addr	specifies multicast group ipv4 address

---

**Default** None

---

**Mode** Global Configuration

---

**Usage** Use the **no ip igmp snooping vlan group** command to delete a group which could be static or dynamic.

You can verify settings by the **show ip igmp snooping group** command.

---

**Example** The following example specifies that set ip igmp snooping static group test.  
Switch(config)# **no ip igmp snooping vlan 1 group 224.1.1.1**

---



## profile range

---

### Syntax

**profile range ip <ip-addr> [ip-addr] action (permit | deny)**

---

<ip-addr>	Start ipv4 multicast address
[ip-addr]	End ipv4 multicast address
(permit   deny)	Permit: allow Multicast address range ip address learning deny: do not allow Multicast address range ip address learning

---

---

### Default

None

---

### Mode

igmp profile configuration mode

---

### Usage

Use the **profile** command to generate IGMP profile.  
You can verify settings by the **show ip igmp profile** command

---

### Example

The following example specifies that set ip igmp profile test.

Switch(config)# **ip igmp profile 1**

Switch(config-igmp-profile)# **profile range ip 224.1.1.1 224.1.1.8 action permit**

---

## ip igmp profile

---

### Syntax

**ip igmp profile <1-128>**  
**no ip igmp profile <1-128>**

---

---

### Parameter

<1-128> specifies profile ID

---

---

### Default

No profie exist by default



---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

<b>Usage</b>	Use the <b>ip igmp profile</b> command to enter profile configuration Use the <b>no</b> form of this command to delete profile You can verify settings by the <b>show ip igmp profile</b> command
--------------	---

---

<b>Example</b>	The following example specifies that set ip igmp profile test. Switch(config)# <b>ip igmp profile 1</b>
----------------	--

## **ip igmp filter**

---

<b>Syntax</b>	<b>ip igmp filter &lt;1-128&gt;</b> <b>[no] ip igmp filter</b>
---------------	---

---

<b>Parameter</b>	<b>&lt;1-128&gt;</b> specifies profile ID
------------------	---

---

<b>Default</b>	None
----------------	------

---

<b>Mode</b>	Port Configuration
-------------	--------------------

---

<b>Usage</b>	Use the <b>ip igmp filter</b> command to bind a profile for port. When the port bind a profile. Then the port learning group will update, if the group is not match the profile rule it will remove the port from the group. Static group is excluded. Use the <b>no</b> form of this command to delete profile You can verify settings by the <b>show ip igmp filter</b> command
--------------	---

---

<b>Example</b>	The following example specifies that set ip igmp filter test.
----------------	---

Switch(config)# **interface gi1**  
Switch(config-if)#**ip igmp filter 1**

---

## **ip igmp max-groups**

---

<b>Syntax</b>	<b>ip igmp max-groups &lt;0-1024&gt;</b> <b>no ip igmp max-groups</b>
---------------	--



<b>Parameter</b>	<0-1024>	The maximum number of IGMP groups that an interface can join.
<b>Default</b>	Default is 1024	
<b>Mode</b>	Port Configuration	
<b>Usage</b>	Use the <b>ip igmp max-groups</b> command to limit port learning max group number. When the port has reach limitation, new group will not add this port. Static group is excluded.  Use the <b>no</b> form of this command to restore to default You can verify settings by the <b>show ip igmp max-groups</b> command.	
<b>Example</b>	The following example specifies that set ip igmp max-groups test. Switch(config-if)# <b>ip igmp max-groups 10</b>	

---

## ip igmp max-groups action

<b>Syntax</b>	<b>ip igmp max-groups action (deny   replace)</b>	
<b>Parameter</b>	(deny   replace)	Deny: current port igmp group arrived max-groups, don't add group. Replace: current port igmp group arrived max-groups, remove port for rand group, and add port to new group.
<b>Default</b>	Default action is deny	
<b>Mode</b>	Port Configuration	
<b>Usage</b>	Use the <b>ip igmp max-groups action</b> command to set the action when the numbers of groups reach the limitation.  Use the <b>no</b> form of this command to restore to default You can verify settings by the <b>show ip igmp max-groups</b> command.	
<b>Example</b>	The following example specifies that set action replace test. Switch(config-if)# <b>ip igmp max-groups action replace</b>	

---



## **clear ip igmp snooping groups**

<b>Syntax</b>	<b>clear ip igmp snooping groups [(dynamic   static)]</b>
<b>Parameter</b>	none                    Clear ip igmp groups include dynamic and static (dynamic   static)    Ip igmp group type is dynamic or static
<b>Default</b>	None
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will clear the ip igmp groups for dynamic or static or all of type. You can verify settings by the <b>show ip igmp snooping groups</b> command.
<b>Example</b>	The following example specifies that clear ip igmp snooping groups test.  Switch# <b>clear ip igmp snooping groups</b> Switch# <b>show ip igmp snooping groups</b> VLAN   Group IP Address   Type   Life(Sec)   Port -----+-----+-----+-----+-----+  Total Number of Entry = 0

## **clear ip igmp snooping statistics**

<b>Syntax</b>	<b>clear ip igmp snooping statistics</b>
<b>Parameter</b>	none
<b>Default</b>	None
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will clear the igmp statistics. You can verify settings by the <b>show ip igmp snooping</b> command.



**Example**

The following example specifies that clear ip igmp snooping statistics test.

Switch# **clear ip igmp snooping statistics**

Switch# **show ip igmp snooping**

IGMP Snooping Status

---

Snooping : Enabled  
Report Suppression : Enabled  
Operation Version : v2  
Forward Method : mac  
Unknown IP Multicast Action : Flood

Packet Statistics

Total RX : 0  
Valid RX : 0  
Invalid RX : 0  
Other RX : 0  
Leave RX : 0  
Report RX : 0  
General Query RX : 0 Specail  
Group Query RX : 0  
Specail Group & Source Query RX : 0  
Leave TX : 0  
Report TX : 0  
General Query TX : 0  
Specail Group Query TX : 0  
Specail Group & Source Query TX : 0

---

## **show ip igmp snooping groups counters**

---

**Syntax** **show ip igmp snooping groups**

---

**Parameter** none

---

**Default** none

---

**Mode** Privileged EXEC

---

**Usage** This command will display the ip igmp group counter include static group.

---

**Example**

The following example specifies that display ip igmp snooping group counter test.

---

Switch# **show ip igmp snooping group counters**



---

Total ip igmp snooping group number: 2  
Total ip igmp snooping static mac number: 0

---

## show ip igmp snooping groups

---

### Syntax

**show ip igmp snooping groups [(dynamic | static)]**

---

### Parameter

none	Show ip igmp groups include dynamic and static
(dynamic   static)	Display Ip igmp group type is dynamic or static

---

### Default

None

---

### Mode

Privileged EXEC

---

### Usage

This command will display the ip igmp groups for dynamic or static or all of type.

---

### Example

The following example specifies that show ip igmp snooping groups.

Switch# **show ip igmp snooping groups**  
VLAN | Group IP Address | Type | Life(Sec) | Port  
-----+-----+-----+-----+-----+-----+  
1 | 224.1.2.3 | Static| -- | fa9  
1 | 224.1.2.4 | Static| -- | fa10

---

Total Number of Entry = 2

## show ip igmp snooping router

---

### Syntax

**show ip igmp snooping router [(dynamic | forbidden |static )]**

---

### Parameter

none	Show ip igmp router include dynamic and static and forbidden
(dynamic   forbidden   static)	Display Ip igmp router info for different type

---

### Default

None



<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will display the ip igmp router info.
<b>Example</b>	<p>The following example specifies that show ip igmp snooping router.</p> <pre>Switch# <b>show ip igmp snooping router</b> Dynamic Router Table  VID   Port   Expiry Time(Sec) -----+-----+ Total Entry 0  Static Router Table  VID   Port Mask -----+-----+  1   fa4  Total Entry 1  Forbidden Router Table  VID   Port Mask -----+-----+  1   fa8  Total Entry 1</pre>
<b>Syntax</b>	<b>show ip igmp snooping querier</b>
<b>Parameter</b>	none Show all vlan ip igmp querier info.
<b>Default</b>	None
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will display all of the static vlan ip igmp querier info.

## **show ip igmp snooping querier**

<b>Syntax</b>	<b>show ip igmp snooping querier</b>
<b>Parameter</b>	none Show all vlan ip igmp querier info.
<b>Default</b>	None
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will display all of the static vlan ip igmp querier info.



---

**Example**

The following example specifies that show ip igmp snooping querier test.

Switch# **show ip igmp snooping querier**

VID	State	Status	Version	Querier IP
1	Disabled	Non-Querier	No	-----

---

Total Entry 1

## **show ip igmp snooping**

---

**Syntax** **show ip igmp snooping**

---

**Parameter** None

---

**Default** None

---

**Mode** Privileged EXEC

---

**Usage** This command will display ip igmp snooping global info.

---

**Example**

The following example specifies that show ip igmp snooping test.

Switch# **show ip igmp snooping**

IGMP Snooping Status

---

```
Snooping : Enabled
Report Suppression : Enabled
Operation Version : v2
Forward Method : mac
Unknown Multicast Action : Flood
```

### Packet Statistics

```
Total RX : 0
Valid RX : 0
Invalid RX : 0
Other RX : 0
Leave RX : 0
Report RX : 0
General Query RX : 0 Specail
Group Query RX : 0
Specail Group & Source Query RX : 0
Leave TX : 0
```



---

Report TX	:	0
General Query TX	:	
0 Specail Group Query TX	:	0
Specail Group & Source Query TX	:	0

---

## show ip igmp snooping vlan

---

### Syntax

**show ip igmp snooping vlan [VLAN-LIST]**

---

### Parameter

none	Show all ip igmp snooping vlan info
[VLAN-LIST]	Show specifies vlan ip igmp snooping info

---

---

### Default

None

---

### Mode

Privileged EXEC

---

### Usage

This command will display ip igmp snooping vlan info.

---

### Example

The following example specifies that show ip igmp snooping vlan test.  
Switch# **show ip igmp snooping vlan 1**  
IGMP Snooping is globaly enabled  
IGMP Snooping VLAN 1 admin : disabled  
IGMP Snooping operation mode : disabled  
IGMP Snooping robustness: admin 2 oper 2  
IGMP Snooping query interval: admin 125 sec oper 125 sec  
IGMP Snooping query max response : admin 10 sec oper 10 sec  
IGMP Snooping last member query counter: admin 2 oper 2  
IGMP Snooping last member query interval: admin 1 sec oper 1 sec IGMP  
Snooping last immediate leave: disabled  
IGMP Snooping automatic learning of multicast router ports: enabled

---

## show ip igmp snooping forward-all

---

### Syntax

**show ip igmp snooping forward-all [vlan VLAN-LIST]**

---

### Parameter

none	Show all ip igmp snooping vlan forward-all info
[vlan VLAN-LIST]	Show specifies vlan of ip igmp forward info.

---

---

### Default

None



---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	This command will display ip igmp snooping forward all info.
--------------	--

---

<b>Example</b>	The following example specifies that show ip igmp snooping forward-all test. Switch# <b>show ip igmp snooping forward-all 1</b> IGMP Snooping VLAN 1 IGMP Snooping static port : None IGMP Snooping forbidden port : None
----------------	---

## show ip igmp profile

---

<b>Syntax</b>	<b>show ip igmp profile [&lt;1-128&gt;]</b>
---------------	---

---

<b>Parameter</b>	none Show all ip igmp snooping profile info
	[<1-128>] Show specifies index profile info

---

<b>Default</b>	None
----------------	------

---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	This command will display ip igmp profile info.
--------------	---

---

<b>Example</b>	The following example specifies that show ip igmp profile test. Switch# <b>show ip igmp profile</b> IP igmp profile index: 1 IP igmp profile action: permit Range low ip: 224.1.1.1 Range high ip: 224.1.1.8  IP igmp profile index: 2 IP igmp profile action: deny Range low ip: 225.1.1.0 Range high ip: 225.1.2.1
----------------	--

## show ip igmp filter

---

<b>Syntax</b>	<b>show ip igmp filter [interfaces IF_PORTS]</b>
---------------	--

---

<b>Parameter</b>	none Show all port filter
------------------	---------------------------



[interfaces  
IF\_PORTS] Show specifies ports filter

---

**Default** None

---

**Mode** Privileged EXEC

---

**Usage** This command will display ip igmp port filter info.

---

**Example** The following example specifies that show ip igmp filter test.

Switch# **show ip igmp filter**

Port ID | Profile ID

-----+-----

gi1 : 1  
gi2 : None  
gi3 : None  
gi4 : None  
gi5 : None

--More--

## show ip igmp max-group

---

### Syntax

**show ip igmp max-group [interfaces IF\_PORTS]**

---

### Parameter

none Show all port max-group

[interfaces  
IF\_PORTS] Show specifies ports max-group

---

**Default** None

---

**Mode** Privileged EXEC

---

**Usage** This command will display ip igmp port max-group.

---

**Example** The following example specifies that show ip igmp max-group test.

Switch(config-if)#**ip igmp max-groups 50**

Switch# **show ip igmp max-group**



---

Port ID | Max Group

-----+  
gi1 : 50  
gi2 : 256  
gi3 : 256  
gi4 : 256  
gi5 : 256

--More--

---

## **show ip igmp max-group action**

---

### **Syntax**

**show ip igmp max-group action [interfaces IF\_PORTS]**

---

### **Parameter**

none	Show all port max-group action
[interfaces IF_PORTS]	Show specifies ports max-group action

---

### **Default**

None

---

### **Mode**

Privileged EXEC

---

### **Usage**

This command will display ip igmp port max-group action.

---

### **Example**

The following example specifies that show ip igmp max-group action test.

Switch(config)#**interface gi1**  
Switch(config-if)#**ip igmp max-groups action replace**  
Switch# **show ip igmp max-group action**

Port ID | Max-groups Action

-----+  
gi1 : replace  
gi2 : deny  
gi3 : deny  
gi4 : deny  
gi5 : deny

--More--

---

## **11. IP Source Guard**

### **ip source verify**



<b>Syntax</b>	<b>ip source verify</b> <b>[mac-and-ip] no ip source verify</b>
<b>Parameter</b>	mac-and-ip      Verify by mac and ip address boundle
<b>Default</b>	IP Source Guard is disabled on interface. Default is that verifying ip address only
<b>Mode</b>	Port Configuration
<b>Usage</b>	<p>Use the <b>ip source verify</b> command to enable IP Source Guard function. Default IP Source Guard filter source IP address. The “<b>mac-and-ip</b>” filters not only source IP address but also source MAC address.</p> <p>Use the <b>no</b> form of this command to disable.</p> <p>You can verify settings by the <b>show ip source interfaces</b> command.</p>
<b>Example</b>	<p>The example shows how to enable IP Source Guard with source IP address filtering on interface gi1.</p> <pre>Switch(config)# interface gi1 switch(config-if)# ip source verify</pre> <p>The example shows how to enable IP Source Guard with source IP and MAC address filtering on interface gi2.</p> <pre>Switch(config)# interface gi2 switch(config-if)# ip source verify mac-and-ip switch(config-if)# do show ip source interfaces gi1-2 Port   Status   Max Entry   Current Entry -----+-----+-----+ gi1   Verify MAC+IP   No Limit   0 gi2   disabled   No Limit   0</pre>

## ip source binding

<b>Syntax</b>	<b>ip source binding A:B:C:D:E:F vlan &lt;1-4094&gt; A.B.C.D interface IF_PORT</b> <b>no ip source binding A:B:C:D:E:F vlan &lt;1-4094&gt; A.B.C.D interface IF_PORT</b>								
<b>Parameter</b>	<table border="1"> <tr> <td>A:B:C:D:E:F</td> <td>Specify a MAC address of a binding entry</td> </tr> <tr> <td>VLAN &lt;1-4094&gt;</td> <td>Specify a VLAN ID of a binding entry</td> </tr> <tr> <td>A.B.C.D</td> <td>Specify IP address and MASK of a binding entry.</td> </tr> <tr> <td>IF_PORT</td> <td>Specify interface of a binding entry.</td> </tr> </table>	A:B:C:D:E:F	Specify a MAC address of a binding entry	VLAN <1-4094>	Specify a VLAN ID of a binding entry	A.B.C.D	Specify IP address and MASK of a binding entry.	IF_PORT	Specify interface of a binding entry.
A:B:C:D:E:F	Specify a MAC address of a binding entry								
VLAN <1-4094>	Specify a VLAN ID of a binding entry								
A.B.C.D	Specify IP address and MASK of a binding entry.								
IF_PORT	Specify interface of a binding entry.								



<b>Default</b>	Default is no binding entry.
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>ip source binding</b> command to create a static IP source binding entry has an IP address, its associated MAC address 、 VLAN ID 、 interface.</p> <p>Use the <b>no</b> form of this command to delete static entry.</p> <p>You can verify settings by the <b>show ip source binding</b> command.</p>
<b>Example</b>	<p>The example shows how to add a static IP source binding entry.</p> <pre>Switch(config)# ip source binding 00:11:22:33:44:55 vlan 1 192.168.1.55 interface fa1 switch(config)# do show ip source binding Bind Table: Maximun Binding Entry Number 192 Port   VID   MAC Address   IP   Type   Lease Time -----+-----+-----+-----+-----+ fa1   1   00:11:22:33:44:55   192.168.1.55(255.255.255.255)   Static   NA</pre>

## show ip source interface

<b>Syntax</b>	<b>show ip source interfaces IF_PORTS</b>
<b>Parameter</b>	<b>IF_PORTS</b> specifies ports to show
<b>Default</b>	No default is defined
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	<p>Use the <b>show ip source interface</b> command to show settings of IP Source Guard of interface</p>
<b>Example</b>	<p>The example shows how to show settings of IP Source Guard of interface g1</p> <pre>switch# show ip source interfaces g1 Port   Status   Max Entry   Current Entry -----+-----+-----+ g1   Verify MAC+IP   No Limit   0</pre>



## show ip source binding

### Syntax

**show ip source binding [(dynamic|static)]**

### Parameter

<b>dynamic</b>	Show entries that added by DHCP snooping learn
<b>static</b>	Show entries that added by user

### Default

No default is defined

### Mode

Privileged EXEC

### Usage

Use the **show ip source binding** command to show binding entries of IP Source Guard.

### Example

The example shows how to show static binding entries of IP Source Guard.

```
switch# show ip source binding
Bind Table: Maximum Binding Entry Number 192
Port | VID | MAC Address | IP | Type | Lease Time
---+---+-----+-----+-----+
fa1 | 1 | 00:11:22:33:44:55 | 192.168.1.55(255.255.255.255) | Static | NA
```

## 12. Link Aggregation

### lag

### Syntax

**lag <1-8> mode (static | active | passive)**  
**no lag**

### Parameter

<b>&lt;1-8&gt;</b>	Specify the LAG id for the interface
<b>static</b>	Specify the LAG to be static mode and join the interface into this LAG.
<b>active</b>	Specify the LAG to be dynamic mode and join the interface into this LAG with LACP active port.
<b>passive</b>	Specify the LAG to be dynamic mode and join the interface into this LAG with LACP passive port.

### Default

There is no LAG in default.



<b>Mode</b>	Interface Configuration
-------------	-------------------------

<b>Usage</b>	Link aggregation group function allows you to aggregate multiple physical ports into one logic port to increase bandwidth. This command makes normal port join into the specific LAG logic port with static or dynamic mode. And use “ <b>no lag</b> ” to leave the LAG logic port.
--------------	---

<b>Example</b>	This example shows how to create a dynamic LAG and join fa1-fa3 to this LAG.
----------------	--

```
Switch(config)# interface range fa1-3
Switch(config-if)# lag 1 mode active
```

This example shows how to show current LAG status.

```
Switch# show lag
Load Balancing: src-dst-mac-ip.
```

Group ID	Type	Ports
1	LACP	Inactive: fa1-3 2
3	-----	
4	-----	
5	-----	
6	-----	
7	-----	
8	-----	

## lag load-balance

<b>Syntax</b>	<b>lag load-balance (src-dst-mac   src-dst-mac-ip)</b> <b>no lag load-balance</b>
---------------	--

<b>Parameter</b>	<b>src-dst-mac</b> Specify algorithm to balance traffic by using source and destination MAC address for all packets.
	<b>src-dst-mac-ip</b> Specify algorithm to balance traffic by using source and destination IP address for IP packets and using source and destination MAC address for non-IP packets.

<b>Default</b>	Default load balance algorithm is src-dst-mac
----------------	---

<b>Mode</b>	Global Configuration
-------------	----------------------

<b>Usage</b>	Link aggregation group port should transmit packets spread to all ports to balance traffic loading. There are two algorithm supported and this command allow you to select the algorithm.
--------------	---



---

**Example**

This example shows how to change load balance algorithm to src-dst-mac-ip.

```
Switch(config) # lag load-balance src-dst-mac-ip
```

This example shows how to show current load balance algorithm.

```
Switch# show lag  
Load Balancing: src-dst-mac-ip.
```

Group	ID	Type	Ports
1			
2			
3			
4			
5			
6			
7			
8			

## lacp port-priority

---

**Syntax**

**lacp port-priority <1-65535>**

**no lacp port-priority**

---

**Parameter**

**<1-65535>** Specify port priority value

---

**Default**

Default port priority is 1.

---

**Mode**

Interface Configuration

---

**Usage**

LACP port priority is used for two connected DUT to select aggregation ports. Lower port priority value has higher priority. And the port with higher priority will be selected into LAG first.

The only way to show this configuration is using “**show running-config**” command.

---

**Example**

This example shows how to configure interface fa1 lacp port priority to 100.

```
Switch(config) # interface fa1  
Switch(config-if) # lacp port-priority 100
```

## lacp system-priority

---

**Syntax**

**lacp system-priority <1-65535>**

**no lacp system-priority**

---

**Parameter**

**<1-65535>** Specify system priority value



**Default** Default system priority is 32768.

**Mode** Global Configuration

**Usage** LACP system priority is used for two connected DUT to select master switch. Lower system priority value has higher priority. And the DUT with higher priority can decide which ports are able to join the LAG.

Use “**no lacp system-priority**” to restore to the default priority value. The only way to show this configuration is using “**show running-config**” command.

---

**Example** This example shows how to configure lacp system priority to 1000.  
Switch(config)# **lacp system-priority 1000**

---

## **lacp timeout**

**Syntax** **lacp timeout (long | short)**  
**no lacp timeout**

**Parameter** **long** Send LACP packet every 30 seconds.  
**short** Send LACP packet every 1 second.

---

**Default** Default LACP timeout is long.

**Mode** Interface Configuration

**Usage** LACP need to send LACP packet to partner switch to check the link status. This command configure the interval of sending LACP packets.

The only way to show this configuration is using “**show running-config**” command.

---

**Example** This example shows how to configure interface fa1 lacp timeout to short.  
Switch(config)# **interface fa1**  
Switch(config-if)# **lacp timeout short**

---

## **show lacp**

**Syntax** **show lacp sys-id**

---

**show lacp [<1-8>] counters**  
**show lacp [<1-8>] (internal | neighbor) [detail]**

---

**Parameter**

**Default** No default values for this command.

**Mode** Privileged EXEC

**Usage** Use “**show lacp sys-id**” command to displays the system identifier that is being used by LACP. The system identifier is made up of the LACP system priority and the switch MAC address.

Use “**show lacp counter**” command to display LACP statistic information. Use “**show lacp internal**” command to display local information.

Use “**show lacp neighbor**” command to display remote information.

State of the specific port. These are the allowed values:

- —Port is in an unknown state.
- **bndl**—Port is attached to an aggregator and bundled with other ports.
- **susp**—Port is in a suspended state; it is not attached to any aggregator.
- **hot-sby**—Port is in a hot-standby state.
- **1indiv**—Port is incapable of bundling with any other port.
- **1indep**—Port is in an independent state (not bundled but able to switch data traffic. In this case, LACP is not running on the partner port).
- **down**—Port is down.

State variables for the port, encoded as individual bits within a single octet with these meanings:

- **bit0**—LACP\_Activity
- **bit1**—LACP\_Timeout
- **bit2**—Aggregation
- **bit3**—Synchronization
- **bit4**—Collecting
- **bit5**—Distributing
- **bit6**—Defaulted
- **bit7**—Expired



## Command Line Interface User Guide

### Example

This example shows how to show LACP statistics.

```
Switch# show lacp counters
          LACPDU斯      LACPDU斯
          Port       Sent   Recv   Pkts Err
          _____
```



```
-----  
Channel group 1  
fa1      0      0      0  
fa2      0      0      0
```

This example shows how to show LACP local information.

```
Switch# show lacp internal  
Flags: S - Device is requesting Slow LACPDUs  
       F - Device is requesting Fast LACPDUs  
       A - Device is in Active mode          P - Device is  
in Passive mode
```

Channel group 1		LACP port	Admin	Oper
Port	Port	Priority	Key	
Port	Flags State Key Number		State	
fa1	SA down 0x3e8 0x1	1	0x3e8	0x45
fa2	SA down 0x3e8 0x2	1	0x3e8	0x45

This example shows how to show LACP remote information.

```
Switch# show lacp neighbor  
Flags: S - Device is sending Slow LACPDUs  
       F - Device is sending Fast LACPDUs  
       A - Device is in Active mode          P - Device is  
in Passive mode
```

```
Channel group 1  
  
neighbors Partner's  
  
information:
```

Port	Port	LACP port			Admin	Oper
Port	Flags	Priority	Dev ID	Age	key	Key Number State
fa1 0x3e8	FP 0x1	32768 0x56	0000.0000.0000	0s	0x3e8	
fa2 0x3e8	FP 0x2	32768 0x56	0000.0000.0000	0s	0x3e8	

## show lag

### Syntax

**show lag**

### Parameter

### Default

No default values for this command.

### Mode

Privileged EXEC



**Usage**

Use “**show lag**” command to show current LAG load balance algorithm and members active/inactive status.

**Example**

This example shows how to show current LAG status.

```
Switch# show lag
Load Balancing: src-dst-mac-ip.
```

Group	ID	Type	Ports
1		LACP	Inactive: fa1-3 2
3			
4			
5			
6			
7			
8			

## 13. LLDP

### clear lldp statistics

**Syntax**

**clear lldp statistics**

**Default**

There is no default configuration for this command

**Mode**

Privileged EXEC

**Usage**

Use “**clear lldp statistics**” command to clear the LLDP RX/TX statistics.

**Example**

This example shows how to clear LLDP statistics.

```
Switch# clear lldp statistics
```

### lldp

**Syntax**

**lldp**  
**no lldp**

**Default**

Default is enabled



---

Mode	Global Configuration
Usage	<p>Use “<b>lldp</b>” command to enable LLDP RX/TX ability. The LLDP enable status is displayed by “<b>show lldp</b>” command.</p> <p>Use the <b>no</b> form of this command to disable the LLDP. When LLDP is disabled, the behavior of receiving LLDP PDU would be decided by “<b>lldp lldpdu</b>” command.</p>
Example	<p>The following example sets LLDP enable/disable.</p> <pre>Switch (config)# lldp Switch# show lldp  State: Enabled Timer: 30 Seconds Hold multiplier: 4 Reinit delay: 2 Seconds Tx delay: 2 Seconds LLDP packet handling: Flooding  Port        State   Optional TLVs   Address ----- + ----- + ----- + ----- fa1           RX, TX               192.168.1.2 fa2      RX, TX               192.168.1.2 fa3      RX, TX               192.168.1.2 fa4      RX, TX               192.168.1.2 fa5      RX, TX               192.168.1.2</pre>

## lldp rx

---

Syntax	<b>lldp rx</b> <b>no lldp rx</b>
Default	Default is enabled
Mode	Port Configuration
Usage	<p>Use “<b>lldp rx</b>” command to enable the LLDP PDU RX ability. The configuration could be shown by “<b>show lldp</b>” command.</p> <p>Use the <b>no</b> form of this command to disable the RX ability.</p>
Example	<p>This example sets port gi1 to enable LLDP TX, port gi2 to disable RX but enable TX, port gi3 to enable RX but disable TX, port gi4 to disable RX and TX.</p> <pre>Switch(config)# interface gi1 Switch(config-if)# lldp rx</pre>



```
Switch(config-if)# lldp tx
Switch(config)# interface
gi2 Switch(config-if)# no
lldp rx Switch(config-if)#
lldp tx Switch(config)#
interface gi3
Switch(config-if)# lldp rx
Switch(config-if)# no lldp
tx Switch(config)#
interface gi4
Switch(config-if)# no lldp
rx Switch(config-if)# no
lldp tx Switch(config-if)#
end
Switch# show lldp interfaces gi1-4

State: Enabled
Timer: 30
Seconds
Hold multiplier: 4
Reinit delay: 2
Seconds Tx delay: 2
Seconds
LLDP packet handling: Bridging

Port      | State | Optional TLVs | Address
----- + ----- + ----- + -----
gi1 | RX,TX |
|192.168.1.254
gi2 | TX |
gi3 | RX |
gi4 | Disable |
```

## lldp tx-interval

### Syntax

**lldp tx-interval <5-32768>**

**no lldp tx-interval**

### Parameter

**<5-32768>** Specify the LLDP PDU TX interval in unit of second.

### Default

Default TX interval is 30 seconds

### Mode

Global Configuration

### Usage

Use “**lldp tx-interval**” command to configure the LLDP TX interval. It should be noticed that both “**lldp tx-interval**” and “**lldp tx-delay**” affects the LLDP PDU TX time. The larger value of the two configurations decides the TX interval. The configuration could be shown by “**show lldp**” command.

Use the **no** form of this command to restore the interval to default value.



---

### Example

This example sets LLDP TX interval to 10 seconds.

```
Switch(config)# lldp tx-interval 10
Switch# show lldp
```

---



State:  
Disabled Timer:  
10 Seconds  
Hold multiplier: 4  
Reinit delay: 2  
Seconds Tx delay: 2  
Seconds  
LLDP packet handling: Flooding

---

## lldp reinit-delay

---

### Syntax

**lldp reinit-delay <1-10>**  
**no lldp reinit-delay**

---

### Parameter

**<1-10>** Specify the LLDP re-initial delay time in unit of second.

---

---

### Default

Default reinitial delay is 2 seconds

---

### Mode

Global Configuration

---

### Usage

Use “**lldp reinit-delay**” to configure the LLDP re-initial delay. This delay avoids LLDP generate too many PDU if the port is up and down frequently. The delay starts to count when the port links down. The port would not generate LLDP PDU until the delay counts to zero. The configuration could be shown by “show lldp” command.

Use the **no** form of this command to restore the delay to default value.

---

### Example

This example sets LLDP re-initial delay to 5 seconds.

```
Switch(config)# lldp reinit-delay 5
Switch# show lldp

State: Disabled
Timer: 10 Seconds
Hold multiplier: 4
Reinit delay: 5 Seconds
Tx delay: 2 Seconds
LLDP packet handling: Flooding
```

---

## lldp holdtime-multiplier

---

### Syntax

**lldp holdtime-multiplier <2-10>**  
**no holdtime-multiplier**

---

### Parameter

**<2-10>** Specify the LLDP hold time multiplier.

---



---

<b>Default</b>	lldp holdtime-multiplier 4
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use “<b>lldp holdtime-multiplier</b>” command to configure the LLDP PDU hold multiplier that decides time-to-live (TTL) value sent in LLDP advertisements: TTL = (tx-interval * holdtime-multiplier). The configuration could be shown by “<b>show lldp</b>” command.</p> <p>Use the <b>no</b> form of this command to restore the multiplier to default value.</p>
<b>Example</b>	<p>This example sets LLDP hold time multiplier to 3.</p> <pre>Switch(config)# lldp holdtime-multiplier 3 Switch# show lldp  State: Disabled Timer: 10 Seconds Hold multiplier: 3 Reinit delay: 2 Seconds Tx delay: 2 Seconds LLDP packet handling: Flooding</pre>

## lldp lldpdu

---

<b>Syntax</b>	<b>lldp lldpdu (filtering flooding bridging)</b>						
<b>Parameter</b>	<table><tr><td><b>bridging</b></td><td>When LLDP is globally disabled, LLDP packets are bridging (bridging LLDP PDU to VLAN member ports).</td></tr><tr><td><b>filtering</b></td><td>When LLDP is globally disabled, LLDP packets are filtered (deleted).</td></tr><tr><td><b>flooding</b></td><td>When LLDP is globally disabled, LLDP packets are flooded (forwarded to all interfaces).</td></tr></table>	<b>bridging</b>	When LLDP is globally disabled, LLDP packets are bridging (bridging LLDP PDU to VLAN member ports).	<b>filtering</b>	When LLDP is globally disabled, LLDP packets are filtered (deleted).	<b>flooding</b>	When LLDP is globally disabled, LLDP packets are flooded (forwarded to all interfaces).
<b>bridging</b>	When LLDP is globally disabled, LLDP packets are bridging (bridging LLDP PDU to VLAN member ports).						
<b>filtering</b>	When LLDP is globally disabled, LLDP packets are filtered (deleted).						
<b>flooding</b>	When LLDP is globally disabled, LLDP packets are flooded (forwarded to all interfaces).						
<b>Default</b>	Default LLDP PDU handling behavior when LLDP disabled is flooding						
<b>Mode</b>	Global Configuration						
<b>Usage</b>	<p>Use “<b>lldp lldpdu</b>” command to configure the LLDP PDU handling behavior when LLDP is globally disabled. It should be noticed that if LLDP is globally enabled and per port LLDP RX status is configured to disabled, the received LLDP PDU would be dropped instead of taking the global disable behavior.</p>						



The configuration could be shown by “**show lldp**” command.

Use the **no** form of this command to restore the behavior to default.

---

## Example

This example sets LLDP disable action to bridging.

```
Switch(config)# lldp lldpdu bridging
Switch# show lldp

State: Enabled
Timer: 30 Seconds
Hold multiplier: 4
Reinit delay: 2 Seconds
Tx delay: 2 Seconds
LLDP packet handling: Bridging
```

---

## lldp med

---

### Syntax

**lldp med**  
**no lldp med**

---

### Default

lldp med

---

### Mode

Port Configuration

---

### Usage

Use “**lldp med**” to configure the LLDP MED enable status. If LLDP MED is enabled, LLDP MED capability TLV and other selected MED TLV would be attached. The configuration could be shown by “**show lldp med**” command.

Use the **no** form of this command to disable the LLDP MED status.

---



# Command Line Interface

## User Guide

### Example

This example sets port gi1 to enable LLDP MED, port gi2 to disable LLDP MED.

```
Switch(config) # interface gi1
Switch(config-if) # lldp med
Switch(config) # interface gi2
Switch(config-if) # no lldp med
Switch# show lldp interfaces gi1-2 med
```

Port	Capabilities	Network Policy	Location
gi1	Yes	Yes	No
gi2	No	Yes	No



## lldp med fast-start-repeat-count

Syntax	<b>lldp med fast-start-repeat-count &lt;1-10&gt;</b> <b>no lldp med fast-start-repeat-count</b>
Parameter	<1-10> LLDP PDU fast start TX repeat counts.
Default	Default fast start TX repeat count is 3
Mode	Global Configuration
Usage	<p>Use “<b>lldp med fast-start-repeat-count</b>” command to configure the LLDP PDU fast start TX repeat count. When port links up, it will send LLDP PDU immediately to notify link partner. The number of LLDP PDU sends when it links up depends on fast-start-repeat-count configuration. The LLDP PDU fast-start transmits in interval of one second. The fast start behavior works no matter LLDP MED is enabled or not. The configuration could be shown by “<b>show lldp med</b>” command.</p> <p>Use the <b>no</b> form of this command to restore count to default.</p>
Example	This example sets fast start repeat count to 10.  <pre>Switch(config)# lldp med fast-start-repeat-count 10 Switch# show lldp med  Fast Start Repeat Count: 10 lldp med network-policy voice: auto</pre>

## lldp med location

Syntax	<b>lldp med location (coordination civic-address ecs-elin) ADDR</b> <b>no lldp med location (coordination civic-address ecs-elin)</b>								
Parameter	<table><tr><td><b>coordination</b></td><td>Location type to be configured. “ecs-elin” is abbreviation of emergency call service – emergency location identifier number</td></tr><tr><td><b>civic-address</b></td><td></td></tr><tr><td><b>ecs-elin</b></td><td></td></tr><tr><td><b>ADDR</b></td><td>Specify the location data. Input format is hexadecimal values without colon (for example: 1234AB). For coordination location type, the length of ADDR is 16 bytes. For civic-address, the length is 6 to 160 bytes. For ecs-elin, the length is 10 to 25 bytes.</td></tr></table>	<b>coordination</b>	Location type to be configured. “ecs-elin” is abbreviation of emergency call service – emergency location identifier number	<b>civic-address</b>		<b>ecs-elin</b>		<b>ADDR</b>	Specify the location data. Input format is hexadecimal values without colon (for example: 1234AB). For coordination location type, the length of ADDR is 16 bytes. For civic-address, the length is 6 to 160 bytes. For ecs-elin, the length is 10 to 25 bytes.
<b>coordination</b>	Location type to be configured. “ecs-elin” is abbreviation of emergency call service – emergency location identifier number								
<b>civic-address</b>									
<b>ecs-elin</b>									
<b>ADDR</b>	Specify the location data. Input format is hexadecimal values without colon (for example: 1234AB). For coordination location type, the length of ADDR is 16 bytes. For civic-address, the length is 6 to 160 bytes. For ecs-elin, the length is 10 to 25 bytes.								



<b>Default</b>	Deafult is no location data.
----------------	------------------------------

<b>Mode</b>	Port Configuration
-------------	--------------------

<b>Usage</b>	Use “ <b>lldp med location</b> ” command to configure the LLDP MED location data. The “coordinate”, “civic-address”, “ecs-elin” locations are independent, so at most three location TLVs could be sent if their data are not empty. The configuration of location could be shown by “ <b>show lldp interface PORT med</b> ” command.
--------------	---

Use the **no** form of this command to clear location data.

<b>Example</b>	This example sets location data for interface g1.
----------------	---

```

Switch(config)# interface g1
Switch(config-if)# lldp med location coordinate
112233445566778899AABBCCDDEEFF00
Switch(config-if)# lldp med location civic-address
112233445566
Switch(config-if)# lldp med location ecs-elin
112233445566778899AA
Switch# show lldp interfaces g1 med

      Port      | Capabilities      | Network Policy | Location |
Inventory
      ----- + ----- + ----- + ----- + -----
      --      g1      |          Yes |          Yes |          Yes |
      Yes

      Port ID: g1
      Network policies: 1, 32
      Location:
      Coordinates: 112233445566778899AABBCCDDEEFF00
      Civic-address: 112233445566
      Ecs-elin: 112233445566778899AA
  
```

---

## lldp med network-policy

<b>Syntax</b>
---------------

**lldp med network-policy <1-32> app (voice|voice-signaling|guest-voice|guest-voice-signaling|softphone-voice|video-conferencing|streaming-video|video-signaling) vlan <1-4094> vlan-type (tag|untag) priority <0-7> dscp <0-63>**

**no lldp med network-policy <1-32>**

<b>Parameter</b>
------------------

<b>&lt;1-32&gt;</b>	Specify the network policy index
<b>voice</b>	Specify the network policy application type.
<b>voice-signaling</b>	
<b>guest-voice</b>	



<b>guest-voice-signaling</b>	
<b>softphone-voice</b>	
<b>video-conferencing</b>	
<b>streaming-video</b>	
<b>video-signaling</b>	
<b>&lt;1-4094&gt;</b>	Specify the VLAN ID
<b>tag</b>	Specify the VLAN tag status
<b>untag</b>	
<b>&lt;0-7&gt;</b>	Specify the L2 priority
<b>&lt;0-63&gt;</b>	Specify the DSCP value

**Default** No network policy is defined

**Mode** Global Configuration

**Usage** Use “**lldp med network-policy**” command to configure the LLDP MED network policy table and add a network policy entry that can be bind to ports. If LLDP MED network policy voice auto mode is enabled, “voice” type network policy can not be created since it is in auto mode. The network policy table configuration could be shown by “**show lldp med**” command.

Use the **no** form of this command to remove network policy entry of specific index. A network policy can be removed only when it is not bind to any port.

**Example** This example create 2 network policies.

```
Switch(config)# lldp med network-policy 1 app voice-signaling
vlan 2 vlan-type tag priority 3 dscp 4
Switch(config)# lldp med network-policy 32 app video-
conferencing vlan 5 vlan-type tag priority 1 dscp 63
Switch# show lldp med
```

```
Fast Start Repeat Count: 10
lldp med network-policy voice: auto
```

```
Network policy 1
-----
Application type: Voice Signaling
VLAN ID: 2 tagged
Layer 2 priority: 3
DSCP: 4
```

```
Network policy 32
-----
Application type: Conferencing
VLAN ID: 5 tagged
Layer 2 priority: 1
DSCP: 63
```



# **Command Line Interface**

## **User Guide**

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

## **lldp med network-policy (Interface)**

---

### Syntax

**lldp med network-policy (add|remove) <1-32>**

---

### Parameter

<b>add</b>	Add network policy binding for ports.
<b>remove</b>	Remove network policy binding for ports.

<1-32> Specify the network policy index

---

### Default

Default is no network policy binding to port.

---

### Mode

Port Configuration

---

### Usage

Use “**lldp med network-policy**” command to bind the network policy to port interface. The binded network policy of one port should be with different types. If network policy TLV is selected over a port, the binded network policies would be attached in LLDP MED PDU. The configuration of network policy binding could be shown by “show lldp med” command.

---

### Example

This example binds network policy for interface gi1 and gi2.

```
Switch# show lldp med

Fast Start Repeat Count: 10
lldp med network-policy voice: auto

Network policy 1
-----
Application type: Voice Signaling
VLAN ID: 2 tagged
Layer 2 priority: 3
DSCP: 4

Network policy 32
-----
Application type: Conferencing
VLAN ID: 5 tagged
Layer 2 priority: 1
DSCP: 63

Switch(config)# interface range gi1,2
Switch(config-if-range)# lldp med network-policy add 1,32
Switch# show lldp interfaces gi1,2 med

  Port      | Capabilities   | Network Policy | Location |
Inventory
  ----- + ----- + ----- + ----- + -----
  --      |
  Yes    |       Yes |           Yes |       Yes |
  Yes    |       Yes |           Yes |       Yes |
  Yes
```



Port ID: gi1  
Network policies: 1, 32

Port ID: gi2  
Network policies: 1, 32

---

## lldp med network-policy voice auto

---

### Syntax

**lldp med network-policy voice auto**  
**no lldp med network-policy voice auto**

---

### Default

lldp med network-policy auto

---

### Mode

Global Configuration

---

### Usage

Use “**lldp med network-policy voice auto**” command to enable network policy voice auto mode. In voice auto mode, if network-policy TLV is selected, a voice type network policy would be attached to PDU that contents comes from voice VLAN configuration. This works for voice VLAN module to exchange voice VLAN information with link partner. If voice auto mode is enabled, user can not manually create an voice type network policy; if an voice type network policy is created, the voice auto mode can not be enabled. The configuration of network policy auto mode could be shown by “**show lldp med**” command.

Use the **no** form of this command to disable voice auto mode.

---

### Example

This example sets network policy auto mode to enable and then disable.

```
Switch (config) # lldp med network-policy auto
Switch# show lldp med

Fast Start Repeat Count: 10
lldp med network-policy voice: auto

Switch (config) # no lldp med network-policy auto
Switch# show lldp med

Fast Start Repeat Count: 10
lldp med network-policy voice: manual
```

---

## lldp med tlv-select

---

### Syntax

**lldp med tlv-select MEDTLV [MEDTLV] [MEDTLV] [MEDTLV]**  
**no lldp med tlv-select**

---

### Parameter

MEDTLV

MED optional TLV. Available optional TLVs are :



---

network-policy, location, poe-pse, inventory.

---

**Default** network-policy TLV

---

**Mode** Port Configuration

---

**Usage** Use “**lldp med tlv-select**” command to configure the LLDP MED TLV selection. It should be noticed that even no MED TLV is selected, MED capability TLV would be attached if LLDP MED is enable. The configuration could be shown by “show lldp med” command.

Use the **no** form of this command to remove all selected MED TLV over the dedicated ports.

**Example** This example sets port gi1-2 to select LLDP MED network policy, location, POE-PSE, inventory TLVs, and it sets port gi3-4 to un-select all LLDP MED TLVs.

```
Switch(config)# interface gi1
Switch(config-if)# lldp med tlv-select network-policy location
inventory
Switch(config)# interface gi2
Switch(config-if)# no lldp med tlv-select
Switch# show lldp interfaces gi1-2 med

      Port      | Capabilities      | Network Policy | Location |
Inventory
      ----- + ----- + ----- + ----- + -----
      --      |
      gi1   |          Yes |          Yes |          Yes |
Yes
      gi2   |          Yes |          No  |          No  |
No
```

---

## **lldp tlv-select**

---

**Syntax** **lldp tlv-select** *TLV* [*TLV*] [*TLV*] [*TLV*] [*TLV*] [*TLV*] [*TLV*] [*TLV*]  
**no lldp tlv-select**

---

**Parameter** **TLV** Specify the selected optional TLV. Available optional TLVs are : sys-name (system name), sys-desc (system description), sys-cap (system capability), mac-phy (802.3 MAC-PHY), lag (802.3 link aggregation), max-frame-size (802.3 max frame size), and management-addr (management address).

---



<b>Default</b>	Default is no selected optional TLV.
----------------	--------------------------------------

<b>Mode</b>	Port Configuration
-------------	--------------------

<b>Usage</b>	Use “lldp tlv-select” command to attach selected TLV in PDU. The configuration could be shown by “show lldp” command.
--------------	---

Use the **no** form of this command to remove all selected TLV.

<b>Example</b>	This example selects system name, system description, system capability, 802.3 MAC-PHY, 802.3 link aggregation, 802.3 max frame size, and management address TLVs for interface gi1 and gi3.
----------------	--

```
Switch(config)# interface range gi 1,3
Switch(config-if-range)# lldp tlv-select port-desc sys-name
sys-desc sys-cap mac-phy lag max-frame-size management-addr
Switch(config-if-range)# end
Switch# show lldp interfaces gi1,3

State: Disabled
Timer: 10 Seconds
Hold multiplier: 3
Reinit delay: 2 Seconds
Tx delay: 2 Seconds
LLDP packet handling: Flooding

Port      | State | Optional TLVs   | Address
----- + ----- + ----- + -----  gi1
          RX,TX | PD, SN, SD, SC | 192.168.1.254
gi3      | RX,TX | PD, SN, SD, SC | 192.168.1.254

Port ID: gi1
802.3 optional TLVs: 802.3-mac-phy, 802.3-lag, 802.3-max-
frame-size, management-addr
802.1 optional TLVs
PVID: Enabled

Port ID: gi3
802.3 optional TLVs: 802.3-mac-phy, 802.3-lag, 802.3-max-
frame-size, management-addr
802.1 optional TLVs
PVID: Enabled
```

---

## lldp tlv-select pvid

<b>Syntax</b>	<b>lldp tlv-select pvid (disable enable)</b> <b>no lldp tlv-select pvid</b>
---------------	--

<b>Parameter</b>	<b>disable</b> Disable LLDP 802.1 PVID TLV attach state <b>enable</b> Enable LLDP 802.1 PVID TLV attach state
------------------	--



**Default** Default is enabled

**Mode** Port Configuration

**Usage** Use “**lldp tlv-select pvid**” command to configure the 802.1 PVID TLV attach enable status. The configuration could be shown by “**show lldp**” command. Use the **no** form of this command to restore the pvid to default value.

**Example** This example sets port gi1 PVID TLV attaches status to disable and port gi2 to enable.

```
Switch(config)# interface gi1
Switch(config-if)# lldp tlv-select pvid disable
Switch(config-if)# interface gi2
Switch(config-if)# lldp tlv-select pvid enable

Switch# show lldp interfaces gi1,gi2

State: Disabled
Timer: 10 Seconds
Hold multiplier: 3
Reinit delay: 2 Seconds
Tx delay: 2 Seconds
LLDP packet handling: Flooding

Port      | State | Optional TLVs | Address
----- + ----- + ----- + ----- gi1
        | RX,TX |           | 192.168.1.254
gi2 | RX,TX |           | 192.168.1.254

Port ID: gi1
802.3 optional TLVs:
802.1 optional TLVs
PVID: Disabled

Port ID: gi2
802.3 optional TLVs:
802.1 optional TLVs
PVID: Enabled
```

## **lldp tlv-select vlan-name**

**Syntax** **lldp tlv-select vlan-name (add|remove) VLAN-LIST**

## Command Line Interface User Guide

<b>Parameter</b>	<b>add <i>VLAN-LIST</i></b>	Add VLAN list for LLDP 802.1 VLAN-NAME TLV on the specific interface. The configured ports should be member of all the specified VLANs or the VLAN-LIST is not valid.
------------------	-----------------------------	---



<b>remove VLAN-LIST</b>	Remove VLAN list of LLDP 802.1 VLAN-NAME TLV from interface.
-------------------------	--

---

<b>Default</b>	Default is no VLAN added.
----------------	---------------------------

---

<b>Mode</b>	Port Configuration
-------------	--------------------

---

<b>Usage</b>	Use “ <b>lldp tlv-select vlan-name</b> ” command to add or remove VLAN list for 802.1 VLAN-NAME TLV. The configuration could be shown by “ <b>show lldp</b> ” command.
--------------	--

---

<b>Example</b>	This example add VLAN 100 to VLAN-NAME TLV for port gi10.
----------------	---

```
Switch(config)# vlan 100
Switch(config-vlan)# exit
Switch(config)# interface gi1
Switch(config-if)# switchport trunk allowed vlan add all
Switch(config-if)# lldp tlv-select vlan-name add 100
Switch(config-if)# end

Switch# show lldp interfaces gi1

State: Enabled
Timer: 30 Seconds
Hold multiplier: 4
Reinit delay: 2 Seconds
Tx delay: 2 Seconds
LLDP packet handling: Flooding

Port      | State | Optional TLVs | Address
----- + ----- + ----- + ----- gi1
          | RX,TX |           | 192.168.1.2

Port ID: gi1
802.3 optional TLVs:
802.1 optional TLVs
PVID: Enabled
VLANs: 100
```

---

## **lldp tx**

---

<b>Syntax</b>	<b>lldp tx</b> <b>no lldp tx</b>
---------------	-------------------------------------

---

<b>Default</b>	Default is enabled
----------------	--------------------



<b>Mode</b>	Port Configuration
<b>Usage</b>	<p>Use “<b>lldp tx</b>” command to enable the LLDP PDU TX ability. The configuration could be shown by “<b>show lldp</b>” command.</p> <p>Use the <b>no</b> form of this command to disable the TX ability.</p>
<b>Example</b>	<p>This example sets port gi1 to enable LLDP TX, port gi2 to disable RX but enable TX, port gi3 to enable RX but disable TX, port gi4 to disable RX and TX.</p> <pre> Switch(config)# interface gi1 Switch(config-if)# lldp rx Switch(config-if)# lldp tx Switch(config)# interface gi2 Switch(config-if)# no lldp rx Switch(config-if)# lldp tx Switch(config)# interface gi3 Switch(config-if)# lldp rx Switch(config-if)# no lldp tx Switch(config)# interface gi4 Switch(config-if)# no lldp rx Switch(config-if)# no lldp tx Switch(config-if)# end Switch# show lldp interfaces gi1-4  State: Enabled Timer: 30 Seconds Hold multiplier: 4 Reinit delay: 2 Seconds Tx delay: 2 Seconds LLDP packet handling: Bridging  Port        State   Optional TLVs   Address ----- + ----- + ----- + ----- gi1           RX, TX               192.168.1.254 gi2      TX                 192.168.1.254 gi3      RX                 192.168.1.254 gi4      Disable               192.168.1.254 </pre>

## lldp tx-delay

<b>Syntax</b>	<b>lldp tx-delay &lt;1-8192&gt;</b> <b>no lldp tx-delay</b>		
<b>Parameter</b>	<table style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 30%;"><b>&lt;1-8192&gt;</b></td> <td>Specify the LLDP tx delay in unit of seconds.</td> </tr> </table>	<b>&lt;1-8192&gt;</b>	Specify the LLDP tx delay in unit of seconds.
<b>&lt;1-8192&gt;</b>	Specify the LLDP tx delay in unit of seconds.		
<b>Default</b>	Default TX delay is 2 seconds		



Mode	Global Configuration
Usage	<p>Use “<b>lldp tx-delay</b>” command to configure the delay in seconds between successive LLDP frame transmissions. The delay starts to count in any case LLDP PDU is sent such as by LLDP PDU advertise routine, LLDP PDU content change, port link up, etc. The configuration could be shown by “<b>show lldp</b>” command.</p> <p>Use the <b>no</b> form of this command to restore the delay to default value.</p>
Example	This example sets LLDP PDU TX delay to 10 seconds.
	<pre>Switch(config)# lldp tx-delay 10 Switch# show lldp  State: Disabled Timer: 10 Seconds Hold multiplier: 4 Reinit delay: 2 Seconds Tx delay: 10 Seconds LLDP packet handling: Flooding</pre>
<h2>show lldp</h2>	
Syntax	<b>show lldp</b> <b>show lldp interface IF_NMLPORTS</b>
Parameter	<i>IF_NMLPORTS</i> Specify the ports to display information
Default	This command has no default value.
Mode	Privileged EXEC
Usage	<p>Use “<b>show lldp</b>” and “<b>show lldp interface</b>” commands to display LLDP global information including LLDP enable status, LLDP PDU TX interval, hold time multiplier, re-initial delay, TX delay, and LLDP packet handling when LLDP is disabled. The per port information displayed includes port LLDP RX/TX enable status, selected TLV to TX and IP address. The abbreviations in optional TLVs are: port description (PD), system name (SN), system description (SD), and system capability (SC).</p>
Example	<p>This example displays lldp information of port gi1 and gi2</p> <pre>Switch# show lldp interfaces gi1,gi2</pre>



```
State:  
Disabled Timer:  
30 Seconds  
Hold multiplier: 4  
Reinit delay: 2  
Seconds Tx delay: 2  
Seconds  
LLDP packet handling: Flooding  
  
Port      | State | Optional TLVs | Address  
----- + ----- + ----- + -----  
gi1 | RX, TX | PD, SN, SD, SC | 192.168.1.254  
gi1 | RX, TX |  
| 192.168.1.254  
  
Port ID: gi1  
802.3 optional TLVs: 802.3-mac-phy, 802.3-lag,  
802.3-max-frame-size, management-addr  
802.1 optional  
TLVs PVID:  
Enabled  
  
Port ID: gi2  
802.3 optional TLVs:  
802.1 optional TLVs  
PVID: Enabled
```

---

## show lldp local-device

---

### Syntax

**show lldp local-device**  
**show lldp interfaces *IF\_NMLPORTS* local-device**

---

### Parameter

*IF\_NMLPORTS*      Specify the ports to display information

---

### Default

There is no default configuration for this command

---

### Mode

Privileged EXEC

---

### Usage

Use “**show lldp local-device**” command to show the local configuration of LLDP PDU. By the commands, a user can view the contents of LLDP/ LLDP-MED TLVs that would be attached in LLDP PDU.



# Command Line Interface

## User Guide

---

### Example

This example displays the local device information.

```
Switch# show lldp local-device

LLDP Local Device Information:
Chassis Type : Mac Address Chassis
ID           : 00:12:12:12:12:12
System Name   : Switch121212
System Description :
System Capabilities Support : Bridge
System Capabilities Enable  : Bridge
Management Address : 192.168.1.254 (IPv4)
```

---



```
Switch121212(config)# show lldp interfaces g1 local-device

Device ID: 00:12:12:12:12:12
Port ID: g1
System Name:
Switch121212
Capabilities: Bridge
System description:
Port description:
Management address:
192.168.1.254 Time To Live: 120
802.3 MAC/PHY Configur/Status
Auto-negotiation support:
Supported Auto-negotiation status:
Enabled
Auto-negotiation Advertised Capabilities: 10BASE-T
half duplex, 10BASE-T
full duplex, 100BASE-TX half duplex,
100BASE-TX full duplex
Operational MAU type: Other or unknown
802.3 Link Aggregation
Aggregation capability: Capable of being
aggregated Aggregation status: Not currently in
aggregation Aggregation port ID: 0
802.3 Maximum Frame Size: 1522
802.1 PVID: 1
LLDP-MED capabilities: Capabilities, Network Policy, Location,
Extended PSE, Inventory
LLDP-MED Device type: Network
Connectivity LLDP-MED Network policy
Application type: Voice
Signaling Flags: Unknown Policy
VLAN ID: 2
Layer 2 priority: 3
DSCP: 4
LLDP-MED Network policy
Application type:
Conferencing Flags: Unknown
Policy
VLAN ID: 5
Layer 2 priority: 1
DSCP: 63
Hardware revision: 1123
Firmware           revision:
2.5.0-beta.32801      Software
revision: 2.5.0-beta.32801 Serial
number: abc
Manufacturer Name:
Model name:
RTL8328-24FE-4GE Asset ID:
LLDP-MED Location
Coordinates: 11:22:33:44:55:66:77:88:99:AA:BB:CC:DD:EE:FF:00
Civic-address: 11:22:33:44:55:66
Ecs-elin: 11:22:33:44:55:66:77:88:99:AA
```

## show lldp med

### Syntax

```
show lldp med
show lldp interfaces IF_NMLPORTS med
```



## Command Line Interface User Guide

---

<b>Parameter</b>	<i>IF_NMLPORTS</i>	Specify the ports to display information
------------------	--------------------	--

---



<b>Default</b>	There is no default configuration for this command
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Use “ <b>show lldp med</b> ” command to display the LLDP MED configuration information.
<b>Example</b>	<pre>Switch# show lldp med  Fast Start Repeat Count: 10 lldp med network-policy voice: manual  Network policy 1 ----- Application type: Voice Signaling VLAN ID: 2 tagged Layer 2 priority: 3 DSCP: 4  Network policy 32 ----- Application type: Conferencing VLAN ID: 5 tagged Layer 2 priority: 1 DSCP: 63        Port        Capabilities       Network Policy   Location   Inventory       ----- + ----- + ----- + ----- + -----       --+       gi1            Yes            Yes            Yes   Yes       gi2            Yes            Yes            Yes   Yes       gi3            Yes            No             No    No       gi4            Yes            No             No    No       gi5            No             Yes            No    No       gi6            No             Yes            No    No       gi7            No             Yes            No    No       gi8            No             Yes            No    No       gi9            Yes            Yes            No    No       gi10           Yes            Yes            No    No       gi11           Yes            Yes            No   </pre>

No	gi12	Yes	Yes	No
No	gi13	Yes	Yes	No
No	gi14	Yes	Yes	No
No	gi15	Yes	Yes	No
No	gi16	Yes	Yes	No
No	gi17	Yes	Yes	No
No	gi18	Yes	Yes	No
No	gi19	Yes	Yes	No
No	gi20	Yes	Yes	No
No	gi21	Yes	Yes	No
No	gi22	Yes	Yes	No
No	gi23	Yes	Yes	No
No	gi24	Yes	Yes	No
No	gi25	Yes	Yes	No
No	gi26	Yes	Yes	No
No	gi27	Yes	Yes	No
No	gi28	Yes	Yes	No
No				

```
Switch# show lldp interfaces gi1 med
```

Port	Capabilities	Network Policy	Location
Inventory			
----- + ----- + ----- + ----- + -----			
--			
gi1	Yes	Yes	Yes
Yes			

```
Port ID: gi1
Network policies: 1,
32 Location:
Coordinates: 112233445566778899AABBCCDDEEFF00
Civic-address: 112233445566
Ecs-elin:
112233445566778899AA
```

---

Switch121212(config)#

---

## show lldp neighbor

---

### Syntax

**show lldp neighbor**  
**show lldp interfaces IF\_NMLPORTS neighbor**



# Command Line Interface

## User Guide

<b>Parameter</b>	<i>IF_NMLPORTS</i> Specify the ports to display information
<b>Default</b>	There is no default configuration for this command
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Use “ <b>show lldp neighbor</b> ” command to display the received neighbor LLDP PDU information. When LLDP PDU is received on LLDP RX enable ports, system would store the PDU information in database until time to live of the PDU counts down to zero.
<b>Example</b>	<p>This example displays the neighbor information.</p> <pre>Switch# show lldp neighbor    Port     Device ID            Port ID              SysName     Capabilities   TTL   +-----+-----+-----+-----+   -- +-----+-----+     gi3   00:12:12:12:12:12             gi1   Switch121212             Bridge     111     gi11             TREEBASE   00:1A:4D:26:EB:E8   TREEBASE     Station Only     33  Switch121212(config)# show lldp interfaces gi3 neighbor  Device ID: 00:12:12:12:12:12 Port ID: gi1 System Name: Switch121212 Capabilities: Bridge System description: Port description: Management address: 192.168.1.254 Time To Live: 98 802.3 MAC/PHY Configur/Status Auto-negotiation support: Supported Auto-negotiation status: Enabled Auto-negotiation Advertised Capabilities: 10BASE-T half duplex, 10BASE-T full duplex, 100BASE-TX half duplex, 100BASE-TX full duplex Operational MAU type: 100BASE-TX full duplex mode 802.3 Link Aggregation Aggregation capability: Capable of being aggregated Aggregation status: Not currently in aggregation Aggregation port ID: 0 802.3 Maximum Frame Size: 1522 802.1 PVID: 1 LLDP-MED capabilities: Capabilities, Network Policy, Location, Extended PSE, Inventory LLDP-MED Device type: Network Connectivity LLDP-MED Network policy Application type: Voice Signaling</pre>



---

```
Flags: Unknown
Policy VLAN ID: 2
Layer 2 priority: 3
DSCP: 4
LLDP-MED Network policy
Application type:
Conferencing Flags: Unknown
Policy
VLAN ID: 5
Layer 2 priority: 1
DSCP: 63
LLDP-MED Power over Ethernet
Device Type: Power Sourcing
Entity Power Source: Primary
Power Source Power priority: Low
Power value: 13.0
Watts Hardware
revision: 1123
Firmware           revision:
2.5.0-beta.32801   Software
revision: 2.5.0-beta.32801 Serial
number: abc
Manufacturer Name:
Model name:
RTL8328-24FE-4GE Asset ID:
LLDP-MED Location
Coordinates: 11:22:33:44:55:66:77:88:99:AA:BB:CC:DD:EE:FF:00
Civic-address: 11:22:33:44:55:66
Ecs-elin: 11:22:33:44:55:66:77:88:99:AA
```

---

## show lldp statistics

---

### Syntax

**show lldp statistics**  
**show lldp interfaces *IF\_NMLPORTS* statistics**

---

### Parameter

*IF\_NMLPORTS*      Specify the ports to display information

---

### Default

There is no default configuration for this command

---

### Mode

Privileged EXEC

---

### Usage

Use “**show lldp statistics**” command to display the LLDP RX/TX statistics.



---

**Example**

This example display the LLDP statistics.

```
Switch# show lldp statistics
```

LLDP Global Statistics:

Insertions	:	3
Deletions	:	0
Drops	:	0
Age Outs	:	1

TX Frames	RX Frames		RX
-----------	-----------	--	----



TLVs		RX Ageouts				
	Port	Total	Total	Discarded	Errors	Discarded
	Unrecognized	Total				
0	gi1	50	0	0	0	0
0	gi2	0	0	0	0	0
0	gi3	0	50	0	0	0
0	gi4	1	0	0	0	0
0	gi5	0	0	0	0	0
0	gi6	0	0	0	0	0
0	gi7	0	0	0	0	0
0	gi8	0	0	0	0	0
0	gi9	0	0	0	0	0
0	gi10	0	0	0	0	0
0	gi11	3377	10129	0	0	0
0	gi12	0	0	0	0	0
0	gi13	0	0	0	0	0
0	gi14	0	0	0	0	0
0	gi15	0	0	0	0	0
0	gi16	0	0	0	0	0
0	gi17	0	0	0	0	0
0	gi18	0	0	0	0	0
0	gi19	0	0	0	0	0
0	gi20	0	0	0	0	0
0	gi21	0	0	0	0	0
0	gi22	0	0	0	0	0
0	gi23	0	0	0	0	0
0	gi24	0	0	0	0	0
0	gi25	3377	0	0	0	0
0	gi26	3377	0	0	0	0
0	gi27	0	0	0	0	0
0	gi28	0	0	0	0	0
0		0				



---

```

Switch121212(config)# show lldp interfaces g1 statistics

LLDP Port Statistics:
  TX Frames | RX Frames | RX TLVs | RX Age
  Port | Total | Total | Discarded | Errors | Discarded
| Unrecognized | Total
-----+-----+-----+-----+-----+
+-----+-----+
  g1 | 51 | 0 | 0 | 0 | 0 |
  0 | 0
-----+

```

---

## show lldp tlv-overloading

### Syntax

**show lldp interfaces *IF\_NMLPORTS* tlvs-overloading**

### Parameter

*IF\_NMLPORTS*      Specify the ports to display information

### Default

There is no default configuration for this command

### Mode

Privileged EXEC

### Usage

The LLDP PDU is composed by TLVs and selected number TLVs may compose a large PDU that the system can not handle. The maximum PDU length is to take the smaller number of jumbo frame size minus 30 bytes (30 bytes kept for header) or 1488 bytes.

Use “**show lldp tlv-overloading**” command to display the length of LLDP TLVs and if the TLVs overload the PDU length. The TLVs with status marked “overload” would not be transmitted.

### Example

This example display the LLDP TLVs overloading status of port g1.

```
Switch# show lldp interfaces g1 tlvs-overloading
```

g1:

TLVs Group	Bytes	Status
Mandatory	21	Transmitted
LLDP-MED Capabilities	9	Transmitted
LLDP-MED Location	53	Transmitted
LLDP-MED Network Policies	20	Transmitted
LLDP-MED POE	9	Transmitted
802.3	30	Transmitted
Optional	38	Transmitted
LLDP-MED Inventory	97	Transmitted
802.1	8	Transmitted



---

```
Total: 285 bytes
Left: 1203 bytes
```

---

## Example

The following example shows the global logging configuration.

```
Switch# show logging
```

Logging service is

enabled

TARGET	STATUS	Server (PORT)	FACILITY	LOG LEVEL
buffered	enabled	emerg, alert, crit, error, warning, notice		
console	enabled	emerg, alert, crit, error, warning, notice		

The following table describes the significant fields shown in the example:

Field	Description
TARGET	The destinations where the logging messages are stored.
STATUS	The status of logging destinations.
Server (PORT)	Server address and port number for the remote logging.
FACILITY	The facility of the log messages.
LOG LEVEL	The severity level of the log messages.

The following example shows the log messages stored in the RAM.

```
Switch# show logging buffered
```

Log messages in buffered

NO.	Timestamp	Category	Severity	Message
1	Jan 01 2000 08:14:47		AAA	notice New console connection for user admin, source async ACCEPTED
2	Jan 01 2000 08:03:12		AAA	notice New console connection for user admin, source async ACCEPTED
3	Jan 01 2000 08:01:13	System Startup!	System	notice
4	Jan 01 2000 08:01:13	Logging is enabled	System	notice

The following table describes the significant fields shown in the example:

Field	Description
NO	The number of log entry.
Timestamp	Time when the message was generated.
Category	The category of the message.



Severity	The severity level of the messages.
----------	-------------------------------------



Message	The message content.
---------	----------------------

## 14. Logging

### clear logging

---

#### Syntax

**clear logging (buffered|file)**

---

#### Parameter

<b>buffered</b>	Clear the log messages stored in the RAM.
<b>file</b>	Clear the log messages stored in the Flash.

---

#### Default

N/A

---

#### Mode

Privileged EXEC

---

#### Usage

To clear the log messages from the internal logging buffer and flash, use the command **clear logging** in the Privileged EXEC mode.

---

#### Example

The following example clear the log messages stored in RAM and Flash.

```
Switch# clear logging buffered
Switch# clear logging file
```

---

### logging

---

#### Syntax

**logging**  
**no logging**

---

#### Parameter

N/A

---

#### Default

Logging service is enabled.

---

#### Mode

Global Configuration

---

#### Usage

To enable logging service on the switch, use the command **logging** in the Global Configuration mode. Otherwise, use the **no** form of the command to disable the logging service on the switch.

The status of global logging server is available from the command **show**

---



**logging** in the Privileged EXEC mode. When the logging service is enabled, logging on and off at each destination rule can be individually configured by the command **logging console**, **logging buffered**, **logging file**, and **logging host** in the Global Configuration mode. If the logging service is disabled, no messages will be sent to these destinations.

---

**Example**

The following example disables and enables the logging service on the switch.

```
Switch(config) # no logging
Switch(config) # logging
```

---

## logging host

---

**Syntax**

**logging host** (*ip-addr|hostname*) [**facility** *facility*] [**port** *port*] [**severity** *sev*]  
**no logging host** (*ip-addr|hostname*)

---

**Parameter**

<b>ipv4-addr</b>	IPv4 address of the remote logging server.
<b>hostname</b>	Hostname of the remote logging server.
<b>facility</b> <i>facility</i>	Specify the facility of the logging messages. It can be one of the following value: local0, local1, local2, local3, local4, local5, local6, and local7. The default value of facility is local7.
<b>port</b> <i>port</i>	Specify the port number of the remote logging server. The valid range is from 0 to 65535, and the default value is 512.
<b>severity</b> <i>sev</i>	Specify the minimum severity of the logging messages. The valid range is from 0 to 7, and the number 0 to 7 represents emerg, alert, critical, error, warning, notice, info, and debug individually. The default value of minimum severity level is 5 (emerg, alert, crit, error, warning, notice).

---

**Default**

No remote logging destination is configured.

---

**Mode**

Global Configuration

---

**Usage**

To define the logging server, use the command **logging host** to add the remote logging server in the Global Configuration mode. Otherwise, use the command **no logging host** to remove the remote logging rules.

For the host name configuration, logging service would try translating the host name to IP address directly. Add the logging host would be failed on the failure of host name translating.

---

**Example**

The following example adds the remote logging rules by IP and Hostname.

---



---

```
Switch(config)# logging host 1.2.3.4
Switch(config)# logging host SYSLOG
```

---

## logging severity

### Syntax

```
logging (buffered|console|file) [severity sev]
no logging (buffered|console|file)
```

### Parameter

<b>buffered</b>	Log messages to RAM.
<b>console</b>	Log messages to console buffer.
<b>file</b>	Log messages to Flash.
<b>severity <i>sev</i></b>	Specify the minimum severity of the logging messages. The valid range is from 0 to 7, and the number 0 to 7 represents emerg, alert, critical, error, warning, notice, info, and debug individually. The default minimum severity of the <b>logging severity</b> configuration is 5 (emerg, alert, crit, error, warning, notice).

### Default

Logging to buffered and console is enabled, and the default minimum severity level is 5 (emerg, alert, crit, error, warning, notice).

### Mode

Global Configuration

### Usage

To set the minimum severity for the messages that are logged to RAM, console, or Flash, use the command `logging severity` in the Global Configuration mode. Use the `no` form of the command to remove the mechanism of logging to RAM, console, or Flash individually.

### Example

The following example sets the minimum severity level of logging to RAM and Flash as debugging.

```
Switch(config)# logging buffered 7
Switch(config)# logging flash 7
```

## show logging

### Syntax

```
show logging [buffered|file]
```

### Parameter

<b>buffered</b>	Display the log messages stored in the RAM.
<b>file</b>	Display the log messages stored in the Flash.

### Default

N/A



<b>Mode</b>	Privileged EXEC
<b>Usage</b>	To display the global logging configuration, and the logging messages stored in the RAM and Flash, use the command <b>show logging</b> in the Privileged EXEC mode.
<b>Example</b>	The following example shows the global logging configuration.

```
Switch# show logging

Logging service is

enabled

      TARGET | STATUS |           Server (PORT) | FACILITY | LOG LEVEL
-----+-----+-----+-----+
-----+
buffered | enabled |           |               |
|emerg, alert, crit, error, warning, notice
console | enabled |           |               |
|emerg, alert, crit, error, warning, notice
```

The following table describes the significant fields shown in the example:

Field	Description
TARGET	The destinations where the logging messages are stored.
STATUS	The status of logging destinations.
Server (PORT)	Server address and port number for the remote logging.
FACILITY	The facility of the log messages.
LOG LEVEL	The severity level of the log messages.

The following example shows the log messages stored in the RAM.

```
Switch# show logging buffered

Log messages in buffered

NO. |   Timestamp   |   Category   | Severity | Message
-----+-----+-----+-----+
-----+
1 | Jan 01 2000 08:14:47 |           AAA |   notice | 
New console connection for user admin, source async
ACCEPTED
2 | Jan 01 2000 08:03:12 |           AAA |   notice | 
New console connection for user admin, source async
ACCEPTED
3 | Jan 01 2000 08:01:13 | System     |   notice | 
System Startup!
4 | Jan 01 2000 08:01:13 | System     |   notice | 
Logging is enabled
```

The following table describes the significant fields shown in the example:

Field	Description
-------	-------------



## **Command Line Interface User Guide**

NO	The number of log entry.
----	--------------------------



Timestamp	Time when the message was generated.
Category	The category of the message.
Severity	The severity level of the messages.
Message	The message content.

---

## 15. MAC Address Table

### clear mac address-table

**Syntax**

**clear mac address-table dynamic [interfaces *IF\_PORTS*|vlan *vlan-id*]**

**Parameter**

<b>interfaces</b>	Delete all dynamic addresses learned on the specific interface.
<b><i>IF_PORTS</i></b>	
<b>vlan <i>vlan-id</i></b>	Delete all source addresses learned on the specific VLAN.

**Default**

N/A

**Mode**

Privileged EXEC

**Usage**

To clear the dynamic (learned) MAC entries from the MAC address table, the specific interface, or the specific VLAN, use the command **clear mac address-table** in the Priveleged EXEC mode.

**Example**

The following example clears the learned MAC addresses on the interface g11.

```
Switch# clear mac address-table dynamic interfaces g11
```

### mac address-table aging-time

**Syntax**

**mac access-table aging-time *seconds***

**Parameter**

<b><i>seconds</i></b>	The time in seconds that an entry remains in the MAC address table. Its valid range is from 10 to 630 seconds, and the default value is 300 seconds.
-----------------------	--

**Default**

The default aging time is 300 seconds.



---

Mode	Global Configuration
Usage	To set the aging time of the MAC address table, use the command <b>mac address-table aging-time</b> in the Global Configuration mode.
Example	The following example set the agimg time to 500 seconds. <pre>Switch(config)# mac address-table aging-time 500</pre>

## mac address-table static

---

Syntax	<b>mac address-table static</b> <i>mac-addr vlan vlan-id interfaces IF_PORTS</i> <b>mac address-table static</b> <i>mac-addr vlan vlan-id drop</i> <b>no mac address-table static</b> <i>mac-addr vlan vlan-id</i>										
Parameter	<table><tr><td><i>mac-addr</i></td><td>MAC address.</td></tr><tr><td><i>vlan vlan-id</i></td><td>Specify the VLAN ID for the interface.</td></tr><tr><td><b>Interface</b></td><td>Specify the interface ID or a list of interface IDs.</td></tr><tr><td><i>IF_PORTS</i></td><td></td></tr><tr><td><b>drop</b></td><td>Drop the packets with the specified source or destination unicast MAC address.</td></tr></table>	<i>mac-addr</i>	MAC address.	<i>vlan vlan-id</i>	Specify the VLAN ID for the interface.	<b>Interface</b>	Specify the interface ID or a list of interface IDs.	<i>IF_PORTS</i>		<b>drop</b>	Drop the packets with the specified source or destination unicast MAC address.
<i>mac-addr</i>	MAC address.										
<i>vlan vlan-id</i>	Specify the VLAN ID for the interface.										
<b>Interface</b>	Specify the interface ID or a list of interface IDs.										
<i>IF_PORTS</i>											
<b>drop</b>	Drop the packets with the specified source or destination unicast MAC address.										

---

Default	No static addresses are configured
---------	------------------------------------

---

Mode	Global Configuration
------	----------------------

---

Usage	To add a static address to the MAC address table, use the command <b>mac address-table static</b> in the Global Configuration mode. For the unicast MAC address filtering, use the command <b>mac address-table static</b> with parameter <b>drop</b> to drop the packets with the specified source or destination unist MAC address. To delete the static entry from the MAC address table, use the <b>no</b> form of the command.
-------	---

---

Example	The following example adds a static address into MAC address table.
---------	---

```
Switch# mac address-table static 00:11:22:33:44:55 vlan 1  
interfaces fa5
```

The following example adds a rule of unist address filtering into MAC address table.

```
Switch# mac address-table static 00:11:22:33:44:55 vlan 1 drop
```



## show mac address-table

### Syntax

```
show mac address-table [dynamic|static] [interface IF_PORTS] [vlan vlan-id]
show mac address-table [mac-addr] [vlan vlan-id]
```

### Parameter

<b>dynamic</b>	Display only dynamic MAC addresses
<b>static</b>	Display only static MAC addresses
<b>Interface</b> <i>IF_PORTS</i>	Display the MAC addresses entries for a specific interface.
<b>vlan</b> <i>vlan-id</i>	Display the MAC address entries for a specific VLAN.
<i>mac-addr</i>	Display entries for a specific MAC address

### Default

N/A

### Mode

Privileged EXEC

### Usage

To show the entry in the MAC address table, use the command **show mac address-table** in the Privileged EXEC mode.

### Example

The following example displays the entire MAC address table.

```
Switch# show mac address-table
  VID |      MAC Address |       Type |     Ports
-----+-----+-----+-----+
  -   |
    1 | DE:AD:BE:EF:01:02 | Management | CPU
    1 | 00:01:02:03:04:05 | Static    | All
   100 | 00:11:22:33:44:55 | Static    | gi1
    1 | 1C:E6:C7:8F:10:02 | Dynamic   | fa3
    1 | AA:BB:CC:DD:EE:FF | Static    | All
    1 | DE:AD:BE:EF:01:0C | Dynamic   | gi1

Total number of entries: 6
Switch#
```

The following example displays the static MAC address configuration for the interface fa1.

```
Switch# show mac address-table static interfaces fa1 VID
  |      MAC Address |       Type |     Ports
-----+-----+-----+-----+
  -   |
    1 | 00:01:02:03:04:05 | Filtering | All
    1 | AA:BB:CC:DD:EE:FF | Filtering | All

Total number of entries: 2
Switch#
```

---



The following example displays address table entries containing the specified MAC address.

```
Switch# show mac address-table 00:11:22:33:44:55 vlan 100
  VID |      MAC Address      |      Type      |      Ports
-----+-----+-----+-----+
  100 | 00:11:22:33:44:55 |  Static      |  gi1
Total number of entries: 1
```

---

## **show mac address-table counters**

**Syntax** **show mac address-table counters**

**Parameter** N/A

**Default** N/A

**Mode** Privileged EXEC

**Usage** To display the total entries in the MAC address table, use the command **show mac address-table counters** in the Privileged EXEC mode.

**Example** The following example displays numbers of addresses in the address table.

```
Switch# show mac address-table counters
Total number of entries: 5
```

---

## **show mac address-table aging-time**

**Syntax** **show mac address-table aging-time**

**Parameter** N/A

**Default** N/A

**Mode** Privileged EXEC

**Usage** To show MAC address aging time, use the command **show mac address-table aging-time** in the Privileged EXEC mode.



---

**Example**

The following example displays aging time for the MAC address table.

```
Switch# show mac address-table aging-time  
Mac Address Table aging time: 300 sec
```

---

## 16. MAC VLAN

### vlan mac-vlan group (Global)

---

**Syntax**

```
vlan mac-vlan group <1- 2147483647> mac-address mask <9-  
48>  
no vlan mac-vlan group mac-address mask <9-48>
```

---

**<Parameter**

<1-2147483647>	Specify the group ID
Mac-address	Specify the MAC address to be mapped.
<9-48>	Specify the mask length of MAC address.

---

**Default**

No MAC Groups are configured.

---

**Mode**

Global Configuration

---

**Usage**

Use the “**vlan mac-vlan group**” command to create MAC address group.

Use the **no** form of this command to delete specify group.

---

**Example**

The following example shows how to create a MAC group with group ID 3.

```
Switch(config)# vlan mac-vlan group 333 22:33:44:55:66:77 mask 48
```

---

### vlan mac-vlan group (Interface)

---

**Syntax**

```
vlan mac-vlan group <1- 2147483647> vlan <1-4094>  
no vlan mac-vlan [group <1- 2147483647>]
```

---

**<Parameter**

<1-2147483647>	Specify the group ID. (optional in no form) Delete all mapping group if not specify.
<1-4094>	Specify the VLAN ID to give to match packet.

---



---

**Default** No mappings are configured.

---

**Mode** Interface Configuration

---

**Usage** Use the “**vlan mac-vlan group**” to create mapping of group and VLAN ID of an interface.

Use the **no** form of this command to delete mapping.

---

**Example** The following example shows how to mapping group id 333 to VLAN 100 on interface fa1.

```
Switch(config)# Interface fa1  
Switch(config-if) # vlan mac-vlan group 333 VLAN 100
```

---

## show vlan mac-vlan groups

---

**Syntax** **show vlan mac-vlan groups**

---

---

**Default** N/A

---

**Mode** Privileged EXEC

---

**Usage** Use the **show vlan mac-vlan groups** command to display mac groups configuration

---

**Example** This following example shows how to display mac group.

```
Switch# show vlan mac-vlan groups  
Mac Address      Mask      Group Id  
-----  
22:33:44:55:66:77  48        222  
44:55:66:77:88:99  48        333  
88:99:00:aa:bb:cc  40        444  
88:99:00:ab:bb:10  48        111
```

---



## show vlan mac-vlan interfaces

---

**Syntax**      **show vlan mac-vlan [interfaces IF\_PORTS]**

---

**Parameter**      **IF\_PORTS**      (Optional) Specify interfaces mac vlan to display.  
Display all ports if not specify.

---

**Default**      N/A

---

**Mode**      Privileged EXEC

---

**Usage**      Use the **show vlan mac-vlan interface** command in EXEC mode to display the mac-vlan interfaces setting

---

**Example**      The following example shows how to display the MAC-Based VLAN interfaces setting

Switch# **show vlan mac-vlan interfaces fa1**

Port fa1 :

  Mac based VLANs:

  Group ID Vlan ID

-----	-----
333	444
444	1

## 17. Management ACL

### management access-list

---

**Syntax**      **management access-list NAME**  
**no management access-list NAME**

---

**Parameter**      **NAME**      The name of management  
ACL

---

**Default**      No management ACL is configured.

---

**Mode**      Global Configuration



---

**Usage**

Use the **management access-list** command to create a management access list and to enter management access-list configuration mode. The name of ACL must be unique that cannot have same name with other management ACL. Use the no form of this command to delete

---

**Example**

The following example shows how to add a management ACL with name “test”

```
Switch(config) # management access-list test
```

---

## management access-class

---

**Syntax**

```
management access-class NAME  
no management access-class
```

---

**Parameter**

NAME	The name of management ACL to be used.
------	--

---

**Default**

Default is no management ACL restrictions

---

**Mode**

Global Configuration

---

**Usage**

Use the **management access-class** command to activate a management ACL. Use the no form of this command to delete

---

**Example**

The following example shows how to add a management ACL with name “test”

```
Switch(config) # management access-list test
```

---

## deny

---

**Syntax**

```
[sequence <1-65535>] deny interfaces IF_PORTS  
service (all|http|https|snmp|ssh|telnet)  
[sequence <1-65535>] deny ip A.B.C.D/A.B.C.D interfaces IF_PORTS  
service (all|http|https|snmp|ssh|telnet)  
[sequence <1-65535>] deny ipv6 X:X::X:X/<0-128> interfaces IF_PORTS  
service (all|http|https|snmp|ssh|telnet)
```

---

**Parameter**

<1-65535>	(Optional) Specify sequence index of ACL entry, the sequence index represent the priority
-----------	---



# Command Line Interface

## User Guide

	of an entry in ACL. If not specified, the switch assigns a number from 1 in ascending order.
<b>interfaces IF_PORTS</b>	Specify the interface ID or a list of interface IDs.
<b>ip A.B.C.D/A.B.C.D</b>	Specify the source IP address and mask of packet.
<b>ipv6 X:X::X:X/&lt;0-128&gt;</b>	Specify the source IPv6 address and prefix length of packet.
<b>(all http https snmp ssh telnet)</b>	Specify the type of services.

**Default** No rules are configured.

**Mode** Management Access-List Configuration

**Usage** Use the deny command to add deny rules that drop those packets hit the rule.

**Example** The following example shows how to add a deny rule to drop all types of services packets that source ip is 1.1.1.1 from interface g1.

```
Switch(config)# management access-list test
Switch(config-macl)# sequence 1 deny ip
1.1.1.1/255.255.255.255 interfaces g1 service all
```

## permit

**Syntax**

```
[sequence <1-65535>] permit interfaces IF_PORTS service
(all|http|https|snmp|ssh|telnet)
[sequence <1-65535>] permit ip A.B.C.D/A.B.C.D interfaces IF_PORTS
service (all|http|https|snmp|ssh|telnet)
[sequence <1-65535>] permit ipv6 X:X::X:X/<0-128> interfaces
IF_PORTS service (all|http|https|snmp|ssh|telnet)
```

**Parameter**

<b>&lt;1-65535&gt;</b>	(Optional) Specify sequence index of ACL entry, the sequence index represent the priority of an entry in ACL. If not specified, the switch assigns a number from 1 in ascending order.
<b>interfaces IF_PORTS</b>	Specify the interface ID or a list of interface IDs.
<b>ip A.B.C.D/A.B.C.D</b>	Specify the source IP address and mask of packet.
<b>ipv6 X:X::X:X/&lt;0-128&gt;</b>	Specify the source IPv6 address and prefix length of packet.
<b>(all http https snmp ssh telnet)</b>	Specify the type of services.



**Default** No rules are configured.

**Mode** Management Access-List Configuration

**Usage** Use the permit command to add permit rules that bypass those packets hit the rule.

**Example** The following example shows how to add a permit rule to bypass http service packets that source ip is 2.2.2.2 from interface g1.

```
Switch(config) # management access-list test
Switch(config-macl) # sequence 2 permit ip
2.2.2.2/255.255.255.255 interfaces g1 service http
```

---

## no sequence

**Syntax** **no sequence <1-65535>**

**Parameter** **<1-65535>** Specify sequence index of ACL entry to delete.

**Default** No rules are configured.

**Mode** Management Access-List Configuration

**Usage** Use the **no sequence** command to delete an entry in management ACL.

**Example** The following example shows how to delete an entry.

```
Switch(config) # management access-list test
Switch(config-macl) # sequence 10 deny interfaces g1 service
all
Switch(config-macl) # no sequence 10
```

---

## show management access-class

**Syntax** **show management access-class**

**Parameter**



---

Default	No default is defined
Mode	Privileged EXEC
Usage	Use the <b>show management access-class</b> command to show the active management access-list.
Example	The example shows how to show management access-class  Switch# <b>show management access-class</b> Management access-class is enabled, using access-list test

---

## show management access-list

---

Syntax	<b>show management access-list [NAME]</b>
Parameter	NAME                  Specify the name of management ACL to displayed
Default	No default is defined
Mode	Privileged EXEC
Usage	Use the <b>show management access-list</b> command to show management ACL.
Example	The example shows how to show management access-list  Switch#Switch# <b>show management access-list</b> 1 management access-list is created test ---- sequence 1 deny ip 1.1.1.1/255.255.255.255 interfaces g1 service all !(Note: all other access implicitly denied)

---

## 18. Mirror

### mirror session destination interface

---

**mirror session <1-4> destination interface IF\_NMLPORT [allow-ingress]**  
**no mirror session <1-4> destination interface IF\_NMLPORT**  
**no mirror session (<1-4> | all)**



---

<b>&lt;Parameter</b>	<table border="1"> <tr> <td><b>&lt;1-4&gt;</b></td><td>Specify the mirror session to configure</td></tr> <tr> <td><b>IF_NMLPORT</b></td><td>Specify the SPAN destination. A destination must be a physical port</td></tr> <tr> <td><b>allow-ingress</b></td><td>Enable ingress traffic forwarding.</td></tr> </table>	<b>&lt;1-4&gt;</b>	Specify the mirror session to configure	<b>IF_NMLPORT</b>	Specify the SPAN destination. A destination must be a physical port	<b>allow-ingress</b>	Enable ingress traffic forwarding.				
<b>&lt;1-4&gt;</b>	Specify the mirror session to configure										
<b>IF_NMLPORT</b>	Specify the SPAN destination. A destination must be a physical port										
<b>allow-ingress</b>	Enable ingress traffic forwarding.										
<b>Default</b>	No monitor sessions are configured.										
<b>Mode</b>	Global Configuration										
<b>Usage</b>	<p>Use the “<b>mirror session destination interface</b>” command to start a destination interface of a port mirror session.</p> <p>Use the <b>no</b> form of this command to stop a destination interface of a port mirroring session.</p> <p>Use the “<b>no mirror session</b>” command to disable all mirror sessions or specific mirror session.</p>										
<b>Example</b>	The following example shows how to create a local session 1 to monitor both sent and received traffic on source port fa1.										
	<pre>Switch(config)# mirror session 1 destination interface fa1 Switch# show mirror session 1 Session 1 Configuration Source RX Port      : fa2-5 Source TX Port : fa2-5 Destination port : fa1 Ingress State: disabled</pre>										
<b>mirror session source interface</b>											
<b>Syntax</b>	<b>mirror session &lt;1-4&gt; source interfaces IF_PORTS (both   rx   tx)</b> <b>no mirror session &lt;1-4&gt; source interfaces IF_PORTS (both   rx   tx)</b> <b>no mirror session (&lt;1-4&gt;   all)</b>										
<b>&lt;Parameter</b>	<table border="1"> <tr> <td><b>&lt;1-4&gt;</b></td> <td>Specify the mirror session to configure</td> </tr> <tr> <td><b>IF_PORTS</b></td> <td>Specify the source interface, Valid interfaces include physical ports and port channels.</td> </tr> <tr> <td><b>both</b></td> <td>Mirror tx and rx direction</td> </tr> <tr> <td><b>rx</b></td> <td>Mirror rx direction only</td> </tr> <tr> <td><b>tx</b></td> <td>Mirror tx direction only</td> </tr> </table>	<b>&lt;1-4&gt;</b>	Specify the mirror session to configure	<b>IF_PORTS</b>	Specify the source interface, Valid interfaces include physical ports and port channels.	<b>both</b>	Mirror tx and rx direction	<b>rx</b>	Mirror rx direction only	<b>tx</b>	Mirror tx direction only
<b>&lt;1-4&gt;</b>	Specify the mirror session to configure										
<b>IF_PORTS</b>	Specify the source interface, Valid interfaces include physical ports and port channels.										
<b>both</b>	Mirror tx and rx direction										
<b>rx</b>	Mirror rx direction only										
<b>tx</b>	Mirror tx direction only										
<b>Default</b>	No monitor sessions are configured.										

<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the “<b>mirror session source interface</b>” command to start a port mirror session.</p> <p>Use the <b>no</b> form of this command to stop a port mirroring session.</p> <p>Use the “<b>no mirror session</b>” command to disable all mirror sessions or specific mirror session.</p>
<b>Example</b>	The following example shows how to create a local SPAN session 1 to monitor both sent and received traffic on source port fa1.
	<pre>Switch(config)# mirror session 1 source interface fa2-5 both Switch(config)# mirror session 1 destination interface fa1 Switch(config)# show mirror session 1 Session 1 Configuration Source RX Port      : fa2-5 Source TX Port      : fa2-5 Destination port    : fa1 Ingress State: disabled</pre>

## show mirror

<b>Syntax</b>	<b>show mirror [session &lt;1-4&gt;]</b>
<b>Parameter</b>	<b>&lt;1-4&gt;</b> Specify the mirror session to display
<b>Default</b>	N/A
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Use the <b>show mirror</b> command to display mirror session configuration
<b>Example</b>	This following example shows how to display mirror session configuration
	<pre>Switch(config)# show mirror Session 1 Configuration Source RX Port      : fa2-5 Source TX Port      : fa2-5 Destination port    : fa1</pre>



```
Ingress State: disabled

Session 2 Configuration
Mirrored source : Not
Config Destination port:
Not Config

Session 3 Configuration
Mirrored source : Not
Config Destination port:
Not Config

Session 4 Configuration
Mirrored source : Not
Config
Destination port : Not Config
```

---

## 19. MLD Snooping

### ipv6 mld snooping

Syntax	<b>ipv6 mld snooping no ipv6 mld snooping</b>
Parameter	None
Default	Default is disabled
Mode	Global Configuration
Usage	Use the <b>ipv6 mld snooping</b> command to enable MLD snooping function. Use the <b>no</b> form of this command to disable. Disable will clear all ipv6 mld snooping dynamic group and dynamic router port, and make the static ipv6 mld group invalid. No more dynamic group and router port by mld message will be learned. You can verify settings by the <b>show ipv6 mld snooping</b> command.
Example	The following example specifies that set <b>ipv6 mld snooping</b> test. Switch(config)# <b>ipv6 mld snooping</b>

---

### ipv6 mld snooping report-suppression



---

**Syntax**

**ipv6 mld snooping report-suppression**  
**no ipv6 mld snooping report-suppression**



<b>Parameter</b>	none
<b>Default</b>	Default is enabled
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>ipv6 mld snooping report-suppression</b> command to enable MLD snooping report-suppression function.</p> <p>Use the <b>no</b> form of this command to disable. Disable report-supression will forward all received reports to the vlan router ports.</p> <p>You can verify settings by the <b>show ipv6 mld snooping</b> command.</p>
<b>Example</b>	<p>The following example specifies that disable ipv6 mld snooping report-suppression test.</p> <pre>Switch(config)# no ipv6 mld snooping report-suppression</pre>

## ipv6 mld snooping version

<b>Syntax</b>	<b>ipv6 mld snooping version (1 2)</b>
<b>Parameter</b>	(1 2) Ipv6 mld snooping running version 1 or 2
<b>Default</b>	Default is version 1
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>ipv6 mld snooping version</b> command to change MLD support version. Version 2 packet won't be processed if choose version 1.</p> <p>You can verify settings by the <b>show ip igmp snooping</b> command.</p>
<b>Example</b>	<p>The following example specifies that set ipv6 mld snooping version 2.</p> <pre>Switch(config)# ipv6 mld snooping version 2</pre>

## ipv6 mld snooping unknown-multicast action

<b>Syntax</b>	<b>ipv6 mld snooping unknown-multicast action (drop   flood  router-port) no ipv6 mld snooping unknown-multicast action</b>
---------------	---



<b>Parameter</b>	(drop   flood   router-port)	Drop ` flood in vlan or forward to router port of unknown multicast packet
<b>Default</b>	Default is flood.	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	When igmp and mld snooping disabled, it can't set action router-port. When disable igmp snooping & mld snooping, it set unknown multicast action flood. When action is router-port to flood or drop, it will delete the unknown multicast group entry.	
	Use the <b>ipv6 mld snooping unknown-multicast action</b> command to change action. Use the <b>no</b> form of this command to restore to default. You can verify settings by the <b>show ipv6 mld snooping</b> command.	
<b>Example</b>	The following example specifies that set ipv6 mld unknown multicast action router-port test. <b>Switch(config)# ipv6 mld snooping unknown-multicast action router-port</b>	

---

## ipv6 mld snooping vlan

<b>Syntax</b>	<b>ipv6 mld snooping vlan VLAN-LIST</b> <b>no ipv6 mld snooping vlan VLAN-LIST</b>	
<b>Parameter</b>	VLAN-LIST	specifies VLAN ID list to set
<b>Default</b>	Default is disabled for all VLANs	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Disable will clear all ipv6 mld snooping dynamic group and dynamic router port and make all static ip igmp group invalid of this vlan. Will not learn dynamic group and router port by igmp message any more. Use the <b>ipv6 mld snooping vlan</b> command to enable MLD on VLAN. Use the <b>no</b> form of this command to disable You can verify settings by the <b>show ipv6 mld snooping vlan</b> command.	



---

**Example**

The following example specifies that set ipv6 mld snooping vlan test.  
Switch(config)# **ipv6 mld snooping vlan 1**

---

## ipv6 mld snooping vlan parameters

---

**Syntax**

```
ipv6 mld snooping vlan <VLAN-LIST> last-member-query-count <1-7>
no ipv6 mld snooping vlan <VLAN-LIST> last-member-query-count
ipv6 mld snooping vlan <VLAN-LIST> last-member-query-interval <1-60>
no ipv6 mld snooping vlan <VLAN-LIST> last-member-query-interval
[no] ipv6 mld snooping vlan <VLAN-LIST> router learn pim-dvmrp
[no] ipv6 mld snooping vlan <VLAN-LIST> fastleave
ipv6 mld snooping vlan <VLAN-LIST> query-interval <30-18000>
no ipv6 mld snooping vlan <VLAN-LIST> query-interval
ipv6 mld snooping vlan <VLAN-LIST> response-time <5-20>
no ipv6 mld snooping vlan <VLAN-LIST> response-time
ipv6 mld snooping vlan <VLAN-LIST> robustness-variable <1-7>
no ipv6 mld snooping vlan <VLAN-LIST> robustness-variable
```

---

---

**Parameter**

VLAN-LIST	specifies VLAN ID list to set
last-member-query- count <1-7>	specifies last member query count to set. Default is
last-member-query- interval <1-60>	2 specifies last member query interval to set.
query-interval <30- 18000>	Default is 1 specifies query interval to set. Default
response-time <5- 20>	is 125
robustness-variable <1-7>	specifies a response time to set. default is 10 specifies a robustness value to set, default is 2

---

---

**Default**

```
no ipv6 mld snooping vlan 1-4094 last-member-query-count
no ipv6 mld snooping vlan 1-4094 last-member-query-interval
ipv6 mld snooping vlan 1-4094 router learn pim-dvmrp
no ipv6 mld snooping vlan 1-4094 fastleave
no ipv6 mld snooping vlan 1-4094 query-interval
no ipv6 mld snooping vlan 1-4094 response-time
no ipv6 mld snooping vlan 1-4094 robustness-variable
```

---

---

**Mode**

Global Configuration



# **Command Line Interface**

## **User Guide**

---

### **Usage**

‘no ipv6 mld snooping vlan 1 (last-member-query-count | last-member-query-interval | query-interval | response-time | robustness-variable)’ will set the vlan parameters to default.

---



The cli setting will change the ipv6 mld vlan parameters admin settings. The configure can use ‘show ipv6 mld snooping vlan 1’.

---

**Example**

The following example specifies that set ipv6 mld snooping vlan parameters test.

```
Switch(config)# ipv6 mld snooping vlan 1 fastleave
Switch(config)# ipv6 mld snooping vlan 1 last-member-query-count 5
Switch(config)# ipv6 mld snooping vlan 1 last-member-query-interval 3
Switch(config)# ipv6 mld snooping vlan 1 query-interval 100
Switch(config)# ipv6 mld snooping vlan 1 response-time 12
Switch(config)# ipv6 mld snooping vlan 1 robustness-variable 4
Switch# show ipv6 mld snooping vlan 1
MLD Snooping is globaly enabled
MLD Snooping VLAN 1 admin : disabled
MLD Snooping oper mode : disabled
MLD Snooping robustness: admin 4 oper 2
MLD Snooping query interval: admin 100 sec oper 125 sec
MLD Snooping query max response : admin 12 sec oper 10 sec
MLD Snooping last member query counter: admin 5 oper 2
MLD Snooping last member query interval: admin 3 sec oper 1 sec
MLD Snooping last immediate leave: enabled
MLD Snooping automatic learning of multicast router ports: enabled
```

---

## ipv6 mld snooping vlan fastleave

---

**Syntax**

**ipv6 mld snooping vlan <VLAN-LIST> fastleave**  
**no ipv6 mld snooping vlan <VLAN-LIST> fastleave**

---

**Parameter**

VLAN-LIST      specifies VLAN ID list to set

---

**Default**

Default is disabled

---

**Mode**

Global Configuration

---

**Usage**

Use the **ipv6 mld snooping vlan fastleave** command to enable fastleave function. Group will remove port immediately when receive leave packet. Use the **no** form of this command to disable. You can verify settings by the **show ipv6 mld snooping vlan** command

---

**Example**

The following example specifies that set ipv6 mld snooping vlan fastleave test.

```
Switch(config)# ipv6 mld snooping vlan 1 fastleave
```

---



## ipv6 mld snooping vlan last-member-query-count

Syntax	<b>ipv6 mld snooping vlan &lt;VLAN-LIST&gt; last-member-query-count &lt;1-7&gt;</b> <b>no ipv6 mld snooping vlan &lt;VLAN-LIST&gt; last-member-query-count</b>
Parameter	VLAN-LIST      specifies VLAN ID list to set last-member-query- count <1-7>      specifies last member query count to set
Default	Default is 2
Mode	Global Configuration
Usage	Use the <b>ipv6 mld snooping vlan last-member-query-count</b> command to change how many query packets will send. Use the <b>no</b> form of this command to restore to default. You can verify settings by the <b>show ipv6 mld snooping vlan</b> command
Example	The following example specifies that set <b>ipv6 mld snooping vlan last-member-query-count</b> test. Switch(config)# <b>ipv6 mld snooping vlan 1 last-member-query-count 5</b>

## ipv6 mld snooping vlan last-member-query-interval

Syntax	<b>ipv6 mld snooping vlan &lt;VLAN-LIST&gt; last-member-query-interval &lt;1-60&gt;</b> <b>no ipv6 mld snooping vlan &lt;VLAN-LIST&gt; last-member-query-interval</b>
Parameter	VLAN-LIST      specifies VLAN ID list to set last-member-query- interval <1-60>      specifies last member query interval to set
Default	Default is 1
Mode	Global Configuration
Usage	Use the <b>ipv6 mld snooping vlan last-member-query-interval</b> command to set interval between each query packet. Use the <b>no</b> form of this command to restore to default



You can verify settings by the **show ipv6 mld snooping vlan** command

---

**Example**

The following example specifies that set **ipv6 mld snooping vlan last-member-query-interval** test.

Switch(config)# **ipv6 mld snooping vlan 1 last-member-query-interval 3**

---

## ipv6 mld snooping vlan query-interval

---

**Syntax**

**ipv6 mld snooping vlan <VLAN-LIST> query-interval <30-18000>**  
**no ipv6 mld snooping vlan <VLAN-LIST> query-interval**

---

**Parameter**

VLAN-LIST      specifies VLAN ID list to set  
query-interval <30-  
18000>      specifies query interval to set

---

**Default**

Default is 125

**Mode**

Global Configuration

---

**Usage**

Use the **ipv6 mld snooping vlan query-interval** command to set interval between each query.

Use the **no** form of this command to restore to default

You can verify settings by the **show ipv6 mld snooping vlan** command

---

**Example**

The following example specifies that set **ipv6 mld snooping vlan query-interval** test.

Switch(config)# **ipv6 mld snooping vlan 1 query-interval 100**

---

## ipv6 mld snooping vlan response-time

---

**Syntax**

**ipv6 mld snooping vlan <VLAN-LIST> response-time <5-20>**  
**no ipv6 mld snooping vlan <VLAN-LIST> response-time**

---

**Parameter**

VLAN-LIST      specifies VLAN ID list to set  
response-time <5-  
20>      specifies a response time to set

---



---

<b>Default</b>	Default is 10
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>ipv6 mld snooping vlan response-time</b> command to set response time.</p> <p>Use the <b>no</b> form of this command to restore to default.</p> <p>You can verify settings by the <b>show ipv6 mld snooping vlan</b> command</p>
<b>Example</b>	<p>The following example specifies that set <b>ipv6 mld snooping vlan response-time</b> test.</p> <p>Switch(config)# <b>ipv6 mld snooping vlan 1 response-time 12</b></p>

---

## ipv6 mld snooping vlan robustness-variable

---

<b>Syntax</b>	<b>ipv6 mld snooping vlan &lt;VLAN-LIST&gt; robustness-variable &lt;1-7&gt;</b> <b>no ipv6 mld snooping vlan &lt;VLAN-LIST&gt; robustness-variable</b>
<b>Parameter</b>	<p>VLAN-LIST      specifies VLAN ID list to set</p> <p>robustness-variable    specifies a robustness value to set                       &lt;1-7&gt;</p>
<b>Default</b>	Default is 2
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>ipv6 mld snooping vlan robustness-variable</b> command to times to retry.</p> <p>Use the <b>no</b> form of this command to restore to default</p> <p>You can verify settings by the <b>show ipv6 mld snooping vlan</b> command</p>
<b>Example</b>	<p>The following example specifies that set ipv6 mld snooping vlan parameters test.</p> <p>Switch(config)# <b>ip igmp snooping vlan 1 robustness-variable</b></p>

---

## ipv6 mld snooping vlan router

---

<b>Syntax</b>	<b>ipv6 mld snooping vlan VLAN-LIST router learn pim-dvmrp</b> <b>no ipv6 mld snooping vlan VLAN-LIST router learn pim-dvmrp</b>
---------------	---

---



<b>Parameter</b>	VLAN-LIST	specifies VLAN ID list to set
<b>Default</b>	Default is enabled	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Use the <b>ipv6 mld snooping vlan router</b> command to enable learning router port by routing protocol packets such as PIM/PIMv2, DVMRP, MOSPF. Use the <b>no</b> form of this command to disable. You can verify settings by the <b>show ipv6 mld snooping vlan</b> command	
<b>Example</b>	The following example specifies that set <b>ipv6 mld snooping vlan 99 router</b>	

## ipv6 mld snooping vlan static-port

<b>Syntax</b>	<b>ipv6 mld snooping vlan &lt;VLAN-LIST&gt; static-port IF_PORTS</b> <b>  no ipv6 mld snooping vlan &lt;VLAN-LIST&gt; static-port IF_PORTS</b>	
<b>Parameter</b>	VLAN-LIST	specifies VLAN ID list to set
	IF_PORTS	specifies a port list to set or remove
<b>Default</b>	No static port by default	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Use the <b>ipv6 mld snooping vlan static-port</b> command to add static forwarding port, all known vlan 1 ipv6 group will add the static ports. Use the <b>no</b> form of this command to delete static port. You can verify settings by the <b>show ipv6 mld snooping forward-all</b> command.	
<b>Example</b>	The following example specifies that set ipv6 mld snooping static port test. Switch(config)# <b>ipv6 mld snooping vlan 1 static -port gi1-2</b>	



## ipv6 mld snooping vlan forbidden-router-port

### Syntax

```
 ipv6 mld snooping vlan <VLAN-LIST> forbidden-router-port
 IF_PORTS
 no ipv6 mld snooping vlan <VLAN-LIST> forbidden-router-port
 IF_PORTS
```

### Parameter

VLAN-LIST	specifies VLAN ID list to set
IF_PORTS	specifies a port list to set or remove

### Default

No forbidden router ports by default

### Mode

Global Configuration

### Usage

Use the **ipv6 mld snooping vlan forbidden-router-port** command to add static forbidden router port. This will also remove port from static router port. The forbidden router port will not forward received query packet.  
.Use the **no** form of this command to delete forbidden router port.  
You can verify settings by the **show ipv6 mld snooping router** command.

### Example

The following example specifies that set ipv6 mld snooping forbidden test.  
Switch(config)# **ipv6 mld snooping vlan 1 forbidden-router-port gi2**

## ipv6 mld snooping vlan forbidden-router-port

### Syntax

```
 ipv6 mld snooping vlan <VLAN-LIST> forbidden-router-port
 IF_PORTS
 no ipv6 mld snooping vlan <VLAN-LIST> forbidden-router-port
 IF_PORTS
```

### Parameter

VLAN-LIST	specifies VLAN ID list to set
IF_PORTS	specifies a port list to set or remove

### Default

No forbidden router ports by default

### Mode

Global Configuration



---

Usage

Use the **ipv6 mld snooping vlan forbidden-router-port** command to add static forbidden router port. This will also remove port from static router port. The forbidden router port will not forward received query packet.  
Use the **no** form of this command to delete forbidden router port.  
You can verify settings by the **show ipv6 mld snooping router** command.

---

Example

The following example specifies that set ipv6 mld snooping forbidden test.  
Switch(config)# **ipv6 mld snooping vlan 1 forbidden-router-port gi2**

---

## ipv6 mld snooping vlan static router port

---

Syntax

**ipv6 mld snooping vlan <VLAN-LIST> static-router-port IF\_PORTS**  
**no ipv6 mld snooping vlan <VLAN-LIST> static-router-port IF\_PORTS**

---

Parameter

VLAN-LIST	specifies VLAN ID list to set
IF_PORTS	specifies a port list to set or remove

---

Default

None static router ports by default

---

Mode

Global Configuration

---

Usage

Use the **ipv6 mld snooping vlan static-router-port** command to add static router port. All query packets will forward to this port.  
Use the **no** form of this command to delete static router port.  
You can verify settings by the **show ipv6 mld snooping router** command..

---

Example

The following example specifies that set ipv6 mld snooping static test.  
Switch(config)# **ipv6 mld snooping vlan 1 static-router-port gi1-2**

---

## ipv6 mld snooping vlan static-group

---

Syntax

**ipv6 mld snooping vlan <VLAN-LIST> static-group [<ipv6-addr>]**  
**interfaces IF\_PORTS**  
**no ipv6 mld snooping vlan <VLAN-LIST> static-group <ipv6-addr>**  
**interfaces IF\_PORTS**

---

Parameter

VLAN-LIST	specifies VLAN ID list to set
Ipv6-addr	specifies multicast group ipv4 address

---



	IF_PORTS	specifies port list to set or remove
<b>Default</b>		No static group by default
<b>Mode</b>		Global Configuration
<b>Usage</b>		<p>Use the <b>ipv6 mld snooping vlan static-group</b> command to add a static group. The static group will not learn other dynamic ports. If the dynamic group exists, then the static group will overlap the dynamic group. The static group set to valid unless igmp snooping global and vlan enable.</p> <p>Use the <b>no</b> form of this command to delete a port in static group. If remove the last member of static group, the static group will be delete.</p> <p>You can verify settings by the <b>show ipv6 mld snooping group</b> command.</p>
<b>Example</b>		<p>The following example specifies that set ipv6 mld snooping static group test.</p> <pre>Switch(config)# ipv6 mld snooping vlan 1 static-group ff13::1 interfaces gi1-2</pre>

## ipv6 mld snooping vlan group

<b>Syntax</b>	<b>no ipv6 mld snooping vlan &lt;VLAN-LIST&gt; group &lt;ipv6-addr&gt;</b>	
<b>Parameter</b>	VLAN-LIST	specifies VLAN ID list to set
	ipv6-addr	specifies multicast group ipv6 address
<b>Default</b>		None
<b>Mode</b>		Global Configuration
<b>Usage</b>	<p>Use the <b>no ipv6 mld snooping vlan group</b> command to delete a group which could be static or dynamic.</p> <p>You can verify settings by the <b>show ipv6 mld snooping group</b> command.</p>	
<b>Example</b>	<p>The following example specifies that set ip igmp snooping static group test.</p> <pre>Switch(config)# no ip igmp snooping vlan 1 group ff13::1</pre>	



## profile range

Syntax	<b>profile range ipv6 &lt;ipv6-addr&gt; [ipv6-addr] action (permit   deny)</b>
<ipv6-addr>	Start ipv6 multicast address
[ipv6-addr]	End ipv6 multicast address
(permit   deny)	Permit: allow Multicast address range ip address learning deny: do not allow Multicast address range ip address learning
Default	None
Mode	mld profile configuration mode
Usage	Use the <b>profile</b> command to generate MLD profile. You can verify settings by the <b>show ipv6 mld profile</b> command

Example	The following example specifies that set ipv6 mld profile test. Switch(config)# <b>ipv6 mld profile 1</b> Switch(config-mld-profile)# <b>profile range ipv6 ff13::1 ff13::10 action permit</b>

## ipv6 mld profile

Syntax	<b>ipv6 mld profile &lt;1-128&gt;</b> <b>no ipv6 mld profile &lt;1-128&gt;</b>
Parameter	<1-128> specifies profile ID
Default	No profie exist by default
Mode	Global Configuration



---

**Usage**

Use the **ipv6 mld profile** command to enter profile configuration. Use the **no** form of this command to delete profile.  
You can verify settings by the **show ipv6 mld profile** command

---

**Example**

The following example specifies that set ipv6 mld profile test.

```
Switch(config)# ipv6 mld profile 1
Switch(config-mld-profile)# profile range ipv6 ff13::1 ff13::10 action
permit
```

---

## ipv6 mld filter

---

**Syntax**

**ipv6 mld filter <1-128>**  
**no ipv6 mld filter**

---

**Parameter**

<1-128> specifies profile ID

[interfaces  
IF\_PORTS] Specifies interfaces to display

---

**Default**

None

---

**Mode**

Port Configuration

---

**Usage**

Use the **ipv6 mld filter** command to bind a profile for port. When the port bind a profile. Then the port learning group will update, if the group is not match the profile rule it will remove the port from the group. Static group is excluded.

Use the **no** form of this command to delete profile

You can verify settings by the **show ipv6 mld filter** command

---

**Example**

The following example specifies that set ipv6 mld filter test.

```
Switch(config)# interface gi1
Switch(config-if)# ipv6 mld filter 1
```

---

## ipv6 mld max-groups

---

**Syntax**

**ipv6 mld max-groups <0-1024>**  
**no ipv6 mld max-groups**

---



<b>Parameter</b>	<0-1024>	specifies profile ID
<b>Default</b>	Default is 1024	
<b>Mode</b>	Port Configuration	
<b>Usage</b>	Use the <b>ipv6 mld max-groups</b> command to limit port learning max group number. When the port has reach limitation, new group will not add this port. Static group is excluded.	
	Use the <b>no</b> form of this command to restore to default You can verify settings by the <b>show ipv6 mld max-groups</b> command.	
<b>Example</b>	The following example specifies that set ipv6 mld max-groups test. <b>Switch(config)# interface g1</b> <b>Switch(config-if)# ipv6 mld max-groups 10</b>	

---

## ip igmp max-groups action

<b>Syntax</b>	<b>ipv6 mld max-groups action (deny   replace)</b>	
<b>Parameter</b>	(deny   replace)	Deny: current port igmp group arrived max-groups, don't add group. Replace: current port igmp group arrived max-groups, remove port for rand group, and add port to new group.
<b>Default</b>	Default action is deny	
<b>Mode</b>	Interface mode	
<b>Usage</b>	Use the <b>ipv6 mld max-groups action</b> command to set the action when the numbers of groups reach the limitation. Use the <b>no</b> form of this command to restore to default You can verify settings by the <b>show ipv6 mld max-groups</b> command.	
<b>Example</b>	The following example specifies that set action replace test. <b>Switch(config-if)#ipv6 mld max-groups action replace</b>	

---



## clear ipv6 mld snooping groups

<b>Syntax</b>	<b>clear ipv6 mld snooping groups [(dynamic   static)]</b>
<b>Parameter</b>	None      Clear ipv6 mld groups include dynamic and static (dynamic   static)      ipv6 mld group type is dynamic or static
<b>Default</b>	None
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will clear the ipv6 mld groups for dynamic or static or all of type. You can verify settings by the <b>show ipv6 mld snooping groups</b> command..
<b>Example</b>	The following example specifies that clear ipv6 mld snooping groups test. <b>Switch# clear ipv6 mld snooping groups static</b>

## clear ipv6 mld snooping statistics

<b>Syntax</b>	<b>clear ipv6 mld snooping statistics</b>
<b>Parameter</b>	none
<b>Default</b>	None
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will clear the igmp statistics. You can verify settings by the <b>show ipv6 mld snooping</b> command.
<b>Example</b>	The following example specifies that clear ipv6 mld snooping statistics test. <b>Switch# clear ipv6 mld snooping statistics</b>



## show ipv6 mld snooping groups counters

### Syntax **show ipv6 mld snooping groups counters**

Parameter	none
Default	None
Mode	Privileged EXEC

**Usage** This command will display the ipv6 mld group counter include static group.

**Example** The following example specifies that display ipv6 mld snooping group counter test.

```
Switch# show ipv6 mld snooping group counters
      Total ipv6 mld snooping group number: 2
```

## show ipv6 mld snooping groups

### Syntax **show ipv6 mld snooping groups [(dynamic | static)]**

Parameter	none	Show ipv6 mld groups include dynamic and static
	(dynamic   static)	Display ipv6 mld group type is dynamic or static
Default	display all ipv6 mld groups	
Mode	Privileged EXEC	

**Usage** This command will display the ipv6 mld groups for dynamic or static or all of type.

**Example** The following example specifies that show ipv6 mld snooping groups test.

```
Switch# show ipv6 mld snooping groups
VLAN |      Group IP Address | Type | Life(Sec) | Port
-----+-----+-----+-----+
      1 |          ff13::1 | Static|   --  | fa1
      1 |          ff13::2 | Static|   --  | fa2
```



---

Total Number of Entry = 2

---

## **show ipv6 mld snooping router**

---

### **Syntax**

**show ipv6 mld snooping router [(dynamic | forbidden | static )]**

---

### **Parameter**

none	Show ipv6 mld router include dynamic and static and forbidden
(dynamic   forbidden   static)	Display ipv6 mld router info for different type

---

### **Default**

None

---

### **Mode**

Privileged EXEC

---

### **Usage**

This command will display the ipv6 mld router info.

---

### **Example**

The following example specifies that show ipv6 mld snooping router test.

Switch# **show ipv6 mld snooping router**

Dynamic Router Table

VID | Port | Expiry Time(Sec)

-----+-----+-----

Total Entry 0

Static Router Table

VID | Port Mask

-----+-----

1 | fa5

Total Entry 1

Forbidden Router Table

VID | Port Mask

-----+-----

Total Entry 0

---



## show ipv6 mld snooping

**Syntax** **show ipv6 mld snooping**

**Parameter** none

**Default** None

**Mode** Privileged EXEC

**Usage** This command will display ipv6 mld snooping global info.

**Example** The following example specifies that show ipv6 mld snooping test.

```
Switch# show ipv6 mld snooping
      MLD Snooping Status
```

```
Snooping          : Disabled
Report Suppression : Enabled
Operation Version   : v1
Forward Method     : mac
Unknown Multicast Action : Flood
```

```
      Packet Statistics
Total RX          : 0
Valid RX          : 0
Invalid RX        : 0
Other RX          : 0
Leave RX          : 0
Report RX         : 0
General Query RX  : 0 Specail
Group Query RX    : 0
Specail Group & Source Query RX : 0
Leave TX          : 0
Report TX         : 0
General Query TX  : 0
Specail Group Query TX : 0
Specail Group & Source Query TX : 0
```



## **show ipv6 mld snooping vlan**

<b>Syntax</b>	<b>show ipv6 mld snooping vlan [VLAN-LIST]</b>
<b>Parameter</b>	none Show all ipv6 mld snooping vlan info [VLAN-LIST] Show specifies vlan ipv6 mld snooping info
<b>Default</b>	Show all ipv6 mld snooping vlan info
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will display ipv6 mld snooping vlan info.
<b>Example</b>	The following example specifies that show ipv6 mld snooping vlan test. Switch# <b>show ipv6 mld snooping vlan 1</b> MLD Snooping is globaly disabled MLD Snooping VLAN 1 admin : disabled MLD Snooping oper mode : disabled MLD Snooping robustness: admin 2 oper 2 MLD Snooping query interval: admin 125 sec oper 125 sec MLD Snooping query max response : admin 10 sec oper 10 sec MLD Snooping last member query counter: admin 2 oper 2 MLD Snooping last member query interval: admin 1 sec oper 1 sec MLD Snooping last immediate leave: disabled MLD Snooping automatic learning of multicast router ports: enabled

## **show ipv6 mld snooping forward-all**

<b>Syntax</b>	<b>show ipv6 mld snooping forward-all [vlan VLAN-LIST]</b>
<b>Parameter</b>	none Show all ipv6 mld snooping vlan forward-all info [vlan VLAN-LIST] Show specifies vlan of ipv6 mld forward info.
<b>Default</b>	Show all vlan ipv6 mld forward all info
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will display ipv6 mld snooping forward all info.



**Example**

The following example specifies that show ipv6 mld snooping forward-all test.

```
Switch# show ipv6 mld snooping forward-all
MLD Snooping VLAN      1
MLD Snooping static port : None
MLD Snooping forbidden port : None
```

---

## show ipv6 mld profile

**Syntax**

**show ipv6 mld profile [<1-128>]**

**Parameter**

none	Show all ipv6 mld snooping profile info
[<1-128>]	Show specifies index profile info

---

**Default**

Show all ipv6 mld profile info

**Mode**

Privileged EXEC

**Usage**

This command will display ipv6 mld profile info.

**Example**

The following example specifies that show ipv6 mld profile test.

```
Switch# show ipv6 mld profile
IPv6 mld profile index: 1
IPv6 mld profile action: permit
Range low ip: ff13::1
Range high ip: ff13::10
```

---

## show ipv6 mld filter

**Syntax**

**show ipv6 mld filter [interfaces IF\_PORTS]**

**Parameter**

none	Show all port filter
[interfaces IF_PORTS]	Show specifies ports filter

---

**Default**

None

**Mode**

Privileged EXEC



**Usage**

This command will display ipv6 mld port filter info.

**Example**

The following example specifies that show ipv6 mld filter test.

Switch# **show ipv6 mld filter**

Port ID | Profile ID

-----+-----

gi1 : 1  
gi2 : None  
gi3 : None  
gi4 : None  
gi5 : None

--More--

---

## show ipv6 mld max-group

**Syntax**

**show ipv6 mld max-group [interfaces IF\_PORTS]**

**Parameter**

none Show all port max-group

[interfaces  
IF\_PORTS] Show specifies ports max-group

---

**Default**

None

**Mode**

Privileged EXEC

**Usage**

This command will display ipv6 mld port max-group.

**Example**

The following example specifies that show ipv6 mld max-group test.

Switch(config-if)# **ipv6 mld max-groups 50**

Switch# **show ipv6 mld max-group**

Port ID | Max Group

-----+-----

gi1 : 50  
gi2 : 256  
gi3 : 256  
gi4 : 256  
gi5 : 256

--More--

---



## show ipv6 mld port max-group action

<b>Syntax</b>	<b>show ipv6 mld max-group action [interfaces IF_PORTS]</b>
<b>Parameter</b>	none Show all port max-group action [interfaces IF_PORTS] Show specifies ports max-group action
<b>Default</b>	Show all ports ipv6 mld max-group action
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	This command will display ipv6 mld port max-group action.
<b>Example</b>	The following example specifies that show ipv6 mld max-group action test. Switch(config-if)# <b>ipv6 mld max-groups action replace</b> Switch# <b>show ipv6 mld max-group action</b> Port ID   Max-groups Action -----+ gi1 : replace gi2 : deny gi3 : deny gi4 : deny gi5 : deny --More--

## 20. MVR

### mvr

<b>Syntax</b>	<b>mvr</b> <b>no mvr</b>
<b>Parameter</b>	None
<b>Default</b>	Default is disabled
<b>Mode</b>	Global Configuration



**Usage**

Use the **mvr** command to enable MVR function. The command will clear all mvr VLAN ID multicast snooping group.

Use the **no** form of this command to disable. Disable will clear all mvr group. You can verify settings by the **show mvr** command.

**Example**

The following example specifies that set **mvr** test.

```
Switch(config)# mvr
Switch(config)# no mvr
Switch# show mvr
MVR Running : Disabled
MVR Multicast VLAN : 1
MVR Group Range : None
MVR Max Multicast Groups : 128 MVR
Current Multicast Groups : 0 MVR
Global query response time : 1 sec
MVR Mode : compatible
```

## **mvr vlan**

**Syntax**      **mvr vlan <VLAN-ID>**

<b>Parameter</b>	<b>&lt;VLAN-ID&gt;</b>	The exist static vlan id
------------------	------------------------	--------------------------

<b>Default</b>	Default mvr vlan id is 1
----------------	--------------------------

<b>Mode</b>	Global Configuration
-------------	----------------------

**Usage**

Use the **mvr vlan** command to modify mvr vlan id when the mvr status is enabled.

Change mvr vlan id will delete the old mvr vlan and new mvr vlan group. If there have configure source or receiver port, there will check the source must only in the mvr vlan , and receiver port must not in the mvr vlan member. You can verify settings by the **show mvr** command.

**Example**

The following example specifies that configure mvr vlan 2 test.

```
Switch(config)# vlan 2
Switch(config)# mvr
The operation will delete groups of VLAN ID is MVR VLAN include static groups. Continue? [yes/no]:y
Switch(config)# mvr vlan 2
```

**The operation will delete the old and new MVR VLAN groups include static MVR groups. Continue? [yes/no]:y**



---

```
Switch# show mvr
MVR Running :
Enabled MVR
Multicast VLAN : 2
MVR Group Range :
None
MVR Max Multicast Groups : 128
MVR Current Multicast Groups : 0
MVR Global query response time : 1
sec
MVR Mode : compatible
```

---

## **mvr group**

---

**mvr group <ip-address> [<1-128>]**

---

< ip-address>	Start MVR IP multicast address
[<1-128>]	Contiguous series of IP addresses.

---

**Default** None

**Mode** Global Configuration

**Usage** Use the **mvr group** command to configure mvr group address range when mvr is enabled. The command will delete all mvr vlan ipv4 group entry You can verify settings by the **show mvr** command

**Example** The following example specifies that set mvr group range is 224.1.1.1 ~ 224.1.1.8 test.

```
Switch(config)# mvr
Switch(config)# mvr group 224.1.1.1 8
The operation will delete the MVR VLAN groups include static MVR groups. Continue? [yes/no]:y
Switch# show mvr
MVR Running : Enabled
MVR Multicast VLAN : 2
MVR Group Range : 224.1.1.1 ~ 224.1.1.8
MVR Max Multicast Groups : 128 MVR
Current Multicast Groups : 0 MVR
Global query response time : 1 sec
MVR Mode : compatible
```

---

## **mvr mode**

---

**Syntax** **mvr mode (dynamic | compatible)**

---

**Parameter** (dynamic|compatible)    dynamic: Allows dynamic MVR membership on



# **Command Line Interface**

## **User Guide**

---

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

source ports  
compatible: does not support IGMP dynamic joins  
on source ports.

---

**Default** Default is compatible.

**Mode** Global Configuration

**Usage** Use the **mvr mode** command to change mvr mode when mvr is enabled.  
You can verify settings by the **show mvr** command.

**Example** The following example specifies that set mvr mode dynamic test.

```
Switch(config)#mvr
Switch(config)#mvr mode dynamic
Switch# show mvr
MVR Running : Enabled
MVR Multicast VLAN : 2
MVR Group Range : 224.1.1.1 ~ 224.1.1.8
MVR Max Multicast Groups : 128 MVR
Current Multicast Groups : 0 MVR
Global query response time : 1 sec
MVR Mode : dynamic
```

---

## **mvr query-time**

**Syntax** **mvr query-time <1-10>**  
**no mvr query-time**

---

**Parameter** **<1-10>** specifies query response time is 1~10 sec.

**Default** Default is 1 sec

**Mode** Global Configuration

**Usage** Use the **mvr query-time** command to configure when mvr is enabled.  
Use the **no** form of this command to set query-time default value. You can verify settings by the **show mvr** command.

**Example** The following example specifies that set mvr query-time 10 sec test.  
Switch(config)# **mvr**

---



---

```
Switch(config)# mvr query-time 10
Switch# show mvr
MVR Running :
Enabled MVR
Multicast VLAN : 2
MVR Group Range : 224.1.1.1 ~ 224.1.1.8
MVR Max Multicast Groups :
128 MVR Current Multicast
Groups : 0
MVR Global query response time : 10 sec
MVR Mode : dynamic
```

---

## mvr port type

Syntax	<b>mvr type (source   receiver)</b> <b>no mvr type</b>
Parameter	(source   receiver)      Source: Configure uplink ports that receive and send multicast data as source ports. Subscribers cannot be directly connected to source ports. All source ports on a switch belong to the single multicast VLAN. Receiver: Configure a port as a receiver port if it is a subscriber port and should only receive multicast data. It does not receive data unless it becomes a member of the multicast group, either statically or by using IGMP leave and join messages. Receiver ports cannot belong to the <u>multicast VLAN</u> .
Default	None
Mode	Port Configuration
Usage	Use the <b>mvr type</b> command to configure mvr port type when mvr is enabled. The source port must only belong to mvr vlan. The receiver port must not belong to mvr vlan, and port mode must be access mode. Use the <b>no</b> form of this command to set mvr type none You can verify settings by the <b>show mvr interface</b> command



## Command Line Interface User Guide

### Example

The following example specifies that set g1 fa1 is source port , fa2 is receiver port test.

```
Switch(config)# vlan 2
Switch(config-vlan)#exit
Switch(config)#mvr
Switch(config)#mvr vlan 2
```



```
Switch(config)#mvr group 224.1.1.1 8
Switch(config)# interface gi1
Switch(config-if)# switchport trunk allowed vlan 2
Switch(config-if)# mvr type
source Switch(config-if)#exit
Switch(config)# interface gi2
Switch(config-if)# switchport mode
access Switch(config-if)#mvr type
receiver Switch# show mvr interface
  Port | Type | Immediate Leave
  -----+-----+
  gi1  |  Source| Disabled
  gi2  | Receiver| Disabled
```

---

## mvr port immediate

Syntax	<b>mvr immediate</b> <b>no mvr immediate</b>
Parameter	None
Default	Default is disabled
Mode	Port Configuration
Usage	<p>Use the <b>mvr immediate</b> command to configure mvr support immediate leave when mvr is enabled.</p> <p><b>Note</b> This command applies to only receiver ports and should only be enabled on receiver ports to which a single receiver device is connected. Use the <b>no</b> form of this command to disable immediate leave. You can verify settings by the <b>show mvr interface</b> command</p>



## Command Line Interface User Guide

### Example

The following example specifies that set gi2 immediate enable test. The configure should configure mvr receiver port firstly.(eg. mvr port type)

```
Switch(config)# interface gi2
Switch(config-if)#mvr immediate
Switch(config-if)#exit
Switch(config)# exit
Switch# show mvr interface
  Port | Type | Immediate Leave
  -----+-----+
  gi1  |   Source| Disabled
  gi2  | Receiver| Enabled
```



# mvr static group

**mvr vlan <VLAN-ID> group <ip-addr> interfaces IF\_PORTS no mvr  
vlan < VLAN-ID> group <ip-addr> interfaces IF\_PORTS**

<b>Parameter</b>	VLAN-ID ip-addr IF_PORTS	specifies MVR VLAN ID for static group specifies multicast MVR group address specifies port list to set or remove
------------------	--------------------------------	---

---

**Default** None

## **Mode** Global Configuration

Usage	<p>Use the <b>mvr vlan group</b> command to add a static group or configure static group member ports when mvr is enabled.</p> <p>This command applies to only receiver ports.</p> <p>In compatible mode, this command applies to only receiver ports. In dynamic mode, it applies to receiver ports and source ports.</p> <p>When remove static mvr group all ports, the static group will be delete. Or can use <b>no ip igmp vlan VLAN-ID group</b> to delete the mvr static group.</p> <p>Static group can't learn dynamic port by igmp messages.</p> <p>Use the <b>no</b> form of this command to delete a port in static group. If remove the last member of static group, the static group will be delete.</p>
-------	---

You can verify settings by the **show mvr members** command.

<b>Example</b>	The following example specifies that set mvr static group test. The configure must configure mvr receiver port firstly.(eg. mvr port type) <b>Switch(config)# mvr vlan 2 group 224.1.1.1 interfaces gi2</b> <b>Switch# show mvr members</b> <b>Gourp IP Address   Type   Life(Sec)   Port</b> -----+-----+-----+-----
	224.1.1.1   Static  --  gi2

## Total Number of Entry = 1

# clear myr members

**clear myr members [dynamic|static]**

**Parameter** dynamic specifies MVR dynamic group

static	specifies MVR static group
--------	----------------------------

---

<b>Default</b>	Clear all of mvr group
----------------	------------------------

---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	This command will clear the mvr groups for selected type.
--------------	---

---

<b>Example</b>	The following example specifies that clear all mvr groups test. Switch# <b>clear mvr members</b>
----------------	---

---

## show mvr members

---

<b>Syntax</b>	<b>show mvr members</b>
---------------	-------------------------

---

<b>Parameter</b>	None
------------------	------

---

<b>Default</b>	None
----------------	------

---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	This command will display the mvr groups for all of type.
--------------	---

---

<b>Example</b>	The following example specifies that show mvr groups test. Switch# <b>show mvr members</b>
----------------	---

---

## show mvr interface

---

<b>Syntax</b>	<b>show mvr interface [IF_PORTS]</b>
---------------	--------------------------------------

---

<b>Parameter</b>	IF_PORTS	Show specifies port list configurationt
------------------	----------	---

---

<b>Default</b>	None
----------------	------



<b>Mode</b>	Privileged EXEC
-------------	-----------------

<b>Usage</b>	This command will display mvr port type and port immediate status.
--------------	--

<b>Example</b>	The following example specifies that show mvr interface test. Switch# <b>show mvr interface</b>
----------------	--

## show mvr

<b>Syntax</b>	<b>show mvr</b>
---------------	-----------------

<b>Parameter</b>	None
------------------	------

<b>Default</b>	None
----------------	------

<b>Mode</b>	Privileged EXEC
-------------	-----------------

<b>Usage</b>	This command will display mvr global information.
--------------	---

<b>Example</b>	The following example specifies that show mvr test. Switch# <b>show mvr</b> MVR Running : Enabled MVR Multicast VLAN : 100 MVR Group Range : 224.1.1.1 ~ 224.1.1.128 MVR Max Multicast Groups : 128 MVR Current Multicast Groups : 0 MVR Global query response time : 1 sec MVR Mode : compatible
----------------	---

## 21. Port

### back-pressure



**Syntax**

**back-pressure**  
**no back-pressure**

**Parameter**

**Default**

Default back pressure state is enabled.

**Mode**

Interface Configuration

**Usage**

Use “**back-pressure**” command to make port to enable back pressure feature.

Use **no** form of this command to disable back pressure feature.

The only way to show this configuration is using “**show running-config**” command.

**Example**

This example shows how to configure port fa1 and fa2 to be protected port.

```
Switch(config)# interface fa1  
Switch(config-if)# no back-pressure
```

This example shows how to show current jumbo-frmae size

```
Switch# show running-config interface fa1  
interface fa1  
    no back-pressure
```

## clear interface

**Syntax**

**clear interfaces *IF\_PORTS* counters**

**Parameter**

*IF\_PORTS*      Specify port to clear counters.

**Default**

No default value for this command.

**Mode**

Privileged EXEC

**Usage**

Use “**clear interface**” command to clear statistic counters on specific ports.



**Example**

This example shows how to clear counters on port fa1.

```
Switch(config)# clear interfaces fa1 counters
```

This example shows how to show current counters

```
Switch# show interfaces fa1
Hardware is Fast Ethernet
Auto-duplex, Auto-speed, media type is Copper
flow-control is off
  0 packets input, 0 bytes, 0 throttles
  Received 0 broadcasts (0 multicasts)
  0 runts, 0 giants, 0 throttles
  0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
  0 multicast, 0 pause input
  0 input packets with dribble condition detected
  0 packets output, 0 bytes, 0 underrun
  0 output errors, 0 collisions, 0 interface resets
  0 babbles, 0 late collision, 0 deferred
  0 PAUSE output
```

---

**description**

**Syntax**

**description WORD<1-32>**

**no description**

**Parameter**

**WORD<1-32>**      Specify port description string.

---

**Default**

Default port description is empty.

**Mode**

Interface Configuration

**Usage**

Use “**description**” command to give the port a name to identify it easily.

If description includes space character, please use double quoted to wrap it. Use **no** form to restore description to empty string.

**Example**

This example shows how to modify port descriptions.

```
Switch(config)# interface fa1
Switch(config-if)# description userport
Switch(config-if)# exit
Switch(config)# interface fa2
Switch(config-if)# description "uplink port"
```

This example shows how to show current port description on interface fa1 and fa2

```
Switch# show interfaces fa1-2 status
Port   Name          Status      Vlan  Duplex  Speed
```

---



Type					
fa1	userport	notconnect	1	auto	auto
Copper					
fa2	uplink port	notconnect	1	auto	auto
Copper					

## duplex

### Syntax

**duplex (auto | full | half)**

### Parameter

<b>auto</b>	Specify port duplex to auto negotiation.
<b>full</b>	Specify port duplex to force full duplex.
<b>half</b>	Specify port duplex to force half duplex.

### Default

Default port duplex is auto.

### Mode

Interface Configuration

### Usage

Use “**duplex**” command to change port duplex configuration.

### Example

This example shows how to modify port duplex configuration.

```
Switch(config)# interface fa1
Switch(config-if)# duplex full
Switch(config-if)# exit
Switch(config)# interface fa2
Switch(config-if)# duplex half
```

This example shows how to show current speed configuration

```
Switch# show running-config interfaces fa1-2
interface fa1
  duplex full
interface fa2
  duplex half
```

This example shows how to show current interface link speed

```
Switch# show interfaces fa1-2 status
Port  Name          Status   Vlan Duplex  Speed    Type
fa1            connected  1      full    a-100M  Copper
fa2            connected  1      half    a-100M  Copper
```

## eee

### Syntax

**eee**  
**no eee**

### Parameter



**Default** Default eee state is disabled.

**Mode** Interface Configuration

**Usage** Use “eee” command to make port to enable the energy efficient Ethernet feature.

Use **no** form of this command to disable eee.

The only way to show this configuration is using “**show running-config**” command.

**Example** This example shows how to configure port fa1 and fa2 to be protected port.

```
Switch(config)# interface fa1  
Switch(config-if)# eee
```

This example shows how to show current jumbo-frmae size

```
Switch# show running-config interface fa1  
interface fa1  
    eee
```

## flowcontrol

**Syntax** **flowcontrol (auto | off | on)**  
**no flowcontrol**

<b>Parameter</b>	<b>auto</b> Automatically enables or disables flow control on the interface.
	<b>off</b> Disable port flow control.
	<b>on</b> Enable port flow control.

**Default** Default port flow control is off.

**Mode** Interface Configuration

**Usage** Use “**flowcontrol**” command to change port flow control configuration.

Use **no** form to restore flow control to default (off) configuration.



**Example**

This example shows how to modify port duplex configuration.

```
Switch(config)# interface fa1  
Switch(config-if)# flowcontrol on
```

This example shows how to show current flow control configuration

```
Switch# show interfaces fa1  
Hardware is Fast Ethernet  
Full-duplex, Auto-speed, media type is Copper  
flow-control is on  
    0 packets input, 0 bytes, 0 throttles  
    Received 0 broadcasts (0 multicasts)  
    0 runts, 0 giants, 0 throttles  
    0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored  
    0 multicast, 0 pause input  
    0 input packets with dribble condition detected  
    379 packets output, 31981 bytes, 0 underrun  
    0 output errors, 0 collisions, 0 interface resets  
    0 babbles, 0 late collision, 0 deferred  
    0 PAUSE output
```

---

## jumbo-frame

**Syntax**

**jumbo-frame <1518-9216>**

**Parameter**

**<1518-9216>** Specify the maximum frame size.

---

**Default**

Default maximum frame size is 1522.

**Mode**

Global Configuration

**Usage**

Use “**jumbo-frame**” command to modify maximum frame size.

The only way to show this configuration is using “**show running-config**” command.

**Example**

This example shows how to modify maximum frame size on fa1 to 9216 bytes.

```
Switch(config)# jumbo-frame 9216
```

This example shows how to show current jumbo-frame size

```
Switch# show running-config  
jumbo-frame 9216
```

---

## media-type

**Syntax**

**media-type (auto-select | rj45 | sfp)**  
**no media-type**

---



<b>Parameter</b>	<b>auto-select</b> Select media automatically. <b>rj45</b> Select copper media. <b>sfp</b> Select fiber media.
<b>Default</b>	Default media type is auto.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	Use “ <b>media-type</b> ” command to change combo port media type. Use <b>no</b> form of this command to restore media type to default.
<b>Example</b>	This example shows how to modify combo port media type to copper. Switch(config)# <b>interface gi1</b> Switch(config-if)# <b>media-type rj45</b>

## protected

<b>Syntax</b>	<b>protected</b> <b>no protected</b>
<b>Default</b>	Default protected state is no protected.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	Use “ <b>protected</b> ” command to make port to be protected. Protected port is only allowed to communicate with unprotected port. In other words, protected port is not allowed to communicate with another protected port. Use <b>no</b> form to make port unprotected.
<b>Example</b>	This example shows how to configure port fa1 and fa2 to be protected port. Switch(config)# <b>interface range fa1-2</b> Switch(config-if-range)# <b>protected</b>  This example shows how to show current protected port state. Switch# <b>show interfaces fa1-2 protected</b> Port         Protected State -----+----- fa1   enabled



fa2 |enabled

---

## show interface

---

### Syntax

**show interfaces *IF\_PORTS***  
**show interfaces *IF\_PORTS* status**  
**show interfaces *IF\_PORTS* protected**

---

### Parameter

*IF\_PORTS* Specifiy port to show.

---

### Default

No default value for this command.

---

### Mode

Privileged EXEC

---

### Usage

Use “**show interface**” command to show detail port counters, parameters and status.

Use “**show interface status**” command to show brief port status.

Use “**show interface protected**” command to show protected status.

---



# Command Line Interface

## User Guide

### Example

This example shows how to show current counters

```
Switch# show interfaces fa1
Hardware is Fast Ethernet
Auto-duplex, Auto-speed, media type is Copper
flow-control is off
  0 packets input, 0 bytes, 0 throttles
  Received 0 broadcasts (0 multicasts)
  0 runts, 0 giants, 0 throttles
  0 input errors, 0 CRC, 0 frame, 0 overrun, 0 ignored
  0 multicast, 0 pause input
  0 input packets with dribble condition detected
  0 packets output, 0 bytes, 0 underrun
  0 output errors, 0 collisions, 0 interface resets
  0 babbles, 0 late collision, 0 deferred
  0 PAUSE output
```

This example shows how to show current protected port state.

```
Switch# show interfaces fa1-2 protected
Port      | Protected State
-----+-----
fa1     | enabled
fa2     | enabled
```

This example shows how to show current port status

```
Switch# show interfaces fa1-2 status
Port  Name          Status    Vlan  Duplex   Speed    Type
fa1           connected   1     full    a-100M  Copper
```



## speed

---

### Syntax

```
speed (10 | 100 | 1000)
speed auto [(10 | 100 | 1000 | 10/100)]
```

```
speed nonegotiate
no speed nonegotiate
```

---

### Parameter

<b>10</b>	Specify port speed to force 10Mbits/s or auto with 10Mbits/s ability.
<b>100</b>	Specify port speed to force 100Mbits/s or auto with 100Mbits/s ability.
<b>1000</b>	Specify port speed to force 1000Mbits/s or auto with 1000Mbits/s ability.
<b>10/100</b>	Specify port speed to auto with 10Mbits/s and 100Mbits/s

---

### Default

Default port speed is auto with all available abilities.

---

### Mode

Interface Configuration

---

### Usage

Use “**speed**” command to change port speed configuration. The speed is only able to configure to the physical maximum speed. For example, in fast Ethernet port, speed 1000 is not available.

You cannot configure the speed on the SFP module ports, but you can configure the speed to not negotiate (nonegotiate) if it is connected to a device that does not support autonegotiation.

---

### Example

This example shows how to modify port speed configuration.

```
Switch(config)# interface fa1
Switch(config-if)# speed 100
Switch(config-if)# exit
Switch(config)# interface fa2
Switch(config-if)# speed auto 10/100
```

This example shows how to show current speed configuration

```
Switch# show running-config interfaces fa1-2
interface fa1
  speed 100
interface fa2
  speed auto 10/100
```

This example shows how to show current interface link speed

```
Switch# show interfaces fa1-2 status
Port Name          Status    Vlan Duplex Speed      Type
```



fa1	connected	1	a-full	a-100M	Copper
fa2	connected	1	a-full	a-100M	Copper

---

## shutdown

---

### Syntax

```
shutdown  
no shutdown
```

---

### Parameter

---

### Default

Default port admin state is no shutdown.

---

### Mode

Interface Configuration

---

### Usage

Use “**shutdown**” command to disable port and use “**no shutdown**” to enable port. If port is error disabled by some reason, use “no shutdown” command can also recovery the port manually.

---

### Example

This example shows how to modify port duplex configuration.

```
Switch(config) # interface fa1  
Switch(config-if) # shutdown
```

This example shows how to show current admin state configuration

```
Switch# show running-config interfaces fa1  
interface fa1  
    shutdown
```

This example shows how to show current link status

Port	Name	Status	Vlan	Duplex	Speed	Type
fa1		<b>disable</b>	1	full	auto	Copper

---

## 22. Port Error Disable

### errdisable recovery cause

---

### Syntax

```
errdisable recovery cause (all|acl|arp-inspection|bpduguard|broadcast-flood|dhcp-rate-limit|psecure-violation|selfloop|unicast-flood|unknown-multicastflood)  
no errdisable recovery cause (all|acl|arp-inspection|bpduguard|broadcast-flood|dhcp-rate-limit|psecure-violation|selfloop|unicast-flood|unknown-multicastflood)
```



<b>Parameter</b>	<b>all</b>	Enable the auto recovery for port error disabled from all causes.
	<b>acl</b>	Enable the auto recovery for port error disabled from the ACL cause.
	<b>arp-inspection</b>	Enable the auto recovery for port error disabled from the ARP inspection cause.
	<b>bpduguard</b>	Enable the auto recovery for port error disabled from the STP BPDU Guard cause.
	<b>broadcast-flood</b>	Enable the auto recovery for port error disabled from the broadcast flooding cause.
	<b>dhcp-rate-limit</b>	Enable the auto recovery for port error disabled from the DHCP rate limit cause.
	<b>psecure-violation</b>	Enable the auto recovery for port error disabled from the port security cause.
	<b>selfloop</b>	Enable the auto recovery for port error disabled from the STP self-loop cause.
	<b>unicast-flood</b>	Enable the auto recovery for port error disabled from the unicast flooding cause.
	<b>unknown-multicastflood</b>	Enable the auto recovery for port error disabled from the unknown multicast flooding cause.
<b>Default</b>	Error disable recovery is disabled for all cause.	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	Ports would be disabled because of the invalid actions detected by protocols. To enable the port error disable recovery from the specific cause, use the command <b>errdisable recovery cause</b> in the Global Configuration mode.	
<b>Example</b>	The following example enables the port error disable recovery for the STP BPDU Guard and self-loop cause.	
	<pre>Switch(config)# errdisable recovery cause bpduguard Switch(config)# errdisable recovery cause selfloop</pre>	

## errdisable recovery interval

<b>Syntax</b>	<b>errdisable recovery interval <i>seconds</i></b>	
<b>Parameter</b>	<i>seconds</i>	The time in seconds to recover from a specific error-disable state. The valid range is 0 to 86400 seconds, and the default value is 300 seconds.



**Default** The default recovery time is 300 seconds.

**Mode** Global Configuration

**Usage** To set the recovery time of the error disabled ports, use the command **errdisable recovert interval** in the Global Configuration mode.

**Example** The following example set the agimg time to 500 seconds.

```
Switch(config)# errdisable recovery interval 60
```

---

## show errdisable recovery

**Syntax** **show errdisable recovery**

**Parameter** N/A

**Default** N/A

**Mode** Privileged EXEC

**Usage** To show the error disable configuration and the interfaces in the error disabled state, use the command **show errdisable recovery** in the Privileged EXEC mode.

**Example** The following example shows the error disable configuration, and the interfaces in the error disabled state.

```
Switch# show errdisable recovery
  ErrDisable Reason      | Timer Status
-----+-----
        bpduguard | enabled
        selfloop  | enabled
        broadcast-flood | disabled
        unknown-multicast-flood | disabled
        unicast-flood | disabled
            acl | disabled
        psecure-violation | disabled
        dhcp-rate-limit | disabled
        arp-inspection | disabled

Timer Interval : 60 seconds
```

---



Interfaces that will be enabled at the next timeout:

Port	Error Disable Reason	Time Left
-----	-----	-----

---

## 23. Port Security

### port-security (Global)

---

#### Syntax

**port-security**  
**no port-security**

---

#### Parameter

None

---

#### Default

Default is disabled

---

#### Mode

Global Configuration

---

#### Usage

The “**port-security**” command enables the port security functionality globally.  
Use the **no** form of this command to disable.  
You can verify settings by the **show port-security** command.

---

#### Example

The following example shows how to enable port security  
switch(config)# **port-security**  
switch# **show port-security**  
port-security is: Enabled

---

### port-security (Interface)

---

#### Syntax

**port-security**  
**no port-security**

---

#### Parameter

None

---

#### Default

Default is disabled

---

#### Mode

Port Configuration



**Usage**

The “**port-security**” command enables the port security functionality on this port.

Use the **no** form of this command to disable

You can verify settings by the **show port-security interface** command.

**Example**

The following example shows how to enable port security on interface fa1

```
switch(config)# interface fa1
switch(config-if)# port-security
switch(config)# show port-security interfaces fa1
  Port | Security | CurrentAddr | Action
  -----+-----+-----+
    fa1 | Enabled ( 1) | 0 | Discard
```

## port-security address-limit

**Syntax**

**port-security address-limit <1-256> action** (forward|discard|shutdown)  
**no port-security address-limit**

**Parameter**

<1-256>	The learning-limit number. It specifies how many MAC addresses this port can learn.
<b>forward</b>	Forward this packet whose SMAC is new to system and exceed the learning-limit number.
<b>discard</b>	Discard this packet whose SMAC is new to system and exceed the learning-limit number.
<b>shutdown</b>	Shutdown this port when receives a packet whose SMAC is new to system and exceed the learning limit number.

**Default**

The address-limit default is 1 and action is “drop”.

**Mode**

Port Configuration

**Usage**

Use the “**port-security address-limit**” command to set the learning-limit number and the violation action.

Use the **no** form of this command to restore the default settings.

You can verify settings by the **show port-security interface** command.

**Example**

The following example shows how to enable port security on port 1 and set the learning limit number to 10.

```
switch(config)# interface fa1
switch(config-if)# port-security address-limit 10 action discard
switch(config-if)# port-security
switch(config)# show port-security interfaces fa1
```



Port	Mode	Security	CurrentAddr	Action
fa1	Dynamic	Enabled ( 10 )	0	Discard

## show port-security

---

### Syntax

**show port-security**

---

### Parameter

None

---

### Default

No default value for this command.

---

### Mode

Privileged EXEC

---

### Usage

Use “**show port-security**” command to show port-security global information.

---

### Example

This example shows how to show port-security configurations.

```
Switch# show port-security  
port-security is: Enabled
```

---

## show port-security interface

---

### Syntax

**show port-security interface IF\_PORTS**

---

### Parameter

*IF\_PORTS*      Select port to show port-security configurations.

---

### Default

No default value for this command.

---

### Mode

Privileged EXEC

---

### Usage

Use “**show port-security interfaces**” command to show port-security information of the specified port.



**Example** This example shows how to show port-security configurations on interface fa1.

```
Switch# show port-security interfaces fa1
Port | Security | CurrentAddr | Action
-----+-----+-----+
fa1 | Enabled ( 10) |0 | Discard
```

---

## 24. Protocol VLAN

### vlan protocol-vlan group (Global)

**Syntax**

```
vlan protocol-vlan group <1-8> frame-type
(ethernet_ii|llc_other|snap_1042) protocol-value VALUE
no vlan protocol-vlan group <1-8>
```

**Parameter**

<1-8>	Specify protocol vlan group to configure
(ethernet_ii llc_other snap_1042)	Specify protocol based frame type
VALUE	Specify protocol value to configure

**Default**

no protocol vlan group are configured

**Mode**

Global Configuration

**Usage**

Use the **vlan protocol-vlan group** Global Configuration mode command to add protocol vlan group with specified proto type and value.  
Use the **no** form of this command to remove protocol vlan group setting.  
You can verify your setting by entering the **show vlan protocol-vlan** Privileged EXEC command

**Example**

The following example shows how to configure protocol vlan group:

```
Switch(config)# vlan protocol-vlan group 1 frame-type ethernet_ii
protocol-value 0x806
Switch(config)# vlan protocol-vlan group 2 frame-type llc_other protocol-
value 0x800
```

Switch# show vlan protocol-vlan

Group ID	Status	Type	value
1	Enabled	Ethernet	0x0806
2	Enabled	LLC other	0x0800
3	Disabled	--	--
4	Disabled	--	--
5	Disabled	--	--
6	Disabled	--	--
7	Disabled	--	--
8	Disabled	--	--



## vlan protocol-vlan group (Interface)

---

### Syntax

```
vlan protocol-vlan group <1-8> vlan <1-4094>
no vlan protocol-vlan group <1-8>
```

---

### Parameter

<1-8>	Specify protocol vlan group to binding
<1-4094>	Specifies the Proto VLAN ID to configure.

---

### Default

In default all group are not binding to any interface.

---

### Mode

Interface configuration

---

### Usage

Use the **vlan protocol-vlan binding** Interface Configuration mode command to binding protocol VLAN Group on specified interfaces,  
Use the **no** form of this command to cancel protocol VLAN Group Binding.  
You can verify your setting by entering the **show vlan protocol-vlan interfaces IF\_PORTS Privileged EXEC** command

---

### Example

The following example how to configure Protocol VLAN function on specified interfaces..

```
Switch(config)# interface fa1
Switch(config-if)# vlan protocol-vlan group 1 vlan 2
Switch(config-if)# vlan protocol-vlan group 2 vlan 3
Switch# show vlan protocol-vlan interfaces fa1
Port fa1 :
  Group 1
    Status   : Enabled
    VLAN ID : 2
  Group 2
    Status   : Enabled
    VLAN ID : 3
  Group 3
    Status   : Disabled
  Group 4
    Status   : Disabled
  Group 5
    Status   : Disabled
  Group 6
    Status   : Disabled
  Group 7
    Status   : Disabled
  Group 8
    Status   : Disabled
```

---



## show vlan protocol-vlan

---

### Syntax

**show vlan protocol-vlan [group <1-8>]**

---

### Parameter

<1-8>      Specify protocol vlan group to display

---

---

### Default

N/A

---

---

### Mode

Privileged EXEC

---

---

### Usage

Use the **show vlan proto-vlan** command in EXEC mode to display Proto VLAN group configuration

---

### Example

The following example how to display Proto VLAN group configuration

Switch# **show vlan protocol-vlan**

Group ID	Status	Type	value
1	Enabled	Ethernet	0x0806
2	Enabled	LLC other	0x0800
3	Disabled	--	--
4	Disabled	--	--
5	Disabled	--	--
6	Disabled	--	--
7	Disabled	--	--
8	Disabled	--	--

---

## show vlan protocol-vlan interfaces

---

### Syntax

**show vlan protocol-vlan interfaces IF\_PORTS**

---

### Parameter

IF\_PORTS      Specify interfaces protocol vlan to display

---

---

### Default

N/A

---

---

### Mode

Privileged EXEC



**Usage**

Use the **show vlan protocol-vlan interface** command in EXEC mode to display the Protocol VLAN interfaces setting

**Example**

The following example shows how to display the Protocol VLAN interfaces setting

Switch# **show vlan protocol-vlan interfaces fa1**

Port fa1 :

Group 1

Status : Enabled

VLAN ID : 2

Group 2

Status : Enabled

VLAN ID : 3

Group 3

Status : Disabled

Group 4

Status : Disabled

Group 5

Status : Disabled

Group 6

Status : Disabled

Group 7

Status : Disabled

Group 8

Status : Disabled

## 25. QoS

### **qos**

**Syntax**

**qos**

**no qos**

**Default**

Default qos is disabled.

**Mode**

Global Configuration

**Usage**

Use “**qos**” command to enable quality of service which according to basic trust type to assign queue for packets, and packets with higher priority are able to send first.

Use no form of this command to disable quality of service.



---

**Example**

This example shows how to change qos to basic mode.

```
Switch(config) # qos basic
```

This example shows how to check current qos mode.

```
Switch# show qos
```

```
QoS Mode: basic
```

```
Basic trust: cos
```

---

**qos cos**

---

**Syntax**

**qos cos <0-7>**

---

**Parameter**

**cos <0-7>** Specify the CoS value for the interface.

---

---

**Default**

Default CoS value for interface is 0.

---

**Mode**

Interface Configuration

---

**Usage**

Sometimes, there is no qos information in the packets, such as CoS, DSCP, IP Precedence. But we still can give the priority for packets by configuring the interface default cos value. If there is no qos information in the packets, the device will use this default cos value and find the cos-queue map to get the final destination queue.

Use “**qos cos**” command to assign port default cos value.

---

**Example**

This example shows how to configure default cos value 7 on interface fa1.

```
Switch(config) # interface GigabitEthernet 1
Switch(config-if) # qos cos 7
Switch(config-if) # end
Switch# show qos interface GigabitEthernet 1
  Port | CoS | Trust State | Remark Cos | Remark DSCP | Remark IP Prec
  -----+-----+-----+-----+-----+-----+
    g1 |   7 |       enabled |      disabled |      disabled |
```

---

**qos map**

---

**Syntax**

**qos map (cos-queue | dscp-queue | precedence-queue) SEQUENCE to <1-8>**

**qos map (queue-cos | queue-precedence) SEQUENCE to <0-7>**

**qos map queue-dscp SEQUENCE to <0-63>**

---

**Parameter**

**cos-queue** Configure or show CoS to queue map

**dscp-queue** Configure or show DSCP to queue map

**precedence-queue** Configure or show IP Precedence to queue map.

**queue-cos** Configure or show queue to CoS map

---



<b>queue-dscp</b>	Configure or show queue to DSCP map
<b>queue-precedence</b>	Configure or show queue to IP Precedence map
SEQUENCE	Specify the cos, dscp, precedence or queue with one or multiple values.
<1-8>	Specify the queue id
<0-7>	Specify the cos or precedence values
<0-63>	Specify the dscp values

## Default

The default values of cos-queue are showing in the following table.

CoS	Queue ID
0	2
1	1
2	3
3	4
4	5
5	6
6	7
7	8

The default values of dscp-queue are showing in the following table.

DSCP	Queue ID
0~7	1
8~15	2
16~23	3
24~31	4
32~39	5
40~47	6
48~55	7
56~63	8

The default values of ip precedence are showing in the following table.

IP Precedence	Queue ID
0	1
1	2
2	3
3	4
4	5
5	6
6	7
7	8

The default values of queue-cos are showing in the following table.

Queue ID	CoS
1	1
2	0
3	2
4	3
5	4
6	5



7	6
8	7

The default values of queue-dscp are showing in the following table.

Queue ID	DSCP
1	0
2	8
3	16
4	24
5	32
6	40
7	48
8	56

The default values of queue-precedence are showing in the following table.

Queue ID	IP Precedence
1	0
2	1
3	2
4	3
5	4
6	5
7	6
8	7

---

## Mode

### Global Configuration

---

## Usage

According to different trust type, packets will be assigned to different queue based on the specific qos map. For example, if the trust type is trust cos, the device will get the cos value in packet and reference the cos-queue mapping to assign the correct queue.

The queue to cos, dscp or precedence maps are used by remarking function. If the port remarking feature is enabled, the remarking function will reference these 3 tables to remark packets.

---

## Example

This example shows how to map cos 6 and 7 to queue 1.

```
Switch(config)# qos map cos-queue 6 7 to 1 Switch#
show qos map cos-queue
CoS to Queue mappings
  COS   0   1   2   3   4   5   6   7
-----
  Queue  2   1   3   4   5   6   1   1
```

This example shows how to map queue 4 and 5 to cos 7.

```
Switch(config)# qos map queue-cos 4 5 to 7
Switch# show qos map queue-cos
Queue to CoS mappings
```

---



Queue	1	2	3	4	5	6	7	8
<hr/>								
-- CoS1	0	2	7	7	5	6	7	

---

## qos queue

### Syntax

**qos queue strict-priority-num <0-8>**

**qos queue weight SEQUENCE**

**show qos queueing**

### Parameter

**strict-priority-num <0-8>** Specify the strict priority queue number

**weight SEQUENCE** Specify the non-strict priority queue weight value. The valid queue weight value is from 1 to 127.

### Default

Default strict priority queue number is 8, it means all queues are strict priority queue.

The default queue weight for each queue is shown in following table.

Queue ID	Queue Weight
1	1
2	2
3	3
4	4
5	5
6	9
7	13
8	15

### Mode

Global Configuration

### Usage

The device support total 8 queues for QoS queueing. It is able to set the queue to be strict priority queue or weighted queue to prevent starvation. The queue with higher id value has higher priority.

First, you need to decide how many strict priority queue you need. The strict priority queue will always occupy the higher priority queue. For example, if you specify the strict priority number to be 2, then the queue 7 and 8 will be the strict priority queues and the others are weighted queues.

After you setup the number of strict priority queue, you need to setup the weight for the weighted queues by using “qos queue weight” command. And the bandwidth will shared by the weight you configured between these weighted queues.



**Example**

This example shows how to setup device with 3 strict priority queues and give other weighted queues with weight 5, 10, 15, 20, 25.

```
Switch(config)# qos queue strict-priority-num 3
Switch(config)# qos queue weight 5 10 15 20 25
Switch# show qos queueing
qid-weights      Ef - Priority
1 -      5       dis- N/A
2 -     10       dis- N/A
3 -     15       dis- N/A
4 -     20       dis- N/A
5 -     25       dis- N/A
6 -   N/A       ena- 6
7 -   N/A       ena- 7
8 -   N/A       ena- 8
```

---

## qos remark

**Syntax**

**qos remark (cos | dscp | precedence)**  
**no qos remark (cos | dscp | precedence)**

**Parameter**

<b>cos</b>	Enable/Disable cos remarking.
<b>dscp</b>	Enable/Disable dscp remarking.
<b>precedence</b>	Enable/Disable precedence remarking.

---

**Default**

Default CoS remarking is disabled. Default DSCP remarking is disabled. Default IP Precedence remarking is disabled.

**Mode**

Interface Configuration

**Usage**

QoS remarking feature allow you to change priority information in packets based on egress queue. For example, you want all packets egress from interface fa1 queue 1 to remark the cos value to be 5 for next tier of device, you can enable the cos remarking feature on fa1 and configure the queue-cos map for queue 1 map to cos 5.

Use “**qos remark**” command to enable remarking feature on specific type. And use “**no qow remark**” command to disable it.

**Example**

This example shows how to enable remarking features on interface fa1.

```
Switch(config)# interface GigabitEthernet 1
Switch(config-if)# qos remark cos
Switch(config-if)# qos remark dscp
Switch(config-if)# qos remark precedence
Switch(config-if)# end
Switch# show qos interface GigabitEthernet 1
  Port | CoS | Trust State | Remark Cos | Remark DSCP | Remark IP Prec
  -----+---+-----+-----+-----+-----+
    g1 | 0 | enabled | enabled | enabled | enabled |
```

---



## **qos trust**

### Syntax

**qos trust (cos | cos-dscp | dscp | precedence)**

### Parameter

<b>cos</b>	Specify the device to trust CoS
<b>cos-dscp</b>	Specify the device to trust DSCP for IP packets, and trust CoS for non-IP packets.
<b>dscp</b>	Specify the device to trust DSCP
<b>precedence</b>	Specify the device to trust IP Precedence

### Default

Default QoS trust type is cos.

### Mode

Global Configuration

### Usage

In QoS basic mode, there are 4 trust types for device to judge the appropriate queue of the packets. This command is able to switch between these trust types.

#### **CoS:**

IEEE 802.1p defined 3bits priority value in vlan tag. Trust this value in packets and assign queue according to cos-queue map.

#### **DSCP:**

IETF RFC2474 defined 6bits priority value in IP packet (highest 6bits in ToS field). Trust this value in packets and assign queue according to dscp-queue map.

#### **IP Precedence:**

The highest 3bits priority value in IP packet ToS field. Trust this value in packets and assign queue according to precedence-queue map.

#### **CoS-DSCP:**

Trust DSCP for IP packets and assign queue according to dscp-queue map. Trust CoS for non-IP packets and assign queue according to cos-queue map.

### Example

This example shows how to change qos basic mode trust types.

```
Switch(config)# qos trust cos
Switch(config)# qos trust cos-dscp
Switch(config)# qos trust dscp
Switch(config)# qos trust precedence
```

This example shows how to check current qos trust type.

```
Switch# show qos
QoS Mode: basic
Basic trust: ip-precedence
```

## **qos trust (Interface)**

### Syntax

**qos trust**



**no qos trust**



**Parameter**

**Default**

Default interface qos trust state is enabled.

**Mode**

Interface Configuration

**Usage**

After QoS function is enabled in basic mode, the device also support per interface enable/disable the qos function. If the trust state on interface is enabled, all ingress packets of this interface will remap according to the trust type and the qos maps. Otherwise, all ingress packets will assign to queue 1.

Use “**qos trust**” to enable trust state on interface and use “**no qos trust**” to disable trust state on interface.

**Example**

This example shows how to disable qos trust state on interface fa1.

```
Switch(config)# interface GigabitEthernet 1
Switch(config-if)# no qos trust
Switch(config-if)# end
Switch# show qos interface GigabitEthernet 1
  Port | CoS | Trust State | Remark Cos | Remark DSCP | Remark IP Prec
-----+-----+-----+-----+-----+
    gi1 |   0 |     disabled |     disabled |     disabled |     disabled |
```

## show qos

**Syntax**

**show qos**

**Parameter**

**Default**

No default value for this command.

**Mode**

Privileged EXEC

**Usage**

Use “**show qos**” command to show qos state and trust type.

**Example**

This example shows how to check current qos mode.

```
Switch# show qos
QoS Mode: basic
Basic trust: cos
```



## show qos interface

### Syntax

**show qos interface *IF\_PORTS***

### Parameter

***IF\_PORTS*** Select port to show qos configurations.

### Default

No default value for this command.

### Mode

Privileged EXEC

### Usage

Use “**show qos interfaces**” command to show port default cos ,remarking state and remarking type state informations.

### Example

This example shows how to show qos configurations on interface fa1.

```
Switch# show qos interface GigabitEthernet 1
      Port | CoS    | Trust State | Remark Cos | Remark DSCP | Remark IP Prec
-----+-----+-----+-----+-----+-----+
      gi1 |    7   |     enabled  |    disabled |    disabled |    disabled |
```

## show qos map

### Syntax

**show qos map [(cos-queue | dscp-queue | precedence-queue | queue-cos | queue-dscp | queue-precedence)]**

### Parameter

**cos-queue** Show CoS to queue map.

**dscp-queue** Show DSCP to queue map.

**precedence-queue** Show IP Precedence to queue

**map. queue-cos** Show queue to CoS map.

**queue-dscp** Show queue to DSCP map.

**queue-precedence** Show queue to IP Precedence map.

### Default

No default value for this command.

### Mode

Privileged EXEC

### Usage

Use “**show qos map**” command to show all kinds of mapping for qos remapping and remarking features.



---

**Example**

This example shows how to show all qos maps.  
Switch(config)# **show qos map**

```
CoS to Queue mappings
  COS   0   1   2   3   4   5   6   7
-----
  Queue  2   1   3   4   5   6   7   8

DSCP to Queue mappings
d1: d2  0   1   2   3   4   5   6   7   8   9
-----
  0:      1   1   1   1   1   1   1   1   2   2
  1:      2   2   2   2   2   2   3   3   3   3
  2:      3   3   3   3   4   4   4   4   4   4
  3:      4   4   5   5   5   5   5   5   5   5
  4:      6   6   6   6   6   6   6   6   7   7
  5:      7   7   7   7   7   7   8   8   8   8
  6:      8   8   8   8

IP Precedence to Queue mappings
  IP Precedence  0   1   2   3   4   5   6   7
-----
  Queue    1   2   3   4   5   6   7   8

Queue to CoS mappings
  Queue   1   2   3   4   5   6   7   8
-----
  CoS     1   0   2   3   4   5   6   7

Queue to DSCP mappings
  Queue   1   2   3   4   5   6   7   8
-----
  DSCP    0   8  16  24  32  40  48  56

Queue to IP Precedence mappings
  Queue   1   2   3   4   5   6   7   8
-----
  ipprec  0   1   2   3   4   5   6   7
```

---

## show qos queueing

---

**Syntax**

**show qos queueing**

---

**Parameter**

---

**Default**

No default value for this command.

---

**Mode**

Privileged EXEC

---

**Usage**

Use “**show qos queueing**” command to show qos queueing information.



**Example**

This example shows how to check current qos queueing information.

```
Switch# show qos queueing
qid-weights      Ef - Priority
1 -   3          dis- N/A
2 -   5          dis- N/A
3 - N/A          ena- 3
4 - N/A          ena- 4
5 - N/A          ena- 5
6 - N/A          ena- 6
7 - N/A          ena- 7
8 - N/A          ena- 8
```

---

## 26. Rate Limit

### rate limit egress

**Syntax**

```
rate-limit egress <16-1000000>
no rate-limit egress
```

**Parameter**

<16-1000000> Specify the committed information rate.

---

**Default**

Default rate limit is disabled.

---

**Mode**

Interface configuration

---

**Usage**

Use the “**rate-limit egress**” command to configure the egress port shaper.

Use the **no** form of this command to disable the shaper.

You can verify your setting by entering the **show running-config interfaces** command.

---

**Example**

The following example show how to configure ingress port rate limit and egress port shaper.

```
Switch(config)# interfaces g1
Switch(config-if)# rate-limit egress 2048
Switch# show running-config interfaces g1
interface g1
    rate-limit egress 2048
```

---

### rate limit egress queue



**Syntax**

**rate-limit egress queue <1-8> <16-1000000>**  
**no rate-limit egress queue <1-8>**

**Parameter**

<b>&lt;1-8&gt;</b>	Specify the egress shaper queue number
<b>&lt;16-1000000&gt;</b>	Specify the queue rate.

**Default**

Default queue rate limit is disabled.

**Mode**

Interface configuration

**Usage**

Use the “**rate-limit egress queue**” command to configure the egress queue shaper.

Use the **no** form of this command to disable the queue shaper.

You can verify your setting by entering the **show running-config interfaces** command.

**Example**

The following example show how to configure ingress port rate limit and egress port shaper.

```
Switch(config)# interfaces g1
Switch(config-if)# rate-limit egress queue 3 2048
Switch# show running-config interfaces g1
interface g1
  rate-limit egress queue 3 2048
```

## rate limit ingress

**Syntax**

**rate-limit ingress <16-1000000>**  
**no rate-limit ingress**

**Parameter**

<b>&lt;16-1000000&gt;</b>	Specify the ingress limit rate
<b>&lt;1-8&gt;</b>	Specify the egress shaper queue number

**Default**

Rate limiting is disabled.

**Mode**

Interface configuration

**Usage**

Use the “**rate-limit ingress**” command to limit the incoming traffic rate on a port.



Use the **no** form of this command to disable the rate limit.

You can verify your setting by entering the **show running-config interfaces** command

---

#### Example

The following example show how to configure ingress port rate limit.

```
Switch(config)# interfaces g1
Switch(config-if)# rate-limit ingress 128
Switch# show running-config interfaces g1
interface g1
  rate-limit ingress 128
```

---

## 27. RMON

### rmon event

---

#### Syntax

```
rmon event <1-65535> [log] [trap COMMUNITY] [description DESCRIPTION] [owner NAME]
no rmon event <1-65535>
```

---

#### Parameter

<b>&lt;1-65535&gt;</b>	Specify event index to create or modify.
<b>[log]</b>	(Optional)Specify to show syslog.
<b>[trap COMMUNITY]</b>	(Optional)Specify SNMP community to show SNMP trap.
<b>[description DESCRIPTION]</b>	(Optional)Specify description of event
<b>[owner NAME]</b>	(Optional)Specify owner of event.

---

#### Default

No default is defined.

---

#### Mode

Global Configuration

---

#### Usage

Use the **rmon event** command to add or modify a RMON evnet entry.

Use the **no** form of this command to delete.

You can verify settings by the **show rmon event** command.

---

#### Example

The example shows how to add RMON event entry with log and trap action and then modify it action to log only.

```
switch(config)# rmon event 1 log trap public description test owner admin
switch(config)# show rmon event 1
```

---



```
Rmon Event Index      1
Rmon Event Type      : Log and
Trap Rmon Event Community :
public Rmon Event Description :
test
Rmon Event Last Sent :
Rmon Event Owner     : admin
```

```
switch(config)# rmon event 1 log description test owner admin
switch(config)# show rmon event 1
Rmon Event Index      1
Rmon Event Type      : Log
Rmon Event Community :
public Rmon Event
Description : test Rmon Event
Last Sent :
Rmon Event Owner     : admin
```

---

## rmon alarm

**Syntax**

```
rmon alarm <1-65535> interface IF_PORT (drop-events|octets|pkts|broadcast-pkts|
multicast-pkts|crc-align-errors|undersize-pkts|oversize-pkts|fragments|jabbers|collisions|
|pkts64octets|pkts65to127octets|pkts128to255octets|pkts256to511octets|pkts512to1023octets|
|pkts1024to1518octets) <1-2147483647> (absolute|delta) rising <0-2147483647> <0-65535>
falling <0-2147483647> <0-65535> startup (rising|rising-falling|falling) [owner NAME]
no rmon alarm <1-65535>
```

<b>Parameter</b>	<b>&lt;1-65535&gt;</b>	Specify alarm index to create or modify
	<b>IF_PORT</b>	Specify the interface to sample
	<b>(variable)</b>	Specify a mib object to sample
	<b>&lt;1-2147483647&gt;</b>	Specify the time in seconds that the alarm monitors the MIB variable.
	<b>(absolute delta)</b>	Specify absolute to compare sample counter absolutely. Specify delta to compare delta counter between samples
	<b>&lt;0-2147483647&gt;</b>	Specify a number which the alarm trigger rising event
	<b>&lt;0-65535&gt;</b>	Specify event index when the rising threshold exceeds.
	<b>&lt;0-2147483647&gt;</b>	Specify a number which the alarm trigger falling event
	<b>&lt;0-65535&gt;</b>	Specify event index when the falling threshold exceeds.
	<b>(rising rising-falling falling)</b>	Specify only to how rising or falling startup event. Or show either rising or falling startup event.
	<b>[owner NAME]</b>	(Optional) Specify owner of alarm.



<b>Default</b>	No default is defined.
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>rmon alarm</b> command to add or modify a RMON alarm entry. Before add alarm entry, at least one event entry must be added. Use the <b>no</b> form of this command to delete. You can verify settings by the <b>show rmon alarm</b> command.</p>
<b>Example</b>	<p>The example shows how to add RMON alarm entry that sample interface fal packets delta count every 300 seconds. Trigger event index 1 if over than rising threshold 10000, trigger event index 2 if lower than falling threshold.</p> <pre>switch(config)# rmon event 1 log switch(config)# rmon event 2 log  Switch(config)# rmon alarm 1 interface gi1 pkts 300 delta rising 10000 1 falling 100 1 startup rising-falling owner admin  Rmon Alarm Index          1 Rmon Alarm Sample Interval 300 Rmon Alarm Sample Interface : gi1 Rmon Alarm Sample Variable : Pkts Rmon Alarm Sample Type    : delta Rmon Alarm Type           : Rising or Falling Rmon Alarm Rising Threshold : 10000 Rmon Alarm Rising Event        1 Rmon Alarm Falling Threshold 100 Rmon Alarm Falling Event   1 Rmon Alarm Owner          : admin</pre>

## rmon history

<b>Syntax</b>	<b>rmon history &lt;1-65535&gt; interface IF_PORT [buckets &lt;1-65535&gt;]</b> <b>[interval &lt;1-3600&gt;] [owner NAME]</b> <b>no rmon history &lt;1-65535&gt;</b>										
<b>Parameter</b>	<table border="0"> <tr> <td><b>&lt;1-65535&gt;</b></td> <td>Specify history index to create or modify.</td> </tr> <tr> <td><b>IF_PORT</b></td> <td>Specify the interface to sample</td> </tr> <tr> <td><b>[bucket &lt;1-65535&gt;]</b></td> <td>(Optional) Specify the maximum number of buckets.</td> </tr> <tr> <td><b>[interval &lt;&gt;1-3600]</b></td> <td>(Optional) Specify time interval for each sample</td> </tr> <tr> <td><b>[owner NAME]</b></td> <td>(Optional)Specify owner of history</td> </tr> </table>	<b>&lt;1-65535&gt;</b>	Specify history index to create or modify.	<b>IF_PORT</b>	Specify the interface to sample	<b>[bucket &lt;1-65535&gt;]</b>	(Optional) Specify the maximum number of buckets.	<b>[interval &lt;&gt;1-3600]</b>	(Optional) Specify time interval for each sample	<b>[owner NAME]</b>	(Optional)Specify owner of history
<b>&lt;1-65535&gt;</b>	Specify history index to create or modify.										
<b>IF_PORT</b>	Specify the interface to sample										
<b>[bucket &lt;1-65535&gt;]</b>	(Optional) Specify the maximum number of buckets.										
<b>[interval &lt;&gt;1-3600]</b>	(Optional) Specify time interval for each sample										
<b>[owner NAME]</b>	(Optional)Specify owner of history										



<b>Default</b>	No default is defined.
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>rmon history</b> command to add or modify a RMON history entry. Use the <b>no</b> form of this command to delete. You can verify settings by the <b>show rmon history</b> command.</p>
<b>Example</b>	<p>The example shows how to add RMON history entry that monitor interface gi1 every 60 seconds and then modify it to monitor every 30 seconds.</p> <pre>switch(config)# rmon history 1 interface gi1 interval 60 owner admin switch(config)# show rmon history 1 Rmon History Index      1 Rmon Collection Interface: gi1 Rmon History Bucket     50 Rmon history Interval   60 Rmon History Owner      : admin  switch(config)# rmon history 1 interface gi1 interval 30 owner admin switch(config)# show rmon history 1 Rmon History Index      1 Rmon Collection Interface: gi1 Rmon History Bucket     50 Rmon history Interval   30 Rmon History Owner      : admin</pre>

## clear rmon interfaces statistics

<b>Syntax</b>	<b>clear rmon interfaces IF_PORTS statistics</b>
<b>Parameter</b>	<b>IF_PORTS</b> specifies ports to clear
<b>Default</b>	No default is defined
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	<p>Use the <b>clear rmon interfaces statistics</b> command to clear RMON etherStat statistics those are recorded on interface. You can verify results by the <b>show rmon interface statistics</b> command.</p>



**Example**

The example shows how to clear RMON etherStat statistics on interface gi1.

```
switch# clear rmon interfaces gi1 statistics
switch# show rmon interfaces gi1 statistics
==== Port gi1 =====
etherStatsDropEvents      0
etherStatsOctets          0
etherStatsPkts            0
etherStatsBroadcastPkts   0
etherStatsMulticastPkts   0
etherStatsCRCAlignErrors  0
etherStatsUnderSizePkts   0
etherStatsOverSizePkts   0
etherStatsFragments       0
etherStatsJabbers         0
etherStatsCollisions      0
etherStatsPkts64Octets    0
etherStatsPkts65to127Octets 0
etherStatsPkts128to255Octets 0
etherStatsPkts256to511Octets 0
etherStatsPkts512to1023Octets 0
etherStatsPkts1024to1518Octets 0
```

---

## **show rmon interfaces statistics**

**Syntax**

**show rmon interfaces IF\_PORTS statistics**

**Parameter**

**IF\_PORTS** specifies ports to show

**Default**

No default is defined

**Mode**

Privileged EXEC

**Usage**

Use the **show rmon interfaces statistics** command to show RMON etherStat statistics of interface.

**Example**

The example shows how to show RMON etherStat statistics of interface gi1.

```
switch(config)# show rmon interfaces gi1 statistics
==== Port gi1 =====
etherStatsDropEvents      0
etherStatsOctets          : 81882
```

---



etherStatsPkts	578
etherStatsBroadcastPkts	10
etherStatsMulticastPkts	0
etherStatsCRCAlignErrors	0
etherStatsUnderSizePkts	0
etherStatsOverSizePkts	0
etherStatsFragments	0
etherStatsJabbers	0
etherStatsCollisions	0
etherStatsPkts64Octets	355
etherStatsPkts65to127Octets	126
etherStatsPkts128to255Octets	0
etherStatsPkts256to511Octets	42
etherStatsPkts512to1023Octets	55
etherStatsPkts1024to1518Octets	0

---

## show rmon event

---

### Syntax

**show rmon event (<1-65535> | all)**

---

### Parameter

<b>&lt;1-65535&gt;</b>	specifies event index to show
<b>all</b>	Show all existed event

---

---

### Default

No default is defined

---

### Mode

Privileged EXEC

---

### Usage

Use the **show rmon event** command to show existed RMON event entry.

---

### Example

The example shows how to show rmon event entry.

```
switch(config)# rmon event 1 log trap public description test owner admin
switch(config)# show rmon event 1
Rmon Event Index      1
Rmon Event Type      : Log and Trap
Rmon Event Community : public
Rmon Event Description : test
Rmon Event Last Sent :
Rmon Event Owner     : admin
```

---



## **show rmon event log**

<b>Syntax</b>	<b>show rmon event &lt;1-65535&gt; log</b>
<b>Parameter</b>	<b>&lt;1-65535&gt;</b> specifies event index to show event log
<b>Default</b>	No entry and log is exist
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Use the <b>show rmon event log</b> command to show log triggered by RMON alarm.
<b>Example</b>	The example shows how to show rmon event log.  switch(config)# <b>show rmon event 1 log</b> =====
	Index 1 Alarm Index 1 Action : Startup Falling Time : (32918334) 3 days, 19:26:23.34 Description : fa1.Pkts=0 <= 100
<b>show rmon alarm</b>	
<b>Syntax</b>	<b>show rmon alarm (&lt;1-65535&gt;   all)</b>
<b>Parameter</b>	<b>&lt;1-65535&gt;</b> specifies alarm index to show <b>all</b> Show all existed alarm
<b>Default</b>	No alarm is defined
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Use the <b>show rmon alarm</b> command to show existed RMON alarm entry.



**Example**

The example shows how to show rmon alarm entry.

```
Switch(config)# rmon alarm 1 interface gi1 pkts 300 delta rising 10000 1
falling 100 1 startup rising-falling owner admin
```

```
Rmon Alarm Index      1
Rmon Alarm Sample Interval 300
Rmon Alarm Sample Interface : gi1
Rmon Alarm Sample Variable : Pkts
Rmon Alarm Sample Type   : delta
Rmon Alarm Type        : Rising or Falling
Rmon Alarm Rising Threshold : 10000 Rmon
Alarm Rising Event     1
Rmon Alarm Falling Threshold 100
Rmon Alarm Falling Event 1
Rmon Alarm Owner       : admin
```

---

## show rmon history

**Syntax**

```
show rmon history (<1-65535> | all)
```

**Parameter**

<b>&lt;1-65535&gt;</b>	specifies history index to show
<b>all</b>	Show all existed history

---

**Default**

No history is defined

**Mode**

Privileged EXEC

**Usage**

Use the **show rmon history** command to show existed RMON history entry.

**Example**

The example shows how to show RMON history entry.

```
switch(config)# rmon history 1 interface gi1 interval 30 owner admin
switch(config)# show rmon history 1
Rmon History Index      1
Rmon Collection Interface: gi1
Rmon History Bucket     50
Rmon history Interval   30
Rmon History Owner      : admin
```

---



## show rmon history statistic

---

### Syntax

**show rmon history <1-65535> statistic**

---

### Parameter

**<1-65535>** specifies history index to show history statistic

---

### Default

No history is defined

---

### Mode

Privileged EXEC

---

### Usage

Use the **show rmon history statistic** command to show statistics that are recorded by RMON history.

---

### Example

The example shows how to show RMON history statistics

```
switch(config)# show rmon history 1 statistics
```

```
=====
```

Sample Index	2
Interval Start	: (32940466) 3 days, 19:30:04.66
DropEvents	0
Octets	: 117226
Pkts	763
BroadcastPkts	9
MulticastPkts	0
CRCAlignErrors	0
UnderSizePkts	0
OverSizePkts	0
Fragments	0
Jabbers	0
Collisions	0
Utilization	1

```
=====
```

```
=====
```

Sample Index	1
Interval Start	: (32939462) 3 days, 19:29:54.62
DropEvents	0
Octets	220
Pkts	3
BroadcastPkts	1
MulticastPkts	0
CRCAlignErrors	0
UnderSizePkts	0
OverSizePkts	0
Fragments	0

```
=====
```



Jabbers	:	0
Collisions	:	0
Utilization	:	0

---

## 28. SNMP

### show snmp

<b>Syntax</b>	<b>show snmp</b>
<b>Parameter</b>	N/A
<b>Default</b>	N/A
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	To show the status of Simple Network Management Protocol (SNMP), use the command <b>show snmp</b> in the Privileged EXEC mode.
<b>Example</b>	The following example shows the SNMP status.  Switch# show snmp SNMP is disabled.

### show snmp community

<b>Syntax</b>	<b>show snmp community</b>
<b>Parameter</b>	N/A
<b>Default</b>	N/A
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	To show the configuration of snmp communities, use the command <b>show snmp community</b> in the Privileged EXEC mode.



**Example**

The following example shows the SNMP communities configuration.

```
Switch# show snmp community
Community Name      Group Name          View
Access
-----
-----
private             all
ro
public             all
rw
Total Entries: 2
```

## show snmp engineid

**Syntax**

**show snmp engineid**

**Parameter**

N/A

**Default**

N/A

**Mode**

Privileged EXEC

**Usage**

To show the SNMPv3 engine IDs defined on the switch, use the command **show snmp engineid** in the Privileged EXEC mode.

**Example**

The following example shows the SNMP engind id information.

```
Switch# show snmp engineid
Local SNMPV3 Engine id: 00036d001122

IP address           Remote SNMP engineID
-----
-----
192.168.1.11        00036D10000A
Total Entries: 1
```

## show snmp group

**Syntax**

**show snmp group**

**Parameter**

N/A



**Default** N/A

**Mode** Privileged EXEC

**Usage** To show the SNMP group configuration on the switch, use the command **show snmp group** in the Privileged EXEC mode.

**Example** The following example shows the SNMP group configuration.

```
Switch# show snmp group
Group Name          Model   Level      ReadView
WriteView           Not
-----
-----
private            v2c     noauth    all
all               ---     auth      all
v3                v3      auth      all
all               all

Total Entries: 2
```

## **show snmp host**

**Syntax** **show snmp host**

**Parameter** N/A

**Default** N/A

**Mode** Privileged EXEC

**Usage** To show the SNMP trap notification recipients defined on the switch, use the command **show snmp host** in the Privileged EXEC mode.

**Example** The following example shows the configuration of SNMP notification recipients on the switch.

```
Switch# show snmp host
Server          Community Name  Notification Version  Notification Type
192.168.1.11    private        v1                  trap
Total Entries: 1
```



## **show snmp trap**

---

**Syntax**           **show snmp trap**

---

**Parameter**       N/A

---

**Default**           N/A

---

**Mode**              Privileged EXEC

---

**Usage**             To show the status of SNMP traps on the switch, use the command **show snmp trap** in the Privileged EXEC mode.

---

**Example**           The following example shows the status of SNMP traps.

```
Switch# show snmp trap
SNMP auth failed trap : Enable
SNMP linkUpDown trap : Enable
SNMP cold-start trap : Enable
SNMP warm-start trap : Enable
```

---

## **show snmp view**

---

**Syntax**           **show snmp view**

---

**Parameter**       N/A

---

**Default**           N/A

---

**Mode**              Privileged EXEC

---

**Usage**             To show the SNMP view defined on the switch, use the command **show snmp view** in the Privileged EXEC mode.

---

**Example**           The following example shows the configuration of SNMP view.

```
Switch# s how snmp view
View Name                                                  Subtree OID
OID Mask                                                  View Type
-----
```

---



all	.1
all	included
private	.1.3.3.1
all	included

Total Entries: 2

---

## show snmp user

**Syntax** **show snmp user**

**Parameter** N/A

**Default** N/A

**Mode** Privileged EXEC

**Usage** To show the SNMP users defined on the switch, use the command **show snmp user** in the Privileged EXEC mode.

**Example** The following example shows the configuration of SNMP user.

```
Switch# show snmp user
Username:          v3
Password:          *****
Privilege Mode:   rw
Access GroupName: v3
Authentication Protocol: md5
Encryption Protocol: none
Access SecLevel:   auth
```

Total Entries: 1

---

## snmp

**Syntax** **snmp**

**Parameter** N/A

**Default** SNMP is disabled by default

**Mode** Global Configuration



---

**Usage**

To enable the SNMP on the switch, use the command **snmp** in the Global Configuration mode. Otherwise, use the **no** form of the command to disable to SNMP.

---

**Example**

The following example enables the SNMP.

```
Switch(config)# snmp
```

---

**snmp community**

---

**Syntax**

```
snmp community community-name [view view-name] (ro|rw)
snmp community community-name group group-name
no snmp community community-name
```

---

**Parameter**

<i>community-name</i>	The SNMP community name. Its maximum length is 20 characters.
<b>view</b> <i>view-name</i>	Specify the SNMP view configured by the command <b>snmp view</b> to define the object available to the community.
<b>ro</b>	Read only access (default)
<b>rw</b>	Writable access
<b>group</b> <i>group-name</i>	Specify the SNMP group configured by the command <b>snmp group</b> to define the object available to the community.

---

**Default**

No SNMP community is configured

---

**Mode**

Global Configuration

---

**Usage**

To define the SNMP community that permit access for SNMP v1 and v2, use the command **snmp community** in the Global Configuration mode.

---

**Example**

The following example defines the SNMP community named *private* with the default view *all*, and the access right is *read-only*.

```
Switch(config)# snmp community private ro
```

---

**snmp engineid**

---

**Syntax**

```
snmp engineid (default|ENGINEID)
```



<b>Parameter</b>	<b>default</b>	Default engine ID generated on the basis of the switch MAC address.
	<i>ENGINEID</i>	Specify SNMP engine ID. The engine ID is the 10 to 64 hexadecimal characters, and the hexadecimal number must be divided by 2.
<b>Default</b>	The default SNMP engine ID on the switch is based on switch MAC address.	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	To define the SNMP engine on the switch, use the command <b>snmp engineid</b> in the Global Configuration mode.	
<b>Example</b>	The following example configure the switch SNMP engine ID  <code>Switch(config)# snmp engineid 00036D001122</code>	
<b>snmp engineid rremote</b>		
<b>Syntax</b>	<b>snmp engineid remote (ip-addr ipv6-addr) ENGINEID</b> <b>no snmp engineid remote (ip-addr ipv6-addr)</b>	
<b>Parameter</b>	<i>ENGINEID</i>	Specify SNMP engine ID. The engine ID is a 10 to 64 hexadecimal characters, and the hexadecimal number must be divided by 2.
	<i>ip-addr</i>	IP address of the remote host
	<i>ipv6-addr</i>	IPv6 address of the remote host
<b>Default</b>	N/A	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	To define the remote host for SNMP engine, use the command <b>snmp engineid remote</b> in the Global Configuration mode; and use the <b>no</b> form of the command to delete the remote host from the SNMP engine.	
<b>Example</b>	The following example adds the remote <i>192.168.1.11</i> into SNMP engine  <code>Switch(config)# snmp engineid remote 192.168.1.11 00036D10000A</code>	
<b>snmp group</b>		



**Syntax**

```
snmp group group-name (1|2c|3) (noauth|auth|priv) read-view read-view
write-view write-view [notify-view notify-view]
no snmp group group-name security-mode version (1|2c|3)
```

**Parameter**

<i>group-name</i>	Specify SNMP group name, and the maximum length is 30 characters.
<b>(1 2c 3)</b>	Specify the SNMP version.
<b>noauth</b>	Specify that no packet authentication is performed.
<b>auth</b>	Specify that no packet authentication without encryption is performed. It is applicable only to the SNMPv3 security mode.
<b>priv</b>	Specify that no packet authentication with encryption is performed. It is applicable only to the SNMPv3 security mode.
<b>read-view</b> <i>read-view</i>	Set the view name that enables configuring the agent, and its maximum length is 30 characters.
<b>write-view</b> <i>write-view</i>	Set the view name that enables viewing only, and its maximum length is 30 characters.
<b>notify-view</b> <i>notify-view</i>	Sets the view name that sends only traps with contents that is included in SNMP view selected for notification. The maximum length is 30 characters.

**Default**

No group entry is existed.

**Mode**

Global Configuration

**Usage**

To define the SNMP group, use the command **snmp group** in the Glocal Configuration mode, and use the **no** form of the command to delete the configuration.

SNMP group configuration is used in the command **snmp use** to map SNMP users to the SNMP group. These users would be automatically mapped to the SNMP views defined in this command.

The security level for SNMP v1 or v2 is always **noauth**.

**Example**

The following example adds SNMPv3 group

```
Switch(config)# snmp group v3 version 3 auth read-view all
write-view all notify-view all
```

**snmp host**



# Command Line Interface

## User Guide

---

### Syntax

```
snmp host (ip-addr|ipv6-addr|hostname) [traps|informs] [version (1|2c)]  
    community-name [udp-port udp-port] [timeout timeout] [retries retries]
```

---



---

**snmp host (*ip-addr|ipv6-addr|hostname*) [**traps|informs**] **version 3****  
**[*auth|noauth|priv*] *community-name* [**udp-port udp-port**] [**timeout**  
**timeout**] [**retries retries**]**  
**no snmp host (*ip-addr|ipv6-addr|hostname*) [**traps|informs**]  
**[version (1|2c|3)]****

---

<i>ip-addr</i>	The IP address of recipient.
<i>ipv6-addr</i>	The IPv6 address of recipient.
<i>hostname</i>	The host name of recipient.
<b>traps</b>	Send SNMP traps to the host. It is the default action.
<b>informs</b>	Send SNMP informs to the host.
<b>version (1 2c 3)</b>	Specify the SNMP version.
<b>noauth</b>	Specify that no packet authentication is performed. It is applicable only to the SNMPv3 security mode.
<b>auth</b>	Specify that no packet authentication without encryption is performed. It is applicable only to the SNMPv3 security mode.
<b>priv</b>	Specify that no packet authentication with encryption is performed. It is applicable only to the SNMPv3 security mode.
<i>community-name</i>	The SNMP community sent with the notification.
<b>udp-port <i>udp-port</i></b>	Specify the UDP port number.
<b>timeout <i>timeout</i></b>	Specify the SNMP informs timeout
<b>retries <i>retries</i></b>	Specify the retry counter of the SNMP informs.

---

#### Default

No SNMP host is configured.  
The default SNMP version for the command is SNMPv1.

#### Mode

Global Configuration

#### Usage

To configure the hosts to receive SNMP notifications, use the command **snmp host** in the Global Configuration mode; and use the **no** form of the command to delete the configuration.

#### Example

The following example adds the recipient *192.168.1.11* for the SNMP traps notification.

---

```
Switch(config)# snmp host 192.168.1.11 private
```

---

## snmp trap

#### Syntax

**snmp trap (*auth|cold-start|linkUpDown|port-security|warm-start*)**  
**no snmp trap (*auth|cold-start|linkUpDown|port-security|warm-start*)**

<b>auth</b>	Enable the SNMP authentication failure trap.
<b>cold-start</b>	Enable the SNMP cold start-up failure trap.
<b>linkUpDown</b>	Enable the SNMP link up and down failure trap.

---



<b>port-security</b>	Enable the SNMP port security trap.
<b>warm-start</b>	Enable the SNMP warm start-up failure trap.

---

**Default** All the SNMP traps are enabled.

---

**Mode** Global Configuration

---

**Usage** To send the SNMP traps, use the command `snmp trap` in the Global Configuration mode; and use the no form of the command to disable the SNMP traps.

---

**Example** The following example disables and enables the SNMP link up and down traps individually.

```
Switch(config)# no snmp trap linkUpDown
Switch(config)# snmp trap linkUpDown
```

---

## snmp user

---

### Syntax

```
snmp user username group-name [auth (md5|sha) AUTHPASSWD]
snmp user username group-name auth (md5|sha) AUTHPASSWD
priv PRIVPASSWD
no snmp user username
```

---

<i>username</i>	Specify the SNMP user name on the host that connects to the SNMP agent. The max character is 30 characters. For the SNMP v1 or v2c, the user name must match the community name by the command <code>snmp host</code> .
-----------------	---

---

<i>group-name</i>	Specify the SNMP group to which the SNMP user belongs. The SNMP group should be SNMPv3 and configured by the command <code>snmp group</code> .
-------------------	--

---

<b>auth (md5 )</b>	Specify the HMAC-MD5-96 authentication protocol as the user authentication.
--------------------	---

---

<b>auth (sha )</b>	Specify the HMAC-SHA-96 authentication protocol as the user authentication.
--------------------	---

---

<i>AUTHPASSWD</i>	The password for authentication and the range of length is from 8 to 32 characters.
-------------------	---

---

<b>Priv</b> <i>PRIVPASSWD</i>	The private password for the privacy key, and the range of length is from 8 to 64 characters.
-------------------------------	---

---



---

**Default** N/A



<b>Mode</b>	Global Configuration
<b>Usage</b>	To define a SNMP user, use the command <b>snmp user</b> in the Global Configuration mode; and use the <b>no</b> form to delete the SNMP user.
<b>Example</b>	The following example adds SNMP user <i>v3</i> into the group <i>v3</i> by the MD5 authentication.
<pre>Switch(config)# snmp user v3 v3 auth md5 12345678</pre>	
<b>snmp view</b>	
<b>Syntax</b>	<b>snmp view <i>view-name</i> subtree <i>oid-tree</i> oid-mask (all oid-mask) viewtype (included excluded)</b> <b>no snmp view <i>view-name</i> subtree (all oid-tree)</b>
<i>view-name</i>	The SNMP view name. Its maximum length is 30 characters.
<b>subtree <i>oid-tree</i></b>	Specify the ASN.1 subtree object identifier (OID) to be included or excluded from the SNMP view.
<b>oid-mask (all oid-mask)</b>	Specify the OID family mask. It is used to define a family of view subtrees. For example, OID mask FA.80 is 11111010.10000000. The length of the OID mask must be less than the length of subtree OID.
<b>viewtype (included excluded)</b>	Include or exclude the selected MIBs in the view.
<b>Default</b>	N/A
<b>Mode</b>	Global Configuration
<b>Usage</b>	To configure the SNMP view, use the command <b>snmp view</b> in the Global Configuration mode; and use the <b>no</b> form of the command to delete the SNMP view.
The default SNMP view cannot be deleted and modified by users. By default, the maximum numbers of SNMP view is limited to 16.	
<b>Example</b>	The following example defines the SNMP view.
<pre>Switch(config)# snmp view private subtree 1.3.3.1 oid-mask all viewtype included</pre>	



## 29. Spanning Tree

### instance (MST)

---

#### Syntax

**instance** *instance-id* **vlan** *vlan-list*  
**no instance** *instance-id* **vlan** *vlan-list*

---

#### Parameter

<i>instance-id</i>	The MSTP instance ID from 0 to 15.
<b>vlan</b> <i>vlan-list</i>	Add the VLAN list to the MSTP instance.

---

#### Default

All VLANs are mapped to the Common and Internal Spanning Tree (CIST) instance (instance 0).

---

#### Mode

MST Configuration

---

#### Usage

To map the VLAN to the Multiple Spanning Tree (MSTP) instances, use the command **instance** in the MST Configuration mode; and use the **no** form of the command to restore its default configuration.

All VLANs that are not explicitly configured to an MSTP instance are mapped to the CIST instance (instance 0).

For two or more switches in the same MSTP region, their VLAN mapping, name and revision number configuration, must be the same.

---

#### Example

The following example maps the vlan 10-20 to the MSTP instance 1, and VLAN 100 to instance 2.

```
Switch(config)# spanning-tree mst configuration
Switch(config-mst)# instance 1 vlan 10-20
Switch(config-mst)# instance 2 vlan 100
```

### name (MST)

---

#### Syntax

**name** *name-str*  
**no name**

---

#### Parameter

<i>name-str</i>	The MSTP instance name. Its maximum length is 32 characters.
-----------------	--

---

#### Default

The default MSTP name is the switch MAC address.

---

#### Mode

MST Configuration



**Usage** To define the name for MSTP instance, use the command **name** in the MST Configuration mode; and use the **no** form to restore the default name configuration.

**Example** The following example configures the name of MST instance to *Valkyrie*.

```
Switch(config)# spanning-tree mst configuration  
Switch(config-mst)# name Valkyrie
```

## revision (MST)

<b>Syntax</b>	<b>revision</b> <i>rev</i> <b>no revision</b>
<b>Parameter</b>	<i>rev</i> The MSTP revision number. Its valid range is from 0 to 65535.

**Default** The default revision number is 0.

## Mode MST Configuration

**Usage** To define the revision for the MSTP configuration, use the command **revision** in the MST Configuration mode; and use the **no** form of the command to restore it default configuration.

**Example** The following example defines the revision MSTP configuration to 1.

```
Switch(config)# spanning-tree mst configuration  
Switch(config-mst)# revision 1
```

## show spanning-tree

---

## Syntax                    show spanning-tree

---

## Parameter N/A

---

## Default N/A

## Mode

---

## Privileged EXEC

---

**Usage**

To display the spanning tree configuration, use the command `spanning-tree` in the Privileged EXEC mode

---

**Example**

The following example shows the spanning tree configuration.

```
Switch# show spanning-tree

Spanning tree enabled mode RSTP
Default port cost method: short

Root ID      Priority    32768
              Address     00:11:22:33:44:55
              This switch is the root
Hello Time   4 sec     Max Age 10 sec  Forward Delay
25 sec

Number of topology changes 2 last change occurred 20:34:30 ago
Times: hold 0, topology change 0, notification 0
       hello 4, max age 10, forward delay 25

Interfaces
Name        State      Prio.Nbr    Cost      Sts      Role EdgePort
Type
-----
-----
fa23      enabled     128.23      19       Blk      Desg      No P2P
(RSTP)
```

---

## show spanning-tree interface

---

**Syntax**

**show spanning-tree interface *IF\_PORTS* [*statistic*]**

---

**Parameter**

**interface** An interface ID or the list of interface IDs.

***IF\_PORTS***

**statistic** Display the STP statistic for an interface.

---

**Default**

N/A

---

**Mode**

Privileged EXEC

---

**Usage**

To show the STP configuration and statistics for an interface, use the command `show spanning-tree interface` in the Privileged EXEC mode.



**Example**

The following example shows the STP configuration for the interface fa23.

```
Switch# show spanning-tree interfaces fa23

Port fa23 enabled
State: forwarding
designated
Port id: 128.23
Type: P2P (RSTP)
Designated bridge Priority : 32768
00:11:22:33:44:55
Designated port id: 128.23
cost: 0
BPDU Filter: Disabled
Disabled
BPDU: sent 21886, received 0

Role: Port cost: 19
Edge Port: No
Address: Designated path
BPDU guard:
```

The following example shows the STP statistic for the interface fa23.

```
Switch# show spanning-tree interfaces fa23 statistic

STP Port Statistic
=====
Port : fa23
Configuration BDPUs Received : 0
TCN BDPUs Received : 0
MSTP BDPUs Received : 0
Configuration BDPUs Transmitted : 0
TCN BDPUs Transmitted : 0
MSTP BDPUs Transmitted : 21917
=====
```

---

## **show spanning-tree mst**

**Syntax**

**show spanning-tree mst *instace-id***

**Parameter**

*instace-id* The MSTP instance ID. Its valid range is from 0 to 15.

**Default**

N/A

**Mode**

Privileged EXEC

**Usage**

To show the information for a specific MSTP instance, use the command **show spanning-tree mst** in the Privileged EXEC mode.

**Example**

The following example displays the information for the MSTP instance 0 and 1 individually.

---



```
Switch# show spanning-tree mst 0

MST Instance Information
=====
    Instance Type : CIST (0)
    Bridge Identifier : 32768/ 0/00:11:22:33:44:55
-----
        Designated Root Bridge : 32768/ 0/00:11:22:33:44:55
        External Root Path Cost : 0
        Regional Root Bridge : 32768/ 0/00:11:22:33:44:55
        Internal Root Path Cost : 0
            Designated Bridge : 32768/ 0/00:11:22:33:44:55
            Root Port : 0/0
            Max Age : 10
            Forward Delay : 25
            Topology changes : 3
            Last Topology Change : 930
-----
--- VLANs mapped: 1-99,111-4094
=====

Interface      Role Sts Cost      Prio.Nbr Type
-----
-----fa23          Desg FWD 19      128.23   P2P (RSTP)

Switch# show spanning-tree mst

1 MST Instance Information
=====
    Instance Type : MSTI (1)
    Bridge Identifier : 32768/ 0/00:11:22:33:44:55
-----
        Regional Root Bridge : 32768/
        0/00:11:22:33:44:55 Internal Root Path Cost : 0
        Remaining Hops :
        10 Topology
        changes : 3
        Last Topology Change : 933
-----
    VLANs mapped: 100-110
=====

Interface      Role Sts Cost      Prio.Nbr Type
-----
-----fa23          Desg FWD 19      128.23   P2P (RSTP)
```

---

## show spanning-tree mst configuration

---

### Syntax

**show spanning-tree mst configuration**

---

### Parameter

N/A



[www.cerio.com.tw](http://www.cerio.com.tw)



+**(886) 2-8911-6160**



[service@cerio.com.tw](mailto:service@cerio.com.tw)

# **Command Line Interface**

## **User Guide**

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

<b>Default</b>	N/A
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	To show the global MST configuration, use the command <b>show spanning-tree mst configuration</b> in the Privileged EXEC mode.
<b>Example</b>	The following example shows the global MST configuration.  Switch# show spanning-tree mst configuration Name [00:11:22:33:44:55] Revision 0 Instances configured 2  Instance Vlans mapped ----- 0 1-99,111-4094 1 100-110 -----
<b>show spanning-tree mst interface</b>	
<b>Syntax</b>	<b>show spanning-tree mst <i>instance-id</i> interface <i>IF_PORTS</i></b>
<b>Parameter</b>	<b><i>instance-id</i></b> The MSTP instance ID. Its valid range is from 0 to 15. <b>interface</b> An interface ID or the list of interface IDs. <b><i>IF_PORTS</i></b>
<b>Default</b>	N/A
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	To show the MSTP instance information on the specific interface, use the command <b>show spanning-tree mst interface</b> in the Privileged EXEC mode.
<b>Example</b>	The following example shows the MSTP 0 and 1 information individually on the interface fa23.  Switch# show spanning-tree mst 0 interfaces fa23 MST Port Information ===== Instance Type : CIST (0) -----



```
Port Identifier : 128/23
External Path-Cost : 0

/19
Internal Path-Cost : 0           /19
-----
Designated Root Bridge :
32768/00:11:22:33:44:55 External Root Cost :
0
Regional Root Bridge :
32768/00:11:22:33:44:55 Internal Root Cost :
0
Designated Bridge :
32768/00:11:22:33:44:55 Internal Port Path Cost :
19
Port Role :
Designated Port
State : Forwarding
-----
```

```
Switch# show spanning-tree mst 1 interfaces fa23
```

```
MST Port Information
```

```
=====
Instance Type : MSTI (1)
=====
```

```
Port Identifier : 128/23
Internal Path-Cost : 0

/19
-----
Regional Root Bridge :
32768/00:11:22:33:44:55 Internal Root Cost :
0
Designated Bridge :
32768/00:11:22:33:44:55 Internal Port Path Cost :
19
Port Role :
Designated Port
State : Forwarding
-----
```

---

## spanning-tree

---

**Syntax**

**spanning-tree**  
**no spanning-tree**

**Parameter**

N/A

**Default**

Spanning-Tree is enabled by default.

---

**Mode**

Global Configuration



---

**Usage**

To enable the spanning tree, use the command `spanning-tree` in the Global Configuration mode; and use the `no` form of the command to disable the spanning tree on the switch.

---

**Example**

The following example disables and enables the spanning tree individually.

---

```
Switch(config)# no spanning-tree
```

---



```
Switch(config) # spanning-tree
```

---

## **spanning-tree bpdu**

<b>Syntax</b>	<b>spanning-tree bpdu (filtering flooding)</b> <b>no spanning-tree bpdu</b>
<b>Parameter</b>	<b>filtering</b> Filter the BPDU when STP is disabled. <b>flooding</b> Flood the BPDU when the STP is disabled.
<b>Default</b>	The default configuration is flooding.
<b>Mode</b>	Global Configuration
<b>Usage</b>	To configure the action of Bridge Protocol Data Unit (BPDU) handling when STP is disabled, use the command <b>spanning-tree bpdu</b> in the Global Configuration mode. To restore the configuration to the default action, use the <b>no</b> form of the command.
<b>Example</b>	The following example configures the action of BPDU handling to filter when the STP is disabled.
	<pre>Switch(config) # spanning-tree bpdu filtering</pre>
<b>spanning-tree bpdu-filter</b>	
<b>Syntax</b>	<b>spanning-tree bpdu-filter</b> <b>no spanning-tree bpdu-filter</b>
<b>Parameter</b>	N/A
<b>Default</b>	BPDU filter is disabled.
<b>Mode</b>	Interface Configuration
<b>Usage</b>	To enable the BPDU filter, use the command <b>spanning-tree bpdu-filter</b> in the Interface Configuration mode; and use <b>no</b> form of the command to disable the BPDU filter.



---

**Example**

The following example enables the BPDU filter for interface fa1.

```
Switch(config)# interface fa1
Switch(config-if)# spanning-tree bpdu-filter
```

---

## **spanning-tree bpdu-guard**

---

**Syntax**

**spanning-tree bpdu-guard**  
**no spanning-tree bpdu-guard**

---

**Parameter**

N/A

---

**Default**

BPDU guard is disabled

---

**Mode**

Interface Configuration

---

**Usage**

To enable the BPDU filter, use the command **spanning-tree bpdu-guard** in the Interface Configuration mode; and use **no** form of the command to disable the BPDU filter.

---

**Example**

The following example enables the BPDU guard for interface gi1.

```
Switch(config)# interface gi1
Switch(config-if)# spanning-tree bpdu-guard
```

---

## **spanning-tree cost**

---

**Syntax**

**spanning-tree cost *cost***  
**no spanning-tree cost**

---

**Parameter**

*cost* The port path cost. For the long path cost method, its valid range is from 0 to 200000000; and the valid range is from 0 to 65535 for the short path cost method. The value 0 indicates AUTO, which the port path cost is determined by the port speed and the path cost method.

---

**Default**

The default port path cost is 0, and it is determined by the port speed and the path cost method (long or short).

Interface	Long	Short
Gigabit Ethernet (1000Mbps)	20000	4
Fast Ethernet (100Mbps)	200000	19
Ethernet (10Mbps)	2000000	100



<b>Mode</b>	Interface Configuration
<b>Usage</b>	To configure the STP path cost for an interface, use the command <b>spanning-tree cost</b> in the Interface Configuration mode; and use the <b>no</b> form of the command to restore it to the default configuration.
<b>Example</b>	The following example configures port path cost to 30000 for interface fa2.  <code>Switch(config)# interface gi1 Switch(config-if)# spanning-tree cost 30000</code>

## **spanning-tree forward-time**

<b>Syntax</b>	<b>spanning-tree forward-time seconds</b> <b>no spanning-tree forward-time</b>
<b>Parameter</b>	<b>seconds</b> STP forward delay time. Its valid range is from 4 to 10 seconds.
<b>Default</b>	The default forward delay time is 15 seconds.

<b>Mode</b>	Global Configuration
<b>Usage</b>	To configure the STP bridge forward delay time, which is the amount of time that a port remains in the Listening and Learning states before it enters the Forwarding state, use the command <b>spanning-tree forward-time</b> in the Global Configuration mode. To restore it to the default configuration, use the <b>no</b> form of the command.

When the forward delay time is configured, the following relationship shold be maintained:

$$2 * (\text{forward-time} - 1) \geq \text{Max-Age}$$

<b>Example</b>	The following example configures STP forward delay time to 25.
	<code>Switch(config)# spanning-tree forward-time 25</code>

## **spanning-tree hello-time**

<b>Syntax</b>	<b>spanning-tree hello-time seconds</b> <b>no spanning-tree hello-time</b>
<b>Parameter</b>	<b>seconds</b> STP hello time in second. Its valid range is from 1 to 10



---

seconds.

---

---

<b>Default</b>	The default STP hello time is 2 seconds.
----------------	--

---

---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

---

<b>Usage</b>	STP hello time is the time interval to broadcast its hello message to other bridges. To configure the STP hello time, use the command <b>spanning-tree hello-time</b> in the Global Configuration mode; and use the <b>no</b> form of the command to restore the hello time to default configuration.
--------------	---

When the hello time is configured, the following relationship should be maintained:

$$\text{Max-Age} \geq 2 * (\text{hello-time} + 1)$$

---

<b>Example</b>	The following example configures BPDU hello time to 4.
----------------	--

---

```
Switch(config)# spanning-tree hello-time 4
```

---

## **spanning-tree edge**

---

<b>Syntax</b>	<b>spanning-tree edge</b> <b>no spanning-tree edge</b>
---------------	---

---

<b>Parameter</b>	N/A
------------------	-----

---

<b>Default</b>	The default configuration is disabled.
----------------	--

---

---

<b>Mode</b>	Interface Configuration
-------------	-------------------------

---

---

<b>Usage</b>	To enable the edge mode for an interface, use the command <b>spanning-tree edge</b> in the Interface Configuration mode; and use the <b>no</b> form of the command to restore it to the default configuration.
--------------	--

In the edge mode, the interface would be put into the Forwarding state immediately upon link up. If the edge mode is enabled for the interface and there are BPDUs received on the interface, the loop might be occurred in the short time.



## Command Line Interface User Guide

### Example

The following example enables the edge mode for the interface fa1.

---

```
Switch(config)# interface fa1
```

---



---

```
Switch(config-if) # spanning-tree edge
```

---

## spanning-tree link-type

---

### Syntax

**spanning-tree link-type (point-to-point|shared)**  
**no spanning-tree link-type**

---

### Parameter

<b>point-to-point</b>	Specify the port link type is point to point.
<b>shared</b>	Specify the port link type is shared.

---

### Default

The default configuration link type is **point-to-point** for the ports with full duplex configuration, and **shared** for the ports with half duplex settings.

---

### Mode

Interface Configuration

---

### Usage

To set the RSTP link-type for an interface, use the command **spanning-tree link** in the Interface Configuration mode. For the default configuration, use the **no** form of the command.

---

### Example

The following example configures the link-type to point-to-point for the interface fa1.

```
Switch(config) # interface fa1
Switch(config-if) # spanning-tree link-type point-to-point
```

---

## spanning-tree max-hops

---

### Syntax

**spanning-tree max-hops *counts***  
**no spanning-tree max-hops**

---

### Parameter

<i>counts</i>	Specify the number of hops in an MSTP region before the BPDU is discarded. The valid range is 1 to 40.
---------------	--

---

### Default

The default max-hops configuration is 20.

---

### Mode

Global Configuration

---

### Usage

To specify the number of hops for a BPDU to be forwarded in the MSTP region, use the command **spanning-tree max-hops** in the Global Configuration mode; and restore the setting to default configuration by the **no** form of the command.



<b>Example</b>	The following example specifies the max hops for BPDU to 10.
----------------	--

```
Switch(config) # spanning-tree max-hops 10
```

---

## **spanning-tree maximum-age**

<b>Syntax</b>	<b>spanning-tree maximum-age <i>seconds</i></b> <b>no spanning-tree maximum-age</b>
---------------	--

<b>Parameter</b>	<i>seconds</i> The interval in seconds for a switch to wait the configuration messages, without attempting to redefine its own configuration.
------------------	---

<b>Default</b>	The default maximum age is 20 seconds.
----------------	--

<b>Mode</b>	Global Configuration
-------------	----------------------

<b>Usage</b>	To set the interval in seconds that the switch can wait without receiving the configuration messages, before attempting to redefine its own configuration, use the command <b>spanning-tree maximum-age</b> in the Global Configuration mode. For the default configuration, use the <b>no</b> form of the commands.
--------------	--

When the maximum age is configured, the following relationship should be maintained:

$$2 * (\text{forward-time} - 1) \geq \text{Max-Age} \geq 2 * (\text{hello-time} + 1)$$

<b>Example</b>	The following example configures STP maximum age to 10.
----------------	---

```
Switch(config) # spanning-tree maximum-age 10
```

---

## **spanning-tree mcheck**

<b>Syntax</b>	<b>spanning-tree mcheck</b>
---------------	-----------------------------

<b>Parameter</b>	N/A
------------------	-----

<b>Default</b>	N/A
----------------	-----

<b>Mode</b>	Interface Configuration
-------------	-------------------------



---

<b>Usage</b>	To restart the Spanning Tree Protocol (STP) migration process (re-negotiate forcibly with its neighborhood) on the specific interface, use the command <code>spanning-tree mcheck</code> in the Interface Configuration mode
--------------	--

---

<b>Example</b>	The following example restarts the STP negotiation on the interface fa1.
----------------	--

```
Switch(config)# interface fa1
Switch(config-if)# spanning-tree mcheck
```

---

## spanning-tree mode

---

<b>Syntax</b>	<b>spanning-tree mode (mstp rstp stp)</b> <b>no spanning-tree force-version</b>
---------------	--

---

<b>Parameter</b>	<b>mstp</b> Enable the Multiple Spanning Tree (MSTP) operation. <b>rstp</b> Enable the Rapid Spanning Tree (RSTP) operation. <b>stp</b> Enable the Spanning Tree (STP) operation.
------------------	---

---

<b>Default</b>	The default mode is rstp.
----------------	---------------------------

---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

<b>Usage</b>	To specify the spanning tree operation mode, use the command of <b>spanning-tree mode</b> in the Global Configuration mode. For the default configuration, use the command <b>no spanning-tree force-version</b> in the Global Configuration mode.
--------------	--

When the switch is configured as MSTP mode, it can use STP and RSTP for the backward compatibility with switches working in STP and RSTP mode individually. For the RSTP configuration, the switch can also use STP for the switches working in the STP operation.

---

<b>Example</b>	The following example sets the STP operation to MSTP.
----------------	---

```
Switch(config)# spanning-tree mode mstp
```

---

## spanning-tree mst configuration

---

<b>Syntax</b>	<b>spanning-tree mst configuration</b>
---------------	--

---

<b>Parameter</b>	N/A
------------------	-----

---

<b>Default</b>	N/A
----------------	-----



---

**Mode**

Global Configuration

---

**Usage**

To enter the MST configuration mode for the MSTP configuration modification, use the command **spanning-tree mst configuration** in the Global Configuration mode.

---

**Example**

The following example modifies the MSTP configuration in the MST Configuration mode.

```
Switch(config)# spanning-tree mst configuration
Switch(config-mst)# instance 1 vlan 10-20
Switch(config-mst)# name Valkyrie
Switch(config-mst)# revision 1
```

---

## **spanning-tree mst cost**

---

**Syntax**

**spanning-tree mst *instance-id* cost *cost***  
**no spanning-tree mst *instance-id* cost *cost***

---

**Parameter**

<i>instance-id</i>	Specify the instance ID. The valid range is from 0 to 15.
<i>cost</i>	Specify the path cost for the interfaces on the specific MSTP instance. For the long path cost method, its valid range is from 0 to 200000000; and the valid range is from 0 to 65535 for the short path cost method. The value 0 indicates AUTO, which the port path cost is determined by the port speed and the path cost method.

---

**Default**

The default port path cost is 0, and it is determined by the port speed and the path cost method (long or short).

<b>Interface</b>	<b>Long</b>	<b>Short</b>
Gigabit Ethernet (1000Mbps)	20000	4
Fast Ethernet (100Mbps)	200000	19
Ethernet (10Mbps)	2000000	100

---

**Mode**

Interface Configuration

---

**Usage**

To configure the path cost for MSTP calculations, use the command **spanning-tree mst cost** in the Interface Configuration mode. If the loop occurs, the MSTP considers the path cost when selecting the interface into the Forwarding state. For the default configuration, use the no form of the command.

When configuring the path cost on the CIST (instance 0), it is equal to the



command **spanning-tree cost** in the Interface Configuration mode.

## Example

The following example configures the path cost of interface fa1 on the instance 1 to 30000

```
Switch(config)# interface gi1
Switch(config-if)# spanning-tree mst 1 cost 30000
```

## spanning-tree mst port-priority

### Syntax

```
spanning-tree mst instance-id port-priority priority
no spanning-tree mst instance-id port-priority
```

### Parameter

*instance-id* Specify the instance ID. The valid range is from 0 to 15.

*priority* Specify the interface priority on the specific instance.

### Default

The default port priority on each instance is 128

### Mode

Interface Configuration

### Usage

To configure the interface priority on the specific instances, use the command **spanning-tree mst port-priority** in the Interface Configuration mode. For the default configuration, use the **no** form of the command.

The priority value must be the multiple of 16. When the port priority on the CIST (instance 0) is configured, it is equal to the command **spanning-tree port-priority** in the Interface Configuration mode.

## Example

The following example sets the port priority of gi1 on the instance 1 to 144; and set the port priority of gi1 on the CIST (instance 0) to 96

```
Switch(config)# interface gi1
Switch(config-if)# spanning-tree mst 1 port-priority 144
Switch(config-if)# spanning-tree mst 0 port-priority 96
```

## spanning-tree mst priority

### Syntax

```
spanning-tree mst instance instance-id priority priority
no spanning-tree mst instance instance-id priority
```

### Parameter

*instance-id* Specify the instance ID. The valid range is from 0 to 15.

*priority* Specify the bridge priority on the specific instance. The



valid range is from 0 to 61440. It ensures the probability that the switch is selected as the root bridge, and the lower values has the higher priority for the switch to be selected as the root bridge.

---

**Default**

The default priority on each instance is 32768.

**Mode**

Global Configuration

**Usage**

To configure the bridge priority on the specific instance, use the command **spanning-tree mst priority** in the Global Configuration mode. To restore the default configuration, use the **no** form of the command.

The value of bridge priority must be the multiple of 4096. A switch with the lowest priority is the root of the STP topology. For the configuration of bridge priority on the CIST (instance 0), it is equal to the command **spanning-tree priority** in the Global Configuration mode.

**Example**

The following example modifies the bridge priority to 4096 on instance 0 and instance 1 individually.

```
Switch(config)# spanning-tree mst 0 priority 4096
Switch(config)# spanning-tree mst 1 priority 4096
```

## **spanning-tree pathcost method**

**Syntax**

**spanning-tree pathcost method (long|short)**

**Parameter**

<b>long</b>	The range for the path cost is from 1 to 200000000.
<b>short</b>	The range for the path cost is from 1 to 65535.

**Default**

The default path cost method is long.

**Mode**

Global Configuration



## Command Line Interface User Guide

### Usage

To set the spanning tree path cost method, use the command **spanning-tree pathcost method** in the Global Configuration mode.

If the short method is specified, the switch calculates the path cost in the range 1 through 65535; Otherwise, it calculates the path cost in the range 1 to 200000000.



---

**Example**

The following example modifies path cost method to short.

```
Switch(config)# spanning-tree pathcost method short
```

---

**spanning-tree port-priority**

---

**Syntax**

**spanning-tree port-priority** *priority*  
**no spanning-tree port-priority** *priority*

---

**Parameter**

*priority* Specify the priority for an interface. The valid range is from 0 to 240.

---

---

**Default**

The default priority for each interface is 128.

---

**Mode**

Interface Configuration

---

**Usage**

To configure the STP priority for an interface, use the command **spanning-tree port-priority** in the Interface Configuration mode. For the default configuration, use the **no** form of the command.

The priority value must be the multiple of 16.

---

**Example**

The following example modifies the port priority to 96 for the interface gi2 .

```
Switch(config)# interface gi2
Switch(config-if)# spanning-tree port-priority 96
```

**spanning-tree priority**

---

**Syntax**

**spanning-tree priority** *priority*  
**no spanning-tree priority**

---

**Parameter**

*instance-id* Specify the instance ID. The valid range is from 0 to 15.

---

*priority* Specify the bridge STP priority. The valid range is from 0 to 61440. It ensures the probability that the switch is selected as the root bridge, and the lower values has the higher priority for the switch to be selected as the root bridge of the STP topology.

---

---

**Default**

The default priority for the switch 32768.



Mode	Global Configuration
------	----------------------

Usage	To configure the bridge priority, use the command <b>spanning-tree mst priority</b> in the Global Configuration mode. To restore the default configuration, use the <b>no</b> form of the command.
-------	--

The value of bridge priority must be the multiple of 4096. A switch with the lowest priority is the root of the STP topology. When switches with the same priority configuration in the environment, the switch with lowest MAC address would be selected as the root bridge.

Example	The following example modifies the bridge priority to 4096.
---------	---

```
Switch(config)# spanning-tree priority 4096
```

## spanning-tree tx-hold-count

Syntax	<b>spanning-tree tx-hold-count</b> <i>count</i> <b>no spanning-tree tx-hold-count</b>
--------	--

Parameter	<i>count</i> Specify the tx-hold-count used to limit the maximum numbers of packets transmission per second. The valid range is from 1 to 10.
-----------	---

Default	The default value is 6.
---------	-------------------------

Mode	Global Configuration
------	----------------------

Usage	To limit the maximum numbers of packets transmission per second, use the command <b>spanning-tree tx-hold-count</b> in the Global Configuration mode. For the default configuration, use the <b>no</b> form of the command.
-------	---

Example	The following example sets the tx-hold-count to 4.
---------	--

```
Switch(config)# spanning-tree tx-hold-count 4
```

## 30. Storm Control

### show storm-control

Syntax	<b>show storm-control</b>
--------	---------------------------



**show storm-control interface *IF\_PORTS***

<b>Parameter</b>	<i>IF_PORTS</i> Specify port to show.
<b>Default</b>	No default value for this command
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	<p>Use “<b>show storm-control</b>” command to show all storm control related configurations including global configuration and per port configurations.</p> <p>Use “<b>show storm-control interface</b>” command to show selected port storm control configurations.</p>
<b>Example</b>	<p>This example shows how to show storm control global configuration.</p> <pre>Switch# show storm-control   Storm control preamble and IFG: Excluded   Storm control unit: pps   .....</pre> <p>This example shows how to show current storm control configuration on interface <b>gi1</b></p> <pre>Switch# show storm-control interfaces gi1   Port        State   Broadcast   Unkown-Multicast   Unknown-Unicast   Action                             pps                 pps              pps       -----+-----+-----+-----+-----+-----+       fa1      enable      200      Off( 10000)      Off( 10000)   Shutdown</pre>

## storm-control

<b>Syntax</b>	<b>storm-control</b> <b>no storm-control</b>  <b>storm-control (broadcast   unknown-unicast   unknown-multicast)</b> <b>no storm-control (broadcast   unknown-unicast   unknown-multicast)</b>
<b>Parameter</b>	<b>broadcast</b> Select broadcast storm control type <b>unknown-unicast</b> Select unknown unicast storm control type <b>unknown-multicast</b> Select unknown multicast storm control type
<b>Default</b>	Default storm control is disabled. Default broadcast storm control is disabled.



Default unknown multicast storm control is disabled  
Default unknown unicast storm control is disabled

---

**Mode** Interface Configuration

---

**Usage** Storm control function is able to enable/disable on each single port. Use the “**storm control**” command to enable storm control feature on the selected ports. And use “**no storm control**” command to disable storm control feature. Not only port is able to enable/disable on the port. Each storm control type is also able to enable/disable on each single port.

Use the “**storm-control (broadcast|unknown-unicast|unknown-multicast)**” command to enable the storm control type you need and use no form to disable it.

---

**Example** This example shows how to enable storm control on interface g1.

```
Switch(config)# interface g1
Switch(config-if)# storm-control
```

This example shows how to enable broadcast storm control and configure broadcast storm control rate to 200.

```
Switch(config)# interface g1
Switch(config-if)# storm-control broadcast
```

This example shows how to show current storm control configuration on interface g1

```
Switch# show storm-control interfaces g1
  Port      | State | Broadcast | Unknown-Multicast | Unknown-Unicast | Action
              |       |     pps    |                 pps          |       pps
  |
  ---+-----+-----+-----+-----+-----+
  g1      enable      200        Off( 10000)      Off( 10000)
  Shutdown
```

---

## storm-control action

---

**Syntax**

**storm-control action (drop | shutdown)**  
**no storm-control action**

---

**Parameter**

<b>drop</b>	Storm control rate calculates by octet-based
<b>shutdown</b>	

---

---

**Default**

Default storm control action is drop.



---

**Mode** Interface Configuration

---

**Usage** Use “**storm-control action**” command to set the action when the received storm control packets exceed the maximum rate on an interface. Use **no** form to restore to default action.

---

**Example** This example shows how to configure storm control action to shutdown port on interface g1.

```
Switch(config)# interface g1
Switch(config-if)# storm-control action shutdown
```

This example shows how to show storm control action on interface g1.

```
Switch# show storm-control interfaces g1
      Port      | State | Broadcast | Unknown-Multicast | Unknown-Unicast | Action
                  |       |      pps     |           pps      |      pps
      |
      -----+-----+-----+-----+-----+
      |
      g1      disable Off( 10000)      Off( 10000)      Off( 10000)
Shutdowm
```

---

## storm-control ifg

---

**Syntax** **storm-control ifg (include | exclude)**

---

<b>Parameter</b>	<b>include</b> Include preamble & IFG (20 bytes) when count ingress storm control rate.
	<b>exclude</b> Exclude preamble & IFG (20 bytes) when count ingress storm control rate

---

---

**Default** Default storm control inter frame gap is excluded.

---

**Mode** Global Configuration

---

**Usage** Storm control mechanism will try to calculate ingress packets is exceed configured rate or not and do corresponding action.

Use **storm-control ifg** command to include/exclude the preamble and inter frame gap into the calculating.

---

**Example** This example shows how to configure storm inter frame gap to include.

```
Switch(config)# storm-control ifg include
```

This example shows how to show storm control global configuration.

```
Switch# show storm-control
      Storm control preamble and IFG: Included
```

---



Storm control unit: pps  
.....

---

## storm-control level

---

### Syntax

**storm-control (broadcast | unknown-unicast | unknown-multicast) level <1-1000000>**  
**no storm-control (broadcast | unknown-unicast | unknown-multicast)**  
**level**

---

### Parameter

<b>broadcast</b>	Select broadcast storm control type
<b>unknown-unicast</b>	Select unknown unicast storm control type
<b>unknown-</b> <b>multicast</b>	Select unknown multicast storm control type
<b>level &lt;1-1000000&gt;</b>	Specify the storm control rate for selected type. For bps, range is 16-1000000 For pps, range is 1-262143

---

### Default

Default broadcast storm control rate is 10000.  
Default unknown multicast storm control rate is 10000.  
Default unknown unicast storm control rate is 10000.

---

### Mode

Interface Configuration

---

### Usage

Each control type is allowed to have different storm control rate.

Use “**storm-control (broadcast|unknown-unicast|unknown-multicast) level**” command to configure it

Use no form to restore to default rate.

---

### Example

This example shows how to enable broadcast storm control and configure broadcast storm control rate to 200.

```
Switch(config)# interface g1
Switch(config-if)# storm-control broadcast
Switch(config-if)# storm-control broadcast level 200
```

This example shows how to show current storm control configuration on interface g1

```
Switch# show storm-control interfaces g1
      Port      | State | Broadcast | Unknown-Multicast | Unknown-Unicast |
Action          |       |    pps    |           |    pps        |    pps
|-----+-----+-----+-----+-----+-----+
---  g1      enable     200      Off( 10000)      Off( 10000)
      Shutdown
```

---



## storm-control unit

<b>Syntax</b>	<b>storm-control unit (bps   pps)</b>
<b>Parameter</b>	<b>bps</b> Storm control rate calculates by octet-based <b>pps</b> Storm control rate calculates by packet-based
<b>Default</b>	Default storm control unit is bps.
<b>Mode</b>	Global Configuration
<b>Usage</b>	Storm control mechanism will try to calculate ingress packets is exceed configured rate or not and do corresponding action.  Use <b>storm-control unit</b> command to change the unit of calculating method.
<b>Example</b>	This example shows how to configure storm control rate unit as pps. Switch(config)# <b>storm-control unit pps</b>  This example shows how to show storm control global configuration. Switch# <b>show storm-control</b> Storm control preamble and IFG: Excluded Storm control unit: pps .....

## 31. System File

### boot system

<b>Syntax</b>	<b>boot system (image0   image1)</b>
<b>Parameter</b>	<b>image0</b> Boot from flash image partition 0 <b>image1</b> Boot from flash image partition 1
<b>Default</b>	Default boot image is image0.
<b>Mode</b>	Global Configuration



---

## Usage

Dual image allow user to have a backup image in the flash partition.  
Use “**boot system**” command to select the active firmware image.  
And another firmware image will become a backup one.

---

## Example

This example shows how to select image1 as active image.

```
Switch(config)# boot system image1  
Select "image1" Success
```

This example shows how to show active image partition.

```
Switch# show flash
```

File Name	File Size	Modified
startup-config	1191	2000-01-01 00:00:23
backup-config	1607	2000-01-01 08:36:23
rsa1	974	2000-01-01 00:00:18
rsa2	1675	2000-01-01 00:00:18
dsa2	668	2000-01-01 00:00:18
ssl_cert	993	2000-01-01 00:00:18
image0 (backup)	4372401	2012-09-24 01:57:29
image1 (active)	5555970	2012-06-12 12:17:46

## copy

---

### Syntax

```
copy (flash:// | tftp://) (flash:// | tftp://)  
copy tftp:// (backup-config | running-config | startup-config)  
copy (backup-config | running-config | startup-config) tftp://
```

```
copy (backup-config | startup-config) running-config  
copy (backup-config | running-config) startup-config  
copy (running-config | startup-config) backup-config
```

---

### Parameter

**flash://** Specify the file stored in flash to operation. Available files are:  
flash://startup-config  
flash://backup-config  
flash://rsa1  
flash://rsa2  
flash://dsa2  
flash://image0  
flash://image1  
flash://ram.log  
flash://flash.log

**tftp://** Specify remote tftp server and remote file name. The format is “**tftp://192.168.1.111/remote\_file\_name**”

**running-config** Running configuration file

**startup-config** Startup configuration file

**backup-config** Backup configuration file

---

### Default

No default value for this command.



<b>Mode</b>	Privileged EXEC
<b>Usage</b>	<p>There are many types of files in system. These files are very important for administrator to manage the switch. The most common file operation is copy. By using these copy commands, we can upgrade, backup following type of files.</p> <ul style="list-style-type: none"><li>• <b>Firmware Image</b></li><li>• <b>Configuration Files</b></li><li>• <b>Syslog Files</b></li><li>• <b>Language Files</b></li><li>• <b>Security Certificate</b></li></ul>
<b>Example</b>	<p>This example shows how to copy running configuration to startup configuration.</p> <pre>Switch# copy running-config startup-config</pre> <p>This example shows how to backup running configuration to remote tftp server 192.168.1.111 with file name test1.cfg.</p> <pre>Switch# copy running-config tftp://192.168.1.111/test1.cfg</pre> <p>Uploading file...Please Wait...</p> <p>Uploading Done</p> <p>This example shows how to upgrade startup configuration from remote tftp server 192.168.1.111 with file name test2.cfg.</p> <pre>Switch# copy tftp://192.168.1.111/test2.cfg startup-config</pre> <p>Downloading file...Please Wait...</p> <p>Downloading Done</p> <p>Upgrade config success. Do you want to reboot now? (y/n)n</p> <p>This example shows how to backup security file dsa2 to remote tftp server 192.168.1.111 with file name dsa2.</p> <pre>Switch# copy flash://dsa2 tftp://192.168.1.111/dsa2</pre> <p>Uploading file...Please Wait...</p> <p>Uploading Done</p>
<b>delete</b>	

## delete

<b>Syntax</b>	<pre>delete (startrup-config   backup-config   flash://)</pre> <pre>delete system (image0   image1)</pre>				
<b>Parameter</b>	<table><tr><td><b>flash://</b></td><td>Specify the configuration file stored in flash to delete. Available files are: flash://startup-config flash://backup-config</td></tr><tr><td><b>startup-config</b></td><td>Delete startup configuration file</td></tr></table>	<b>flash://</b>	Specify the configuration file stored in flash to delete. Available files are: flash://startup-config flash://backup-config	<b>startup-config</b>	Delete startup configuration file
<b>flash://</b>	Specify the configuration file stored in flash to delete. Available files are: flash://startup-config flash://backup-config				
<b>startup-config</b>	Delete startup configuration file				



<b>backup-config</b>	Delete backup configuration file
<b>image0</b>	Delete flash image0.
<b>image1</b>	Delete flash image1.

---

**Default** No default value for this command.

---

**Mode** Privileged EXEC

---

**Usage** Use “**delete**” command to delete configuration files or use “**delete system**” command to delete firmware image stored in flash.  
The “**delete startup-config**” command is using to restore factory default and it is equal to command “**restore-defaults**”.

---

**Example** This example shows how to delete backup configuration file.  
Switch# **delete backup-config**

This example shows how to delete backup firmware image from flash.  
Switch# **delete system image1**

This example shows how to show file status in flash.

```
Switch# show flash
-----
```

File Name	File Size	Modified
startup-config	1191	2000-01-01 00:00:23
backup-config	1607	2000-01-01 08:36:23
rsa1	974	2000-01-01 00:00:18
rsa2	1675	2000-01-01 00:00:18
dsa2	668	2000-01-01 00:00:18
ssl_cert	993	2000-01-01 00:00:18
image0 (active)	4372401	2012-09-24 01:57:29
image1 (backup)	0	

---

## restore-defaults

---

**Syntax** **restore-defaults [interfaces *IF\_PORTS*]**

---

**Parameter** **interfaces *IF\_PORTS*** Specify port to restore its’ running config

---

**Default** No default value for this command.

---

**Mode** Privileged EXEC



**Usage**

Use “**restore-defaults**” command to restore factory default of all system. The command is equal to “**delete startup-config**”,

**Example**

This example shows how to restore factory defaults.

```
Switch# restore-defaults
Restore Default Success. Do you want to reboot now? (y/n)n
```

---

**save**

**Syntax**

**save**

**Parameter**

**Default**

No default value for this command.

**Mode**

Privileged EXEC

**Usage**

Use “**save**” command to save running configuration to startup configuration file. This command is equal to “**copy running-config startup-config**”.

**Example**

This example shows how to save running configuration to startup configuration.

```
Switch# save
Success
```

This example shows how to show startup configuration

```
Switch# show startup-config
! System Description: RTK RTL8328-24FE-4GE Switch
! System Version: v2.5.0-beta.32811
! System Name: SwitchEF0102
! System Up Time: 0 days, 4 hours, 31 mins, 43 secs
!
!
!
!
username "" privilege user secret "dnXencJRwfLV6"
username "admin" secret "FzjrGO6vfbERY"
voice-vlan vpt 0
voice-vlan dscp 0
.....
```

---

**show bootvar**

**Syntax**

**show bootvar**



**Parameter**

**Default** No default value for this command.

**Mode** Privileged EXEC

**Usage** Use “**show bootvar**” command to show image information in both flash partitions. It also shows current active image and active image on next booting.

**Example** This example shows how to show dual image information

```
Switch# show bootvar
Image Version Date Status File Name
---- ----- -----
0 3.0.5 2014-09-22 16:53:53 Active v3.0.5.bix
1 3.1.0 2014-10-09 18:32:26 Not active* v3.1.0.bix
```

## show config

**Syntax**

**show (running-config | startup-config | backup-config)**

**show running-config interfaces *IF\_PORTS***

**Parameter**

**running-config** Show running configuration on terminal

**startup-config** Show startup configuration on terminal

**backup-config** Show backup configuration on terminal

***IF\_PORTS*** Specify port to show its’ running config

**Default**

No default value for this command.

**Mode**

Privileged EXEC

**Usage**

Our configuration file is text based. Therefore, we can show the configuration on terminal and read it by this command.

Use “**show config**” command to show configuration files stored in system. Use “**show config interfaces**” command to show specific port configurations.



### Example

This example shows how to show startup configuration

```
Switch# show startup-config
! System Description: RTK RTL8328-24FE-4GE Switch
! System Version: v2.5.0-beta.32811
! System Name: SwitchEF0102
! System Up Time: 0 days, 4 hours, 31 mins, 43 secs
!
!
!
!
username "" privilege user secret "dnXencJRWflV6"
username "admin" secret "FzjrGO6vfbERY"
voice-vlan vpt 0
voice-vlan dscp 0
.....
```

This example shows how to show running configuration

```
Switch# show running-config
! System Description: RTK RTL8328-24FE-4GE Switch
! System Version: v2.5.0-beta.32811
! System Name: SwitchEF0102
! System Up Time: 0 days, 5 hours, 23 mins, 42 secs
!
!
!
!
username "" privilege user secret "dnXencJRWflV6"
username "admin" secret "FzjrGO6vfbERY"
voice-vlan vpt 0
voice-vlan dscp 0
.....
```

This example shows how to display running configuration on specific port.

```
Switch# show running-config interfaces g1
interface g1
    rate-limit ingress 128
```

## show flash

### Syntax

**show flash**

### Parameter

### Default

No default value for this command.

### Mode

Privileged EXEC

### Usage

Use “**show flash**” command to show all files’ status which stored in flash.



**Example**

This example shows how to show all files status stored in flash.

Switch# **show flash**

File Name	File Size	Modified
startup-config	1191	2000-01-01 00:00:23
backup-config	1607	2000-01-01 08:36:23
rsa1	974	2000-01-01 00:00:18
rsa2	1675	2000-01-01 00:00:18
dsa2	668	2000-01-01 00:00:18
ssl_cert	993	2000-01-01 00:00:18
image0 (active)	4372401	2012-09-24 01:57:29
image1 (backup)	0	

## 32. Surveillance VLAN

### surveillance-vlan (Global)

**Syntax**

**surveillance-vlan**

**no surveillance -vlan**

**Parameter**

**Default**

Surveillance VLAN is disabled

**Mode**

Global Configuration

**Usage**

Use the **surveillance vlan** global configuration command to enable the functional Surveillance VLAN on the device.

Use the **no** form of this command to disable Surveillance VLAN function. You can verify your setting by entering the **show surveillance vlan Privileged EXEC** command.

**Example**

The following example shows how to enable Surveillance VLAN.

Switch(config)# **surveillance -vlan**

Switch# **show surveillance -vlan**

Administratve Surveillance VLAN state : disabled

Surveillance VLAN ID : none (disable)

Surveillance VLAN Aging : 1440 minutes

Surveillance VLAN CoS 6

Surveillance VLAN 1p Remark: disabled

### surveillance-vlan (Interface)

**Syntax**

**surveillance-vlan**

**no surveillance-vlan**

**Parameter**

N/A



<b>Default</b>	Disable by default.																				
<b>Mode</b>	Interface Configuration																				
<b>Usage</b>	<p>Use the <b>surveillance vlan</b> Interface configuration command to enable OUI surveillance VLAN configuration on an interface Use the <b>no</b> form of this command to disable Surveillance VLAN on an interfaces You can verify your setting by entering the <b>show surveillance vlan</b> Privileged EXEC command</p>																				
<b>Example</b>	<p>The following example how to enable Surveillance VLAN function in oui mode on an interface</p> <pre>Switch(config)#interface range fa1-3 Switch(config-if)#surveillance-vlan Switch# show surveillance-vlan interfaces fa1-3 Surveillance VLAN Aging : 1440 minutes Surveillance VLAN CoS    7 Surveillance VLAN 1p Remark: enabled</pre> <p>OUI table</p> <table><thead><tr><th>OUI MAC</th><th>Description</th></tr></thead><tbody><tr><td>00:01:02</td><td>  Test</td></tr></tbody></table> <hr/> <table><thead><tr><th>Port</th><th>State</th><th>Port Mode</th><th>Cos Mode</th></tr></thead><tbody><tr><td>fa1</td><td>Disabled</td><td>Auto</td><td>Src</td></tr><tr><td>fa2</td><td>Disabled</td><td>Auto</td><td>Src</td></tr><tr><td>fa3</td><td>Disabled</td><td>Auto</td><td>Src</td></tr></tbody></table>	OUI MAC	Description	00:01:02	Test	Port	State	Port Mode	Cos Mode	fa1	Disabled	Auto	Src	fa2	Disabled	Auto	Src	fa3	Disabled	Auto	Src
OUI MAC	Description																				
00:01:02	Test																				
Port	State	Port Mode	Cos Mode																		
fa1	Disabled	Auto	Src																		
fa2	Disabled	Auto	Src																		
fa3	Disabled	Auto	Src																		

## surveillance-vlan vlan

<b>Syntax</b>	<b>surveillance-vlan vlan &lt;1-4094&gt;</b> <b>no surveillance-vlan vlan</b>
<b>Parameter</b>	<b>&lt;1-4094&gt;</b> Specify the Surveillance VLAN ID
<b>Default</b>	The default Surveillance VLAN ID is None.



---

Mode	Global Configuration
Usage	<p>Use the <b>surveillance vlan id</b> global configuration command to configure the VLAN identifier of the surveillance VLAN statically.</p> <p>Use the <b>no</b> form of this command to restore surveillance VLAN id to default. You can verify your setting by entering the <b>show surveillance vlan Privileged EXEC</b> command</p>
Example	<p>The following example shows how to set Surveillance VLAN id. The VLAN id must be created first.</p> <pre>Switch(config)# surveillance-vlan vlan 128 Switch# show surveillance-vlan Administratve Surveillance VLAN state : enabled Surveillance VLAN ID      128 Surveillance VLAN Aging   : 1440 minutes Surveillance VLAN CoS     6 Surveillance VLAN 1p Remark: disabled</pre>

## surveillance-vlan oui-table

---

Syntax	<b>surveillance-vlan oui-table A:B:C [DESCRIPTION]</b> <b>no surveillance-vlan oui-table [A:B:C]</b>				
Parameter	<table><tr><td>A:B:C</td><td>Specify OUI Mac address to add or remove</td></tr><tr><td>DESCRIPTION</td><td>Specify description of the specified MAC address to the surveillance VLAN OUI table</td></tr></table>	A:B:C	Specify OUI Mac address to add or remove	DESCRIPTION	Specify description of the specified MAC address to the surveillance VLAN OUI table
A:B:C	Specify OUI Mac address to add or remove				
DESCRIPTION	Specify description of the specified MAC address to the surveillance VLAN OUI table				
Default	Default has no pre-defined OUI.				
Mode	Global Configuration				
Usage	<p>Use the <b>surveillance vlan oui-table</b> global configuration command to add OUI mac address to OUI Table</p> <p>Use the <b>no</b> form of this command to remove all or specified OUI mac address..</p> <p>You can verify your setting by entering the <b>show surveillance vlan Privileged EXEC</b> command</p>				
Example	<p>This following example shows how to add OUI Mac.</p> <pre>Switch(config)# surveillance-vlan oui-table 00:01:02 "Test" Switch# show surveillance-vlan interfaces fa1-3 Surveillance VLAN Aging   : 1440 minutes Surveillance VLAN CoS     : 6</pre>				



---

Surveillance VLAN 1p Remark: disabled

OUI table  
  OUI MAC | Description  
-----+-----  
  00:01:02 | Test

Port	State	Port Mode	Cos Mode
fa1	Disabled	Auto	
Src fa2			
Disabled		Auto	
Src			
fa3	Disabled	Auto	Src

---

## **surveillance-vlan cos (Global)**

---

### Syntax

**surveillance-vlan cos <0-7> [remark]**  
**no surveillance-vlan cos**

---

### Parameter

<0-7>	Specify the surveillance VLAN Class of Service value in telephone OUI mode
remark	Specify that the L2 user priority is remarked with the CoS value

---

---

### Default

The default cos value is 6, remark is disabled.

---

### Mode

Global Configuration

---

### Usage

Use the **surveillance vlan cos** global configurations command to configure the surveillance VLAN cos value and 1p remark function.  
Use the “**no**” form to restore to default mode.  
You can verify your setting by entering the **show surveillance vlan Privileged EXEC** command

---

### Example

The following example show how to set cos value and enable 1p remark function

```
Switch(config)# surveillance-vlan cos 7 remark
Switch# show surveillance-vlan
Administate Surveillance VLAN state : disabled
Surveillance VLAN ID      128
Surveillance VLAN Aging   : 1440 minutes
Surveillance VLAN CoS     7
Surveillance VLAN 1p Remark: enabled
```

---



**surveillance-vlan cos (Interface)**



**Syntax**

```
surveillance-vlan cos ( src | all )
no surveillance-vlan cos
```

**Parameter**

src	Specify QoS attributes are applied to packets with OUIs in the source MAC address.
All	Specify QoS attributes are applied to packets that are classified to the Surveillance VLAN.

**Default**

The default all port in Src mode.

**Mode**

Interface configuration

**Usage**

Use the **surveillance vlan cos mode** Interface configuration command to configure OUI surveillance VLAN cos mode configuration on an interface. Use the “**no**” form to restore to default mode. You can verify your setting by entering the **show surveillance-vlan interfaces Privileged EXEC** command

**Example**

The following example how to configure surveillance packet QoS attributes on an interface

```
Switch(config)#interface range fa1-3
Switch(config-if)#surveillance-vlan cos all
Switch# show surveillance-vlan interfaces fa1-3
Surveillance VLAN Aging : 1440 minutes
Surveillance VLAN CoS 7
Surveillance VLAN 1p Remark: enabled
```

OOUI table

OUI MAC	Description
00:01:02	Test

Port	State	Port Mode	Cos Mode
------	-------	-----------	----------

fa1	Disabled	Auto	All
fa2	Disabled	Auto	All
fa3	Disabled	Auto	All

## surveillance-vlan mode

**Syntax**

```
surveillance-vlan mode
(auto|manual) no
surveillance-vlan mode
```



## Command Line Interface User Guide

<b>Parameter</b>	<b>auto</b>	Specifies that the port is identified as a candidate to join
------------------	-------------	--



[www.cerio.com.tw](http://www.cerio.com.tw)



+[\(886\) 2-8911-6160](tel:+886289116160)



[service@cerio.com.tw](mailto:service@cerio.com.tw)

the surveillance VLAN. When a packet with a source OUI MAC address that identifies the remote equipment as surveillance equipment is seen on the port, the port joins the surveillance VLAN as a tagged port.

---

<b>manual</b>	Specifies that the port is manually assigned to the surveillance VLAN.
---------------	--

---

<b>Default</b>	The default is auto mode.
----------------	---------------------------

<b>Mode</b>	Interface Configuration
-------------	-------------------------

<b>Usage</b>	Use the <b>surveillance-vlan mode</b> global configuration command to configure the surveillance VLAN mode for interface. Use the “ <b>no</b> ” form to restore to default mode. You can verify your setting by entering the <b>show surveillance-vlan interfaces Privileged EXEC</b> command.
--------------	--

<b>Example</b>	The following example how to configure surveillance mode to manual Switch(config)# <b>interface range fa1-3</b> Switch(config-if)# <b>surveillance-vlan mode manual</b> Switch# <b>show surveillance-vlan interfaces fa1-3</b> Surveillance VLAN Aging : 1440 minutes Surveillance VLAN CoS 7 Surveillance VLAN 1p Remark: enabled
----------------	--

OUI table
OUI MAC   Description

---

Port	State	Port Mode	Cos Mode
fa1	Enabled	Manual	Src
fa2	Enabled	Manual	Src
fa3	Enabled	Manual	Src

---

## **surveillance-vlan aging-time**

---

<b>Syntax</b>	<b>surveillance-vlan aing-time &lt;30-65536&gt;</b> <b>no surveillance-vlan aing-time</b>
---------------	--

---

<b>Parameter</b>	<b>&lt;30-65536&gt;</b>	Specify the Surveillance VLAN aging timeout interval in minutes
------------------	-------------------------	---

---



---

**Default** The default aging-timeout value is 1440 minutes

---

**Mode** Global Configuration

---

**Usage** Use the **surveillance vlan aging-time** global configuration command to configure the surveillance VLAN aging timeout.  
Use the “**no**” form to restore to default time.  
You can verify your setting by entering the **show surveillance vlan Privileged EXEC** command

---

**Example** The following example shows how to set aging time.  
Switch(config)# **surveillance-vlan aging-time 720**  
Switch# **show surveillance-vlan**  
Administate Surveillance VLAN state : disabled  
Surveillance VLAN ID 1  
Surveillance VLAN Aging : 720 minutes  
Surveillance VLAN CoS 5  
Surveillance VLAN 1p Remark: enabled

---

## **show surveillance-vlan**

---

**Syntax** **show surveillance-vlan**  
**show surveillance-vlan interfaces [IF\_PORTS]**

---

**Parameter** **IF\_PORTS** Specifies interfaces to display surveillance VLAN settings in OUI mode

---

---

**Default** N/A

---

**Mode** Privileged EXEC

---

**Usage** Use the **show surveillance vlan** command in EXEC mode to display the surveillance VLAN status for all interfaces or for a specific interface if the surveillance VLAN type is OUI



**Example**

The following example show how to display surveillance vlan OUI mode settings

```
Switch# show surveillance-vlan
Administratve Surveillance VLAN state : disabled
Surveillance VLAN ID    : none (disable)
Surveillance VLAN Aging : 720 minutes
Surveillance VLAN CoS   : 6
Surveillance VLAN 1p Remark: disabled
```

```
Switch# show surveillance-vlan interfaces fa1-4
Surveillance VLAN Aging : 720 minutes
Surveillance VLAN CoS   : 5
Surveillance VLAN 1p Remark: enabled
```

OOUI table

OUI MAC	Description
00:01:02	Test

Port	State	Port Mode	Cos Mode
fa1	Disabled	Auto	Src
fa2	Disabled	Auto	Src
fa3	Disabled	Auto	Src

## 33. Time

### clock set

**Syntax**

**clock set HH:MM:SS (jan|feb|mar|apr|may|jun|jul|aug|sep|oct|nov|dec)  
<1-31> <2000-2035>**

**Parameter**

**HH:MM:SS**      Specify static time of year, month, day, hour, minute, second  
**(jan|feb|mar|apr|may|jun|jul|aug|sep|oct|nov|dec)**  
**<1-31> <2000-2035>**

**Default**

No default is defined.

The clock set to 2000/01/01 08:00:00 by default at startup.

**Mode**

Privileged EXEC



---

**Usage**

Use the **clock set** command to set static time. The static time won't save to configuration file.  
You can verify your setting by entering the **show clock Privileged EXEC** command.

---

**Example**

The example shows how to set static time of switch.

```
switch# clock set 11:03:00 sep 21 2012
11:03:00 DFL(UTC+8) Sep 21 2012
```

```
switch# show clock
11:03:21 DFL(UTC+8) Sep 21 2012
No time source
```

---

## **clock timezone**

---

**Syntax**

**clock timezone ACRONYM HOUR-OFFSET [minutes <0-59>]**  
**no clock timezone**

---

**Parameter**

<b>ACRONYM</b>	Specify acronym name of time zone
<b>HOUR-OFFSET</b>	Specify hour offset of time zone
<b>Minutes &lt;1-59&gt;</b>	Specify minute offset of time zone

---

---

**Default**

Default time zone is UTC+8.

---

**Mode**

Global Configuration

---

**Usage**

Use the **clock timezone** command to set timezone setting.  
Use the **no** form of this command to restore to default setting.  
You can verify your setting by entering the **show clock detail Privileged EXEC** command.

---

**Example**

The example shows how to set time zone of switch and then restore to default time zone.

```
switch(config)# clock timezone test +5
switch(config)# show clock detail
10:13:27 test(UTC+5) Sep 21 2012
No time source
```

Time zone:

Acronym is test

Offset is UTC+5

```
switch(config)# no clock timezone
switch(config)# show clock detail
```

---



13:14:50 DFL(UTC+8) Sep 21 2012  
No time source

Time zone:  
Acronym is  
DFL Offset  
is UTC+8

---

## **clock source**

---

### Syntax

**clock source (local|snntp)**

---

### Parameter

<b>local</b>	Specify to use static time
<b>snntp</b>	Specify to use snntp time

---

### Default

Default is using local time.

---

### Mode

Global Configuration

---

### Usage

Use the **clock source** command to set the source of time.  
Use the no form of this command to restore to default setting.  
You can verify your setting by entering the **show clock detail** **Privileged EXEC** command.

---

### Example

The example shows how to set clock source of switch.

```
switch(config)# clock source snntp
switch(config)# show clock detail
08:32:12 test(UTC+5) Sep 21 2012
Time source is snntp
```

Time zone:  
Acronym is DFL  
Offset is UTC+8

---

## **clock summer-time**



# Command Line Interface

## User Guide

---

### Syntax

```
clock summer-time ACRONYM date
(jan|feb|mar|apr|may|jun|jul|aug|sep|oct|nov|dec) <1-31> <2000-2037>
HH:MM (jan|feb|mar|apr|may|jun|jul|aug|sep|oct|nov|dec) <1-31> <2000-
2037> HH:MM [<1-1440>]
clock summer-time ACRONYM recurring (usa|eu) [<1-1440>]
clock summer-time ACRONYM recurring (<1-5>|first|last)
```

---



(sun|mon|tue|wed|thu|fri|sat)  
 (jan|feb|mar|apr|may|jun|jul|aug|sep|oct|nov|dec) HH:MM (<1-  
 5>|first|last) (sun|mon|tue|wed|thu|fri|sat)  
 (jan|feb|mar|apr|may|jun|jul|aug|sep|oct|nov|dec) HH:MM [<1-1440>]  
 no clock summer-time

<b>Parameter</b>	<b>ACRONYM</b>	Specify acronym name of time zone
	(jan feb mar apr  may jun jul aug sep  oct nov dec) <1-31> <2000-2037> HH:MM	Specify non-recurring daylight saving time duration.
	(jan feb mar apr  may jun jul aug sep  oct nov dec) <1-31> <2000- 2037> HH:MM	
	<1-1440>	Specify adjust offset of daylight saving time
	usa	Using daylight saving time in the United States that starts on the second Sunday of March and ends on the first Sunday of November
	eu	Using daylight saving time in the Europe that starts on the last Sunday in March and ending on the last Sunday in October
	(<1-5> first last) (sun mon  tue wed thu fri sat) (jan  feb mar apr may jun  jul aug sep oct nov dec) HH:MM (<1-5> first last) (sun mon tue wed thu fri sat) (jan feb mar apr may  jun jul aug sep oct nov dec) HH:MM	Specify recurring daylight saving time duration.
<b>Default</b>	No default daylight saving time is defined.	
<b>Mode</b>	Global Configuration	
<b>Usage</b>	<p>Use the <b>clock summer-time</b> command to set daylight saving time for system time. The “usa” or “eu” means that use the global daylight saving policy which defined by international organization. In both the “date” and “recurring”, the first part of the command specifies when summer time begins, and the second part specifies when it ends. All times are relative to the local time zone. The “recurring” means that adjust time every year within the month.</p> <p>Use the no form of this command to default setting.</p> <p>You can verify your setting by entering the <b>show clock detail Privileged EXEC</b> command.</p>	



**Example**

The example shows how to set clock summer time of switch. You can verify settings by the following show show clock command.

```
switch(config)# clock summer-time test recurring usa
switch(config)# show clock detail
08:32:12 test(UTC+5) Sep 21 2012
No time source
```

Time zone:

Acronym is DFL  
Offset is UTC+8

Summertime:

Acronym is test  
Recurring every year.  
Begins at 2 0 3 2:0  
Ends at 1 0 11 2:0  
Offset is 60 minutes.

---

## show clock

**Syntax**

**show clock [detail]**

**Parameter**

detail	Show more detail information of clock
--------	---------------------------------------

**Default**

No default is defined

**Mode**

Privileged EXEC

**Usage**

Use the **show clock** command to show clock of switch. The “**detail**” means that show more information of clock such as time zone and daylight saving time.

**Example**

The example shows how to show clock of switch and detail information.

```
Switch334455(config)# clock source sntp
Switch334455(config)# clock summer-time DLS recurring usa
Switch334455(config)# sntp host 192.168.1.100
Switch334455(config)# show clock
14:34:43 DLS(UTC+9) Sep 25 2012
Time source is sntp
```

```
Switch334455(config)# show clock detail
14:35:39 DLS(UTC+9) Sep 25 2012
```

---



Time source is sntp

Time zone:  
Acronym is  
DFL Offset  
is UTC+8

Summertime:  
Acronym is DLS  
Recurring every  
year. Begins at 2 0  
3 2:0  
Ends at 1 0 11  
2:0 Offset is 60  
minutes.

---

## sntp

---

### Syntax

**sntp host HOSTNAME [port <1-65535>]**  
**no sntp**

---

### Parameter

<b>HOSTNAME</b>	Specify ip address or hostname of sntp server
<b>sntp</b>	Specify server port of sntp server

---

### Default

No default SNTP server defined. Default server port is 123 when server created.

---

### Mode

Global Configuration

---

### Usage

Use the sntp command to set remote SNTP server. Use the no form of this command to default setting.  
You can verify your setting by entering the **show sntp Privileged EXEC** command.

---

### Example

The example shows how to set remote SNTP server of switch.

```
switch(config)# clock source sntp
switch(config)# sntp host 192.168.1.100
switch(config)# show sntp
SNTP is Enabled
SNTP Server address: 192.168.1.100
SNTP Server port: 123
```

---

## show sntp



## Command Line Interface User Guide

---

**Syntax**      **show sntp**

---

**Parameter**      **None**

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+(886) 2-8911-6160



[service@cerio.com.tw](mailto:service@cerio.com.tw)

<b>Default</b>	No default is defined
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Use the <b>show sntp</b> command to remote SNTP server information.

---

**Example** The example shows how to show remote SNTP server.

```
Switch334455(config)# show sntp
SNTP is Enabled
SNTP Server address: 192.168.1.100
SNTP Server port: 123
```

---

## 34. UDLD

### errdisable recovery cause udld

<b>Syntax</b>	<b>errdisable recovery cause udld</b> <b>no errdisable recovery cause udld</b>
<b>Parameter</b>	<b>N/A</b>
<b>Default</b>	Error disable auto recovery is disabled by default.
<b>Mode</b>	Global EXEC
<b>Usage</b>	Use the <b>errdisable recovery cause udld</b> to enable auto recovery of UniDirectional Link Detection (UDLD). Use the “ <b>no</b> ” to disable it.
<b>Example</b>	The example shows how to enable auto recovery of UniDirectional Link Detection (UDLD).
	<pre>switch(config)# errdisable recovery cause udld switch# show errdisable recovery ErrDisable Reason Timer Status -----+ bpduguard   disabled</pre>



---

udld	enabled
...	

---

## udld

---

### Syntax

**udld**  
**no udld**

---

---

### Parameter

**N/A**

---

---

### Default

UDLD is disabled by default.

---

---

### Mode

Interface Configuration

---

---

### Usage

Use the **udld** command to enable UniDirectional Link Detection (UDLD) normal mode of interface.

Use the no form of this command to restore to default setting.

You can verify your setting by entering the **show udld interface Privileged EXEC** command.

---

---

### Example

The example shows how to enable UniDirectional Link Detection (UDLD) normal mode in interface gi1.

```
switch(config)# interface gi1
switch(config-if)# udld
switch# show udld interfaces gi1
Port enable administrative configuration setting: Enabled
Port enable operational state: Enabled
Current bidirectional state: Bidirectional
Current operational state: Advertisement - SINGLE NEIGHBOR
DETECTED
```

---

## udld aggressive

---

### Syntax

**udld**  
**aggressive no**  
**udld**  
**aggressive**

---

---

### Parameter

**N/A**

---

---

### Default

UDLD aggressive mode is disabled by default.

---



---

<b>Mode</b>	Interface Configuration
-------------	-------------------------

---

<b>Usage</b>	<p>Use the <b>udld aggressive</b> command to enable UniDirectional Link Detection (UDLD) aggressive mode of interface.</p> <p>Use the no form of this command to restore to default setting.</p> <p>You can verify your setting by entering the <b>show udld interface Privileged EXEC</b> command.</p>
--------------	---

---

<b>Example</b>	The example shows how to enable udld aggressive mode in interface gi1.
----------------	--

```
switch(config)# interface gi1
switch(config-if)# udld
switch# show udld interfaces gi1
Port enable administrative configuration setting: Enabled / in aggressive mode
Port enable operational state: Enabled / in aggressive mode
Current bidirectional state: Bidirectional
Current operational state: Advertisement - SINGLE NEIGHBOR
DETECTED
```

---

## udld message time

---

<b>Syntax</b>	<b>udld message time</b> <i>message-time-interval</i>
---------------	---

---

<b>Parameter</b>	<i>message-time-interval</i> Specify the interval for sending message. Range is 1 -90 seconds.
------------------	---

---

<b>Default</b>	Default interval is 15 seconds.
----------------	---------------------------------

---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

<b>Usage</b>	Use the <b>udld message time</b> to set interval of UniDirectional Link Detection (UDLD) sent message.
--------------	--

---

<b>Example</b>	The example shows how to set interval of UniDirectional Link Detection (UDLD) message.
----------------	--

```
switch(config)# udld message time 30
```

---



## **udld reset**

<b>Syntax</b>	<b>udld reset</b>
<b>Parameter</b>	<u>N/A</u>
<b>Default</b>	No default is defined
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	<p>Use the <b>udld reset</b> command to reset all interfaces disabled by the UniDirectional Link Detection (UDLD) and permit traffic to begin passing through them again.</p> <p>If the interface configuration is still enabled for UDLD, these ports begin to run UDLD again and are disabled for the same reason if the problem has not been corrected.</p>
<b>Example</b>	<p>The example shows how to reset all interfaces disabled by UDLD</p> <pre>Switch# udld reset 1 ports shutdown by UDLD were reset.</pre>

## **show udld**

<b>Syntax</b>	<b>show udld</b> <b>show udld interfaces <i>IF_NMLPORTS</i></b>
<b>Parameter</b>	<i>IF_NMLPORTS</i> Specify the normal interfaces to display udld information
<b>Default</b>	No default is defined
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	<p>Use the <b>show udld</b> command to display UniDirectional Link Detection (UDLD) administrative and operational status for all ports or the specified port.</p>
<b>Example</b>	<p>The example shows how to show UniDirectional Link Detection (UDLD) settings and operational status of interface gi1.</p>



```
Switch334455(config)# show udld interfaces gi1
Interface gi1
---
Port enable administrative configuration setting: Enabled / in aggressive mode
Port enable operational state: Enabled / in aggressive mode
Current bidirectional state: Bidirectional
Current operational state: Advertisement - SINGLE
NEIGHBOR DETECTED
Message interval:
15 Time out
interval: 5

Entry 1
---
Expiration time: 20
Current neighbor state:
Bidirectional Device ID : COM4
Device name:
com4 Port ID:
gi3 Message
interval: 7 Time
out interval: 5
Neighbor echo 1 device:
COM3 Neighbor echo 1 port:
gi11
```

---

## 35. VLAN

### vlan

---

#### Syntax

**vlan**  
**no vlan**

---

#### Default

VLAN 1 created by default

---

#### Mode

Global Configuration

---

#### Usage

Use the **vlan** global configuration command to create VLAN. Use the **no** form of this command to remove exist VLAN.  
You can verify your setting by entering the **show vlan Privileged EXEC** command.

---



## Command Line Interface User Guide

---

### Example

The following example creates and removes a VLAN entry (100).

```
Switch# configure
Switch (config)# vlan 100
Switch# show vlan
```

---



VID   VLAN Name   Untagged Ports   Tagged Ports   Type
1   default   fa1-48,gi1-4,lag1-8   ---   ---
Default 100   VLAN0100   ---   ---   Static

## Name (vlan)

### Syntax

**name NAME**

### Parameter

NAME	Specify the name of the VLAN (Max. 32 chars).
------	---

### Default

Default name of new vlan is VLANxxxx. Xxxx is 4-digit vlan number.

### Mode

VLAN Configuration

### Usage

Use the **name** vlan configuration command to set name of vlan  
You can verify your setting by entering the **show vlan Privileged EXEC** command.

### Example

This example sets the VLAN name of VLAN 100 to be 'VLAN-one-hundred'.

```
SwitchEF0101(config)# vlan 100
SwitchEF0101(config-vlan)# name VLAN-one-hundred
Switch# show vlan
VID | VLAN Name | Untagged Ports | Tagged Ports | Type
-----+-----+-----+-----+-----+
1 | default | fa1-48,gi1-4,lag1-8 | --- | Default
100 | VLAN-one-hundred | --- | --- | Static
```

## switchport mode

### Syntax

**switchport mode ( access | hybrid | trunk [uplink] | tunnel )**

### Parameter

access	Specify the VLAN mode to Access port.
hybrid	Specify the VLAN mode to Hybrid port.
trunk	Specify the VLAN mode to Trunk port.
uplink	Specify the Uplink property on this Trunk port.
tunnel	Specify the VLAN mode to Dot1Q Tunnel port.

### Default

Default is trunk mode of all interfaces



<b>Mode</b>	Port Configuration
<b>Usage</b>	<p>The VLAN mode is used to configure the port for different port role.</p> <p><b>Access port:</b> Accepts only untagged frames and join an untagged VLAN.</p> <p><b>Hybrid port:</b> Support all functions as defined in IEEE 802.1Q specification.</p> <p><b>Trunk port:</b> An untagged member of one VLAN at most, and is a tagged member of zero or more VLANs. If it is an uplink port, it can recognize double tagging on this port.</p> <p><b>Tunnel port:</b> Port-based Q-in-Q mode.</p>
	<p>Use the <b>switch mode</b> port configuration command to set mode of interface You can verify your setting by entering the <b>show interfaces switchport Privileged EXEC</b> command.</p>
<b>Example</b>	<p>This example sets VLAN mode to Access port.</p> <pre>SwitchEF0101(config)# interface fa12 SwitchEF0101(config-if)# switchport mode access SwitchEF0101# show interfaces switchport fa12 Port : fa12 Port Mode : Access Ingress Filtering : enabled Acceptable Frame Type : untagged-only Ingress UnTagged VLAN ( NATIVE ) : 1 Trunking VLANs Enabled:  Port is member in: Vlan   Name   Egress rule ----- 1    default   Untagged  Forbidden VLANs: Vlan   Name ----- SwitchEF0101#</pre>
	<h3><b>switchport hybrid pvid</b></h3>
<b>Syntax</b>	<b>switchport hybrid pvid &lt;1-4094&gt;</b>
<b>Parameter</b>	<b>&lt;1-4094&gt;</b> Specify the port-based VLAN ID on the Hybrid port.
<b>Default</b>	Default pivd is 1.



---

**Mode** Port Configuration

---

**Usage** Use the **switch hybrid pvid** port configuration command to set pvid of interface.  
You can verify your setting by entering the **show interfaces switchport Privileged EXEC** command.

---

**Example** This example sets PVID to 100.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport mode hybrid
SwitchEF0101(config-if)# switchport hybrid pvid 100
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Hybrid
Ingress Filtering : enabled
Acceptable Frame Type : all
Ingress UnTagged VLAN ( NATIVE ) : 100
Trunking VLANs Enabled:
```

```
Port is member in:
Vlan Name Egress rule
-----
1 default Untagged
```

```
Forbidden VLANs:
Vlan Name
```

---

```
SwitchEF0101#
```

## **switchport hybrid ingress-filtering**

---

**Syntax** **switchport hybrid**  
**ingress-filtering no switchport**  
**hybrid ingress-filtering**

---

**Default** Default is enabled

---

**Mode** Port Configuration

---

**Usage** Use the **switchport hybrid ingress-filtering** port configuration command to enable vlan ingress filter.  
Use the **no** form of this command to disable.



You can verify your setting by entering the **s show interfaces switchport Privileged EXEC** command.

---

**Example**

This example sets ingress-filtering to disable.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport mode hybrid
SwitchEF0101(config-if)#no switchport hybrid ingress-filtering
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Hybrid
Ingress Filtering : disabled
Acceptable Frame Type : all
Ingress UnTagged VLAN ( NATIVE ) : 100
Trunking VLANs Enabled:

Port is member in:
Vlan Name Egress rule
-----
1 default Untagged

Forbidden VLANs:
Vlan Name

SwitchEF0101#
```

---

## switchport hybrid acceptable-frame-type

---

**Syntax**

**switchport hybrid acceptable-frame-type ( all | tagged-only | untagged-only )**

---

**Parameter**

all	Specify to accept all frames.
tagged-only	Specify to only accept tagged frames.
untagged-only	Specify to only accept untagged frames.

---

---

**Default**

Default is accept all frames

---

**Mode**

Port Configuration

---

**Usage**

Use the **switchport hybrid acceptable-frame-type** port configuration command to choose which type of frame can be accepted.

You can verify your setting by entering the **s show interfaces switchport Privileged EXEC** command



---

**Example**

This example sets acceptable-frame-type to tagged-only.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport mode hybrid
SwitchEF0101(config-if)# switchport hybrid acceptable-frame-type tagged-only
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Nybrid
Ingress Filtering : disabled
Acceptable Frame Type : tagged-only
Ingress UnTagged VLAN ( NATIVE ) : 100
Trunking VLANs Enabled:

Port is member in:
Vlan Name Egress rule
-----
1 default Untagged

Forbidden VLANs:
Vlan Name

SwitchEF0101#
```

---

## **switchport hybrid allowed vlan**

---

**Syntax**

**switchport hybrid allowed vlan add VLAN-LIST [(tagged|untagged)]**  
**switchport hybrid allowed vlan remove VLAN-LIST**

---

**Parameter**

<b>VLAN-LIST</b>	Specifies the VLAN list to be added or removed.
( tagged   untagged )	Specifies the member type is tagged or untagged.

---

---

**Default**

Only vlan 1 is untagged member by default.  
Default is tagged member when added.

---

**Mode**

Port Configuration

---

**Usage**

Use the **switchport hybrid allow vlan add** port configuration command to allow vlan on interface.  
Use the **switchport hybrid allow vlan remove** port configuration command to remove vlan on interface.  
You can verify your setting by entering the **s show interfaces switchport Privileged EXEC** command.



---

**Example**

This example sets port fa10 VLAN to join the VLAN 100 as tagged member.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport hybrid allowed vlan add 100-105
SwitchEF0101(config-if)# switchport hybrid allowed vlan remove 105
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Hybrid
Ingress Filtering : disabled
Acceptable Frame Type : tagged-only
Ingress UnTagged VLAN ( NATIVE ) : 100
Trunking VLANs Enabled:
```

Port is member in:

Vlan	Name	Egress rule
------	------	-------------

---

1	default	Untagged
100	VLAN-one-hundred	Tagged
101	VLAN0101	Tagged
102	VLAN0102	Tagged
103	VLAN0103	Tagged
104	VLAN0104	Tagged

Forbidden VLANs:

Vlan	Name
------	------

---

---

SwitchEF0101#

## **switchport access vlan**

---

**Syntax**

**switchport access vlan**  
**<1-4094> No switchport**  
**access vlan**

---

---

**Parameter**

**<1-4094>** Specifies the access VLAN ID.

---

---

**Default**

Default is vlan 1

---

**Mode**

Port Configuration

---

**Usage**

Use the **switchport access vlan** port configuration command to set native vlan on interface. The vlan will be pvid on interface as well.

Use the **no** form of this command to restore to default vlan

You can verify your setting by entering the **s show interfaces switchport Privileged EXEC** command.



**Example**

This example sets Access port fa10 native VLAN ID to 100.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport mode access
SwitchEF0101(config-if)# switchport access vlan 100
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Access
Ingress Filtering : enabled
Acceptable Frame Type : untagged-only
Ingress UnTagged VLAN ( NATIVE ) : 100
Trunking VLANs Enabled:

Port is member in:
Vlan Name          Egress rule
-----
100 VLAN-one-hundred Untagged
```

Forbidden VLANs:

```
Vlan Name
```

## switchport tunnel vlan

**Syntax**

```
switchport tunnel vlan
<1-4094> no switchport
tunnel vlan
```

**Parameter**

```
<1-4094>           Specifies the tunnel VLAN ID.
```

**Default**

Default is vlan 1

**Mode**

Port Configuration

**Usage**

Use the **switchport tunnel vlan** port configuration command to set dot1q tunnel vlan on interface. The vlan will be pvid on interface as well.

Use the **no** form of this command to remove vlan on interface. The tunnel vlan id will set to reserve vlan 4095.

You can verify your setting by entering the **s show interfaces switchport Privileged EXEC** command.



## Command Line Interface User Guide

### Example

This example sets Tunnel port fa10 native VLAN to 100.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport mode tunnel
SwitchEF0101(config-if)# switchport tunnel vlan 100
```

---



```
SwitchEF0101# show interfaces switchport
fa10 Port : fa10
Port Mode : Tunnel
Ingress Filtering :
enabled
Acceptable Frame Type : all
Ingress UnTagged VLAN ( NATIVE ) :
100 Trunking VLANs Enabled:

Port is member in:
Vlan Name          Egress rule
-----
100 VLAN-one-hundred Untagged

Forbidden
VLANs:
Vlan Name
-----
```

---

## **switchport trunk native vlan**

<b>Syntax</b>	<b>switchport trunk native vlan &lt;1-4094&gt;</b> <b>no switchport trunk native vlan</b>
<b>Parameter</b>	<b>&lt;1-4094&gt;</b> Specifies the native VLAN ID.
<b>Default</b>	Default is vlan 1
<b>Mode</b>	Port Configuration
<b>Usage</b>	Use the <b>switchport trunk native vlan</b> port configuration command to set native vlan on interface. Use the <b>no</b> form of this command to restore to default vlan. You can verify your setting by entering the <b>s show interfaces switchport Privileged EXEC</b> command.



## Command Line Interface User Guide

---

### Example

This example sets Trunk port fa10 native VLAN to 100.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport mode trunk
SwitchEF0101(config-if)# switchport trunk native vlan 100
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Trunk Ingress
Filtering : enabled
Acceptable Frame Type : all
```

---



Ingress UnTagged VLAN ( NATIVE ) :  
100 Trunking VLANs Enabled:

Port is member in:  
Vlan Name                  Egress rule

## 100 VLAN-one-hundred Untagged

Forbidden  
VLANs:  
Vlan Name

## **switchport trunk allowed vlan**

Syntax	switchport trunk allowed vlan ( add   remove ) ( VLAN-LIST   all )
Parameter	( add   remove )      Specify the action to add or remove the allowed VLAN list. ( VLAN-LIST   all )      Specify the VLAN list or all VLANs to be added or removed.
Mode	Port Configuration
Usage	<p>Use the <b>switchport trunk allow vlan add</b> port configuration command to allow vlan on interface.</p> <p>Use the <b>switchport trunk allow vlan remove</b> port configuration command to remove vlan on interface.</p> <p>You can verify your setting by entering the <b>s show interfaces switchport Privileged EXEC</b> command.</p>

# Command Line Interface

## User Guide

---

### Example

This example sets Trunk port fa10 to add the allowed VLAN 100.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport trunk allowed vlan add 100
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Trunk Ingress
Filtering : enabled
Acceptable Frame Type : all
Ingress UnTagged VLAN ( NATIVE ) : 1
Trunking VLANs Enabled: 100
```

Port is member in:

Vlan	Name	Egress rule
1	default	Untagged

---



100 VLAN-one-hundred Tagged

Forbidden  
VLANs:  
Vlan Name

---

## **switchport default-vlan tagged**

---

### Syntax

**switchport default-vlan tagged**  
**no switchport default-vlan tagged**

---

### Parameter

None

---

### Default

Default is untagged

---

### Mode

Port Configuration

---

### Usage

Use the **switchport default vlan tagged** port configuration command to become default vlan tagged member.  
Use the **no switchport default vlan tagged** port configuration command to restore to default  
You can verify your setting by entering the **s show interfaces switchport Privileged EXEC** command

---



# Command Line Interface

## User Guide

### Example

This example sets Trunk port fa10 membership with the default VLAN to tag.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport default-vlan tagged
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Hybrid
Ingress Filtering : enabled
Acceptable Frame Type : all
Ingress UnTagged VLAN( NATIVE ) : 1 Trunking
VLANs Enabled:
```

Port is member in:

Vlan	Name	Egress rule
1	default	Tagged

Forbidden VLANs:

Vlan	Name



## switchport forbidden default-vlan

Syntax	<b>switchport forbidden default-vlan no switchport forbidden default-vlan</b>
Parameter	None
Default	Default is allowed
Mode	Port Configuration
Usage	<p>Use the <b>switchport forbidden default-vlan</b> port configuration command to forbid default-vlan on interface.</p> <p>Use the <b>no switchport forbidden default-vlan</b> port configuration command to restore to default</p> <p>You can verify your setting by entering the <b>s show interfaces switchport Privileged EXEC</b> command</p>
Example	<p>This example sets the membership of the default VLAN with port fa10 to forbidden.</p> <pre>SwitchEF0101(config)# interface fa10 SwitchEF0101(config-if)# switchport forbidden default-vlan SwitchEF0101# show interfaces switchport fa10 Port : fa10 Port Mode : Trunk Ingress Filtering : enabled Acceptable Frame Type : all Ingress UnTagged VLAN ( NATIVE ) : 4095 Trunking VLANs Enabled:  Port is member in: Vlan Name Egress rule ----- Forbiden VLANs: Vlan Name ----- 1 default</pre>

## switchport forbidden vlan



## Command Line Interface User Guide

---

### Syntax

**switchport forbidden vlan ( add | remove ) VLAN-LIST**

---



[www.cerio.com.tw](http://www.cerio.com.tw)



+[\(886\) 2-8911-6160](tel:+886289116160)



[service@cerio.com.tw](mailto:service@cerio.com.tw)

<b>Parameter</b>	(add   remove)      Add or remove forbidden membership. VLAN-LIST      Specify the VLAN list.
<b>Default</b>	No vlan is forbidden by default
<b>Mode</b>	Port Configuration
<b>Usage</b>	<p>Use the <b>switchport forbidden vlan add</b> port configuration command to forbid vlan on interface.</p> <p>Use the <b>switchport forbidden vlan remove</b> port configuration command to accept vlan on interface.</p> <p>You can verify your setting by entering the <b>s show interfaces switchport Privileged EXEC</b> command</p>
<b>Example</b>	<p>This example sets the membership of the VLAN 100 with port fa10 to forbidden.</p> <pre>SwitchEF0101(config)# interface fa10 SwitchEF0101(config-if)# switchport forbidden vlan add 100 SwitchEF0101# show interfaces switchport fa10 Port : fa10 Port Mode : Trunk Ingress Filtering : enabled Acceptable Frame Type : all Ingress UnTagged VLAN ( NATIVE ) : 1 Trunking VLANs Enabled: 100  Port is member in: Vlan   Name      Egress rule ----- 1    default    Untagged  Forbidden VLANs: Vlan  Name ----- 100  VLAN-one-hundred</pre>

## **switchport vlan tpid**

---

### Syntax

**switchport vlan tpid (0x8100|0x88a8|0x9100|0x9200)**



---

<b>Parameter</b>	(0x8100 0x88a8 0x9100 0x9200) Select TPID to set.
<b>Default</b>	Default TPID is 0x8100
<b>Mode</b>	Port Configuration
<b>Usage</b>	<p>Use the <b>switchport vlan tpid</b> port configuration command to set TPID on interface.</p> <p>You can verify your setting by entering the <b>s show running-config Privileged EXEC</b> command</p>
<b>Example</b>	<p>This example sets the TPID to 0x9100 on interface fa10.</p> <pre>SwitchEF0101(config)# interface fa10 SwitchEF0101(config-if)# switchport vlan tpid 0x9100</pre>

---

## management-vlan

---

<b>Syntax</b>	<b>management-vlan vlan</b> <b>&lt;1-4094&gt; no</b> <b>management-vlan</b>
<b>Parameter</b>	<b>&lt;1-4094&gt;</b> Specify the VLAN ID of management-vlan.
<b>Default</b>	Default management vlan is 1.
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>management vlan</b> Global Configuration mode command to set management vlan id. Vlan id must be created first.</p> <p>Use the <b>no</b> form of this command to restore to default setting.</p> <p>You can verify your setting by entering the <b>show management-vlan Privileged EXEC</b> command</p>
<b>Example</b>	<p>(1) The following example specifies that management vlan 2 is created</p> <pre>Switch(config)#vlan 2 Switch(config)# management-vlan vlan 2</pre> <p>(2)The following example specifies that management-vlan is restored to be default VLAN.</p> <pre>Switch(config)# no management-vlan</pre>

---



## show vlan

**Syntax** **show vlan [(VLAN-LIST|dynamic|static)]**

**Parameter** **(VLAN-LIST|dynamic|static)** Specify vlan id to show information or show all static or dynamic vlan entries.

**Default** Nones

**Mode** Privileged EXEC

**Usage** Display information about vlan entry

**Example** The following example specifies that show vlan  
Switch# show vlan

VID	VLAN Name	Untagged Port	Tagged Port	Type
1	default	fa1-8,fa10-48,lag1-8	---	Default
100	VLAN-one-hundred	---	---	Static
101	VLAN0101	---	---	Static
102	VLAN0102	---	---	Static

## show vlan interface membership

**Syntax** **show vlan VLAN-LIST interfaces IF\_PORTS membership**

**Parameter** **<VLAN-List>** Specify vlan to show  
**IF\_PORTS** Specify interface is to show

**Default** Nones

**Mode** Privileged EXEC

**Usage** Display information about vlan membership on interfaces.

**Example** The following example specifies that show vlan interface membership  
Switch# show vlan 100 interfaces fa10 membership

VLAN ID : 100  
VLAN Type : Static



```
-----+-----  
Port | Membership  
-----+-----  
fa10 | Excluded  
-----+-----
```

---

## show interface switchport

**Syntax** **show interface switchport interfaces IF\_PORTS**

**Parameter** **IF\_PORTS** Specify interfaces protocol vlan to display

**Default** None

**Mode** Privileged EXEC

**Usage** Display information about default vlan

**Example** The following example specifies that show interfacce switchport.

```
SwitchEF0101(config)# interface fa10
SwitchEF0101(config-if)# switchport trunk allowed vlan add 100
SwitchEF0101# show interfaces switchport fa10
Port : fa10
Port Mode : Trunk Ingress
Filtering : enabled
Acceptable Frame Type : all
Ingress UnTagged VLAN ( NATIVE ) : 1
Trunking VLANs Enabled: 100
```

Port is member in:

Vlan	Name	Egress rule
------	------	-------------

---

1	default	Untagged
100	VLAN-one-hundred	Tagged

Forbidden VLANs:

Vlan	Name
------	------

---

## show management-vlan

**Syntax** **show management-vlan**

---

<b>Parameter</b>	None
<b>Default</b>	Nones
<b>Mode</b>	Privileged EXEC
<b>Usage</b>	Display information about management vlan
<b>Example</b>	<p>The following example specifies that show management vlan</p> <pre>Switch(config)# show management-vlan Management VLAN-ID : default(1)</pre>

---

## 36. Voice VLAN

### voice-vlan (Global)

---

<b>Syntax</b>	<b>voice-vlan</b> <b>no voice-vlan</b>
<b>Parameter</b>	
<b>Default</b>	Voice VLAN is disabled
<b>Mode</b>	Global Configuration
<b>Usage</b>	<p>Use the <b>voice vlan</b> global configuration command to enable the functional Voice VLAN on the device.</p> <p>Use the <b>no</b> form of this command to disable voice vlan function.</p> <p>You can verify your setting by entering the <b>show voice vlan</b> <b>Privileged EXEC</b> command.</p>
<b>Example</b>	<p>The following example shows how to enable voice vlan.</p> <pre>Switch(config)# voice-vlan Switch# show voice-vlan Administrative Voice VLAN state : disabled Voice VLAN ID      : none (disable) Voice VLAN Aging   : 1440 minutes Voice VLAN CoS     : 6 Voice VLAN 1p Remark: disabled</pre>

---

## voice-vlan (Interface)

---

### Syntax

**voice-vlan**  
**no voice-vlan**

---

### Parameter

N/A

---

### Default

The default all port admin-status is disabled.

---

### Mode

Interface Configuration

---

### Usage

Use the **voice vlan** Interface configuration command to enable OUI voice VLAN configuration on an interface

Use the **no** form of this command to disable voice vlan on an interfaces  
You can verify your setting by entering the **show voice vlan Privileged EXEC** command

---

### Example

The following example how to enable voice VLAN function in oui mode on an interface

```
Switch(config)#interface range fa1-3
Switch(config-if)#voice-vlan
Switch# show voice-vlan interfaces fa1-8
Voice VLAN Aging : 1440 minutes
Voice VLAN CoS    7
Voice VLAN 1p Remark: enabled
```

OUI table

OUI MAC	Description
---------	-------------

OUI MAC	Description
00:E0:BB	3COM
00:03:6B	Cisco
00:E0:75	Veritel
00:D0:1E	Pingtel
00:01:E3	Siemens
00:60:B9	NEC/Philips
00:0F:E2	H3C
00:09:6E	Avaya

Port	State	Port Mode	Cos Mode
------	-------	-----------	----------

Port	State	Port Mode	Cos Mode
fa1	Disabled	Auto	Src
fa2	Disabled	Auto	Src
fa3	Disabled	Auto	Src
fa4	Disabled	Auto	Src



fa5	Disabled	Auto	Src
fa6	Disabled	Auto	Src
fa7	Disabled	Auto	Src
fa8	Disabled	Auto	Src

---

## voice-vlan vlan

### Syntax

**voice-vlan vlan <1-4094>**

**no voice-vlan vlan**

### Parameter

<1-4094> Specify the voice VLAN ID

---

### Default

The default Voice VLAN ID is None.

### Mode

Global Configuration

### Usage

Use the **voice vlan id** global configuration command to configure the VLAN identifier of the voice VLAN statically.

Use the **no** form of this command to restore voice vlan id to default. You can verify your setting by entering the **show voice vlan** Privileged EXEC command

### Example

The following example shows how to set Voice vlan id. The vlan id must be created first.

```
Switch(config)# voice-vlan vlan 128
Switch# show voice-vlan
Administratice Voice VLAN state : enabled
Voice VLAN ID      128
Voice VLAN Aging   : 1440 minutes
Voice VLAN CoS     6
Voice VLAN 1p Remark: disabled
```

---

## voice-vlan oui-table

### Syntax

**voice-vlan oui-table A:B:C [DESCRIPTION]**

**no voice-vlan oui-table [A:B:C]**

### Parameter

A:B:C Specify OUI Mac address to add or remove

DESCRIPTION Specify description of the specified MAC address to the voice VLAN OUI table

---

### Default

The system default has 8 oui addresses.



---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

<b>Usage</b>	<p>Use the <b>voice vlan oui-table</b> global configuration command to add oui mac address to OUI Table</p> <p>Use the <b>no</b> form of this command to remove all or specified oui mac address.. You can verify your setting by entering the <b>show voice vlan Privileged EXEC</b> command</p>
--------------	---

---

<b>Example</b>	<p>This following example shows how to add OUI Mac.</p> <pre>Switch(config)# voice-vlan oui-table 00:01:02 "Test" Switch# show voice-vlan interfaces all Voice VLAN Aging : 1440 minutes Voice VLAN CoS    6 Voice VLAN 1p Remark: disabled</pre>
----------------	---

OUI table

OUI MAC	Description
00:E0:BB	3COM
00:03:6B	Cisco
00:E0:75	Veritel
00:D0:1E	Pingtel
00:01:E3	Siemens
00:60:B9	NEC/Philips
00:0F:E2	H3C
00:09:6E	Avaya
00:01:02	Test

Port	State	Port Mode	Cos Mode
fa1	Disabled	Auto	Src
fa2	Disabled	Auto	Src
fa3	Disabled	Auto	Src
.....			

---

## voice-vlan cos (Global)

---

<b>Syntax</b>	<b>voice-vlan cos &lt;0-7&gt; [remark]</b> <b>no voice-vlan cos</b>
---------------	--

---

<b>Parameter</b>	<b>&lt;0-7&gt;</b> Specify the voice VLAN Class of Service value in telephone oui mode
	<b>remark</b> Specify that the L2 user priority is remarked with the CoS value



**Default** The default cos value is 6, remark is disabled.

**Mode** Global Configuration

**Usage** Use the **voice vlan cos** global configuration command to configure the voice VLAN cos value and 1p remark function  
Use the “**no**” form to restore to default mode.  
You can verify your setting by entering the **show voice vlan Privileged EXEC** command

**Example** The following example show how to set cos value and enable 1p remark function  
**Switch(config)# voice-vlan cos 7 remark**  
**Switch# show voice-vlan**  
Administrative Voice VLAN state : disabled  
Voice VLAN ID 128  
Voice VLAN Aging : 1440 minutes  
Voice VLAN CoS 7  
Voice VLAN 1p Remark: enabled

---

## **voice-vlan cos (Interface)**

**Syntax** **voice-vlan cos ( src | all )**  
**no voice-vlan cos**

**Parameter** **src** Specify QoS attributes are applied to packets with OUIs in the source MAC address.  
**All** Specify QoS attributes are applied to packets that are classified to the Voice VLAN.

---

**Default** The default all port in Src mode.

**Mode** Interface configuration

**Usage** Use the **voice vlan cos** Interface configuration command to configure OUI voice VLAN cos mode configuration on an interface  
Use the “**no**” form to restore to default mode.  
You can verify your setting by entering the **show voice-vlan interfaces Privileged EXEC** command

**Example** The following example how to configure voice packet QoS attributes on an interface  
**Switch(config)#interface range fa1-3**  
**Switch(config-if)#voice-vlan cos all**

---



---

```
Switch# show voice-vlan interfaces fa1-8
Voice VLAN Aging : 1440
minutes Voice VLAN CoS
    7
Voice VLAN 1p Remark: enabled
```

OUI table

OUI MAC	Description
-----	-----
00:E0:BB	3COM
00:03:6B	Cisco
00:E0:75	Veritel
00:D0:1E	Pingtel
00:01:E3	Siemens
00:60:B9	
	NEC/Philips
00:0F:E2	H3C
00:09:6E	Avaya

Port | State | Port Mode | Cos Mode

Port	State	Port Mode	Cos Mode
fa1	Disabled	Auto	
All fa2	Disabled	Auto	
All fa3	Disabled		
Auto	All fa4	Disabled	
Auto	Src fa5		
Disabled	Auto	Src fa6	
Disabled	Auto	Src	
fa7	Disabled	Auto	
Src			
fa8	Disabled	Auto	Src

---

## voice-vlan mode

---

### Syntax

**voice-vlan mode (auto|manual)**  
**no voice-vlan mode**

---

### Parameter

<b>auto</b>	Specifies that the port is identified as a candidate to join the voice VLAN. When a packet with a source OUI MAC address that identifies the remote equipment as voice equipment is seen on the port, the port joins the voice VLAN as a tagged port.
<b>manual</b>	Specifies that the port is manually assigned to the voice VLAN.

---

---

### Default

The default is auto mode.

---

### Mode

Interface Configuration



---

**Usage**

Use the **voice-vlan mode** global configuration command to configure the voice VLAN mode for interface.

Use the “**no**” form to restore to default mode.

You can verify your setting by entering the **show voice-vlan interfaces Privileged EXEC** command.

---

**Example**

The following example how to configure voice mode to manual

```
Switch(config)#interface range fa1-3
Switch(config-if)#voice-vlan mode manual
Switch# show voice-vlan interfaces fa1-8
Voice VLAN Aging : 1440 minutes
Voice VLAN CoS    7
Voice VLAN 1p Remark: enabled
```

OUI table

OUI MAC   Description
-----+-----
00:E0:BB   3COM
00:03:6B   Cisco
00:E0:75   Veritel
00:D0:1E   Pingtel
00:01:E3   Siemens
00:60:B9   NEC/Philips
00:0F:E2   H3C
00:09:6E   Avaya

Port   State   Port Mode   Cos Mode
-----+-----+-----+-----

## voice-vlan aging-time

---

**Syntax**

**voice-vlan aing-time <30-65536>**

**no voice-vlan aing-time**

---

**Parameter**

<b>&lt;30-65536&gt;</b>	Specify the voice VLAN aging timeout interval in minutes
-------------------------	--



---

<b>Default</b>	The default aging-timeout value is 1440 minutes
----------------	---

---

<b>Mode</b>	Global Configuration
-------------	----------------------

---

<b>Usage</b>	Use the <b>voice vlan aging-time</b> global configuration command to configure the voice VLAN aging timeout. Use the “ <b>no</b> ” form to restore to default time. You can verify your setting by entering the <b>show voice vlan Privileged EXEC</b> command
--------------	--

---

<b>Example</b>	The following example shows how to set aging time. Switch(config)# <b>voice-vlan aging-time 720</b> Switch# <b>show voice-vlan</b> Administratice Voice VLAN state : disabled Voice VLAN ID 1 Voice VLAN Aging : 720 minutes Voice VLAN CoS 5 Voice VLAN 1p Remark: enabled
----------------	--

## show voice-vlan

---

<b>Syntax</b>	<b>show voice-vlan</b> <b>show voice-vlan interfaces [IF_PORTS]</b>
<b>Parameter</b>	<b>IF_PORTS</b> Specifies intefaces to display voice VLAN settings in oui mode

---

<b>Default</b>	N/A
----------------	-----

---

<b>Mode</b>	Privileged EXEC
-------------	-----------------

---

<b>Usage</b>	Use the <b>show voice vlan</b> command in EXEC mode to display the voice VLAN status for all interfaces or for a specific interface if the voice VLAN type is OUI
--------------	---

---

<b>Example</b>	The following example show how to display voice vlan oui mode settings Switch# <b>show voice-vlan</b>
----------------	--



---

Administrate Voice VLAN state : disabled  
Voice VLAN ID : none (disable)  
Voice VLAN Aging : 720  
minutes Voice VLAN CoS 6  
Voice VLAN 1p Remark: disabled

Switch# show voice-vlan interfaces  
fa1-4 Voice VLAN Aging : 720  
minutes Voice VLAN CoS 5  
Voice VLAN 1p Remark: enabled

OUI table

OUI MAC	Description
-----	-----
00:E0:BB	3COM
00:03:6B	Cisco
00:E0:75	Veritel
00:D0:1E	Pingtel
00:01:E3	Siemens
00:60:B9	
	NEC/Philips
00:0F:E2	H3C
00:09:6E	Avaya

Port | State | Port Mode | Cos Mode

Port	State	Port Mode	Cos Mode
-----	-----	-----	-----
fa1	Disabled	Auto	
Src fa2	Disabled	Auto	
Src fa3	Disabled	Auto	
Src			
<u>fa4</u>	<u>Disabled</u>	<u>Auto</u>	<u>Src</u>

---

## 37. Static Routing

### IPv4 Interface

---

**Syntax**

```
interface vlan
ip address ipaddr mask
no interface vlan
no ip address
```

---

**Parameter**

<i>ipaddr</i>	Specify IPv4 address for switch
<i>mask</i>	Specify net mask address for switch

---

**Default**

The vlan interface and ip address are not configured by default.



# Command Line Interface

## User Guide

---

### Mode

Global configuration and vlan interface configuration.

---

### Usage

Use the **interface vlan** global configuration command to config ip interface on the device.

Use the **ip address** command in vlan interface mode to configure the device's ip address.

Use the **no ip address** command to delete the configured ip address.

Use the **no interface vlan** command to delete ip interface on the device.

You can verify your setting by entering the **show ip interface vlan** Privileged EXEC command.

---

### Example

The following example shows how to config ip interface.

```
Switch(config)# interface vlan 2
Switch(config-if)# ip address 192.168.3.1 255.255.255.0
Switch# show ip interface vlan 2
```

IP Address	I/F	I/F Status	admin/oper	Type
192.168.3.1/24 Valid	VLAN 2	UP/DOWN		Static

---



## IPv4 Routes

### Syntax

```
ip route dest-ipaddr mask router-ipaddr
no ip route dest-ipaddr mask router-ipaddr
```

### Parameter

<i>dest-ipaddr</i>	Destination ip address prefix
<i>mask</i>	Destination ip address prefix mask
<i>router-ipaddr</i>	Forwarding router's ip address

### Default

Static route is not configured by default.

### Mode

Global Configuration mode.

### Usage

Use the **ip route** command in global mode to configure a static route rule.  
Use the **no ip route** command to delete a static routing rule.  
You can verify your setting by entering the **show ip route** Privileged EXEC command

### Example

The following example shows how to configure a static route.

```
Switch(config)# vlan 2
Switch(config)# interface GigabitEthernet 4
Switch(config-if)# switchport trunk allowed vlan add 2
Switch(config)# interface vlan 2
Switch(config-if)# ip address 192.168.3.1 255.255.255.0
Switch(config)# ip route 1.1.1.1 255.0.0.0 192.168.3.11
Switch# show ip route
Codes: > - best, C - connected, S - static

S> 1.0.0.0/8 [1/1] via 192.168.3.11, VLAN 2
C> 192.168.0.0/24 is directly connected, MGMT VLAN
C> 192.168.3.0/24 is directly connected, VLAN 2
```

## IPv4 ARP

### Syntax

```
arp ip-addr mac-addr vlan vlanid
no arp ip-addr mac-addr vlan vlanid
```

### Parameter

<i>ip-addr</i>	IP address of ARP entry
<i>mac-addr</i>	MAC address of ARP entry
<i>vlanid</i>	Vlan ID of this arp entry

### Default

The device contains ARP entries of the vlan interface.



---

**Mode** Global Configuration mode.

---

**Usage** Use the **arp** command to add a static arp entry.  
Use the **no arp** command to delete a static arp entry.  
You can verify your setting by entering the **show arp** Privileged EXEC command

---

**Example** The following example shows how to configure and view a static arp entry.  
Switch(config)# **arp 192.168.3.22 00:00:11:11:11:11 vlan 2**  
Switch# **show arp**

VLAN Interface	IP address	HW address	Status
vlan 1	192.168.0.112	00:D0:00:00:00:01	Dynamic
vlan 2	192.168.3.22	00:00:11:11:11:11	Static

---

## IPv6 Interface

---

**Syntax** **interface vlan *vlanid***  
**ipv6 enable**  
**no interface vlan *vlanid***  
**no ipv6 enable**

---

**Parameter** *vlanid* Vlan id for vlan interface

---

**Default** The vlan interface are not configured by default.Ipv6 is disabled.

---

**Mode** Global configuration and vlan interface configuration.

---

**Usage** Use the **interface vlan** global configuration command to config ip interface on the device.  
Use the **ipv6 enable** command in vlan interface mode to enable ipv6 function.  
Use the **no ipv6 enable** command to disable ipv6 function.  
Use the **no interface vlan** command to delete ip interface on the device.  
You can verify your setting by entering the **show ipv6 interface vlan** Privileged EXEC command.

---



## Example

The following example shows how to config ip interface.

```
Switch(config)# interface vlan 2
Switch(config-if)# ipv6 enable
Switch# show ipv6 interface vlan 2
```

VLAN 2 is up/up  
IPv6 is enabled, link-local address is fe80::2e0:4cff:fe00:0  
IPv6 Forwarding is enabled  
No global unicast address is configured  
Joined group address(es):  
ff02::1:ff00:0  
ff02::1  
ff01::1  
ND DAD is enabled, number of DAD attempts: 1  
Stateless autoconfiguration is enabled

# IPv6 Address

<b>Syntax</b>	<b>ipv6 address</b> <i>ipv6-addr</i> <b>no ipv6 address</b>
<b>Parameter</b>	<i>ipv6-addr</i> Manually configured ipv6 address
<b>Default</b>	The vlan interface are not configured by default.Ipv6 is disabled.
<b>Mode</b>	Global configuration and vlan interface configuration.
<b>Usage</b>	<p>Use the <b>ipv6 address</b> command in vlan interface mode to config manual ipv6 address.</p> <p>Use the <b>no ipv6 address</b> command in vlan interface mode to delete all manual ipv6 addresses on this vlan interface.</p> <p>You can verify your setting by entering the <b>show ipv6 interface</b> v Privileged EXEC command.</p>
<b>Example</b>	<p>The following example shows how to config ip interface.</p> <pre>Switch(config)# interface vlan 2 Switch(config-if)# ipv6 address 2001:01::01:01/64 Switch# show ipv6 interface vlan 2 VLAN 2 is up/up IPv6 is enabled, link-local address is fe80::2e0:4cff:fe00:0 IPv6 Forwarding is enabled Global unicast address(es): IPv6 Global Address          Type 2001:1::1:1/64                Manual Joined group address(es): ff02::1:ff01:1 ff02::1:ff00:0 ff02::1</pre>



ff01::1  
 ND DAD is enabled, number of DAD attempts: 1  
 Stateless autoconfiguration is enabled Stateless autoconfiguration is enabled

---

## IPv6 Routes

<b>Syntax</b>	<b>ipv6 route</b> <i>ipv6-addr/length</i> <i>route-ipv6-addr</i> <b>no ipv6 address</b> <i>ipv6-addr/length</i>				
<b>Parameter</b>	<table> <tr> <td><i>ipv6-addr/length</i></td><td>Destination ipv6 prefix and length</td></tr> <tr> <td><i>route-ipv6-addr</i></td><td>Forwarding router's ipv6 address</td></tr> </table>	<i>ipv6-addr/length</i>	Destination ipv6 prefix and length	<i>route-ipv6-addr</i>	Forwarding router's ipv6 address
<i>ipv6-addr/length</i>	Destination ipv6 prefix and length				
<i>route-ipv6-addr</i>	Forwarding router's ipv6 address				
<b>Default</b>	The ipv6 routing entry is not configured by default.				
<b>Mode</b>	Global configuration and vlan interface configuration.				
<b>Usage</b>	<p>Use the <b>ipv6 route</b> command to configure a static ipv6 routing entry.          Use the <b>no ipv6 address</b> command to delete a static ipv6 routing entry.          You can verify your setting by entering the <b>show ipv6 route static</b> Privileged EXEC command.</p>				
<b>Example</b>	<p>The following example shows how to configure an ipv6 routing entry.</p> <pre>Switch(config)# <b>ipv6 route</b> 2002:01::01:01/96 2001:01::01:02 Switch# <b>show ipv6 route static</b> Codes: A - active, I - inactive</pre> <p>I 2002:1::/96 [1/1] via 2001:1::1:2, inactive</p>				

## IPv6 Neighbors

<b>Syntax</b>	<b>ipv6 neighbor</b> <i>ipv6-addr</i> <b>vlan</b> <i>vlanid</i> <b>macaddr</b> <b>no ipv6 neighbor</b>						
<b>Parameter</b>	<table> <tr> <td><i>ipv6-addr</i></td><td>Neighbor ipv6 address</td></tr> <tr> <td><i>vlanid</i></td><td>Vlan interface number</td></tr> <tr> <td><i>macaddr</i></td><td>MAC address of ipv6 neighbor entry</td></tr> </table>	<i>ipv6-addr</i>	Neighbor ipv6 address	<i>vlanid</i>	Vlan interface number	<i>macaddr</i>	MAC address of ipv6 neighbor entry
<i>ipv6-addr</i>	Neighbor ipv6 address						
<i>vlanid</i>	Vlan interface number						
<i>macaddr</i>	MAC address of ipv6 neighbor entry						
<b>Default</b>	No ipv6 neighbor address by default.						
<b>Mode</b>	Global configuration.						
<b>Usage</b>	Use the <b>ipv6 neighbor</b> command to configure a static ipv6 neighbor entry.						



# Command Line Interface

## User Guide

Use the **no ipv6 neighbor** command to delete ipv6 neighbor entry.

You can verify your setting by entering the **show ipv6 neighbors** Privileged EXEC command.

### Example

The following example shows how to configure an ipv6 neighbor entry.

```
Switch(config)# ipv6 neighbor 2001:01::01:11 vlan 2
```

```
00:00:00:11:11:12
```

```
Switch# show ipv6 neighbors
```

VLAN Interface address	Status	IPv6 address Router State	HW
---------------------------	--------	------------------------------	----

vlan 2	2001:1::1:11
00:00:00:11:11:12	Static
	No

Total number of entries: 1

## 38. POE

### POE Port Setting

#### Syntax

```
poe
```

```
no poe
```

#### Parameter

#### Default

All ports are enabled for poe power supply by default.  
( Poe-enabled device)

#### Mode

interface configuration.

#### Usage

Use the **poe** command in interface mode to enable port poe power supply.  
Use the **no poe** command in interface mode to disable port poe power supply.  
You can check the port poe working status by using the **show poe** Privileged EXEC command.

### Example

The following example shows how to config poe.

```
Switch(config)# interface GigabitEthernet 1
```

```
Switch(config-if)# poe
```

```
Switch# show poe
```

Get poe power:

Port	Enable	State	type	level	actual-current(mA)	volatge(V)	power(mW)



gi1 13	enable	on	AT	4	676	52	
gi2 N/A	enable	off	AF	0	N/A	N/A	
gi3 N/A	enable	off	AF	0	N/A	N/A	
gi4 N/A	enable	off	AF	0	N/A	N/A	
gi5 N/A	enable	off	AF	0	N/A	N/A	
gi6 N/A	enable	off	AF	0	N/A	N/A	
gi7 N/A	enable	off	AF	0	N/A	N/A	
gi8 N/A	enable	off	AF	0	N/A	N/A	

Total used power: 676 (mW)

Current Temperature: 65 (C)

---

## POE Port Schedule Setting

<b>Syntax</b>	<b>poe schedule week days hour hours</b>
	<b>no poe schedule week days hour hours</b>

<b>Parameter</b>	<i>days</i> Port poe power supply days
	<i>hours</i> Port poe power supply hours

<b>Default</b>	All ports open POE function all day by default. ( Poe-enabled device)
----------------	--

<b>Mode</b>	interface configuration.
-------------	--------------------------

<b>Usage</b>	<p>Use the <b>poe schedule</b> command in interface mode to set port poe power supply time.</p> <p>Use the <b>no poe schedule</b> command in interface mode to clear port poe power supply time..</p> <p>You can check the port poe work time setting view through the web.</p>
--------------	---

<b>Example</b>	<p>The following example shows how to config poe schedule.</p> <pre>Switch(config)# interface GigabitEthernet 1 Switch(config-if)# poe schedule week mon hour 1</pre>
----------------	---

---

Note: The configured time has a deviation of about 0~10 minutes.



## 39.ERPS

### Erps (global)

<b>Syntax</b>	erps no erps
<b>Parameter</b>	no
<b>Default</b>	disable
<b>Mode</b>	global configuration.
<b>Usage</b>	Run the "erps" command to enable global ERPS.
<b>Example</b>	Enable ERPS Switch(config)# erps

---

### Erps instance (Global)

<b>Syntax</b>	erps instance <1-15> no erps instance <1-15>
<b>Parameter</b>	<1-15>instance id range
<b>Default</b>	no
<b>Mode</b>	global configuration.
<b>Usage</b>	Run the erps instance command to create an ERPS instance.



**Example** Set ERPS instance to 0  
Switch(config)# erps instance 0

---

## Control-vlan

**Syntax** control-vlan <1-4094>

no control-vlan

**Parameter** <1-4094>vlan id range

**Default** default vlan id 1

**Mode** ERPS configuration mode.

**Usage** Run the control-vlan command to set up an ERPS instance to control a VLAN.

**Example** Example Set the control VLAN to 2  
Switch(config-erps-inst)# control-vlan 2

---

## wtr-timer

**Syntax** wtr-timer <1-12>

no wtr-timer

**Parameter** <1-12> wtr timer value is from 1 to 12 minutes

**Default** default 5 minutes

**Mode** erps configuration mode.

**Usage** Run the wtr-timer command to set the WTR time in the ERPS.



**Example** Set the WTR time of the ERPS to 6 minutes  
Switch(config-erps-inst)# **wtr-timer 6**

---

## guard-timer

**Syntax** **guard-timer <100-2000>**  
**no guard-timer**

**Parameter** <100-2000>ms

**Default** default guard timer is 500ms

**Mode** erps configuration mode.

**Usage** Run the guard-timer command to set the guard time in the ERPS.

**Example** Set erps ring guard-timer 100ms  
Switch(config-erps-inst)# **guard-timer 100**

---

## work-mode

**Syntax** **work-mode non\_revertive**

**work-mode revertive**

**Parameter** no

**Default** Default Revertive Indicates the reversible mode

**Mode** erps configuration mode.

**Usage** Run the "work-mode revertive" command to set the working mode in ERPS..



**Example** Set ERPS working mode to the reversible mode  
Switch(config-erps-inst)# work-mode revertive

---

## ring<ID>

**Syntax** **ring <1-239>**

**Parameter** <1-239>ring id is from 1 to 239

**Default** The default ring ID is 1

**Mode** erps configuration mode.

**Usage** Run the "ring <1-239>" command to set the ring ID of the ERPS.

**Example** Example Set the ring ID to 2  
Switch(config-erps-inst)# **ring 2**

---

## ring-level

**Syntax** **ring-level <0-1>**

**Parameter** <0-1>0 is the primary ring and 1 is the subring

**Default** 0 is the primary ring

**Mode** erps configuration mode.

**Usage** Run the "ring-level <0-1>" command to set the primary ring to 0 and the subring to 1 in the ERPS



**Example** Set the ERPS ring to subring  
Switch(config-erps-inst)# **ring-level 1**

---

## port

**Syntax** **port0 IF\_PORTS (owner|neighbour|next-neighbour)**

**Port1 IF\_PORTS (owner|neighbour|next-neighbour)**

**Parameter** IF\_PORTS port number

**Default** port1

**Mode** erps configuration mode.

**Usage** Use the command "port0 IF\_PORTS (owner | neighbour | next - neighbour)" set the erps central to the owner, neighbour, next - neighbour.

**Example** Set port 2 as the owner node  
Switch(config-erps-inst)# **port0 GigabitEthernet2 owner**

---

## mel

**Syntax** **mel <0-7>**

**Parameter** <0-7> mel value is form 0 to 7

**Default** mel is 0

**Mode** erps configuration mode.

**Usage** Use the command "MEL <0-7>" to set the instance level in ERPS.



**Example** Example Set the instance mel to 2  
Switch(config-erps-inst)# **mel 2**

---

## Ring enable

**Syntax** **ring enable**

**ring disable**

**Parameter** no

**Default** disable

**Mode** erps configuration mode.

**Usage** Use the command "ring (enable | disable)" set the erps central is enabled.

**Example** Set ring enable

Switch(config-erps-inst)# **ring enable**

---

## protected-instance

**Syntax** **protected-instance <0-15>**

**Parameter** <0-15> mstp instance id is form 0 to 15

**Default** no

**Mode** erps configuration mode.

**Usage** Using the command ‘protected-instance’ Sets the loop protection instance



**Example** Set ring protected-instance is 1  
Switch(config-erps-inst)# **protected-instance 1**

---

## Show erps instance

**Syntax** **show erps instance all**

**show erps instance <0-15>**

**Parameter** <0-15>instance id form 0 to 15

**Default** no

**Mode** global configuration.

**Usage** display erps information

**Example** Display erps information

Switch# **show erps instance all**

Erps instance	: 1
Erps ring status	: disable
Erps mel	: 1
Erps control vlan	: 1
Erps WTR time	: 5 min
Erps guard time	: 500 ms
Erps work-mode	: revertive
Erps ring ID	: 1
Erps ring-level	: 0
Erps protected-instance	: 0
Erps port0 portId:GE1, port role	: rpl, port status:forwarding
Erps port1 portId:GE1, port role	: rpl, port status:forwarding
Erps ring node state	: init

---

## 40.DNS

### ip domain

**Syntax** **ip domain lookup**

**no ip domain lookup**

**Parameter** no



---

<b>Default</b>	disable
<b>Mode</b>	global configuration.
<b>Usage</b>	The DNS server was enabled or disabled.
<b>Example</b>	Enabling the DNS Server Switch(config)# ip domain lookup

---

## ip domain name

---

<b>Syntax</b>	<b>ip domain name HOSTNAME</b> <b>no ip domain name</b>
<b>Parameter</b>	HOSTNAME Domain name character
<b>Default</b>	<b>no</b>
<b>Mode</b>	<b>global</b> configuration.
<b>Usage</b>	Run the ‘ <b>ip domain name</b> ’ command to The domain name .
<b>Example</b>	Set The domain name is test Switch(config)# <b>ip domain name test</b>

---

## ip name-server

---

<b>Syntax</b>	<b>ip name-server (A.B.C.D X:X::X:X) [(A.B.C.D X:X::X:X)] [(A.B.C.D X:X::X:X)] [(A.B.C.D X:X::X:X)] no ip name-server (A.B.C.D X:X::X:X) [(A.B.C.D X:X::X:X)] [(A.B.C.D X:X::X:X)] [(A.B.C.D X:X::X:X)]</b>
<b>Parameter</b>	A.B.C.D Ipv4 address X:X::X:X Ipv6 address



---

**Default** no

---

**Mode** global configuration.

---

**Usage** Configure the available domain name servers.

---

**Example** Set the DNS server to 192.168.2.10.  
Switch(config)# **ip name-server 192.168.2.10**

---

## ip host

---

**Syntax** **ip host HOSTNAME (A.B.C.D|X:X::X:X)**  
**no ip host HOSTNAME**

---

---

**Parameter** A.B.C.D Ipv4 address  
X: X: X: X Ipv6 address  
HOSTNAME Domain name String

---

---

**Default** no

---

**Mode** global configuration.

---

**Usage** Configure the mapping between static domain names and IP address.

---

**Example** Set the static mapping between domain name 'test' and IP address '192.168.2.10'.  
Switch(config)# **ip host test 192.168.2.10**

---

## show hosts

---

**Syntax** **show hosts**

---

**Parameter** no

---

**Default** no

---

**Mode** global configuration.

---

**Usage** The DNS configuration information is displayed.



# Command Line Interface

## User Guide

### Example

The DNS configuration information is displayed.  
Switch(config)# **show hosts**

Name/address lookup is enabled

#### Default Domain Table

Domain	Source	Preference
<hr/>		

#### Name Server Table

IP Address	Source	Preference
192.168.2.10	Static	1

#### Cache Table

Flags: (STA, OK)

STA - Static

OK - Okay

Host	IP Address	Type	State
test	192.168.2.10	IPv4	STA,OK

---

